

TABLE OF CONTENTS

TABLE OF CONTENTS 1

1- LAPTOP PREPARATION 2

2- PERFORMING CHECK..... 4

3- SYSTEM RESTORATION..... 4

REVISION HISTORY 5

1- LAPTOP PREPARATION

The field laptop will be configured as a VT-100 communications terminal in order to command the Gradient Switch, via the serial link, to check the status. HyperTerminal will be used to configure the laptop to perform as a VT-100 communications terminal. HyperTerminal must be properly configured or else it will not be possible to establish communication via the serial link with the Gradient Switch.



Disable any software running in the background on the laptop, such as Personal Digital Assistant (PDA) syncing or “Hotlink” programs, that take exclusive control of the COM 1 port and will prevent HyperTerminal from using this port. Failure to do this will result in COM 1 port availability errors when attempting to configure the port from HyperTerminal.

1. On the laptop, position the mouse cursor into the lower left corner of the screen and click **Start**, then **Run**.
2. Type **hypertrm** in the entry box and then click **OK**.
3. **IF** the system reports that HyperTerminal is **not** found, then it must be installed. Do the following:
 - a. Select **Start**, then **Settings**, then **Control Panel**, then **Add/Remove Programs**.
 - b. At the top of the *Add/Remove Programs Properties* window select **Windows Setup**.
 - c. Scroll down the menu from the left scroll bar and select **Communications**.
 - d. Scroll down the menu from the left scroll bar and click on the check mark box to the left of **HyperTerminal**. A check mark will appear in the left box when it has been selected. Click on **OK**.
 - e. At the *Add/Remove Programs Properties* window click on **OK**. The system will indicate that it is attempting to load this program.
 - f. Windows 95 users will, at this point, be asked to reboot. Select **Yes**. After the reboot repeat step 1.
 - g. Windows 98 users will notice that the installation ends but will not see any special prompt.
3. In the *Connection Description* window enter **GradSwitch** as the *Name*.
4. Select the GE logo as the icon and then click **OK**.

5. In the *Connect To* window, left mouse click on the down-arrow mark in the *Connect using* box. Select **Direct to Com1** and then click **OK**.
6. Refer to Table 2-1 and configure the *COM1 Properties* windows as shown.

TABLE 2-1
COMMUNICATIONS SETTINGS

Bits per second	9600
Data Bits	8
Stop Bits	1
Parity	none
Flow Control	Xon/Xoff

7. Select and click on **OK** when done.
8. Select File from the top of the window and then click on Save. This saves this configuration for future use as an entry labeled gradswitch.ht.

Note

This configuration can be used again in the future by clicking on **Gradswitch.ht** from the *HyperTerminal* window.

2- PERFORMING CHECK

1. Lock Out and Tag out the Gradient Switch Cabinet.
2. After ensuring power is OFF, remove the protective plastic panel on the rear of the Gradient Switch module.
3. Connect one end of the Serial Port Cable to the J6 Debug Terminal on the rear of the Gradient Switch and the other end to the 9 pin Sub-D COM1 serial port on the rear of the laptop.

Note

The serial port cable (P/N 2283292) ships with the Gradient Switch Cabinet and is secured in the bottom of the cabinet.

4. Remove the Lock out/ Tag out.
5. Power ON the Gradient Switch cabinet, Default is WB and the 3 WB LEDs are lit. PS LED is lit.
6. Double click the GradSwitch icon on the laptop to open the Hyper Terminal window to begin session.
7. Type: **File/Properties/Settings/ASCII Setup/ <ENTER>**.
8. Choose **SEND LINE ENDS WITH LINE FEEDS** and **ECHO TYPED CHARACTERS LOCALLY**, confirm **OK**.
9. Type in all capital letters **GSC_SW 1 1 1**ENTER.
 - WB is still ON.
 - The Terminal response display will be: **GSC_STAT 1 1 1**
10. Type : **GSC_SW 2 2 2**<ENTER>
 - The Switch will change to ZM status(the 3 green Led's ZM will be ON).
 - The Terminal response display will be : **GSC_STAT 2 2 2**
 - If error exists, it will be displayed on the Terminal display screen.
8. End the Hyper Terminal session on Laptop.

3- SYSTEM RESTORATION

1. Lock Out and Tag out the Gradient Switch Cabinet.
2. Disconnect the Serial cable from the J6 Debug Terminal.
3. Replace the protective plastic panel.
4. Remove Lock out /Tag out.
5. Perform Good bye Scan.

REVISION HISTORY

REV	DATE	AUTHOR	PRIMARY REASONS FOR CHANGE
0	August 15, 2001	Illan Keren	Initial release.