

New ramp profiles for Mobiles

Use these profiles when using all three switch heaters from the ramp supply and the shim supply simultaneously during magnet ramp-up.

For CX 1.0T and LCC 1.0T magnets:

PS current	Fixed Site	Mobile(using both switch heaters)
0 to 100 amps	5.00	4.49
100 to 200 amps	4.60	4.13
200 to 300 amps	4.20	3.78
300 to 400 amps	3.80	3.42
400 to 500 amps	3.30	2.97
500 to 550 amps	2.50	2.25
550 to 600 amps	2.00	1.80
600 to 625 amps	1.50	1.35
625 to 650 amps	1.00	.90
650 to 675 amps	.75	.67
675 to 700 amps	.60	.54
700 to 720 amps	.50	.45
720 to 730 amps	.30	.27

At 730 lower drive voltage to .09

When magnet reaches .999 tesla lower drive voltage to .022

When magnet reaches parking frequency lower drive voltage to zero and park magnet at desired frequency.

For CX 1.5T and LCC 1.5T magnets:

PS current	Fixed Site	Mobile(using both switch heaters)
0 to 100 amps	6.00	5.39
100 to 200 amps	5.60	5.03
200 to 300 amps	5.20	4.67
300 to 400 amps	4.70	4.22
400 to 500 amps	4.30	3.86
500 to 550 amps	3.50	3.15
550 to 600 amps	3.00	2.70
600 to 625 amps	2.35	2.11
625 to 650 amps	2.00	1.80
650 to 675 amps	1.00	.90
675 to 700 amps	.75	.67
700 to 720 amps	.50	.45
720 to 730 amps	.30	.27

At 730 lower drive voltage to .09

When magnet reaches 1.490 tesla lower drive voltage to .022

When magnet reaches parking frequency lower drive voltage to zero and park magnet at desired frequency.

For SX magnets:

Fixed site	Mobile(using both switch heaters)
4.5 volts	4.05 volts

Follow ramping procedure in direction 46-015537, section 9 in set up and calibration.

For SX-C magnets:

Fixed site	Mobile(using both switch heaters)
4.00 volts	3.60 volts

Follow ramping procedure in direction 2145089, section 9 in set up and calibration.