

GE Healthcare Functional CT (FCT) Class C eService Notes are copyright (c) to General Electric Company Inc with all rights reserved. Class C eService Notes issued by GE Healthcare are proprietary to GE Healthcare Systems. Disclosure to persons not employed by GE Healthcare or not in possession of a Advanced Service Agreement with GE Healthcare is prohibited.
Duplication and distribution of any class of FCT eService Notes, in any form by entities other than GE Healthcare is strictly prohibited.

FCT SERVICE NOTE

SN06061311a

Class C information is Property of GE.

Date: June 13, 2006

Subject: Patch for VCT 32 Version 06MW03.4 IG boot failure

Effectivity: VCT 32 Version 06MW03.4 with 1IG configuration

Details:

VCT-Select (Pro32) Version 06MW03.4 has intermittent IG boot up issue during the system start up. When this problem happens, customer will see the pop up message which states that reconstruction can not work. Also the following error message is seen in gesyslog.

```
Fri Feb 17 11:02:32 2006 2900090154
darc recon_control
recon_control_cb.cxx          1905
Recon connect timer triggered on 1
```

Frequency: Less than 10% (1 failure per 10 reboots: depending on system)

Resolution:

A patch software CDROM was released to resolve intermittent IG boot failure on VCT 32 Version 06MW03.4 with 1IG configuration. This patch changes boot up sequence of DARC/IG. This patch can be applied to only VCT-Select(Pro32) Version 06MW03.4

Part Number: 5176557 (1IG Boot Up Issue Patch for 06MW03.4)

This software patch has been installed on systems shipped after FW21.

For the M3A systems, this patch will be delivered with M4 FMI kit (FMI#26807).

For the M4 systems shipped before FW21, you can download the patch iso file from CT On Line SupportCentral.

http://supportcentral.ge.com/bookupload/sup_book_default.asp?prod_id=15768&trng_doc_id=281360&vendor_flag=11&doc_cat_id=115255

Go to **LightSpeed 7.x (VCT64, VCT32) > LightSpeed VCT32**

Please make a CD and install on the system.

This patch CD will be also available as FRU by the end of June.

IMPORTANT NOTICE:

When replacing the VDARC or performing VDARC LFC for repairs, the patch (5176557) must be un-installed FIRST (refer to 'Patch Un-Installation' and 'Verification of Patch Un-Installation' below). Otherwise, the system needs to perform Full LFC (Host and VDARC).

After completing repairs, re-install the patch (5176557).

When replacing VIG or updating the configuration from 1IG to 3IG for upgrade, there is no need to un-install the patch.

Appendix Patch Install/Un-install Procedure

1. Patch Installation

To install the patch, insert the patch CD into the DVD drive of SCSI tower. Applications will need to be shutdown to install the patch.

- 1.) Insert the patch CD into the DVD Drive of the SCSI tower.
- 2.) Open a Unix Shell.
- 3.) Type the following:

```
su - <ENTER>
#bigguy <ENTER>
mount /mnt/cdrom1 <ENTER>
cd /mnt/cdrom1 <ENTER>
./install_patch -p VCT_Select_1IG_patch-1-1.i386.rpm <ENTER>
cd / <ENTER>
```

(The installation message appears.)

```
umount /mnt/cdrom1 <ENTER>
```
- 4.) Eject and remove the patch CD from the DVD drive of SCSI tower.
- 5.) Type: **reboot** <ENTER>

2. Verification of Patch Installation

- 1.) Open a Unix Shell.
- 2.) Type the following, then verify that the verification results indicated by boldface are the following. If not, perform Full LFC (Host and VDARC).

```
[root@liblab 12]# su - <ENTER>
#bigguy <ENTER>
[root@liblab 12]# showprods|grep -i patch <ENTER>
|patch 03/07/2006 The GNU patch command, for modifying/upgrading
files. ver 2.5.4 rel 2.5.4.19
|VCT_Select_1IG_patch 03/25/2006 VCT_Select_1IG_patch ver 1 rel 1.1
[root@liblab 12]# ls -l /etc/rc.d/rc5.d/*darcpower <ENTER>
|rw-rw-rw- 1 root root 19 Mar 25 10:55 /etc/rc.d/rc5.d/S25darcpower
-> ../init.d./darcpower
[root@liblab 12]# rsh darc -n "ls -l /etc/init.d/igpower" <ENTER>
-rxr-xr-x 1 root root 3059 Mar 25 10:55 /etc/init.d/igpower
[root@liblab 12]# rsh darc -n "ls -l /etc/rc.d/rc5.d/S*" <ENTER>
/etc/rc.d/rc5.d/S00microcode_ctl
/etc/rc.d/rc5.d/S04readahead_early
:
:
/etc/rc.d/rc5.d/S25cliservice
/etc/rc.d/rc5.d/S25dhcpd
/etc/rc.d/rc5.d/S25netfs
/etc/rc.d/rc5.d/S25nfs
/etc/rc.d/rc5.d/S25xinetd
/etc/rc.d/rc5.d/S26igpower1
/etc/rc.d/rc5.d/S26igpower2 (three IG config only)
/etc/rc.d/rc5.d/S26igpower3 (three IG config only)
/etc/rc.d/rc5.d/S26sensors
:
:
```

Duplication and distribution of any class of FCT eService Notes, in any form by entities other than GE Healthcare is strictly prohibited.

3. Patch Un-Installation

- i.) Insert the patch CD into the DVD drive of SCSI tower.
- ii.) Shutdown application from common service desktop.
- III.) Open a Unix Shell, and type the following:

```
su - <ENTER>
#bigguy <ENTER>
mount /mnt/cdrom1 <ENTER>
cd /mnt/cdrom1 <ENTER>
./uninstall_patch <ENTER>
```

Following messages appear on the shell, select 1 to un-install the patch.

The installed patch are listed below.
Please selected the number associated with the patch to be un-installed.

```
0 - exit
1 - VCT_Select_1IG_patch-1-1
Enter a number: 1 <ENTER>
```

- iv.) Eject and remove the patch CD from the DVD drive of SCSI tower.
- v.) Type: **reboot** <ENTER>

4. Verification of Patch Un-Installation

- i.) Open a Unix Shell, and type the following,
then verify that the verification results indicated by boldface are the following.
If not, perform Full LFC (Host and VDARC).

```
[roog@liblab 12]# su - <ENTER>
#bugguy <ENTER>
[roog@liblab 12]# showprods|grep -i patch <ENTER>
|patch 03/07/2006 The GNU patch command, for modifying/upgrading
files. ver 2.5.4 rel 2.5.4.19
[roog@liblab 12]# ls -l /etc/rc.d/rc5.d/*darcpower <ENTER>
|rw-rw-rw- 1 root root 19 Mar 25 10:55 /etc/rc.d/rc5.d/S55darcpower
-> ./init.d/darcpower
[root@liblab12]# rsh darc -n "ls -l /etc/init.d/igpower" <ENTER>
-r-xr-xr-x 1 root root 2166 Mar 25 10:55 /etc/init.d/igpower
[root@liblab12]# rsh darc -n "ls -l /etc/rc.d/rc5.d/S*" <ENTER>
/etc/rc.d/rc5.d/S00microcode_ctl
/etc/rc.d/rc5.d/S04readahead_early
:
:
/etc/rc.d/rc5.d/S56rawdevices
/etc/rc.d/rc5.d/S56xinetd
/etc/rc.d/rc5.d/S60nfs
/etc/rc.d/rc5.d/S60vsftpd
/etc/rc.d/rc5.d/S61bmcscrip
/etc/rc.d/rc5.d/S65dhcpcd
/etc/rc.d/rc5.d/S70igpower1
/etc/rc.d/rc5.d/S70igpower2 (three IG config only)
/etc/rc.d/rc5.d/S70igpower3 (three IG config only)
/etc/rc.d/rc5.d/S85gpm
```

GE Healthcare Functional CT (FCT) Class C eService Notes are copyright (c) to General Electric Company Inc with all rights reserved. Class C eService Notes issued by GE Healthcare are proprietary to GE Healthcare Systems. Disclosure to persons not employed by GE Healthcare or not in possession of a Advanced Service Agreement with GE Healthcare is prohibited.

Duplication and distribution of any class of FCT eService Notes, in any form by entities other than GE Healthcare is strictly prohibited.

:

Takashi Uehara,
Lead Service Integrator VCT 32