

Uncontrolled copy!

Dependencies between MR hosts, imagers, software- and BIOS versions!

About 1993 Siemens Healthcare started to sell MR systems. This and the rapid progress of MR technologies in past years result in a large number of different MR system types and software versions.

Since not all combinations are operational, the following pages try to show the dependencies between the relevant components.

[MRC hosts](#)

In the first column the host type is roughly described with its components
In the second column usually the date of availability is listed and the changes made to the hosts.

The third column lists the corresponding Numaris version and the valid BIOS version.

The fourth column just holds the material number of the host (IVK)

[MRSC hosts](#)

In the first column the host type is roughly described with its components

In the second column usually the date of availability is listed and the changes made to the hosts.

The third column lists the corresponding Numaris version and the valid BIOS version.

The fourth column just holds the material number of the host (IVK)

[VA-, VB-imagers](#)

In the first column the host type is roughly described with its components

In the second column usually the date of availability is listed and the changes made to the hosts.

The third column lists the corresponding Numaris version and the valid BIOS version.

The fourth column just holds the material number of the host (IVK)

[VC-, VD-imagers](#)

In the first column the host type is roughly described with its components

In the second column usually the date of availability is listed and the changes made to the hosts.

The third column lists the corresponding Numaris version and the valid BIOS version.

The fourth column just holds the material number of the host (IVK)

[HW;SW;BIOS](#)

This is an overview or summary of the four previous tabs.

Additionally the material numbers of the BIOS CDs are listed.

Uncontrolled copy!

Host-Configuration	Changes during life-time	released Mrease/syngo	Basic Host (IVK)
Primergy470: 2*550MHz, 2GB, 9+9+18GB HDD Mill-II 8MB, 2*Intel Fast-Ether-Express-Pro/100+ Server, TTSOLO1, Moxa, 2940UW (opt.), Dongle Flex-Id7, Plextor 8/20. SCSI-CD-ROM	25.10.99 Start 02.06.00 new graphics adapter G200 06.09.00 new CD-W Plextor 12/4/32 04.04.01 new CD-W Plextor PX-W1210TS (12/10/32)	VA11C/VA43Q VA12B/VA47S VA15A/VA47V VA21C/VB10J	7127140
Primergy470: 2*850MHz, 2GB, 18+18+36GB HDD G200 8MB, 2*Intel Fast-Ether-Express-Pro/100+ Server, TTSOLO1, Moxa, 2940UW (opt.), Dongle Flex-Id8, Plextor 12/4/32. SCSI-CD-ROM	03.01.01 Start 29.03.01 new CD-W Plextor PX-W1210TS (12/10/32)	VA12B/VA47S VA15A/VA47V VA21C/VB10J	7128148
Celsius670 VA12: 2*1,7GHz (P4-Xeon), 2GB, 18+18+36GB HDD, Matrox G200 PCI, 2*Intel Pro 100+ Server, 1*Audio Codec97 compatible onboard, 1*Adaptec 29160N (for HDD und CD-R), Moxa, Dongle Flex-Id8. Plextor 12/10/32. IDE-CD-ROM	15.11.01 Start (Compromise with VA12, approx. 80 systems on site will be replaced)	VA12B/VA47S	7129963
Celsius670 2*1,7GHz (P4-Xeon), 2GB, 18+18+36GB HDD, Quadro2 64MB, 1*Intel 82550 LAN Controller onboard, 1*Intel Ether-Express- Pro/100S, 1*Audio Codec97 compatible onboard, 1*Adaptec 29160N (for CD-R), Moxa, 2940UW (opt.), Dongle Flex-Id8, Plextor 12/10/32. IDE-CD-ROM	30.08.01 Start 02.01.02 basic host changed from Rev. 2B to 3 (corresponding ES1)	VA15A/VA47V VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25D	7129997
Celsius670/2200: 2*2,2GHz (P4-Xeon), 2GB, 18+18+73GB HDD, Elsa Gloria DCC, 1*Intel 82550 LAN Controller onboard, 1*Intel Ether- Express-Pro/100S, 1*Audio Codec97 compatible onboard, 1*Adaptec 29160N (for HDD), Moxa, 2940UW (opt.), Dongle Flex-Id8, Plextor PX-W4012TA (40X, IDE), IDE-CD-ROM	10.04.02 Start	VA21A/VB10I VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7129914
Celsius R610/3066 2*3GHz (P4-Xeon), 2GB, 36+36+73GB HDD, graphics adapter: Elsa Gloria DCC, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Intel Pro/1000 MT, 1*Audio Codec97 compatible onboard, Moxa, 2940UW (opt.for ext. MOD), Dongle Flex-Id8, Plextor PX-W4824TA (48X, IDE), IDE-CD-ROM (48X)	Start 06/03	VA21B-revision B/VB10J VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7712008

Uncontrolled copy!

Host-Configuration	Changes during life-time	released Mrease/syngo	Basic Host (IVK)
Celsius R610/3066-980 VA21: 2*3GHz (P4-Xeon), 2GB (2*1GB), 36+36+73GB HDD, graphics adapter: Quadro4 980 XGL, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Intel Pro/1000 MT, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), Dongle Flex-Id8, Plextor PX-W5224TA (52X, IDE), IDE-DVD-ROM	Start 01/04	VA21B-revision B/VB10J VA21C/VB10J additional graphic driver-CD; VA23A-revision B/VB10J additional graphic driver-CD; VA25A / VD20M/N current Bios-CD: VA25D	8618584
Celsius R610/3066-980: 2*3GHz (P4-Xeon), 2GB (2*1GB), 36+36+73GB HDD, graphics adapter: Quadro4 980 XGL, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Intel Pro/1000 MT, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-W5224TA (52X, IDE), IDE-DVD-ROM	Start M08/04 with VA25A	VA25A / VD20M/N current Bios-CD: VA25F	7712024
Celsius R610-980: 2*3GHz (P4-Xeon), 2GB (2*1GB), 36+36+73GB HDD, graphics adapter: Quadro4 980 XGL, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Intel Pro/1000 MT, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-W5224TA (52X, IDE), IDE-DVD-ROM	Start 04/04 with Avanto	VB11A / VD20L VB11D / VD20M/N VB12A / VD20M/N current Bios-CD: VB11G	8379997
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 2GB (2*1GB), 73+73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Syskonnect GBit Ethernet, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716A (16X, IDE; DVD+-R/RW), IDE-DVD-ROM	Start CW25/05 for the Symphonie-line, Symphony and corresponding Upgrades, Concerto, Allegra, Trio, Novus, C!	VA25A-Rev B / VD20M/N (COEM VD10G) current Bios-CD: VA25F	10049280
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 3GB (2*1GB + 2*512MB), 73+73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Syskonnect GBit Ethernet, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716A (16X, IDE; DVD+-R/RW), IDE-DVD-ROM	Start April 2007 for the Symphonie-line, Symphony and corresponding Upgrades, Concerto, C! Restverbrauch R630	VA30A current Bios-CD: VA30D 103 92 781	10304172

Uncontrolled copy!

Host-Configuration	Changes during life-time	released Mrease/syngo	Basic Host (IVK)
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 2GB (2*1GB), 73+73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Syskonnect GBit Ethernet, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716A (16X, IDE; DVD+-R/RW) IDE-DVD-ROM	Start E06/05 for the Avanto-line, Avanto, Espree, SaTS and TaTS	VB11D-Rev B / VD20M/N (COEM VD10G) VB12A-Rev B / VD20M/N (COEM VD10G) current Bios-CD: VB11G	10049284
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 3GB (2*1GB/2*512MB), 73+73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Syskonnect GBit Ethernet, 1*Audio Codec97 compatible onboard, Moxa, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716 (16X, IDE; DVD+-R/RW) or Plextor PX-760A, IDE-DVD-ROM	Start E07/06 for the Avanto-line, Avanto, Espree, SaTS and TaTS	VB13A current Bios-CD: 8880358 VB13C	10142434
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 4GB (2*1GB/4*512MB), 73+73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Syskonnect GBit Ethernet, 1*Audio Codec97 compatible onboard, Moxa, USB-Dongle Flex-Id9, Plextor PX-716 (16X, IDE; DVD+-R/RW) or Plextor PX-760A IDE-DVD-ROM	Built by upgrading 10142434 by 1 Gbyte	VB15A current Bios-CD: 10497972 VB15H	10392498
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (4*1GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1GBit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, Moxa or 2 * 2 RS232 board, USB-Dongle Flex-Id9, Plextor PX-760A IDE-DVD-ROM	Start 02/07 for the Avanto-line, Avanto, Espree, SaTS and TaTS 2.10.2007: new DVD-burner PX-800A HOST MR005 R640	VB13A Rev. B current Bios-CD: VB13E	10143228
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),3GB (2*1GB + 2*512MB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1GBit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, Moxa or 2 * 2 RS232 board, (SCSI-Contr. for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-760A IDE-DVD-ROM	Start 7.08.2007 for the Sympony line, Symphony, Harmony, Concerto, Sonata, Allegra, Trio, Novus, Cl, incl. all Upgrades and Evolve 2.10.2007 new DVD-burner PX-800A HOST MR 059 R640	VA30A current Bios-CD: VA30D	10143230

Uncontrolled copy!

Host-Configuration	Changes during life-time	released Mrease/syngo	Basic Host (IVK)
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (4*1GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1GBit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, Moxa or 2 * 2 RS232 board, <u>USB-Dongle Flex-Id9, Plector PX-760A, IDE-DVD-ROM</u>	Start CO ME 12.07.2007 Tim line, Avanto, Espree, SATS, TATS, Verio (VB15B), and Evolve 2.10.2007 new DVD-burner PX-800A HOST MR 005 R640	VB15A (VB15B) current Bios-CD: 104 97 972 VB15H	10145155
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (4*1GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1GBit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, Moxa or 2 * 2 RS232 board, <u>USB-Dongle Flex-Id9, Plector PX-800A, IDE-DVD-ROM</u>	Start KW22/08 as Master and Slave of TX-Array 3T and 7T MR TX-Master R640	VB15A current Bios-CD: 104 97 972 VB15H	10145155
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (4*1GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1GBit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, <u>USB-Dongle Flex-Id9, Plector PX-760A, IDE-DVD-ROM</u>	Start 2.Quartal 2008 for Essenza 2.10.2007: new DVD-burner PX-800A Host aXXess60 R640	VC11A current Bios-CD: 103 92 782 VC11C	10144293
Celsius R650: 2* 2,83 GHz E5440 (Intel-Seaburg (Quad-Core),4GB (2*2GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1GBit Ethernet Intel 82563EB Gilgal , 1* Audio Realtek ALC888 on board, Moxa, (SCSI-Contr. for opt. ext. MOD), USB-Dongle Flex-Id9, SATA DVD-burner, <u>SATA DVD-ROM</u>	Start Nov. 2008 for the Sympony line incl. all Upgrades and Evolve MR Host 059 R650	VA30A Rev.B current Bios-CD: 10497973 VA30E	10497898
Celsius R650 2* 2,83 GHz E5440 (Intel-Seaburg (Quad-Core),4GB (2*2GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1GBit Ethernet Intel 82563EB Gilgal , 1* Audio Realtek ALC888 on board, Moxa <u>USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM</u>	Start Nov. 2008 for the Tim line, Avanto, Espree, SATS, TATS and Evolve, sowie Verio (VB15B) Host MR005 R650	VB15A Rev.B (VB15B Rev.B) current Bios-CD: 10497972 VB15H VB17A current Bios-CD: 10498240 VB17A	10497894
Celsius R650 2* 2,83 GHz E5440 (Intel-Seaburg (Quad-Core),4GB (2*2GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1GBit Ethernet Intel 82563EB Gilgal , 1* Audio Realtek ALC888 on board, Moxa <u>USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM</u>	Start Nov. 08 as Master and Slave with TX-Array 3T and 7T MR TX-Master R650	VB15A Rev.B current Bios-CD: 10497972 VB15H	10497894

Uncontrolled copy!

Host-Configuration	Changes during life-time	released Mrease/syngo	Basic Host (IVK)
HP xw4600: 1*2,66GHz Intel Core2Quad Q9450, 4GB (2*2GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1 Gbit Ethernet, 1* Audio on board, USB-Dongle Flex-Id9, SATA DVD-burner, SATA-DVD-ROM	Start KW10/09 for Essenza 8 channel MRC011 HP XW4600	VC11A Rev.B VC13A current Bios-CD: 10498026 VC11D	10392837
HP xw4600: 1*2,66GHz Intel Core2Quad Q9450, 4GB (2*2GB DDR2 FB-DIMM) 73+73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1 Gbit Ethernet, 1* Audio on board, USB-Dongle Flex-Id9, SATA DVD-burner, SATA-DVD-ROM	Planned Start KW21/ 09 for C2! MRC029 HP XW4600	VC12A current Bios-CD: VC11D 10498026	10392837
HP z400: 1*2,66GHz IntelW3520, 4 GB (2*2GB DDR3), 146+146+146 GB SAS, graphics adapter nVidia FX3800, 2 * 1 Gbit Ethernet (1* onboard, 1* extra pcb), 1* Audio on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	Planned Start KW05/10 MRC 059 HP z400	VA35A	10590536
Celsius M470 1*2,66GHz Intel W3520, 6 GB (3 *2 GB DDR3) 146+146+146 GB SAS, graphics adapter nVidia FX3800, 2 * 1 Gbit Ethernet (1* onboard, 1* extra pcb), 1* Audio on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	Planned Start KW05/10	VB17A Rev. B	10498078
HP z400: 1*2,66GHz IntelW3520, 4 GB (2*2GB DDR3), 146+146+146 GB SAS, graphics adapter nVidia FX3800, 2 * 1 Gbit Ethernet (1* onboard, 1* extra pcb), 1* Audio on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	Planned Start KW05/10 MRC011/029 HP z400	VC15A	10590541
Celsius M470: 1*2,66GHz Intel W3520, 6 GB (3*2 GB DDR3) 146+146+146 GB SAS, graphics adapter nVidia FX3800, 2 * 1 Gbit Ethernet (1* onboard, 1* extra pcb), 1* Audio on board, SATA DVD-burner, SATA DVD-ROM	Basic host MR AWP 098 M470	VD11A	10498275

Uncontrolled copy!

MRSC-Configuration	Changes during life-time	released Mrease/syngo	Basic Host
Primergy470: 2*550MHz, 2GB, 9+9GB HDD Mill-II 8MB, 1*Intel Fast-Ether-Express-Pro/100+ Server, TTSOLO1, 2940UW (opt.), Dongle Flex-Id7, Plextor 8/20, SCSI-CD-ROM	25.10.99 Start 02.06.00 new graphics adapter G200 06.09.00 new CD-W Plextor 12/4/32	VA11C/VA43Q VA12B/VA47S VA15A/VA47V VA21C/VB10J	7128387
Primergy470: 2*850MHz, 2GB, 18+18GB HDD G200 8MB, 1*Intel Fast-Ether-Express-Pro/100+ Server, TTSOLO1, 2940UW (opt.), Dongle Flex-Id8, Plextor 12/4/32, SCSI-CD-ROM	25.01.01 Start 10.04.01 new CD-W Plextor PX-W1210TS (12/10/32)	VA12B/VA47S VA15A/VA47V VA21C/VB10J	7128387
Celsius670 VA12: 2*1,7GHz (P4-Xeon), 2GB, 18+18GB HDD, Matrox G200 PCI, 1*Intel Pro 100+ Server, 1*Audio Codec97 compatible onboard, 1*Adaptec 29160N (for HDD and CD-R), 2940UW (opt.), Dongle Flex-Id8, Plextor 12/10/32, IDE-CD- ROM	15.11.01 Start	VA12B/VA47S	7129971
Celsius670: 2*1,7GHz (P4-Xeon), 2GB, 18+18GB HDD, Quadro2 64MB, 1*Intel 82550 LAN Controller onboard, 1*Audio Codec97 compatible onboard, 1*Adaptec 29160N (for CD-R), 2940UW (opt.), Dongle Flex-Id8, Plextor 12/10/32, IDE- CD-ROM	30.08.01 Start 02.11.01 HDD-configuration changed from 18+18 to 18+36 Adaption to MM-WS) 02.01.02 basic host changed from Rev. 2B to 3 (corresponding ES1)	VA15A/VA47V VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7129989
Celsius670/2200: 2*2,2GHz (P4-Xeon), 2GB, 18+73GB HDD, Elsa Gloria DCC, 1*Intel 82550 LAN Controller onboard, 1*Audio Codec97 compatible onboard, 1*Adaptec 29160N (for HDD), 2940UW (opt.), Dongle Flex-Id8, Plextor PX- W4012TA (40X, IDE), IDE-CD-ROM	11.04.02 Start	VA21A/VB10I VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7129922
Celsius R610/3066: 2*3GHz (P4-Xeon), 2GB, 36+73GB HDD, graphics adapter: Elsa Gloria DCC, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, 2940UW (opt.for ext. MOD), Dongle Flex-Id8, Plextor PX-W4824TA (48X, IDE), IDE-CD-ROM (48X)	Start 06/03	VA21B-revision B/VB10J VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7712016

Uncontrolled copy!

MRSC-Configuration	Changes during life-time	released Mrease/syngo	Basic Host
Celsius R610/3066-980 VA21: 2*3GHz (P4-Xeon), 2GB (2*1GB), 36+73GB HDD, graphics adapter: Quadro4 980 XGL, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), Dongle Flex- Id8, Plextor PX-W5224TA (52X, IDE), IDE-DVD-ROM	Start 01/04	VA21B-revision B/VB10J VA21C/VB10J additional graphic driver-CD; VA23A-revision B/VB10J additional graphic driver-CD; VA25A / VD20M/N current Bios-CD: VA25F	8618592
Celsius R610/3066-980: 2*3GHz (P4-Xeon), 2GB (2*1GB), 36+73GB HDD, graphics adapter: Quadro4 980 XGL, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-W5224TA (52X, IDE), IDE-DVD-ROM	Start M08/04 with VA25A	VA25A / VD20M/N current Bios-CD: VA25F	7712032
Celsius R610-980: 2*3GHz (P4-Xeon), 2GB (2*1GB), 36+73GB HDD, graphics adapter: Quadro4 980 XGL, 1*Intel i82540 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-W5224TA (52X, IDE), IDE-DVD-ROM	Start 04/04 with Avanto	VB11A / VD20L VB11D / VD20M/N VB12A / VD20M/N current Bios-CD: VB11G	8379989
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 2GB (2*1GB), 73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716A (16X, IDE; DVD+-R/RW), IDE-DVD-ROM	Start E06/05 for the Symphonie-line, Symphony and corresponding Upgrades, Concerto, Allegra, Trio, Novus, C! and Evolve	VA25A-Rev B / VD20M/N (COEM VD10G) current Bios-CD: VA25F	10049282
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 3GB (2*1GB + 2*512MB), 73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716A (16X, IDE; DVD+-R/RW), IDE- DVD-ROM	Start April 2007 for the Symphonie-line, Symphony and corresponding Upgrades, Concerto, C! and Evolve using up R630s	VA30A current Bios-CD: VA30D 10392781	10304173
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 2GB (2*1GB), 73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716A (16X, IDE; DVD+-R/RW), IDE-DVD-ROM	Start E06/05 for the Tim-line, d.h. Avanto, Espre, SaTS and TaTS	VB11D-Rev B / VD20M/N (COEM VD10G) VB12A-Rev B / VD20M/N (COEM VD10G) current Bios-CD: VB11F	10049285

Uncontrolled copy!

MRSC-Configuration	Changes during life-time	released Mrease/syngo	Basic Host
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 3GB (2*1GB+2*512MB), 73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, Slotblech (for opt. ext. MOD), USB-Dongle Flex-Id9, Plextor PX-716 (16X, IDE; DVD+-R/RW) or <u>Plextor PX-760A, IDE-DVD-ROM</u>	Start E07/06 for Avanto, Espree, SaTS and TaTS	VB13A/syngo MR B13 current Bios-CD: VB13C 8880358 P9901	10142435
Celsius R630/3600: 2*3,6GHz (P4-Xeon), 4GB (2*1GB+4*512MB), 73+73GB HDD, graphics adapter: Nvidia FX3400, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*Audio Codec97 compatible onboard, USB-Dongle Flex-Id9, Plextor PX-716 (16X, IDE; DVD+-R/RW) or Plextor PX-760A, IDE-DVD-ROM	Built by upgrading 101 42 433 by 1 Gbyte	VB15A current Bios-CD: VB15H 10497972	103 92 499
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),3GB (2*1GB + 2*512MB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1Gbit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, (SCSI-Contr. for opt. ext. MOD), <u>USB-Dongle Flex-Id9, Plextor PX-760A, IDE-DVD-ROM</u>	Start 4/07 for the Symphonie-line, Symphony, Harmony, Sonata, Concerto, Allegro, Trio, C!, Novus, incl. all Upgrades and Evolve H2 2007: new DVD-burner PX-800A	VA30A current Bios-CD: VA30D 10392781	10143231
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),3GB (2*1GB + 2*512MB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1Gbit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, <u>USB-Dongle Flex-Id9, Plextor PX-760A, IDE-DVD-ROM, SCSI-Controller 29320A-R</u>	Optional MOD Reading Station for customers needing to read SPI MOD media, and performing the VB15 Evolve . H2 2007: new DVD-burner PX-800A	VA30A current Bios-CD: VA30C 10392781	10392691
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (2*1GB + 2*512MB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1Gbit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, <u>USB-Dongle Flex-Id9, Plextor PX-760A, IDE-DVD-ROM</u>	Start 1. Quartal 2007 for the TIM-line, Avanto, Espree, SaTS and TaTS H2 2007: new DVD-burner PX-800A	VB13A Rev. B current Bios-CD: VB13E 10304146	10143229
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (4*1GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1Gbit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, <u>USB-Dongle Flex-Id9, Plextor PX-760A, IDE-DVD-ROM</u>	Start 7/07 for the Tim line, Avanto, Espree, SATS,TATS and Evolve H2 2007: new DVD-burner PX-800A	VB15A (VB15B) current Bios-CD: VB15I 10498183	10145156

Uncontrolled copy!

MRSC-Configuration	Changes during life-time	released Mrease/syngo	Basic Host
Celsius R640: 2*2,6GHZ (Intel-Woodcrest),4GB (4*1GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3500, 2 * 1GBit Ethernet onboard Intel ESB2, 1* Audio Realtek ALC888 on board, USB-Dongle Flex-Id9, Plector PX-760A, IDE-DVD-ROM	Start 2.Quartal 2008 for Essenza H2 2007: new DVD-burner PX-800A MRSC 011 R640	VC11A current Bios-CD: VC11C 10392782	10144294
Celsius R650: 2* 2,83 GHz E5440 GHz (Intel-Seaburg (Quad-Core),4GB (2*2GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1GBit Ethernet Intel 82563EB Gilgal , 1* Audio Realtek ALC888 on board, (SCSI-Contr. for opt. ext. MOD), USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	Start Nov. 2008 for the Sympony line incl. all Upgrades and Evolve MRSC 059 R650	VA30A Rev.B current Bios-CD: VA30E 10497973	10497899
Celsius R650: 2* 2,83 GHz E5440 GHz (Intel-Seaburg (Quad-Core),4GB (2*2GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1GBit Ethernet Intel 82563EB Gilgal , 1* Audio Realtek ALC888 on board, (SCSI-Contr. for opt. ext. MOD), USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	Optional MOD Reading Station for customers needing to read SPI MOD media, and performing a VB15/VB17 Evolve.	VA30A Rev.B current Bios-CD: VA30E 10497973	10392803
Celsius R650: 2* 2,83 GHz E5440 (Intel-Seaburg (Quad-Core),4GB (2*2GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1GBit Ethernet Intel 82563EB Gilgal , 1* Audio Realtek ALC888 on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	Start Nov. 2008 for Avanto, Espree, SATS, TATS, Verio (VB15B), and Evolve MRSC MR005 R650	VB15A Rev.B (VB15B Rev.B) current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A 10498240	10497895
HP xw4600: 1*2,66GHz Intel Core2Quad Q9450, 4GB (2*2GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3700, 1 x 1 Gbit Ethernet 1* Audio on board, USB-Dongle Flex-Id9, SATA DVD-burner, SATA-DVD-ROM	Planned Start KW10/09 for Essenza 8 channel MRSC011 HP XW4600	VC11A Rev.B VC13A current Bios-CD: VC11D 10498026	10392838

Uncontrolled copy!

MRSC-Configuration	Changes during life-time	released Mrease/syngo	Basic Host
HP xw4600: 1*2,66GHz Intel Core2Quad Q9450, 4GB (2*2GB DDR2 FB-DIMM) 73+73 GB SAS, graphics adapter: Nvidia FX3700, 2 x 1 Gbit Ethernet, 1* Audio on board, USB-Dongle Flex-Id9, SATA DVD-burner, SATA-DVD-ROM	Planned Start KW21/ 09 for C2! MRSC029 HP XW4600	VC12A current Bios-CD: VC11D 10498026	10392838
HP z400 1*2,66GHz Intel W3520, 4 GB (2*2 GB DDR3) 146+146 GB SAS, graphics adapter nVidia FX3800, 1 * 1 Gbit Ethernet (1* onboard), 1* Audio on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	<i>MRSC 059 HP z400</i>	VA35A	10590537
Celsius M470 1*2,66GHz Intel W3520, ? GB (x*2 GB DDR3) 146+146 GB SAS, graphics adapter nVidia FX3800, 1 * 1 Gbit Ethernet (1* onboard), 1* Audio on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM		VB17A Rev. B	10498079
HP z400 1*2,66GHz Intel W3520, 4 GB (2*2 GB DDR3) 146+146 GB SAS, graphics adapter nVidia FX3800, 1 * 1 Gbit Ethernet (1* onboard), 1* Audio on board USB-Dongle Flex-Id9, SATA DVD-burner, SATA DVD-ROM	<i>MR011/029 MRSC z400</i>	VC15A	10590542
Celsius M470: 1*2,66GHz Intel W3520, 6 GB (3*2 GB DDR3) 146+146 GB SAS, graphics adapter nVidia FX3800, 1 * 1 Gbit Ethernet (1* onboard), 1* Audio on board, SATA DVD-burner, SATA DVD-ROM	<i>basic host MR WP 098 M470</i>	VD11A	10498276

Uncontrolled copy!

IR-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
Alpha 21264: 1*500MHz (4MB L2), 512MB, 9+[1+(3)]*9GB HDD (10k) Combo-Card, 1*PCI-Receiver, 1* Keyboard-/Mouse-Dummy	25.10.99 Start 13.04.00 NV-RAM updated 20.11.00 PCI-Receiver AS01	VA11C/VA43Q VA12B/VA47S VA15A/VA47V VA21C/VB10J	5651455
Celsius 460 P4-TT: 1*1,5GHz (P4), 1GB (+1GB optional), 18+4*18GB HDD (in extra tower), GM1000, 1*Intel Pro/100, 1*Adaptec 29160N, 1*PCI-Receiver, IDE-CD-ROM, 1* Keyboard-/Mouse-Dummy	28.05.01 Start (27.8.01 in assembling line)	VA12B-Imager P4/VA47S VA15A/VA47V VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7129070
Celsius670: 1*1,7GHz (P4-Xeon), 1GB (+1GB optional), 18+4*18GB HDD, GM1000, 1*Intel 82550 LAN Controller onboard, 1*PCI-Receiver, IDE-CD-ROM, 1* Keyboard-/Mouse-Dummy	30.08.01 Start 02.01.02 basic host changed from Rev. 2B to 3 (corresponding to ES1)	VA15A/VA47V VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7130011
Celsius670/2200: 1*2,2GHz (P4-Xeon), 1GB (+1GB optional), 18GB/10k+(4*18GB/7,2k) HDD, GM1000, 1*Intel 82550 LAN Controller onboard, 1*Adaptec 29160N (for HDD), 1*PCI-Receiver, IDE-CD-ROM, 1* Keyboard-/Mouse-Dummy	11.04.02 Start	VA21A/VB10I VA21C/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7130268
Celsius R610/3066: 1*3GHz (P4-Xeon), 1GB (+1GB optional), 36GB/10k+(4*36GB/10k) HDD, graphics adapter: Matrox G450, 1*Intel i82540 Gbit-LAN Controller onboard, 1*PCI-Receiver, IDE-CD-ROM (48X), 1* Keyboard-/Mouse-Dummy	Start 06/03 Start 01/04 for Trio	VA21B-revision B/VB10J VA21C/VB10J VA23A-revision B/VB10J VA25A / VD20M/N current Bios-CD: VA25E	7711968
Celsius R610/3066-2X: 2*3GHz (P4-Xeon), 1GB (+1GB optional), 36GB/10k+(4*36GB/10k) HDD, graphics adapter: Matrox G450, 1*Intel i82540 Gbit-LAN Controller onboard, 1*PCI-Receiver, IDE-DVD-ROM, 1* Keyboard-/Mouse-Dummy	Start M08/04 with VA25A	VA25A / VD20M/N current Bios-CD: VA25E	7712057
Celsius R630/3600: 2*3,6GHz (P4-Xeon), SPECint2000= 2*1703, SPECfp2000= 2*1765, 1GB (+1GB optional), 73GB/10k+ (4*73GB/10k) HDD, graphics adapter: Nvidia NVS 280, 1*Broadcom BCM5751 Gbit-LAN Controller onboard, 1*PCI-Receiver, IDE-DVD-ROM, 1* Keyboard-/Mouse-Dummy	Start KW25/05 for the Symphony-line, Symphony and according Upgrades, Concerto, Allegra, Trio, Novus, C! Updated to VA30A onsite	VA25A-Rev B / VD20M/N (COEM VD10G) current Bios-CD: VA25F VA30A current Bios-CD: VA30E 10392781	10049278
Celsius M450: 1*2,66 GHz Intel Core 2 Duo E6700, SPECint2000= 2847, SPECfp2000= 2708, 1887 FFTs/sec, 1 GB DDR2(+1GB DDR2 optional), 73GB/15K SAS-Disc+(2*73GB/15K SAS-Discs), graphics adapter: Nvidia NVS285, 1*Broadcom BCM5751 Gbit-LAN controller onboard, 1*PCI-Receiver, DVD-ROM, 1* Keyboard-/Mouse-Dummy	Start 08/07 for the Symphony-line, Symphony and corresponding Upgrades, Concerto, Allegra, Trio, Novus, C!	VA30A VA30A Rev.B current Bios-CD: VA30E 10392781	10143232
HP xw4600: 1*3.00GHz Intel Core2Duo E8400, 2x1GB, 2*73GB/15K SAS-Discs, graphics adapter: Nvidia NVS290, 1*PCI-Receiver, DVD-ROM, 1* Keyboard-/Mouse-Dummy	imager 059 xw4600 for the Symphony-line	VA30A Rev. B current Bios-CD: VA30E 10497973	10497887

Uncontrolled copy!

IR-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
imager MR 005 Step1: 2*3GHz/1MB-L3-Cache (P4-Xeon), 3,5GB, 18GB/15k+(4*18GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, 1*PCI-RX mit 1*Sigi-Distrib, IDE-DVD-ROM, no FDD, 1* Keyboard-/Mouse-Dummy	Start 04/04 for Avanto	VB11A / VD20L VB11D / VD20M/N current Bios-CD: VB11E	7714004
imager MR 005-Opteron Step2 LE: (Matno.: 8879905, 8 GB, 103 04 092, 16 GB) 2*2,2GHz/1MB-L2-Cache (AMD-Opteron 248), SPECint2000= 2858, SPECfp2000= 2794, 8GB RAM, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, 1*PCI-RX mit 1*Sigi-Distrib, IDE-DVD-ROM, no FDD	Start 11/04 for Avanto (also used with Espree, SaTS and TaTS). 16 GB with VB13A-SW as sparepart only Avanto 005 : 25 222 Espree 022 : 30 011 TaTS 092 : 35 101 Upgr TRIO 092 : 35 001 SaTS 094 : 37 001	VB11D / VD20M/N VB12A / VD20M/N bzw. VB11D-Rev B / VD20M/N (COEM VD10G) VB12A-Rev B / VD20M/N (COEM VD10G) current Bios-CD: VB11H 10304233 bzw. for VB13A / VE30A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183	8879005
Imager MR 005 Step2 Standard (MCPro Multi2): 8 GB -> 32 channels with 2 * PCI_RX16 boards, 2 CPUs each at 2,6GHz/1MB-L2-Cache (AMD-Opteron 252), SPECint2000= 3430, SPECfp2000= 3353, 1250 FFTs/sec, Interprocessor-communication at 6.4 GByte/sec, 8 GB RAM, Memory Bandwith 11.9 GByte/sec, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change with VB13A 07/06 for Avanto, Espree, SaTS und TaTS Start 16 GB-versions via change with VB15A 07/07 for Avanto, Espree, SaTS and TaTS 8 GB: Avanto 005 : 25 997 Espree 022 : 30 238 TaTS 092 : 35 177 u. 35 175 Upgr TRIO 092 : 35 030 SaTS 094 : 37 025 16 GB: Avanto 005 : 26 446 Espree 022 : 30 465 TaTS 092 : 35 287 Upgr TRIO 092 : 35 049 SaTS 094 : 37 084	VB13A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A	10140755

Uncontrolled copy!

IR-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
Imager MR 005 Step2 Standard (MCPro Multi2): 8 GB -> 18 channels with 1 * PCI_RX16 and 1* PCI_RX16_8 board, 2 CPUs each at 2,6GHz/1MB-L2-Cache (AMD-Opteron 252), SPECint2000= 3430, SPECfp2000= 3353, 1250 FFTs/sec , Interprocessor-communication at 6.4 GByte/sec, 8 GB RAM, Memory Bandwith 11.9 GByte/sec, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change with VB13A 07/06 for Avanto, Espree, SaTS und TaTS Start 16 GB-versions via change with VB15A 07/07 for Avanto, Espree, SaTS and TaTS 8 GB: Avanto 005 : 25 997 Espree 022 : 30 238 TaTS 092 : 35 177 u. 35 175 Upgr TRIO 092 : 35 030 SaTS 094 : 37 025 16 GB: Avanto 005 : 26 446 Espree 022 : 30 465 TaTS 092 : 35 287 Upgr TRIO 092 : 35 049 SaTS 094 : 37 084	VB13A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A	10140754
Imager MR 005 Step2 Standard (MCPro Multi2): 8 GB -> 8 channels with 1* PCI_RX16_8 board, 2 CPUs each at 2,6GHz/1MB-L2-Cache (AMD-Opteron 252), SPECint2000= 3430, SPECfp2000= 3353, 1250 FFTs/sec , Interprocessor-communication at 6.4 GByte/sec, 8 GB RAM, Memory Bandwith 11.9 GByte/sec, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change with VB13A 07/06 for Avanto, Espree, SaTS und TaTS Start 16 GB-versions via change with VB15A 07/07 for Avanto, Espree, SaTS and TaTS 8 GB: Avanto 005 : 25 997 Espree 022 : 30 238 TaTS 092 : 35 177 u. 35 175 Upgr TRIO 092 : 35 030 SaTS 094 : 37 025 16 GB: Avanto 005 : 26 446 Espree 022 : 30 465 TaTS 092 : 35 287 Upgr TRIO 092 : 35 049 SaTS 094 : 37 084	VB13A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A	10140753
Imager MR 005 Step2 Standard (MCPro Multi2): 16 GB -> 32 channels with 2 * PCI_RX16 boards,, 2 CPUs each at 2,6GHz/1MB-L2-Cache (AMD-Opteron 252), SPECint2000= 3430, SPECfp2000= 3353, 1250 FFTs/sec , Interprocessor-communication at 6.4 GByte/sec, 8 GB RAM, Memory Bandwith 11.9 GByte/sec, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change with VB13A 07/06 for Avanto, Espree, SaTS und TaTS Start 16 GB-versions via change with VB15A 07/07 for Avanto, Espree, SaTS and TaTS 8 GB: Avanto 005 : 25 997 Espree 022 : 30 238 TaTS 092 : 35 177 u. 35 175 Upgr TRIO 092 : 35 030 SaTS 094 : 37 025 16 GB: Avanto 005 : 26 446 Espree 022 : 30 465 TaTS 092 : 35 287 Upgr TRIO 092 : 35 049 SaTS 094 : 37 084	VB13A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A	10304091

Uncontrolled copy!

MR-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
Imager MR 005 Step2 Standard (MCPro Multi2): 16 GB -> 18 channels with 1 * PCI_RX16 and 1* PCI_RX16_8 board, 2 CPUs each at 2,6GHz/1MB-L2-Cache (AMD-Opteron 252), SPECint2000= 3430, SPECfp2000= 3353, 1250 FFTs/sec , Interprocessor-communication at 6.4 GByte/sec, 8 GB RAM, Memory Bandwith 11.9 GByte/sec, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change with VB13A 07/06 for Avanto, Espree, SaTS und TaTS Start 16 GB-versions via change with VB15A 07/07 for Avanto, Espree, SaTS und TaTS 8 GB: Avanto 005 : 25 997 Espree 022 : 30 238 TaTS 092 : 35 177 u. 35 175 Upgr TRIO 092 : 35 030 SaTS 094 : 37 025 16 GB: Avanto 005 : 26 446 Espree 022 : 30 465 TaTS 092 : 35 287 Upgr TRIO 092 : 35 049 SaTS 094 : 37 084	VB13A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A	10304090
Imager MR 005 Step2 Standard (MCPro Multi2): 16 GB -> 8 channels with 1* PCI_RX16_8 board) 2 CPUs each at 2,6GHz/1MB-L2-Cache (AMD-Opteron 252), SPECint2000= 3430, SPECfp2000= 3353, 1250 FFTs/sec , Interprocessor-communication at 6.4 GByte/sec, 8 GB RAM, Memory Bandwith 11.9 GByte/sec, 36GB/15k+(4*36GB/15k) HDD, 1* Adaptec 2200 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change with VB13A 07/06 for Avanto, Espree, SaTS und TaTS Start 16 GB-versions via change with VB15A 07/07 for Avanto, Espree, SaTS und TaTS 8 GB: Avanto 005 : 25 997 Espree 022 : 30 238 TaTS 092 : 35 177 u. 35 175 Upgr TRIO 092 : 35 030 SaTS 094 : 37 025 16 GB: Avanto 005 : 26 446 Espree 022 : 30 465 TaTS 092 : 35 287 Upgr TRIO 092 : 35 049 SaTS 094 : 37 084	VB13A current Bios-CD: VB13E 10304146 VB15A current Bios-CD: VB15I 10498183 VB17A current BIOS CD: VB17A	10304089
Imager MR 005 Step2 High End (MCPro Multi8): 32 channels -> 2 * PCI_RX16 boards 8 CPUs each at 2,2GHz with 2 MB-L2-Cache (4*AMD-Opteron 875, Dual-Core), SPECint2000= ca. 8988, SPECfp2000= ca. 9060, 3768 FFTs/sec, Interprozessor-communication with 12.8 GByte/sec, 16GB RAM, Memory Bandwith 21.3 GByte/sec, 73GB/15k+(4*73GB/15k) HDD, 1* Adaptec 2230 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM-drive, no FDD		VB13A current Bios-CD: VB13E 103 04 146 P9901 VB15A current Bios-CD: VB15I 104 98 183	8880200
Imager MR 005 Step2 High End (MCPro Multi8): 18 channels -> 1 * PCI_RX16 and 1 * PCI_RX16_8 board 8 CPUs each at 2,2GHz with 2 MB-L2-Cache (4*AMD-Opteron 875, Dual-Core), SPECint2000= ca. 8988, SPECfp2000= ca. 9060, 3768 FFTs/sec, Interprozessor-communication with 12.8 GByte/sec, 16GB RAM, Memory Bandwith 21.3 GByte/sec, 73GB/15k+(4*73GB/15k) HDD, 1* Adaptec 2230 Raid-Controller for Rawdata-Disk (System-disk connected to onboard Adaptec AIC-7902 U320-SCSI-Controller), onboard Grafik: ATI Rage XL, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM-drive, no FDD		VB17A current BIOS CD: VB17A 104 98 240	10140719

Uncontrolled copy!

IR-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
Imager MR 005 Step3 Standard (MCPro Multi4): 8 GB -> 32 channels with 2 * PCI_RX16 boards, 2 Dual-Core-CPU's each at 2,4GHz/2x1MB-L2-Cache (AMD-Socket-F-Opteron 2216), SPECint2000= ???, SPECfp2000= ???, 1736 FFTs/sec , 73GB/15k+(2*73GB/15k) SAS-HDD, onboard Grafik, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change 10/07 for Avanto, Espree, SaTS und TaTS Avanto 005 : 26 536 Espree 022 : 30 502 TaTS 092 : 35 308 Upgr TRIO 092 : 35 050 SaTS 094 : 37 098	VB15A current Bios-CD: VB15I 104 98 183 VB17A current BIOS CD: VB17A 104 98 240	10144829
Imager MR 005 Step3 Standard (MCPro Multi4): 8 GB -> 18 channels with 1 * PCI_RX16 and 1* PCI_RX16_8 board, 2 Dual-Core-CPU's each at 2,4GHz/2x1MB-L2-Cache (AMD-Socket-F-Opteron 2216), SPECint2000= ???, SPECfp2000= ???, 1736 FFTs/sec , 73GB/15k+(2*73GB/15k) SAS-HDD, onboard Grafik, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change 10/07 for Avanto, Espree, SaTS und TaTS Avanto 005 : 26 536 Espree 022 : 30 502 TaTS 092 : 35 308 Upgr TRIO 092 : 35 050 SaTS 094 : 37 098	VB15A current Bios-CD: VB15I 104 98 183 VB17A current BIOS CD: VB17A 104 98 240	10144828
Imager MR 005 Step3 Standard (MCPro Multi4): 8 GB -> 8 channels with 1* PCI_RX16_8 board, 2 Dual-Core-CPU's each at 2,4GHz/2x1MB-L2-Cache (AMD-Socket-F-Opteron 2216), SPECint2000= ???, SPECfp2000= ???, 1736 FFTs/sec , 73GB/15k+(2*73GB/15k) SAS-HDD, onboard Grafik, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change 10/07 for Avanto, Espree, SaTS und TaTS Avanto 005 : 26 536 Espree 022 : 30 502 TaTS 092 : 35 308 Upgr TRIO 092 : 35 050 SaTS 094 : 37 098	VB15A current Bios-CD: VB15I 104 98 183 VB17A current BIOS CD: VB17A 104 98 240	10144827
Imager MR 005 Step3 Standard (MCPro Multi4): 16 GB -> 32 channels with 2 * PCI_RX16 boards, 2 Dual-Core-CPU's each at 2,4GHz/2x1MB-L2-Cache (AMD-Socket-F-Opteron 2216), SPECint2000= ???, SPECfp2000= ???, 1736 FFTs/sec , 73GB/15k+(2*73GB/15k) SAS-HDD, onboard Grafik, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change 10/07 for Avanto, Espree, SaTS und TaTS Avanto 005 : 26 536 Espree 022 : 30 502 TaTS 092 : 35 308 Upgr TRIO 092 : 35 050 SaTS 094 : 37 098	VB15A current Bios-CD: VB15I 104 98 183 VB17A current BIOS CD: VB17A 104 98 240	10304088
Imager MR 005 Step3 Standard (MCPro Multi4): 16 GB -> 18 channels with 1 * PCI_RX16 and 1* PCI_RX16_8 board, 2 Dual-Core-CPU's each at 2,4GHz/2x1MB-L2-Cache (AMD-Socket-F-Opteron 2216), SPECint2000= ???, SPECfp2000= ???, 1736 FFTs/sec , 73GB/15k+(2*73GB/15k) SAS-HDD, onboard Grafik, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change 10/07 for Avanto, Espree, SaTS und TaTS Avanto 005 : 26 536 Espree 022 : 30 502 TaTS 092 : 35 308 Upgr TRIO 092 : 35 050 SaTS 094 : 37 098	VB15A current Bios-CD: VB15I 104 98 183 VB17A current BIOS CD: VB17A 104 98 240	10304087
Imager MR 005 Step3 Standard (MCPro Multi4): 16 GB -> 8 channels with 1* PCI_RX16_8 board) 2 Dual-Core-CPU's each at 2,4GHz/2x1MB-L2-Cache (AMD-Socket-F-Opteron 2216), SPECint2000= ???, SPECfp2000= ???, 1736 FFTs/sec , 73GB/15k+(2*73GB/15k) SAS-HDD, onboard Grafik, onboard Ethernet: Broadcom Gigabit, no CD/DVD-ROM, no FDD	Start via change 10/07 for Avanto, Espree, SaTS und TaTS Avanto 005 : 26 536 Espree 022 : 30 502 TaTS 092 : 35 308 Upgr TRIO 092 : 35 050 SaTS 094 : 37 098	VB15A current Bios-CD: VB15I 104 98 183 VB17A current BIOS CD: VB17A 104 98 240	10304086

Uncontrolled copy!

IR-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
Imager MR 005 Step 4 (MCProX), 8 GB -> 8 channels 1 Quad-Core CPU Intel Xeon E5440, 2. 83 GHz 146 GB/15k6+(2*146GB/15k6) SAS-HDD, onboard Grafik, onboard Ethernet, no CD-DVD-ROM	Start via change 07/09 for Avanto, Espree, SaTS and TaTS;	VB17A, current Bios-CD: VB17A 10498240	10498207
Imager MR 005 Step 4 (MCProX):16 GB -> 8 channels 1 Quad-Core CPU Intel Xeon E5440, 2. 83 GHz 146 GB/15k6+(2*146GB/15k6) SAS-HDD, onboard Grafik, onboard Ethernet, no CD-DVD-ROM	Start via change 07/09 for Avanto, Espree, SaTS and TaTS;	VB17A, current Bios-CD: VB17A 10498240	10498208
Imager MR 005 Step 4 (MCProX): 8 GB -> 18 channels 2 Quad-Core CPU Intel Xeon E5410, 2. 33 GHz 146 GB/15k6+(2*146GB/15k6) SAS-HDD, onboard Grafik, onboard Ethernet, no CD-DVD-ROM	Start via change 07/09 for Avanto, Espree, SaTS and TaTS;	VB17A, current Bios-CD: VB17A 10498240	10498209
Imager MR 005 Step 4 (MCProX): 16 GB -> 18 channels 2 Quad-Core CPU Intel Xeon E5410, 2. 33 GHz 146 GB/15k6+(2*146GB/15k6) SAS-HDD, onboard Grafik, onboard Ethernet, no CD-DVD-ROM	Start via change 07/09 for Avanto, Espree, SaTS and TaTS;	VB17A, current Bios-CD: VB17A 10498240	10498210
Imager MR 005 Step 4 (MCProX): 16 GB -> 32 channels 2 Quad-Core CPU Intel Xeon E5440, 2. 83 GHz 32 channel at 2.83 GHz(Intel E5440): 8576 FFTs/sec mit VB15B (VB17 not yet determined), 146 GB/15k6+(2*146GB/15k6) SAS-HDD, onboard Grafik, onboard Ethernet, no CD-DVD-ROM	Start via change 07/09 for Avanto, Espree, SaTS and TaTS;	VB17A, current Bios-CD: VB17A 10498240	10498211

Uncontrolled copy!

MARS-Configuration	Comments	released Mrease/syngo	Basic Host (IVK)
MARS: 2* 2,0GHZ (AMD Opteron), 8 GB, 8 channels with 1 * PCI_RX16_8 board, PCI_STAR, Fiber_IO, 73GB SAS, 2 * 1GBit Ethernet on board, on board graphic for debugging purposes)	Start End 1. quarter 2008	VC11A current Bios-CD: VC11C 10392782	10141449
MARS-C2!: (Matno.: 10497982) 2* AMD Opteron 2214 , 8 GB, 8 channels with 1 * PCI_RX16_8, PCI-STAR D4, Fiber_IO D17, 250GB SATA 7k	planned Start VC11A_SP3 Dec. 2008 planned Start VC12A Jan. 2009	VC11A_SP3 and VC12A current Bios-CD: VC11D 10498026	10497982
MaRS-16RX: (Matno.: 10498103) 2* AMD Opteron 2214 , 8 GB, 16 channels with 1 * PCI_RX16 D3, PCI-STAR D4, Fiber_IO D17, 250GB SATA 7k	Start End 1. quarter 2009	VC13A current Bios-CD: VC11D 10498026	10498103
MR098 MaRS2 48 GB, 48 channels 2 Quad-Core CPU Intel Nehalem E5540, 2.53 GHz, 1 x OPEC TX, 1 x OPEC RX, 4 x 146 GB SAS 48 channels, 2.53 GHz (Intel E5540): 12195 FFTs/sec with VD11A	Start End 1. quarter 2010	VD11A	10498360
MR098 MaRS2 64 GB, 64 channels 2 Quad-Core CPU Intel Nehalem W5580, 3.2 GHz, 1 x OPEC TX, 1 x OPEC RX, 5 x 146 GB SAS + 1 x GPGPU Tesla C1060 (48 channels, 2.53 GHz (Intel E5540): 12195 FFTs/sec with VD11A)			10498361
MR098 MaRS2 96 GB, 128 channels 2 Quad-Core CPU Intel Nehalem W5580, 3.2 GHz, 1 x OPEC TX, 2 x OPEC RX, 7? x 146 GB SAS + 1 x GPGPU Tesla C1060 (48 channels, 2.53 GHz (Intel E5540): 12195 FFTs/sec with VD11A)			10498362

Uncontrolled copy!

Software Versions syngo MR 2002B/2004A/2004V/2005E/2006T/B13/B15/B17/C11/C12, corresponding Hardware , and BIOS Versions.

Hardware			rel. Date for HW	Software			
				syngo MR 2002B	syngo MR 2004A	syngo MR VA30A	
MRC			MRIR (Imager)	NUMARIS	NUMARIS	NUMARIS	
PC	Graphic	P/N	PC	P/N	Bios CD Vers.	Bios CD Vers.	
P3 550	Mat. Mill II	7127140	Alpha	5651455	10/99	VA21B	
P3 850	Mat. G200	7128148	460 TT	(7129096)	01/01	VA21B	
670 1.7	Nvidia Q2	7129997	670 1.7	7130011	08/01	VA21B	VA25A VA25C/D
670 2.2	Elsa DCC	7129914	670 2.2	7130268	04/02	VA21B	VA25A VA25C/D
R610	Elsa DCC	7712008	R610	7711968	06/03	VA21B-Rev. B	VA25A VA25C/D
R610	Nv Q4-980	8618584					
R610	Nv Q4-980	7712024	R610 2x	7712057	01/04	VA21B-Rev. B	VA25A VA25C/D
R630	Nv FX3400	10049280			08/04		VA25A VA25C/D
R630	Nv FX3400	10304172	R630 2x	10049278	06/05		VA25A-RevB VA25F
R640	Nv FX3500	10143230	M450 1x	10143232	04/07		VA30A VA30C
R650	Nv FX3700	10497900	xw4600 1x	10497887			VA30A Rev. E VA30E

* incl. Driver-CD VA21D

Bios CD Vers.	P/N	Bios CD Vers.	P/N	Bios CD Vers.	P/N
VA25C	8880366	VB11E	8880341	VC11A	10144830
VA25D	8618642	VB11G	7712107	VC11B	10392601
VA25E	10049286	VB11H	10304233	VC11C	10392781
VA25F		VB11I	10498281	VC11D	10498026
VA30B	10304145				
VA30C	10392540	VB13C	10143215	VC12A	10498027
VA30D	10392781	VB13D	10144852		
VA30E	10497973	VB13E	10304146		
VA30F	10498184				
		VB15C	10304232		
		VB15D	10392516		
		VB15E	10392539		
		VB15F	10392602		
		VB15G	10392780		
		VB15H	10497972		
		VB15I	10498183		
		VB17A	10498240		

Important: Rev B-SW is not backward compatible
Bios-CDs are backward compatible!

			syngo MR 2004V	syngo MR 2005E	syngo MR 2006T	syngo MR B 13	syngo MR B15	syngo MR B17
MRC			NUMARIS	NUMARIS	NUMARIS	NUMARIS	NUMARIS	NUMARIS
PC	Graphic	P/N	PC	P/N	Bios CD Vers.	Bios CD Vers.	Bios CD Vers.	Bios CD Vers.
R610	Nv Q4-980	8379997	BR MR005	7714004	08/04	VB11D	VB11E	
			BR MR 005 Step2 LE	8879905	11/04	VB11D	VB11E	VB12A VB11E
R630	Nv FX3400	10049284	BR MR 005 Step2 LE	8879905	06/05	VB11D-Rev. B	VB11G	VB12A-Rev. B VB11G
R630	Nv FX3400		BR MR 005 Step2 LE	8879905	07/06			
R630	Nv FX3400	10142434	BR MR 005 Standard	mehrere	07/06			VB13A VB13C,D,E
R630	Nv FX3400		BR MR 005 Step2 HE	mehrere	07/06			VB13A VB13C,D,E
R640	Nv FX3500	10143228			04/07			VB13A VB13C,D,E
R640	Nv FX3500	10145155			07/07			VB13A-RevB VB13F
R650	Nv FX3700	10497894	BR MR 005 Step3	mehrere	11/08			VB15A VB15F
R650	Nv FX3700		BR MR 005 Step 4	mehrere				VB15A-Rev.B VB15H

			syngo MR C11	syngo MR C12
MRC			NUMARIS	NUMARIS
PC	Graphic	P/N	PC	P/N
R640	Nv FX3500	10144293		
xw4600	Nv FX3700	10392837	MARS	10141449
xw4600	Nv FX3700	10392837	MARS C2	10497982