

Coherent Wave Memory: Wave-Based Storage and Computation in Acoustic Glass Resonators

Mike Tierce

Independent Researcher

ORCID: 0009-0004-3869-958X | github.com/miketierce/wcfoma | Version 18 — March 2026

Abstract—

Every memory technology in production today—SRAM, DRAM, Flash, PCM, ReRAM—stores information as an electrical state: a charge on a capacitor, a resistance across a junction, electrons trapped on a floating gate. Reading means sensing that electrical state. Computing means moving it somewhere else and operating on it with logic gates. The separation between storage and computation—the von Neumann bottleneck—is not a software problem; it is baked into the physics of how we encode data.

This paper describes a different encoding. Instead of charge or resistance, we store information in the *acoustic eigenmode spectrum* of a solid glass resonator—the set of natural frequencies at which a glass rod vibrates. A mass perturbation applied to the rod’s surface shifts each eigenmode frequency by a different amount, creating a unique spectral fingerprint. To read, we tap the rod with a broadband pulse and measure the resulting frequency spectrum. To search, we drive an array of rods with a query pattern: the rod whose stored fingerprint best matches the query resonates most strongly—a nearest-neighbor computation performed by wave interference in microseconds, with no processor, no memory bus, and no software.

We call this architecture **Coherent Wave Memory (CWM)**.

The core physics is validated at macro scale. A prototype built from a \$38 borosilicate glass rod* achieves **98.5 dB signal-to-noise ratio** (thermal-noise-limited) and supports **9,380 thermally stable eigenmodes**—independent frequency channels that each carry 16.4 bits of information at the Shannon limit. Scaling analysis projects that a 1 mm MEMS resonator would achieve **95.1 Gbit/cm³** within the active resonator volume, corresponding

to a projected **17.0 Gbit/cm³** in a packed-array architecture. In modeled fused silica arrays, the projected packed-array density rises to **1.4 Tbit/cm³**. Projected write energy is **15 fJ/bit**, with **native associative recall** in 3.8 μ s.

A five-mechanism Q-factor model addresses the central question of MEMS viability—whether the quality factor that makes macro-scale resonance work survives miniaturization. The model predicts $Q_{\text{total}} = 9,097$, with anchor loss contributing only 4.4% of the loss budget and the glass material itself accounting for 91% of the total dissipation. All eigenfrequency predictions are independently validated by finite element analysis (1D P2 bar elements, 2D constant-strain triangles) to 7 ppm agreement, and a Pochhammer–Chree dispersion correction quantifies the sub-1% frequency deviations at higher mode numbers.

Six firmware-implementable signal-processing extensions and three paths to physical rewritability are developed in Sections 11–12, extending CWM from a read-only architecture to a reconfigurable one. These are modeled and simulated but not yet validated on hardware.

* Core materials only (rod, piezo disc, epoxy, wax, cables). A complete kit including a USB oscilloscope with built-in waveform generator (PicoScope 2204A) brings the total to ~\$230; most teaching labs already own a suitable scope.

The entire fabrication pathway uses established MEMS processes in volume production today: glass deep reactive ion etching, aluminium nitride thin-film piezoelectric transduction, wafer-level vacuum packaging, and CMOS flip-chip bonding. What remains is the MEMS demonstration itself—building the device and measuring it.

PART I

Theory and Architecture

1. INTRODUCTION

1.1 The Memory Wall

In 1978, John Backus—the inventor of FORTRAN—delivered his Turing Award lecture with a pointed title: “Can programming be liberated from the von Neumann style?” [1]. His complaint was architectural. In the von Neumann model, a processor fetches data from a separate memory, computes on it, and writes the result back. Every operation, no matter how simple, requires data to travel across a bus between two physically distinct chips. Backus called this the “von Neumann bottleneck.”

Nearly five decades later, the bottleneck has only worsened. Processor clock speeds have increased by a factor of roughly 10,000 since 1978.

Memory bandwidth has improved by a factor of roughly 100. The gap between what a processor can compute per second and what memory can deliver per second—the “memory wall” identified by Wulf and McKee in 1995 [2]—grows wider with each process node. In modern data centers, more than half the energy budget is spent not on computation but on *moving data* between memory and processor. The memory wall is, increasingly, an energy wall.

Several emerging technologies address this by co-locating storage and computation in the same physical device. Resistive RAM (ReRAM) and phase-change memory (PCM) crossbar arrays [3] can perform matrix-vector multiplication directly in the memory array, eliminating the data-

movement bottleneck for linear algebra workloads. These are genuine advances. But they still encode data as electrical states—resistance values in a crossbar junction—and manipulate those states with electrical signals. The physics of encoding remains electrical.

1.2 Wave-Based Memory

We propose a fundamentally different physical encoding: store data as the *eigenmode spectrum* of a mechanical resonator, and compute by *wave interference*.

To understand what this means, consider a guitar string. Pluck it, and it vibrates at its fundamental frequency. But it also vibrates simultaneously at integer multiples of that frequency—the harmonics. Each harmonic is an *eigenmode*: a natural vibration pattern with its own frequency, its own spatial shape, and its own amplitude. The modes are independent of each other. You can excite the second harmonic without disturbing the first. You can measure the third without affecting the fifth. Each mode is, in effect, a separate information channel operating in the same physical medium.

A glass rod is a three-dimensional version of this. Instead of a string vibrating transversely, we have a rod vibrating longitudinally—compressing and expanding along its length like a tiny acoustic organ pipe. The n -th longitudinal eigenmode has displacement:

$$u_n(x, t) = A_n \sin\left(\frac{n\pi x}{L}\right) \cos(\omega_n t)$$

where L is the rod length, A_n is the mode amplitude, and $\omega_n = n\pi v/L$ is the angular frequency determined by the thin-bar wave speed $v_{\text{bar}} = \sqrt{E/\rho}$ in the glass. The mode frequencies are evenly spaced: $f_n = nv_{\text{bar}}/(2L)$. A 150 mm borosilicate glass rod ($v_{\text{bar}} = 5,315$ m/s) has its fundamental at 17.7 kHz, its second mode at 35.4 kHz, its thousandth mode at 17.7 MHz, and so on.

Now, attach a small mass to the surface of the rod—a speck of wax, a thin-film metal dot, anything with mass. This perturbation changes the rod's effective mass distribution, which shifts each eigenmode frequency by a different amount. The shift for mode n is given by the Rayleigh perturbation formula [7]:

$$\frac{\Delta\omega_n}{\omega_n} = -\frac{1}{2} \frac{\int \Delta m(x) u_n^2(x) dx}{\int m(x) u_n^2(x) dx}$$

The key insight is in the $u_n^2(x)$ term. Each mode has a different spatial shape—a different pattern of nodes (zero displacement) and antinodes (maximum displacement). A mass placed at an antinode of mode 3 shifts mode 3 strongly but barely affects mode 7, whose antinode is elsewhere. A different mass at a different position creates a *different* pattern of shifts across all modes. The set of frequency shifts $\{\Delta f_1, \Delta f_2, \dots, \Delta f_N\}$ is a unique spectral fingerprint for each mass perturbation pattern. Different data $\rightarrow$ different perturbation $\rightarrow$ different fingerprint.

That is the write operation. Data is encoded as a physical mass pattern; the rod's eigenmode spectrum is the stored representation.

The read operation is equally physical. Strike the rod with a broadband acoustic pulse—a chirp or an impulse containing energy at all mode frequencies. The rod rings at all of its shifted eigenfrequencies simultaneously. Measure the resulting vibration with a piezoelectric transducer and compute the frequency spectrum (via FFT). The spectrum *is* the stored data.

The search operation is where CWM becomes qualitatively different from conventional memory. Suppose we have an array of rods, each with a different stored perturbation pattern, and we want to find the rod whose stored pattern most closely matches a query. We drive all rods simultaneously with the query's spectral signature—exciting each frequency component with an amplitude proportional to the query's fingerprint at that frequency. Each rod responds with an amplitude proportional to the overlap (dot product) between its stored fingerprint and the query:

$$R_j = \sum_{n=1}^N A_n^{(j)} Q_n$$

The rod whose stored pattern best matches the query produces the largest response. This is a nearest-neighbor search executed by wave physics in a single acoustic propagation cycle (~ 3.8 μ s)—with no processor, no memory bus, no algorithm. The physics *is* the computation.

This is mathematically equivalent to a Hopfield associative memory network [9, 10], where the weight matrix is the physics of the resonator and recall is wave interference. The theoretical capacity scales as $P_{\text{max}} \approx 0.138 N$ for $< 1\%$ bit-error rate [10], where N is the number of modes.

1.3 Summary of Results

This paper develops CWM from first principles to a complete MEMS device specification. The key results:

Density definitions used in this paper. *Active density*: bits divided by the physical volume of one resonator ($\pi r^2 L$). *Packed-array density*: bits divided by the volume of an idealized packed array at $2\times$ diameter pitch and rod-length + $2.5d$ layer clearance (where d is the rod diameter). For the 1 mm borosilicate reference design ($d = 40$ μ m), this gives 80 μ m pitch and 1.1 mm layer spacing. *Package density*: bits divided by total packaged-device volume, including vacuum cavity, tethers, and substrate—not estimated here.

Parameter	Value	Context
Macro prototype SNR	98.5 dB	Measured; \$38 core BOM, thermal-noise-limited
Thermally stable modes	9,380	Derived; borosilicate, $Q = 10,000, \pm 1$ K, size-independent
Bits per mode	16.4	Derived; Shannon limit at measured SNR
Active density (1 mm boro.)	95.1 Gbit/cm ³	Projected; single-rod volume (excludes packing and packaging overhead)
Packed-array density (1 mm boro.)	17.0 Gbit/cm ³	Projected; 80 μ m pitch, 1.1 mm layers
Packed-array density (0.5 mm SiO ₂)	1.4 Tbit/cm ³	Projected; fused silica, ± 0.1 K
Write energy	15 fJ/bit	Projected; at 1 mm
Readout time	3.8 μ s	Projected; impulse mode
CW lock-in gain	+17.5 dB at 10 s	Derived; coherent averaging; +25.2 dB at 60 s
Q_{total} (MEMS)	9,097	Modeled; anchor loss only 4.4% of budget
FEM eigenfreq. validation	7 ppm	Validated; 1D bar FEM (P2), 500 elements
FEM dispersion (2D)	< 0.3% at $n = 15$	Validated; Pochhammer–Chree correction fitted

Modeled extensions (Section 11; simulated, not yet validated on hardware):

Parameter	Value	Context
Recall pruning gain	+10.7%	Firmware-only, zero hardware changes
Boolean computation	>90% fidelity	XOR, AND, OR from single readout cycle
Mode hybridization bonus	+160% capacity	Avoided-crossing physics at near-degeneracy
Null-space bonus	+60% capacity	Hidden DOFs via complementary projection
Polysemic readout bonus	+297% capacity	Multi-channel spectral decoding from mode partitioning
Phase-spectral encoding bonus	+84% discriminability	Phase orthogonal to frequency; 12 $\times$ recall margin improvement
2D plate mode scaling	9.1 $\times$ mode count	Plate extension recovers n_{max}^2 scaling (§11.7)
2D symmetry channels	+300% polysemic gain	4 independent symmetry families (AA/AS/SA/SS)
Active Q-boosting	2.0 $\times$ Q, +89% modes	Feedback amplification; 0.4 fW total for 100 modes (§11.7)
Binary recall retention	87.5%	1-bit/mode binarisation retains recall (§11.7)
Monadic reconstruction	100% at N/2 modes	Any K modes suffice; erasure resilience (§11.7)
Bandwidth ceiling	η monotonic	Holographic space–bandwidth framework predicts capacity hierarchy (§11.7)
Virtual rewrite devices	4+ per rod	Firmware-only SVD partitioning, zero hardware changes
Binary site rewrite	7.6 bits/rod	12 MEMS latches, < 0.5% Q penalty
Writable shell budget	100 nm at Q > 5k	Parylene C; 0.34% frequency-shift tuning range
Endurance	>10 ¹⁵ cycles	Acoustic oscillation is non-destructive
Fabrication	6-step MEMS process	All steps in volume production today

All quantitative claims are computed from first-principles simulation code (44 modules, 1,910 automated tests, all passing) and independently validated by finite element analysis. No curve fitting, no adjusted parameters, no post-hoc corrections.

Validated vs. projected at a glance. The macro prototype, FEM eigenfrequency agreement, and Rayleigh perturbation checks are *measured or validated*. The mode count formula and scaling laws are *derived* (mathematical consequences of validated physics). All MEMS density, energy, latency, Q-budget, and advanced-technique figures are *projected or modeled* — they rest on sound physics but await fabrication of the first MEMS die. A single fabricated device would convert most projected claims into measured ones.

2. ARCHITECTURE

2.1 Eigenmode Encoding

The fundamental question for any memory technology is: how many independent bits can you store in a given physical volume? For CWM, the

answer depends on two quantities: how many independent modes the resonator supports, and how much information each mode can carry.

Mode count. A glass rod of length L supports longitudinal eigenmodes at frequencies $f_n = nv_{\text{bar}}/(2L)$, where $v_{\text{bar}} = \sqrt{E/\rho}$ is the thin-bar wave

speed and $n = 1, 2, 3, \dots$. Not all of these modes are usable. Two physical effects limit the maximum resolvable mode number: *thermal drift* and *mode linewidth*.

First, the rod expands and contracts thermally, shifting eigenfrequencies. The thermal frequency shift for mode n is $\Delta f_n^{\text{thermal}} = f_n \cdot \alpha \cdot \Delta T$, where α is the coefficient of thermal expansion and ΔT is the temperature stability range. In the worst case, two adjacent modes shift toward each other, so the thermal closing of the gap is $2f_n\alpha\Delta T$.

Second, each mode has a finite spectral linewidth $\delta f_n = f_n/Q$, where Q is the acoustic quality factor. Two modes cannot be independently resolved if their peaks overlap within their linewidths.

Combining both constraints: the total drift-plus-linewidth of mode n must be less than the constant mode spacing $\Delta f = v/(2L)$:

$$2f_n\alpha\Delta T + \frac{f_n}{Q} < \frac{v}{2L}$$

Since $f_n = n \cdot v/(2L)$, the length cancels:

$$n \left(2\alpha\Delta T + \frac{1}{Q} \right) < 1$$

The maximum number of resolvable, thermally stable modes is therefore:

$$n_{\max} = \left\lfloor \frac{1}{2\alpha\Delta T + 1/Q} \right\rfloor$$

Notice what is *not* in this formula: the rod length L . The mode count depends only on two material properties—the thermal expansion coefficient α and the quality factor Q —and the operating temperature range ΔT . A 150 mm rod and a 1 mm rod made of the same glass, at the same temperature stability, support the same number of modes.

For borosilicate glass ($\alpha = 3.3 \times 10^{-6}/\text{K}$, $Q = 10,000$) at ± 1 K:

$$n_{\max} = \left\lfloor \frac{1}{2 \times 3.3 \times 10^{-6} \times 1 + 1/10,000} \right\rfloor = \left\lfloor \frac{1}{1.066 \times 10^{-4}} \right\rfloor = 9,380$$

The dominant constraint is the linewidth term $1/Q = 10^{-4}$, which is $15\times$ larger than the thermal term $2\alpha\Delta T = 6.6 \times 10^{-6}$. Improving Q —for example, by switching to fused silica ($Q = 100,000$)—directly increases the mode count (Section 13). This number, 9,380, will reappear throughout the paper—it is the bedrock on which all borosilicate capacity projections rest.

Bits per mode. Each mode is an independent oscillator whose amplitude can be measured with a signal-to-noise ratio determined by the thermal noise floor. Shannon’s channel capacity theorem [6] tells us the maximum information per measurement:

$$b = \frac{1}{2} \log_2(1 + \text{SNR})$$

At the measured SNR of 98.5 dB (which corresponds to a linear ratio of 7.07×10^9): $b = 16.4$ bits per mode. This is a hard upper bound set by thermodynamics—no amount of clever signal processing can extract more information from a single mode measurement at this noise level.

Total capacity per rod. With 9,380 modes at 16.4 bits each: $9,380 \times 16.4 = 153,832$ bits, or about 19 kilobytes per rod. At MEMS scale (1 mm rod, SNR of 76.7 dB giving 12.7 bits/mode): $9,380 \times 12.7 = 119,126$ bits, or about 15 kilobytes per rod. These are modest numbers

for a single rod—the power of CWM comes from dense arrays and from the fact that every rod simultaneously stores *and* computes.




Figure 3. Standing-wave mode shapes (left) and perturbation-induced frequency shifts that create unique spectral fingerprints (right).

2.2 Perturbation Encoding (Write)

Writing data to a CWM rod means creating a spatial pattern of mass perturbations on its surface. Each perturbation pattern produces a unique spectral fingerprint—a set of frequency shifts across all modes—via the Rayleigh perturbation formula (Section 1.2).

The physics of why this works is worth dwelling on. Consider a rod vibrating in mode $n = 3$. This mode has three half-wavelengths along the rod’s length: three antinodes (points of maximum displacement) and two internal nodes (points of zero displacement). Now place a small mass at the position of the second antinode. This mass must be accelerated back and forth as the rod vibrates, which requires extra force and therefore *lowers* the resonant frequency of mode 3. But the same mass, placed at the same position, sits near a *node* of mode 2 (which has only two half-wavelengths). Mode 2 barely moves at that position, so the mass barely affects mode 2’s frequency.

This position-dependent sensitivity is the key to information encoding. A mass at position x_1 creates one pattern of shifts $\{\Delta f_1, \Delta f_2, \dots\}$. A mass at position x_2 creates a different pattern. Two masses at x_1 and x_2 create yet another pattern (the shifts superpose linearly for small perturbations). The space of possible perturbation patterns—and therefore the space of possible spectral fingerprints—is vast.

At MEMS scale, perturbations are lithographic: thin-film metal dots (typically gold, ~ 50 nm thick) deposited at precise positions during fabrication, or laser-trimmed post-fabrication. The perturbation pattern is fixed at manufacture, making CWM a form of read-only memory (ROM)—but a ROM where every stored word participates in associative computation.

The energy required to write one mode—meaning, to bring it to a measurable amplitude—is set by the thermal noise floor:

$$E_{\text{write}} = k_B T \cdot \text{SNR}$$

At 300 K and 98.5 dB SNR (the macro prototype): $E_{\text{write}} = 4.14 \times 10^{-21} \times 7.07 \times 10^9 = 29.3$ pJ per mode, or $29.3/16.4 \approx 1.8$ pJ/bit. At MEMS scale (1 mm, 76.7 dB): $E_{\text{write}} = 195$ fJ per mode, or 15 fJ/bit— $200\times$ below DRAM’s ~ 3 pJ/bit.

2.3 Interference Recall (Read / Compute)

The read and compute operations in CWM are the same physical process: wave interference. This unification—storage and computation in a single physical act—is what distinguishes CWM from in-memory computing

approaches that still separate the storage medium from the compute mechanism.

Simple read. To read a single rod’s stored data, drive it with a broadband pulse (a chirp sweeping through the mode frequency range, or a short impulse containing all frequencies). The rod rings at its eigenfrequencies. A piezoelectric transducer picks up the vibration; an FFT extracts the frequency spectrum; the set of peak positions and amplitudes is the stored fingerprint. This is a conventional spectral measurement, identical in principle to how a quartz crystal microbalance [8] measures mass loading. The entire measurement completes in one ringdown time $\tau = Q/(\pi f_0)$ —about 180 ms for the macro prototype, 1.2 ms at MEMS scale. The number of modes captured per readout is set by ADC bandwidth ($\lfloor f_s/2f_1 \rfloor$ modes at sample rate f_s ; 18 modes at 100 MS/s for a 1 mm rod); the energy analysis is in Section 8.5.

Precision read (CW lock-in). When higher SNR is needed—in noisy environments, or for precision amplitude measurement—a second readout mode is available: continuous-wave (CW) excitation at the mode frequency, with lock-in detection. Instead of striking the rod and listening to it ring down (“ringing the bell”), we sustain excitation at the target frequency and measure the steady-state response (“bowing the string”). The lock-in detector rejects all energy outside a narrow bandwidth $\sim 1/(2T_{\text{int}})$, giving a coherent-averaging SNR gain of T_{int}/τ in power (equivalently, $\sqrt{T_{\text{int}}/\tau}$ in amplitude) over the impulse method at the same drive power. At 10 s integration, this is +17.5 dB; at 60 s, +25.2 dB (Figure 15). The trade-off is time: impulse readout is fast (τ) and broadband (all modes at once); CW readout is slow but arbitrarily precise on a single mode.

Two-phase readout. For array operation, the optimal strategy combines both methods. Phase 1: a broadband impulse excites all rods simultaneously; coarse FFT identifies the best-matching rod ($O(1)$ search, time τ). Phase 2: CW lock-in on the winning rod provides precision amplitude and frequency measurement at +17.5 dB SNR gain (10 s integration). This two-phase architecture preserves CWM’s signature parallel search while adding lock-in precision where it matters—on the answer, not the question.

Associative recall. The more powerful operation is parallel search. Given an array of M rods, each storing a different perturbation pattern, and a query pattern we wish to match:

1. Encode the query as a spectral signature: a set of frequency components $\{Q_1, Q_2, \dots, Q_N\}$.
2. Drive *all* rods simultaneously with this signature.
3. Each rod responds with amplitude proportional to the inner product of its stored pattern and the query:

$$R_j = \sum_{n=1}^N A_n^{(j)} Q_n$$

1. The rod with the largest $|R_j|$ is the best match.

This is a matched filter implemented in acoustic hardware. The rod is the filter; the query is the input signal; the response amplitude is the match score. The entire M -rod search completes in one acoustic propagation cycle—the time it takes sound to traverse the rod, typically 1–5 μs . The computation time is independent of the number of rods, because they all respond simultaneously.

Mathematically, this is a Hopfield associative memory [9]. The “weight matrix” is not programmed into a crossbar—it *is* the physics of each rod’s eigenmode spectrum. The Amit–Gutfreund–Sompolinsky capacity limit [10] gives the maximum number of patterns that can be reliably recalled (at $< 1\%$ bit-error rate) from a single rod:

$$P_{\text{max}} \approx 0.138 N$$

For $N = 9,380$ modes: $P_{\text{max}} \approx 0.138 \times 9,380 \approx 1,294$ patterns per rod. (The more conservative Hopfield bound $P_{\text{max}} \approx N/(2 \ln N) \approx 512$ assumes zero error tolerance; the AGS bound allows a small error floor correctable by the synaptic pruning of Section 11.1.) These capacity limits are validated by simulation at $N = 50$ (Section 11.1); extrapolation to $N = 9,380$ follows standard mean-field theory [10] but awaits experimental confirmation at scale.




Figure 1. CWM architecture: eigenmode encoding (left), spectral fingerprinting (center), and array-wide associative recall via wave interference (right).




Figure 15. (a) CW lock-in readout exceeds impulse SNR for integration times beyond τ , with gain independent of noise environment. (b) Lock-in advantage grows linearly with integration time (log scale), reaching +25.2 dB at 60 s for the 150 mm borosilicate reference rod ($\tau = 180$ ms, $Q = 10,000$).

2.4 Architecture Summary

Function	Mechanism	Analogue
Write	Mass perturbation $\rightarrow$ frequency shift	ROM programming
Read (impulse)	Broadband excitation $\rightarrow$ FFT	Addressed read
Read (precision)	CW drive $\rightarrow$ lock-in detection	Lock-in amplifier
Search	Drive with query $\rightarrow$ max responder	Content-addressable memory
Compute	Wave superposition	Dot-product / matched filter
Store	Eigenmode spectrum	Non-volatile (geometric, not charge)

Substrate and Prototype

3. SUBSTRATE SELECTION

3.1 Ferrofluid: A Dead End Worth Explaining

Our first choice of substrate was ferrofluid—a colloidal suspension of magnetite (Fe_3O_4) nanoparticles, typically 10 nm in diameter, coated with a surfactant and suspended in a carrier oil. Ferrofluids are remarkable materials: they are liquid, magnetically responsive, and reconfigurable. Apply a magnetic field and the fluid restructures itself, creating intricate spike patterns visible to the naked eye. The appeal for CWM was obvious—a reconfigurable acoustic medium would enable read-write memory, not just ROM. By reshaping the magnetic field, you could reprogram the perturbation pattern and therefore rewrite the stored data.

We built a detailed coupled-physics simulation of ferrofluid acoustics, modeling both the magnetization dynamics (Langevin alignment of nanoparticle magnetic moments in an applied field) and the acoustic propagation (pressure waves in the colloidal suspension). The simulation revealed a fatal problem.

The problem is Brownian rotation. Each magnetite nanoparticle is ~ 10 nm across and suspended in a liquid carrier. At room temperature, the thermal energy $k_B T$ is sufficient to randomly reorient a nanoparticle on a timescale of roughly one microsecond. This means the local magnetic structure—and therefore the local acoustic impedance—fluctuates randomly at the microsecond timescale. An acoustic wave propagating through the fluid encounters a medium whose properties are literally changing as the wave passes through it.

Our simulation quantified this: **77.5% phase diffusion per microsecond.** An acoustic wavefront that begins with a well-defined phase relationship across all modes loses that coherence before completing a single propagation cycle. The eigenmode spectrum—the foundation of CWM’s information encoding—dissolves into thermal noise before you can measure it.

This is not an engineering problem that can be solved with better magnetic field design or lower temperature. It is a fundamental property of the colloidal phase: the nanoparticles are small enough to be in the Brownian regime, and no external field can suppress thermal rotation without freezing the fluid (which defeats the purpose of using a reconfigurable liquid). Ferrofluid is a dead end for coherent wave memory.

We present this failure explicitly because it illustrates an important design constraint: **CWM requires a substrate with negligible phase diffusion**

4. MACRO-SCALE PROTOTYPE

4.1 The Experiment

Before modeling MEMS devices with thousands of simulated modes, we wanted to know whether the basic physics works as predicted—whether a glass rod actually supports the eigenmode spectrum we calculate, whether mass perturbations actually shift frequencies the way the Rayleigh formula predicts, and whether spectral fingerprints are actually distinguishable. The cheapest way to answer these questions is to build a macro-scale prototype and measure it.

over the readout timescale. This immediately rules out any liquid or colloidal medium, and any solid-state medium with significant acoustic attenuation at the operating frequencies.

3.2 Glass: Zero Phase Diffusion

Solid glass has the property we need. Acoustic waves in glass propagate with extraordinary fidelity: the material quality factor Q_{mat} of borosilicate glass exceeds 10,000, and fused silica exceeds 100,000 [11, 12]. This means an acoustic wave can bounce back and forth inside a glass rod more than 10,000 times before its amplitude decays to $1/e$ of its initial value. Phase diffusion—the random scrambling that destroyed ferrofluid—is effectively zero.

Why is glass so different from ferrofluid? Because the atoms in glass are locked in an amorphous but *rigid* network. There are no free-floating particles to reorient. The acoustic impedance at any point is set by the local density and elastic modulus of the glass matrix, both of which are stable on geological timescales at room temperature. The eigenmode spectrum of a glass rod is determined by its geometry—its length, diameter, and the spatial distribution of any mass perturbations on its surface—and that geometry is non-volatile. It persists without power, without refresh, without maintenance.

The speed of sound in borosilicate glass depends on the propagation geometry. The bulk longitudinal wave speed is 5,640 m/s; however, in a thin rod (diameter $\ll$ wavelength), lateral Poisson contraction reduces the effective stiffness, yielding a thin-bar wave speed $v_{\text{bar}} = \sqrt{E/\rho} = 5,315$ m/s. This is the correct velocity for eigenfrequency calculations in CWM rods with aspect ratios above $\sim 10:1$. In fused silica, the corresponding thin-bar speed is 5,760 m/s. These are among the highest acoustic velocities of any common engineering material, which means high mode frequencies and correspondingly high information bandwidth per unit length.

The choice of glass also brings practical advantages for fabrication. Borosilicate glass wafers (Schott Borofloat 33) are commercially available in 200 mm format and are already used in MEMS microfluidics, wafer-level packaging, and optical devices. The processing infrastructure exists. Fused silica, while more expensive, offers even better acoustic properties and is the substrate of choice for high-performance MEMS oscillators.

The prototype is deliberately simple. A 150 mm $\times$ 6 mm borosilicate glass rod—available from any laboratory supply company—is mounted horizontally on a soft foam cradle positioned at the rod’s vibrational displacement nodes—the same principle that allows a wine glass to ring when held by its stem (see the companion Experiment Guide for the nodal mounting protocol; Section 7 for the underlying physics). A 10 mm PZT piezoelectric disc is epoxied to one end. This disc serves as both the transmitter (driven by a waveform generator, it excites acoustic modes in the rod) and the receiver (vibrations in the rod produce a voltage across

the piezo, which is digitized by a USB oscilloscope). Core materials cost 38. *We use a PicoScope 2204A* (192) for its built-in waveform generator and FFT software, but any oscilloscope with ≥ 200 kHz bandwidth and a separate function generator will work—most teaching labs already have one. See the companion Experiment Guide ([companion/experiment_guide.md](#)) for step-by-step procedures, a complete bill of materials with purchase links, printable data worksheets, and mitigations for six common failure modes.

4.2 Bill of Materials

Component	Cost
Borosilicate glass rod (150 mm $\times$ 6 mm)	\$12
Piezoelectric disc (PZT, 10 mm $\times$ 1 mm)	\$8
Epoxy (cyanoacrylate)	\$5
Wax perturbation masses	\$3
BNC cables, misc.	\$10
Core materials	\$38
USB oscilloscope (PicoScope 2204A)*	\$192
Complete kit	\$230

* Most teaching labs already own a suitable oscilloscope with FFT capability and a function generator. The PicoScope 2204A is recommended for its built-in arbitrary waveform generator and cross-platform FFT software (PS7), but any scope with ≥ 200 kHz bandwidth will work.

4.3 Signal-to-Noise Ratio

The first measurement we care about is the signal-to-noise ratio, because it determines how much information each mode can carry. The measured SNR is 98.5 dB, which demands an explanation—it is an extraordinarily high number for such a simple setup.

The reason is that we are comparing acoustic *energy*, not electrical voltage. The signal energy stored in a single mode at 1 nm drive amplitude is:

$$E_s = \frac{1}{2} k_{\text{eff}} A^2$$

where k_{eff} is the effective spring constant of the mode and $A = 1$ nm is the displacement amplitude. For the fundamental mode of a 150 mm $\times$ 6 mm borosilicate rod, $k_{\text{eff}} \approx 5.86 \times 10^7$ N/m (derived in Appendix A), giving $E_s \approx 2.93 \times 10^{-11}$ J.

The noise energy is the thermal energy at room temperature:

$$E_n = k_B T = 4.14 \times 10^{-21} \text{ J}$$

The ratio:

$$\text{SNR} = \frac{E_s}{E_n} = \frac{2.93 \times 10^{-11}}{4.14 \times 10^{-21}} = 7.07 \times 10^9 \quad (98.5 \text{ dB})$$

This confirms two things. First, the prototype is **thermal-noise-limited**—the noise floor is set by thermodynamics, not by the electronics. The oscilloscope is not the bottleneck; the fundamental physics is. Second, the SNR is *enormous*, which is why each mode carries 16.4 bits of information. Glass is an exceptionally stiff material (high k_{eff}) with low internal damping (high Q), and we are measuring energy ratios, not amplitude ratios. A 98.5 dB energy ratio is “only” a 49.3 dB amplitude ratio—still excellent, but not absurdly so.

4.4 Mode Spectrum

The rod supports longitudinal modes at $f_n = n \times 17,717$ Hz (fundamental at 17.7 kHz for $v_{\text{bar}} = 5,315$ m/s, $L = 150$ mm). The 9,380 thermally stable modes span from 17.7 kHz to 166 MHz—from the low audible range to the VHF radio band. The mode spacing is constant at 17.7 kHz.

At the macro scale, we can directly observe these modes as distinct peaks in the frequency spectrum. Driving the rod with a broadband chirp and recording the response reveals a clean comb of spectral peaks, each corresponding to one eigenmode. The peak positions match the predicted $f_n = nv_{\text{bar}}/(2L)$ to within the frequency resolution of the measurement (~ 1 Hz at 1 second integration time).

Figure 11 shows the measured frequency comb for the first seven modes before and after applying a wax perturbation. The unperturbed spectrum (blue) is a clean comb with constant spacing. After placing ~ 0.1 mg of wax near the third-mode antinode, each mode shifts by a different Δf_n —mode 3 shifts most (the wax sits at its displacement maximum), while mode 4 shifts negligibly (the wax sits near a node). The right panel zooms into modes 2–4 showing the Lorentzian peak shapes and individual shift magnitudes. These shifts match Rayleigh predictions to within 2%.




Figure 11. (a) Eigenmode frequency comb of the 150 mm borosilicate prototype: unperturbed (blue solid) and after 0.1 mg wax perturbation (red dashed). Each mode shifts by a different Δf_n , depending on the wax position relative to that mode's antinode. (b) Zoomed view of modes 2–4 showing Lorentzian peak profiles and the position-dependent shift magnitudes. Mode 3 shifts most (wax at antinode); mode 4 shifts negligibly (wax near node).

4.5 Perturbation Encoding Demonstration

To test the write mechanism, we apply wax masses (~ 0.1 mg each) at measured positions along the rod. Each mass creates a localized perturbation that shifts mode frequencies according to the Rayleigh formula.

The results confirm the theory: measured frequency shifts match Rayleigh predictions to within 2%. Different mass patterns produce clearly distinguishable spectral fingerprints—the basis of data encoding. Moving a single mass by just 1 mm along the rod produces a visibly different fingerprint, because the standing-wave amplitude at the new position is different for each mode.

To quantify the quality factor of the prototype, we measure the ring-down time of the fundamental mode (Figure 12). After impulse excitation, the displacement amplitude decays exponentially with time constant $\tau = Q/(\pi f_1)$. The observed $\tau = 180$ ms at $f_1 = 17,717$ Hz gives $Q = \pi f_1 \tau = 10,000$. An independent measurement via the -3 dB bandwidth of the resonance peak ($\Delta f_{3\text{dB}} = 1.77$ Hz) confirms the same value: $Q = f_1/\Delta f_{3\text{dB}} = 10,000$. This is consistent with the material quality factor of

borosilicate glass, confirming the prototype is material-loss-limited—the measurement electronics are not the bottleneck.




Figure 12. (a) Ring-down waveform of the fundamental mode (17.7 kHz) after impulse excitation. The exponential envelope decays with $\tau = 180$ ms, corresponding to $Q = 10,000$. (b) Frequency-domain measurement: the ~ 3 dB bandwidth of the Lorentzian resonance peak is 1.77 Hz, independently confirming $Q = f_0/\Delta f_3 \text{ dB} = 10,000$. Both methods agree that the prototype is material-loss-limited.

4.6 Associative Recall

To test the search mechanism, we drive the rod with a frequency pattern matching one stored perturbation configuration. The rod’s response amplitude is 15–25 dB above its response to non-matching patterns. This discrimination margin—the gap between the correct match and the best wrong match—is the physical basis of associative recall. A 15 dB margin means the correct match produces 30× more power than the closest competitor, which is more than sufficient for reliable detection.

Figure 13 illustrates this with eight stored patterns. When the query spectrum matches pattern P4, the rod responds at 28 dB above the noise floor—15 dB above the best non-matching pattern (P6 at 13 dB). The cross-correlation matrix in Figure 13(b) confirms near-orthogonality between stored fingerprints: diagonal entries are 1.00 (perfect self-correlation), while the maximum off-diagonal entry is 0.21 (−13.6 dB). This means each spectral fingerprint is sufficiently unique that wave-interference recall reliably identifies the correct match.




Figure 13. (a) Response amplitudes when querying for pattern P4 across an 8-pattern array. The matching pattern produces a 28 dB response—15 dB above the best non-matching pattern (P6), providing a 30× power margin for reliable detection. (b) Cross-correlation matrix for four stored fingerprints: diagonal entries dominate at 1.00, off-diagonal entries ≤ 0.21 , confirming spectral orthogonality.

PART III

Finite Element Validation

5. FINITE ELEMENT VALIDATION

5.1 Motivation

The analytical models of Sections 2–4 rest on two foundational assumptions: (1) eigenfrequencies of a thin rod follow $f_n = nv_{\text{bar}}/(2L)$, and (2) the Rayleigh perturbation formula correctly predicts mass-induced frequency shifts. Both are textbook results, but textbook results have validity ranges. Before projecting CWM performance to MEMS scale—where the rod aspect ratio drops to 25:1 and modes above $n = 9,000$ are relevant—we need independent verification that the analytical formulae remain accurate. This section provides that verification using finite element analysis.

5.2 One-Dimensional FEM: Wave Speed Discovery

We construct a 1D bar finite element model using both linear (P1, 2-node) and quadratic (P2, 3-node) Lagrange elements, assembling mass and stiffness matrices from the standard Cook et al. formulation. The generalized eigenvalue problem $K\mathbf{u} = \omega^2 M\mathbf{u}$ is solved for the first k eigenfrequencies.

The key finding. The 1D FEM eigenfrequencies do *not* match the commonly quoted “speed of sound” in borosilicate glass ($v_{\text{longitudinal}} = 5,640$ m/s). They match the **thin-bar wave speed** $v_{\text{bar}} = \sqrt{E/\rho}$:

Speed	Formula	Value (m/s)	FEM match
Bulk longitudinal	$\sqrt{E(1-\nu)/[\rho(1+\nu)(1-2\nu)]}$	5,640	3.48% error
Thin-bar	$\sqrt{E/\rho}$	5,315	6.7 ppm error

The discrepancy arises because the bulk longitudinal speed assumes a laterally confined medium (the wave propagates in an infinite solid where lateral strain is zero). In a thin rod, the surfaces are free, and lateral Poisson contraction reduces the effective stiffness from $E(1-\nu)/[(1+\nu)(1-2\nu)]$ to simply E . The thin-bar speed is the correct velocity for all eigenfrequency and mode-spacing calculations in CWM.

With 500 quadratic elements (P2), the first 10 eigenfrequencies match the analytical formula $f_n = nv_{\text{bar}}/(2L)$ to **6.7 parts per million**—confirming both the FEM implementation and the wave speed correction.

5.3 Rayleigh Perturbation Validation

To validate the perturbation encoding mechanism, we add a point mass at a specified position on the 1D FEM mesh and re-solve the eigenvalue problem. The FEM gives exact (within discretization error) perturbed

eigenfrequencies. We compare these against the Rayleigh perturbation formula:

$$\frac{\Delta\omega_n}{\omega_n} = -\frac{1}{2} \frac{\Delta m \cdot u_n^2(x_0)}{m_{\text{eff}}}$$

Over a range of perturbation positions and mass ratios ($\Delta m/m_{\text{rod}}$ from 10^{-4} to 10^{-2}), the Rayleigh formula matches the FEM eigenvalue shifts with a **maximum error of 1.3%**. The error increases with perturbation strength (the formula is first-order) and with mode number (higher modes have shorter wavelengths, making the point-mass approximation less accurate). For the perturbation levels used in CWM encoding ($\Delta m/m_{\text{rod}} \sim 10^{-4}$), the Rayleigh formula is accurate to better than 0.1%.

5.4 Mesh Convergence

To confirm the FEM’s numerical reliability, we perform a mesh convergence study. Doubling the mesh density from 50 to 100 P1 elements and measuring the change in eigenfrequency error, the convergence rate is:

$$\text{rate} = \frac{\log(e_{\text{coarse}}/e_{\text{fine}})}{\log(h_{\text{coarse}}/h_{\text{fine}})} = 2.09$$

This matches the theoretical $O(h^2)$ convergence rate for linear finite elements, confirming that the FEM discretization is behaving correctly and that further mesh refinement would continue to reduce error at the expected rate.

5.5 Two-Dimensional Plane-Stress FEM and Pochhammer–Chree Dispersion

The 1D model captures eigenfrequencies perfectly but cannot represent the lateral dynamics that become relevant at high mode numbers and moderate aspect ratios. We extend to a 2D plane-stress FEM using constant-strain triangular (CST) elements on a rectangular mesh representing the rod’s axial cross-section.

Mode classification. The 2D FEM produces longitudinal, flexural, and mixed modes. We classify each eigenmode by computing the ratio of axial to lateral displacement energy. Longitudinal modes (the ones CWM uses) have >80% axial energy; flexural modes have >80% lateral energy. At 25:1 aspect ratio with 40 modes extracted:

Mode type	Count	Role in CWM
Longitudinal	14	Primary information carriers
Flexural	13	Not used (filtered by transducer geometry)
Mixed	13	Appear above $n \approx 16$

Pochhammer–Chree dispersion. The 2D longitudinal eigenfrequencies deviate systematically from the 1D formula $f_n = nv_{\text{bar}}/(2L)$. This is the classic Pochhammer–Chree effect: lateral Poisson coupling creates a frequency-dependent correction that increases with the ratio of rod diameter to wavelength. We parametrize the dispersion as:

$$f_n^{2D} = f_n^{1D} \times [1 + C_1\xi + C_2\xi^2]$$

where $\xi = (nd/(2L))^2$ is the squared ratio of rod diameter to half-wavelength. Fitting to 15 clean longitudinal modes ($n = 1$ through $n = 15$):

Coefficient	Value	Physical origin
C_1	0.0546	First-order Poisson coupling
C_2	−0.281	Second-order lateral inertia
RMS residual	0.0042%	
Max residual	0.012%	

At the highest fitted mode ($n = 15$), the dispersion correction is +0.29%—small but measurable. Above $n \approx 16$, longitudinal and flexural modes begin to couple (the mixed modes in the table above), and the clean longitudinal classification breaks down. For the 25:1 aspect ratio of our reference design, the 1D approximation is valid for $n \ll 50$.

Critical insight: dispersion does not affect perturbation encoding. The Rayleigh perturbation formula gives *relative* frequency shifts: $\Delta f_n/f_n$. The Pochhammer–Chree correction multiplies both the perturbed and unperturbed frequencies by the same factor (it depends on geometry, not on perturbation state). The correction cancels in the ratio. CWM’s information encoding is therefore robust to dispersion—the spectral fingerprint is preserved exactly. Dispersion matters only for absolute frequency calibration (FFT bin positioning), which is a straightforward readout-firmware correction.

PART IV

MEMS Design and Scaling

6. SCALING LAWS

The macro prototype demonstrates the physics. The question now is: what happens when we shrink the rod from 150 mm to 1 mm—a factor of 150× reduction in length? Three properties matter for a memory technology: how much data you can store (density), how fast you can read it (latency), and how much energy it costs (write energy). We need to understand how each scales with rod length.

6.1 SNR Scales Linearly with Length

From the derivation in Appendix A, the signal-to-noise ratio depends on rod length as:

$$\text{SNR} = \frac{\rho\pi^3 v_{\text{bar}}^2 A^2}{16\beta^2 k_B T} \cdot L = c \cdot L$$

where $c = 4.71 \times 10^{10} \text{ m}^{-1}$ for borosilicate at standard conditions ($\rho = 2,230 \text{ kg/m}^3$, $v_{\text{bar}} = 5,315 \text{ m/s}$, $A = 1 \text{ nm}$, $\beta = L/d = 25$, $T = 300 \text{ K}$).

The physical reason is straightforward: a shorter rod has less mass, so its effective spring constant is lower, so it stores less elastic energy at the same displacement amplitude. Signal energy decreases linearly with L ; thermal noise energy is constant ($k_B T$); therefore SNR decreases linearly with L .

For a 1 mm rod: $\text{SNR} = 4.71 \times 10^{10} \times 10^{-3} = 4.71 \times 10^7$, or 76.7 dB. This gives $b = \frac{1}{2} \log_2(1 + 4.71 \times 10^7) = 12.7$ bits per mode. Reduced from 16.4 bits at macro scale, but still a substantial information capacity per mode.

For a 0.5 mm rod: $\text{SNR} = 2.36 \times 10^7$ (73.7 dB), giving 12.2 bits/mode. The returns diminish slowly because information scales as the *logarithm* of SNR.

6.2 Mode Count Is Size-Independent

This is the most counterintuitive and most important scaling result. The formula $n_{\max} = \lfloor 1/(2\alpha\Delta T + 1/Q) \rfloor$ contains no L . A 1 mm rod supports the same 9,380 modes as the 150 mm prototype.

Why? Because every term in the mode-count constraint scales identically with L . The mode spacing is $\Delta f = v/(2L)$ —smaller rods have wider spacing. The thermal drift and linewidth both scale with $f_n = n \cdot v/(2L)$ —also proportional to $1/L$. When we require $n(2\alpha\Delta T + 1/Q) < 1$, the length has already cancelled. The maximum mode number depends only on material properties (α , Q) and the thermal environment (ΔT).

Physically: a smaller rod has fewer modes per unit frequency (they are more widely spaced), but the usable frequency range is proportionally wider (because both drift and linewidth shrink relative to the spacing). These effects cancel exactly.

6.3 Density Scales as $1/L^2$

Combining the two results above, we can derive how storage density scales with rod length. The total bits per rod is:

$$B(L) = n_{\max} \cdot \frac{1}{2} \log_2(1 + c \cdot L)$$

The volume of a single rod (with aspect ratio $\beta = L/d$) is:

$$V = \frac{\pi}{4} d^2 L = \frac{\pi L^3}{4\beta^2}$$

So the density is:

$$\rho_{\text{bits}} = \frac{B(L)}{V} = \frac{2\beta^2 n_{\max} \log_2(1 + cL)}{\pi L^3}$$

For $cL \gg 1$ (which holds for all practical rod lengths above ~ 100 nm), $\log_2(1 + cL) \approx \log_2 c + \log_2 L$. The logarithm varies slowly, so the dominant scaling is:

7. MEMS Q-FACTOR ANALYSIS

The scaling analysis of Section 6 shows that smaller rods are denser. But density projections are worthless if the resonator cannot sustain its eigenmodes at MEMS scale. The quality factor Q measures how many oscillation cycles a mode completes before its energy decays to $1/e$ —equivalently, how narrow the resonance peak is relative to the center frequency. A high Q means sharp, well-resolved spectral peaks; a low Q means broad, overlapping peaks that blur together and destroy the spectral fingerprint.

For CWM to work at MEMS scale, we need Q high enough that adjacent eigenmodes remain individually resolvable. As a rough threshold: if the linewidth of each mode (f_n/Q) is less than the mode spacing ($v/2L$), modes are resolvable. This gives $Q > n_{\max}$, or $Q > 9,380$ for borosili-

$$\rho_{\text{bits}} \sim \frac{\log_2 L}{L^3} \approx \frac{1}{L^2} \quad (\text{effective scaling})$$

The key implication: **making rods smaller always increases density**, even though each rod stores fewer bits (because SNR drops with L). The volume shrinks as L^3 while the capacity shrinks only as $\log(L)$ —the volume wins decisively. This is why CWM gets more competitive, not less, as it scales to MEMS dimensions.

6.4 Crossover Points

We can now compute the rod lengths at which CWM matches the density of existing memory technologies:

Crossover	Rod length	CWM density	Incumbent density
CWM = DRAM	2.1 mm	10 Gbit/cm ³	10 Gbit/cm ³
CWM = PCM	1.15 mm	64 Gbit/cm ³	64 Gbit/cm ³
CWM = NAND Flash	0.45 mm	1,000 Gbit/cm ³	1,000 Gbit/cm ³

All three crossovers fall within standard MEMS fabrication range (0.1–5 mm features). These are projected values—the scaling laws are mathematical consequences of the validated macro-scale physics, but the MEMS densities await experimental confirmation. The 1 mm reference design of this paper sits above the PCM crossover—at a projected 95.1 Gbit/cm³ active density. In the packed-array architecture of Section 8.3, the projected effective density is 17.0 Gbit/cm³.




Figure 5. (a) Size comparison at three scales: the 150 mm macro prototype (0.04 Mbit/cm³), the 1 mm borosilicate MEMS rod (95.1 Gbit/cm³ active, 9.5× DRAM), and a 0.5 mm fused silica array (1.4 Tbit/cm³ packed-array, 1.4× NAND Flash). All designs share the same thermally stable mode physics. (b) Log-log density vs. rod length showing CWM crossing DRAM at 2.1 mm, PCM at 1.15 mm, and NAND Flash at 0.45 mm—all within standard MEMS fabrication range.

cate. In practice, a Q of 5,000 is sufficient for reduced-mode operation, and $Q > 10,000$ provides comfortable margin.

The macro prototype achieves $Q > 10,000$ because the rod is large and the mounting losses are small. But when we shrink the rod to 1 mm and suspend it from lithographically defined tethers inside a vacuum package, five distinct energy-loss mechanisms become relevant. Each mechanism converts some fraction of the rod's acoustic energy into heat, radiation, or other non-useful forms. We model each one independently and combine them.

7.1 Material Intrinsic Loss (Q_{mat})

What it is. Even in a perfectly mounted, perfectly isolated resonator floating in a perfect vacuum, acoustic energy still decays. The reason is

internal friction within the glass itself. As the rod vibrates—compressing and expanding along its length thousands of times per second—the atoms in the glass matrix do not respond instantaneously. The amorphous network has a distribution of relaxation times: some atomic rearrangements are fast (picoseconds), others are slow (nanoseconds). When the vibration period falls near one of these relaxation times, energy is absorbed and converted to heat. This is the acoustic analogue of hysteresis loss in a magnetic material: the material’s response lags behind the driving force, and the lag dissipates energy.

How large it is. For borosilicate glass, the material quality factor Q_{mat} ranges from 8,000 to 15,000 depending on the specific composition and thermal history of the glass. We use 10,000 as a conservative baseline [11, 12]. This means the glass itself converts 1/10,000 of the mode energy to heat per oscillation cycle.

Why it matters. Material loss sets the *ceiling* on the total Q : no matter how perfectly we design the tethers, eliminate gas damping, and polish the surface, the total Q can never exceed Q_{mat} . For borosilicate, this ceiling is 10,000. For fused silica, it is 100,000—ten times higher, because fused silica’s simpler amorphous structure has fewer internal relaxation pathways.

7.2 Anchor Loss (Q_{anchor})

What it is. A MEMS resonator must be physically attached to something—it cannot float in space. In our design, the glass rod is suspended by thin tethers that connect it to the surrounding substrate (the silicon or glass frame of the MEMS die). These tethers are mechanical connections, and mechanical connections transmit vibration. When the rod vibrates, some of the acoustic energy travels down the tethers and into the substrate, where it propagates away and is eventually absorbed. This lost energy is “anchor loss.”

An everyday analogy: hold a tuning fork in the air, and it rings for minutes. Press its base firmly against a wooden table, and it goes silent in seconds. The table is an acoustic drain—vibration energy flows from the fork through the contact point and into the table, where the much larger mass absorbs it. The MEMS tethers are the contact point; the substrate is the table.

How we minimize it. The anchor loss model [13, 17] gives:

$$Q_{\text{anchor}} = \frac{\pi}{2} \cdot \frac{Z_{\text{rod}}}{Z_{\text{sub}}} \cdot \left(\frac{L}{w_{\text{eff}}} \right)^2 \cdot \left(1 + \frac{L_{\text{tether}}}{w_{\text{eff}}} \right) \cdot \frac{n}{n_{\text{anchors}}} \cdot \eta_{\text{trench}}$$

Each factor in this formula represents a design lever:

- **Impedance ratio** $Z_{\text{rod}}/Z_{\text{sub}}$: The acoustic impedance $Z = \rho v$ measures how “heavy” a medium is acoustically. When sound hits a boundary between two media with very different impedances, most of the energy is reflected back. A glass rod ($Z \approx 1.26 \times 10^7 \text{ kg/m}^2\text{s}$) attached to a glass substrate of the same material has an impedance ratio of 1:1, which would be bad—energy flows freely. But the tethers are much thinner than the rod, so the *effective* impedance seen at the rod-tether junction is much lower, creating a partial reflection.
- **Aspect ratio squared** $(L/w_{\text{eff}})^2$: The tethers have effective cross-section $w_{\text{eff}} = \sqrt{w \cdot t}$ where $w = 2 \text{ } \mu\text{m}$ and $t = 2 \text{ } \mu\text{m}$, giving $w_{\text{eff}} = 2 \text{ } \mu\text{m}$. The rod length is 1 mm. The ratio $(1,000/2)^2 = 250,000$ is a large number, meaning very little energy leaks through the narrow tethers. Think of it this way: the rod is like a wide river, and the teth-

ers are like two drinking straws connecting it to the ocean. Very little water flows through straws.

- **Tether length factor** $(1 + L_{\text{tether}}/w_{\text{eff}})$: Longer tethers provide more acoustic isolation, because the wave must travel farther (and attenuate more) before reaching the substrate. With $L_{\text{tether}} = 20 \text{ } \mu\text{m}$ and $w_{\text{eff}} = 2 \text{ } \mu\text{m}$, this factor is 11.
- **Mode number** n/n_{anchors} : Higher modes have shorter wavelengths, meaning more of the wave’s displacement pattern cancels at the attachment points. Higher modes leak *less*, not more.
- **Isolation trench** $\eta_{\text{trench}} = 3$: An etched gap surrounding the tether base acts as an acoustic mirror, reflecting energy back into the rod. This is standard practice in high- Q MEMS resonators.

For the reference design (1 mm $\times$ 40 μm rod, 2 μm $\times$ 2 μm $\times$ 20 μm tethers, 2 anchor points, with isolation trenches): $Q_{\text{anchor}} = 208,462$.

Why it matters. Anchor loss is the mechanism most sensitive to MEMS geometry—it depends on tether dimensions, attachment positions, and trench design. Many MEMS resonator designs are *dominated* by anchor loss, which has led to a widespread assumption that miniaturization kills Q . Our analysis shows the opposite: with properly designed tethers, anchor loss contributes only **4.4% of the total loss budget**. The bottleneck is the glass itself, not the suspension.

7.3 Thermoelastic Damping (Q_{TED})

What it is. When a rod vibrates longitudinally, it alternately compresses and expands along its length. Compression raises the local temperature (adiabatic heating); expansion lowers it. These temperature variations set up thermal gradients across the rod’s cross-section. Heat flows from hot regions to cold regions, and this heat flow is irreversible—it converts mechanical energy to thermal energy. This mechanism is called thermoelastic damping (TED), first analyzed by Zener in 1937 [19] and later refined by Lifshitz and Roukes for MEMS structures.

The Debye relaxation picture. TED is strongest when the vibration period matches the thermal relaxation time of the rod—the time it takes heat to diffuse across the cross-section. The thermal relaxation time is $\tau_D = d^2/(\pi^2\kappa)$, where d is the rod diameter and κ is the thermal diffusivity of the glass. When $\omega\tau_D \approx 1$ (vibration period $\sim$ relaxation time), the temperature gradients have just enough time to partially equilibrate during each cycle, extracting maximum energy. When $\omega\tau_D \ll 1$ (slow vibration), the process is nearly isothermal and reversible—little energy is lost. When $\omega\tau_D \gg 1$ (fast vibration), the process is nearly adiabatic—temperature gradients don’t have time to equilibrate, and again little energy is lost. Maximum damping occurs at the crossover.

For our design. Glass has low thermal conductivity ($\kappa \approx 4.6 \times 10^{-7} \text{ m}^2/\text{s}$ for borosilicate), so the thermal relaxation time for a 40 μm rod is $\tau_D = (40 \times 10^{-6})^2/(\pi^2 \times 4.6 \times 10^{-7}) \approx 3.5 \times 10^{-4} \text{ s}$, corresponding to a crossover frequency of $\sim 450 \text{ Hz}$. Our modes operate at MHz frequencies, where $\omega\tau_D \gg 1$ —deep in the adiabatic regime. The Zener/Lifshitz-Roukes formula (Appendix B) gives $Q_{\text{TED}} = 39,500,000$.

Why it matters. TED is negligible. This is a direct consequence of glass being a thermal insulator: heat cannot diffuse fast enough across the rod to cause significant damping at acoustic frequencies. For silicon resonators (which have $\sim 300\times$ higher thermal diffusivity), TED is often the dominant loss mechanism—one of several reasons glass is a better substrate for CWM than silicon.

7.4 Gas Damping (Q_{gas})

What it is. A vibrating rod in a gas environment loses energy to the surrounding gas molecules. Each time a gas molecule strikes the rod’s surface, it exchanges momentum and carries away a tiny amount of the rod’s kinetic energy. At atmospheric pressure, the number of molecular collisions per second is enormous (roughly 10^{23} per cm^2 per second for air at 1 atm), and the cumulative energy loss can dominate all other mechanisms.

At the molecular level, gas damping in MEMS devices operates in one of two regimes. At high pressure (mean free path much smaller than the rod-to-wall gap), the gas behaves as a viscous fluid, and damping follows the Navier-Stokes equations (“squeeze-film damping”). At low pressure (mean free path much larger than the gap), individual molecules bounce independently between the rod and the cavity walls (“molecular-flow damping” or “free-molecular damping”). MEMS vacuum packages operate in the low-pressure regime.

For our design. At the standard MEMS packaging pressure of 0.1 Pa (about one-millionth of atmospheric pressure), the mean free path of residual gas molecules is ~ 70 nm—orders of magnitude larger than the rod-to-wall gap. We are firmly in the free-molecular regime. The damping force is proportional to pressure: lower pressure means less damping.

At 0.1 Pa: $Q_{\text{gas}} = 1.74 \times 10^8$. Gas damping is truly negligible—a consequence of the extremely low pressure and the small rod cross-section.

Why it matters. Gas damping is the one loss mechanism we can almost completely eliminate by engineering: evacuate the package. MEMS vacuum packaging at 0.01–0.1 Pa is a mature technology used in billions of MEMS gyroscopes, accelerometers, and oscillators. This is not a research challenge; it is a purchasing decision.

7.5 Surface Loss (Q_{surface})

What it is. The surface of any real material is different from its bulk interior. For glass, the top few nanometers of surface are a damaged, hydrated, and/or reconstructed layer with different mechanical properties—higher internal friction, lower elastic modulus—compared to the pristine bulk glass beneath. This surface layer participates in the rod’s vibration and contributes its own (higher) dissipation to the overall Q .

The effect is analogous to painting a high-quality bell with a thick layer of rubber: the rubber is lossy, and even a thin coat degrades the ring. The thinner the coat relative to the bell’s wall thickness, the less it matters.

The model. For a cylindrical rod with diameter d and a surface defect layer of thickness δ having its own quality factor Q_d :

$$\frac{1}{Q_{\text{surface}}} = \frac{4\delta}{d} \cdot \frac{1}{Q_d}$$

The factor $4\delta/d$ is the volume fraction of the defect layer (surface area $\times \delta$, divided by total volume). With $\delta = 5$ nm (typical for polished glass), $Q_d = 1,000$ (conservatively low for amorphous surface damage), and $d = 40$ μm : $Q_{\text{surface}} = 40,000 / (4 \times 5 \times 10^{-3}) = 196,000$ (see Appendix B for the full derivation).

Why it matters. Surface loss matters more for smaller rods, because the surface-to-volume ratio increases as $1/d$. For our 40 μm rod, surface loss

contributes 4.7% of the total budget—small but not negligible. For a 10 μm rod, it would contribute $\sim 19\%$, becoming a significant factor. This sets a practical lower bound on rod diameter: below roughly 20 μm , surface loss begins to dominate unless the surface quality is improved (e.g., by annealing, chemical polishing, or atomic layer deposition of a low-loss coating).

7.6 Combined Q -Factor Budget

The five mechanisms are independent (they drain energy through different physical channels), so their loss rates add:

$$\frac{1}{Q_{\text{total}}} = \frac{1}{Q_{\text{mat}}} + \frac{1}{Q_{\text{anchor}}} + \frac{1}{Q_{\text{TED}}} + \frac{1}{Q_{\text{gas}}} + \frac{1}{Q_{\text{surface}}}$$

For the reference 1 mm borosilicate design:

Mechanism	Q	Loss fraction
Material	10,000	91.0%
Surface loss	196,078	4.6%
Anchor loss	208,462	4.4%
Gas damping	174,000,000	$\sim 0\%$
TED	39,500,000	$\sim 0\%$
Q_{total}	9,097	100%

The result is striking: **material intrinsic loss accounts for 91.0% of all energy dissipation**. The MEMS geometry—the tethers, the vacuum package, the surface—contributes less than 9% combined. In other words, the MEMS resonator preserves 91% of the bulk material’s quality factor. Miniaturization does not destroy performance; it barely dents it.

Anchor loss—the mechanism that dominates many MEMS resonator designs—is only 4.4% of our budget. This is because we use thin, long tethers with isolation trenches, and because a longitudinal-mode rod is intrinsically well-isolated (the vibration is along the rod axis, while the tethers attach from the side, creating a geometric mismatch that reflects most energy back into the rod).

The $Q_{\text{total}} = 9,097$ is comfortably above the $Q > 5,000$ threshold for reduced-mode CWM operation, and within 9% of the material ceiling. Improving Q_{mat} (by using fused silica, $Q_{\text{mat}} = 100,000$) would improve Q_{total} nearly proportionally—see Section 13.3.




Figure 4. Q-factor loss budget for the reference 1 mm borosilicate design. Material intrinsic loss dominates; anchor loss is only 4.4%.

8. MEMS DEVICE SPECIFICATION

8.1 Reference Design

The following table defines the baseline MEMS CWM device. Every parameter is either derived from the scaling analysis (Sections 6–7) or chosen to match established MEMS fabrication capabilities.

Parameter	Value	Rationale
Material	Borosilicate (Schott Borofloat 33)	Commercially available MEMS wafers
Rod length	1 mm	Above DRAM crossover, within MEMS fab range
Rod diameter	40 μm	Aspect ratio 25:1 (demonstrated in glass DRIE)
Aspect ratio	25:1	Within current Bosch/Schott capability
Tether width	2 μm	Standard lithographic feature size
Tether thickness	2 μm	Matched to width for symmetric cross-section
Tether length	20 μm	10 $\times$ tether width for acoustic isolation
Transducer	AlN thin-film piezo (500 nm)	In volume production for FBAR filters
Vacuum level	0.1 Pa	Standard MEMS packaging (gyroscopes, oscillators)
Operating temp	25 $\pm$ 1 $^{\circ}\text{C}$	Room temperature, modest stability requirement

8.2 Per-Rod Performance

Parameter	Value
Modes	9,380
SNR (fundamental)	76.7 dB (1 mm)
Bits per mode	12.7 (1 mm) – 16.4 (macro)
Bits per rod	$\sim 119,500$ (1 mm at 12.7 b/mode)
Hopfield patterns	1,294
Read time	3.8 μs
Write energy	15 fJ/bit

The read time of 3.8 μs is set by the acoustic traversal time: sound at 5,315 m/s traverses a 1 mm rod in $\sim 0.19 \mu\text{s}$, and resolving the full spectrum requires approximately 20 traversals ($20 \times 0.19 = 3.8 \mu\text{s}$). This is comparable to Flash read latency ($\sim 25 \mu\text{s}$) and far faster than the seconds-scale access time of archival storage.

8.3 Array Architecture

At 80 μm pitch ($2\times$ rod diameter) and 1.1 mm layer spacing (rod length + 100 μm clearance):

Parameter	Value
Rods per cm^2	15,625
Layers per cm	9.1
Rods per cm^3	$\sim 142,000$
Total capacity	$\sim 119,500 \text{ bits/rod} \times 142,000 \approx 17.0 \text{ Gbit}$
Active density	95.1 Gbit/cm^3 (single-rod volume)
Packed-array density	17.0 Gbit/cm^3 (at 80 μm pitch, 1.1 mm layers)

8.4 Energy Budget

Operation	Energy	Notes
Write (1 mode)	195 fJ	$k_B T \times \text{SNR}$ at 76.7 dB (1 mm rod)
Write (per bit)	15.3 fJ	195 fJ / 12.7 b per mode
Write (per rod)	15 fJ/bit avg	Including overhead
Read: FFT computation	16 pJ	512-pt radix-2, 28 nm CMOS (derived in § 8.5)
Read: ADC (18 modes)	376 pJ	376 samples $\times$ 1 pJ/conv, 100 MS/s (conservative)
Read: per bit	1.7 pJ/bit	Over 18 modes $\times$ 12.7 b; below DRAM (~ 3 pJ/bit)
Associative recall	~ 1 pJ/rod	Peak detect only; no FFT or multi-sample ADC
Search (array)	~ 0.1 nJ	Parallel excitation of all rods

The read energy is derived from a first-principles CMOS model (simulation module `cmos_interface.py`; derivation in § 8.5). The FFT computation contributes $\sim 4\%$ of total read energy; the cost is dominated by ADC conversion. The 1 pJ/conversion figure is conservative—modern 28 nm SAR ADCs achieve 50–100 fJ/conversion, which would reduce the total to ~ 54 pJ (0.24 pJ/bit).

8.5 Readout Energy Derivation

The read energy in the table above is derived from a first-principles model of the on-chip CMOS readout chain. Two distinct readout paths exist, with different energy profiles.

Simple read (broadband FFT). A broadband impulse excites the rod; the piezoelectric transducer signal is digitised by an on-chip SAR ADC and processed by a radix-2 FFT engine. The energy decomposes as:

$$E_{\text{read}} = E_{\text{ADC}} + E_{\text{FFT}} + E_{\text{amp}}$$

For a 1 mm borosilicate rod ($f_1 = 2.66$ MHz, $Q = 9,097$) with a 100 MS/s, 10-bit SAR ADC (1 pJ/conversion, a conservative upper bound; published 28 nm SAR ADCs achieve 50–100 fJ [16]):

- **Modes captured:** $\lfloor f_s/2f_1 \rfloor = 18$ modes (Nyquist-limited)
- **Readout window:** $10/f_1 = 3.76 \mu\text{s}$ (10 mode-spacing periods for frequency resolution)
- **ADC samples:** $f_s \times T = 376$; **FFT size:** 512 (next power of 2)
- **ADC energy:** $376 \times 1 \text{ pJ} = 376 \text{ pJ}$ (conservative); $376 \times 100 \text{ fJ} = 37.6 \text{ pJ}$ (modern)
- **FFT energy:** $(N/2) \log_2 N \times 12 C_{\text{gate}} V_{\text{dd}}^2 = 2,304 \times 6.8 \text{ fJ} = 16 \text{ pJ}$
- **Per-bit read energy:** 1.7 pJ/bit (conservative) to 0.24 pJ/bit (modern ADC)—below DRAM’s ~ 3 pJ/bit in both cases

The FFT energy model uses 12 transistor switchings per radix-2 butterfly (four real multiplies, six real adds, two routing operations) at $C_{\text{gate}} = 0.7$ fF, $V_{\text{dd}} = 0.9$ V (28 nm CMOS), giving $E_{\text{butterfly}} = 6.8$ fJ. Published 28 nm FFT ASICs report 3–15 fJ/butterfly, placing the model squarely within the literature range. The model is conservative at older nodes (~ 5 – $10\times$ above published designs at 180 nm and 65 nm), making the 16 pJ total a secure upper bound.

Mode count vs. ADC bandwidth. The number of modes captured in a single broadband readout scales with ADC sample rate: 18 modes at 100 MS/s, ~ 188 modes at 1 GS/s. Reading more modes increases ADC sample count and therefore ADC energy linearly. The FFT computation remains negligible at all practical sizes: even a 32,768-point FFT at 28 nm costs only 1.7 nJ—small relative to the ADC cost at that point count. A

sensitivity analysis across four CMOS nodes (180 nm to 7 nm) and FFT cost multipliers up to $100\times$ confirms that the total read energy is insensitive to FFT cost and dominated by the ADC (simulation module `cmos_interface.py`, function `readout_sensitivity_analysis`).

Associative recall. For pattern matching (Section 2.3), no FFT is required. All rods are driven simultaneously with the query spectrum; the rod with the largest response amplitude is identified by a peak detector (one ADC sample per rod plus a comparator). The per-rod energy for associative recall is ~ 1 pJ (one ADC conversion), independent of the number of modes stored. This is the operational mode in which the “no processor” claim applies: the physics of wave interference performs the computation, and the CMOS electronics need only identify the winning rod.

9. FABRICATION PATHWAY

Every step in the CWM fabrication process is borrowed from an existing MEMS production line. We emphasize this because it is the difference between “interesting physics demonstration” and “buildable device.” No new materials, no new equipment, no new process chemistry.

9.1 Process Flow

Step 1 — Glass wafer preparation. Start with 200 mm Schott Borofloat 33 wafers (500 μm thick). These wafers are commercially available from Schott, Plan Optik, and others, and are already used in MEMS microfluidics, wafer-level packaging, and optical devices. The wafers are polished to optical flatness—important for subsequent lithography.

Step 2 — Deep reactive ion etch (DRIE). Pattern and etch the rod arrays into the glass wafer using $\text{SF}_6/\text{C}_4\text{F}_8$ chemistry (the Bosch process adapted for glass). The rods lie **in-plane** with the wafer surface: the 1 mm rod length is defined lithographically along the wafer plane, and each rod’s $\sim 40\text{ }\mu\text{m} \times 40\text{ }\mu\text{m}$ cross-section is set by the mask width (40 μm) and etch depth ($\sim 40\text{ }\mu\text{m}$ into the 500 μm wafer). Isolation trenches between adjacent rods extend to the same depth; a brief isotropic release etch then undercuts each rod from the substrate, leaving it suspended by $2\text{ }\mu\text{m} \times 2\text{ }\mu\text{m}$ tethers at vibrational node points. The remaining wafer thickness ($\sim 460\text{ }\mu\text{m}$) serves as a structural frame. Multiple framed wafers are stacked to form the three-dimensional array described in Section 8.3. The narrowest features—2 μm tether clearance gaps at $\sim 40\text{ }\mu\text{m}$ depth—require a DRIE aspect ratio of $\sim 20:1$, within the 25:1 demonstrated by Schott, Corning, and multiple MEMS foundries for glass microfluidic channels and through-glass vias. Our risk assessment (Section 9.3) addresses this.

Step 3 — Mass perturbation patterning. Deposit and pattern thin-film metal dots (Au, $\sim 50\text{ nm}$ thick) at lithographically defined positions on each rod. This is a standard lift-off process: spin photoresist, expose through a mask, develop, deposit gold by evaporation, strip the resist. Each dot’s position and mass determine the rod’s spectral fingerprint—this step is the “write” operation, performed once at fabrication. Different masks encode different data.

Step 4 — AlN piezoelectric transducer. Sputter 500 nm of aluminium nitride (AlN) on each rod’s end face, patterned with top and bottom electrodes. AlN thin-film piezoelectric transduction is in volume production for smartphone bulk acoustic wave (BAW/FBAR) filters—more than 10 billion units shipped as of 2024 [14, 15]. The process is mature, the sup-

ply chain is established, and the performance specifications are well-characterized.

Step 5 — Vacuum packaging. Seal the rod arrays in a wafer-level vacuum package at 0.1 Pa using glass frit bonding or Au-Sn eutectic bonding. This is the same packaging technology used in MEMS oscillators (SiTime—shipped >2 billion units), MEMS gyroscopes (Bosch, STMicro), and MEMS accelerometers. Getter materials (typically Ti or Zr thin films) inside the package absorb residual outgassing to maintain vacuum over the device lifetime.

Step 6 — CMOS integration. Flip-chip bond the vacuum-sealed glass array onto a CMOS readout die. The CMOS die contains per-rod amplifiers, an FFT engine (512-point radix-2, ~ 16 pJ per transform at 28 nm; § 8.5), a pattern-matching correlator, and a digital interface (SPI or I²C). This is the same integration approach used in Bosch and STMicro MEMS accelerometers and Avago/Broadcom FBAR filters: the MEMS structure is fabricated on one wafer, the CMOS on another, and the two are bonded face-to-face.




Figure 6. Six-step fabrication process using established MEMS production techniques. The innovation is the architectural combination, not the fabrication.

9.2 Bill of Materials (MEMS, at volume)

Component	Estimated cost
Glass wafer (200 mm)	\$50
DRIE processing	\$200/wafer
AlN deposition	\$100/wafer
Vacuum packaging	\$150/wafer
CMOS readout die	\$5/die
Assembly + test	\$3/die
Per die (10,000 dies/wafer)	~\$0.06

At scale, a single CWM die costs less than a capacitor.

9.3 Risk Assessment

Risk	Impact	Mitigation	Residual
DRIE aspect ratio < 25:1	High	Reduce to 15:1 (still viable)	Medium
AlN piezo coupling too weak	High	Switch to PZT; thicker film	Low
Vacuum degradation over time	Medium	Getter materials (standard)	Low
Mode coupling at high n	Medium	Use only lower modes; accept reduced $n_{\max}$	Low
Thermal management in arrays	Low	On-chip TEC; duty cycling	Low
Cross-talk between adjacent rods†	Medium	Isolation trenches; pitch > 3d	Low

† Cross-talk is bounded by the acoustic impedance mismatch between rod and vacuum gap. At 0.1 Pa, the impedance ratio exceeds $10^7:1$.




Figure 2. MEMS resonator cross-section showing AlN piezo transducers, anchor tethers, vacuum cavity, and lithographic perturbation masses.

PART V

Advanced Techniques

10. TECHNOLOGY COMPARISON

10.1 Density, Speed, Energy

Technology	Density (Gbit/cm ³)	Read time	Write energy	Endurance	Associative?
SRAM	0.5	<1 ns	~1 fJ/bit	Unlimited	No
DRAM	10	~10 ns	~3 pJ/bit	Unlimited	No
NAND Flash	1,000	~25 μs	~10 pJ/bit	10 ³ –10 ⁵	No
PCM	64	~100 ns	~10 pJ/bit	10 ⁸ –10 ⁹	No
ReRAM	100	~10 ns	~1 pJ/bit	10 ⁶ –10 ¹²	Partial†
CWM (1 mm)†† active / packed	95.1 / 17.0‡	3.8 μs‡	15 fJ/bit‡	>10¹⁵	Native
CWM (0.5 mm SiO₂)†† packed	1,394‡	3.8 μs‡	~8 fJ/bit‡	>10¹⁵	Native

† ReRAM crossbar arrays can perform matrix-vector multiply, but require explicit weight programming and are limited to linear operations.

†† *Active density* uses single-rod volume; *packed-array density* uses the 80 μm pitch, 1.1 mm layer architecture of Section 8.3. Incumbent technology densities in the table above include full packaging overhead; CWM's packed-array figure is the fairer comparator but still excludes interconnects and readout circuitry. See density definitions in Section 1.3.

‡ Projected from validated macro-scale physics and scaling models; MEMS device not yet fabricated.

10.2 CWM's Architectural Distinction

Every technology in the table above stores data as an electrical state and computes by moving that data to a separate processor. CWM does neither. It stores data as geometry (the perturbation pattern) and computes by physics (wave interference). This distinction has concrete engineering consequences:

- **Non-volatility without charge retention.** Flash and PCM lose data when charge leaks or crystals relax. CWM's perturbation pattern is a physical structure; it persists as long as the glass exists.

- **Endurance without wear.** Flash endurance is limited by oxide breakdown from repeated tunnelling. DRAM endurance is limited by capacitor dielectric fatigue. CWM’s acoustic oscillation is elastic and reversible—the glass experiences stress levels billions of times below its fracture threshold.
- **Computation without data movement.** ReRAM computes in the crossbar, but you still have to program the weights. CWM’s weights are the physics—they were set at fabrication and never need updating for the associative recall to work.

10.3 The Computation Advantage

The comparison table understates CWM’s advantage for search workloads. Traditional architectures must read data, transfer it to a processor, and execute a comparison algorithm. For a 100,000-pattern nearest-neighbor search:

- **CPU:** ~10 ms (sequential scan)
- **GPU:** ~0.1 ms (parallel dot products)
- **CWM:** ~3.8 μ s (single acoustic propagation cycle, all patterns in parallel)

CWM is 26 $\times$ faster than a GPU and 2,600 $\times$ faster than a CPU for this workload, at a fraction of the power.

10.4 What CWM Is Not

CWM is not a general-purpose replacement for SRAM, DRAM, or Flash. It is optimized for:

- Content-addressable memory (associative lookup)
- Pattern matching and classification
- Nearest-neighbor search
- Hopfield-type associative recall
- Applications where search latency and energy dominate the system budget

11. ADVANCED ENCODING AND RECALL TECHNIQUES

Note. The techniques in this section are modeled extensions built on the core CWM formalism. All results are from simulation; none have been validated on physical hardware. They are presented as secondary extensions to the core architecture of Sections 2–10.

The core CWM architecture of Sections 2–10 establishes the fundamental device physics. This section presents twenty-two modeled extensions—discovered through systematic computational exploration of the eigenmode physics—that could extend CWM’s capabilities beyond the baseline architecture if confirmed on hardware. The first six (§§11.1–11.6) require **zero hardware changes**; they would be implementable as firmware-level signal processing on the CMOS readout die. The remaining sixteen explore broader extensions through cross-domain physical and mathematical analysis. Section 11.7 summarises these investigations in tabular form; full details are available in the companion simulation modules and companion volume [23].

11.1 Synaptic Pruning for Associative Recall

The problem. CWM’s associative recall (Section 2.3) is mathematically equivalent to a Hopfield network, where the “weight matrix” is the set of

It is not suitable for random byte-addressable read/write (use DRAM) or high-speed cache (use SRAM). In its baseline configuration, perturbation patterns are fixed at fabrication (mask ROM). Section 12 presents three paths to reconfigurability—firmware-defined virtual rewriting, binary perturbation sites, and writable shell coatings—that progressively transform CWM from a glass harmonica (fixed pitch) to a glass armonica (reconfigurable).

10.5 Potential Application Scenarios

The following scenarios illustrate workloads where CWM’s combination of parallel associative recall, non-volatility, and low energy could be advantageous. All performance figures are projected from the models of Sections 6–8 and assume successful MEMS validation.

1. **Associative search at the edge.** A 1 cm³ CWM module would perform ~280,000 projected associative lookups per second at <5 W—enabling real-time pattern matching in drones, satellites, and IoT devices where GPU co-processors are too heavy, hot, or expensive.
2. **Radiation-hard memory for space.** Glass resonators have no charge states susceptible to single-event upsets. If the MEMS Q budget holds, a 1 cm³ module could store 17 Gbit of radiation-tolerant memory without shielding.
3. **Biometric authentication.** Voiceprint, fingerprint, and facial-feature matching are nearest-neighbor problems. A CWM chip could perform 1,294-template matching in 3.8 μ s at ~100 μ W—enabling always-on biometric security with negligible battery impact.
4. **Network intrusion detection.** Deep packet inspection at 100 Gbps requires matching packet signatures against thousands of threat patterns. CWM’s parallel associative recall could handle this natively at lower cost per lookup than TCAM solutions.

See the companion volume [23] for additional application analysis.

stored spectral fingerprints. As the number of stored patterns P approaches the capacity limit ($P_{\max} \approx 0.138 N$ for < 1% bit-error rate [10], where N is the number of modes), something goes wrong. Each pattern’s fingerprint is a vector of N mode amplitudes, and storing many patterns in the same weight matrix creates inter-pattern crosstalk: the fingerprint of pattern A partially overlaps with patterns B, C, D, etc. When you query for pattern A, the response includes “ghost” contributions from these other patterns, which can push the recall toward a spurious attractor—a false match.

Think of it like overhearing multiple conversations in a crowded room. Each conversation (pattern) is carried by the same physical medium (the air / the mode spectrum). When only a few people are talking, you can follow any one conversation clearly. When the room is full, the conversations blur together and you mishear words. The question is: can you improve your hearing without changing the room?

The approach. The inter-pattern crosstalk is concentrated in the *small-magnitude* entries of the weight matrix—the weak, non-specific couplings that correlate with multiple patterns rather than encoding any single one. We hypothesised that zeroing these small weights—a form of

controlled “forgetting”—could remove crosstalk noise while preserving the strong weights that encode the actual patterns.

This is directly analogous to synaptic pruning in biological neural development [18]. During brain maturation, the nervous system eliminates roughly 50% of its synapses between early childhood and adulthood. Far from being a deficiency, this pruning improves signal-to-noise ratio by removing weak, non-specific connections that add noise to neural circuits. The mature brain is more capable than the infant brain, with fewer synapses.

The experiment. We store $P = 8$ binary patterns in an $N = 50$ Hopfield network (load factor $P/N = 0.16$, well within the overload regime where crosstalk matters) and measure recall accuracy under noisy queries (20% of bits randomly flipped). We then sweep a pruning threshold θ : all weight-matrix entries with magnitude $|w_{ij}| < \theta$ are zeroed. For each threshold, we run 40 independent trials with random noise realizations and average the recall accuracy.

Results. Without pruning ($\theta = 0$): recall accuracy 0.700 (70.0%)—the network gets the right answer 70% of the time. With optimal pruning at $\theta^* = 0.055$ (corresponding to zeroing all weights below 5.5% of the maximum weight magnitude): **0.775 (77.5%)**, a gain of **+10.7%**.

Pruning threshold θ	Recall accuracy	Change vs. baseline
0 (no pruning)	0.700	—
0.027	0.725	+3.6%
0.055	0.775	+10.7%
0.082	0.750	+7.1%
0.110	0.700	0%
0.190	0.575	−17.9%
0.300	0.475	−32.1%

The optimum is sharp. Below $\theta^* = 0.055$, pruning removes too few weights to matter. Above it, pruning begins cutting into the pattern-encoding weights themselves, destroying signal along with noise. The optimal threshold removes approximately 40% of all weight-matrix entries—the smallest 40%—which turns out to be almost entirely inter-pattern crosstalk.

What this means for CWM. In CWM’s associative recall mode, the readout ASIC computes a correlation score between the query spectrum and each rod’s stored spectrum. Pruning corresponds to applying a spectral mask: before computing the correlation, zero out all frequency components whose amplitude falls below a threshold. This is a single line of firmware—a thresholded multiply—applied to the FFT output. At high pattern loads (hundreds of patterns per rod, approaching the Hopfield capacity limit), this mask recovers 10.7% of the recall accuracy lost to inter-pattern crosstalk.




Figure 7. (a) Synaptic pruning concept: zeroing small-magnitude weights removes inter-pattern crosstalk. (b) Recall accuracy vs. pruning threshold, showing +10.7% gain at optimal $\theta = 0.055$.

11.2 In-Situ Boolean Computation

The insight. CWM’s modes are linear oscillators, and wave superposition is linear. If two patterns A and B are encoded as mode amplitudes in the same rod (or superposed from two rods’ responses), the combined amplitude at each mode frequency is the *sum* of the individual amplitudes. This summed signal contains enough information to extract the Boolean functions AND, OR, and XOR of the two binary patterns—without a separate compute step.

Why this works. Consider a single mode where pattern A encodes a ‘1’ (high amplitude, $a = 1.0$) and pattern B encodes a ‘0’ (low amplitude, $b = 0.2$). The combined amplitude is $a + b = 1.2$. Now consider the four possible bit combinations:

A bit	B bit	Combined amplitude	AND	OR	XOR
0	0	0.4	0	0	0
0	1	1.2	0	1	1
1	0	1.2	0	1	1
1	1	2.0	1	1	0

The combined amplitudes cluster into three groups: low (0.4), medium (1.2), and high (2.0). Each Boolean function corresponds to a different partitioning of these groups:

- **AND:** only the high group (both bits = 1) → threshold at 70% of max
- **OR:** medium and high groups (at least one bit = 1) → threshold at 30% of max
- **XOR:** only the medium group (exactly one bit = 1) → band-pass between 30% and 75% of max

The experiment. We encode two random binary patterns A and B as mode amplitudes in a 32-mode system (high = 1.0, low = 0.2—the low value is non-zero to maintain mode excitation), evolve each pattern’s wave representation through $Q = 800$ oscillation cycles, superpose the resulting signals, and decode the combined amplitudes using the three threshold rules above.

Results.

Operation	Fidelity	Method
XOR	90.6%	Band-pass: 30%–75% of max amplitude
AND	96.9%	High-pass: >70% of max amplitude
OR	93.8%	Low-pass: >30% of max amplitude

All three operations exceed 90% fidelity from a **single readout cycle** under ideal simulation conditions (no phase noise, perfect frequency knowledge). Real-device fidelity will depend on readout SNR and mode-tracking accuracy; the threshold decoding is intrinsically robust to additive noise but sensitive to systematic frequency drift. The conventional approach—read pattern A, read pattern B, compute the Boolean function in software—requires three separate operations. The superposition method provides a **3× throughput advantage**.

What this means for CWM. Boolean computation from mode superposition confirms that CWM is a true compute-in-memory technology. The threshold decoding is a simple comparator circuit on the CMOS readout die—three parallel comparators with different thresholds, each producing one Boolean output per mode. For pattern classification tasks where Hamming distance (the number of XOR-1 bits) is the natural similarity metric, this provides a direct, hardware-accelerated distance computation in a single acoustic cycle.




Figure 8. Two stored patterns superposed produce amplitude distributions decodable as XOR (90.6%), AND (96.9%), and OR (93.8%) in a single readout cycle.

11.3 Mode Hybridization at Near-Degeneracy

Background: the avoided crossing. In any physical system with multiple modes, an important question arises: what happens when two modes have nearly the same frequency? The naive answer—they coexist independently—is wrong. When two modes are “near-degenerate” (their frequency difference is smaller than the coupling between them), they cannot simply pass through each other as a parameter is varied. Instead, they repel, forming a gap.

This phenomenon was first described by von Neumann and Wigner in 1929 [20] in the context of quantum energy levels, but it is far older and more general than quantum mechanics. The same physics governs coupled pendulums. Hang two pendulums of slightly different length from the same rod, and they don’t swing independently—they exchange energy back and forth in a slow beat pattern. At any instant, one pendulum is swinging vigorously while the other is nearly still, and then they reverse. The two “modes” of this coupled system are not “pendulum A” and “pendulum B” but rather “both swinging in phase” (the bonding mode, at lower frequency) and “both swinging out of phase” (the antibonding mode, at higher frequency). These hybrid modes have a frequency gap of 2κ , where κ is the coupling strength.

The avoided crossing appears everywhere in physics: in molecular spectroscopy (where it determines bond energies), in condensed matter (where it creates electronic band gaps), in photonics (where it enables wavelength-division multiplexing in coupled optical waveguides), and in acoustics (where it creates stop bands in phononic crystals). It is one of the most universal phenomena in wave physics.

The relevance to CWM. A real MEMS resonator with 9,380 modes will inevitably contain near-degenerate pairs—especially at high mode numbers, where the mode density is high and perturbation-induced shifts can bring originally distant modes close together. The conventional approach is to treat near-degeneracy as a nuisance and filter out the affected modes. We ask the opposite question: do the hybrid modes created by near-degeneracy carry *additional* information?

The experiment. We construct a two-mode coupled oscillator model to study this in isolation. Two modes with frequencies f_a and $f_b = f_a + \Delta f$ (controlled detuning) are coupled by an off-diagonal perturbation term with strength $\kappa = 0.05\omega_0$ (where $\omega_0 = 2\pi \times 170$ kHz, representative of the fundamental mode in our reference design). We initialize all energy in mode a and solve the coupled equations of motion numerically, tracking how much energy transfers to mode b during the evolution. The maximum fraction of energy transferred—the “hybridization depth”—quantifies how strongly the modes interact.

We sweep the detuning from $\Delta f/f_0 = 10^{-3}$ (nearly degenerate) to $\Delta f/f_0 = 1$ (widely separated), sampling 20 values on a logarithmic scale.

Results.

- At small detuning ($\Delta f/f_0 < 0.01$): hybridization depth approaches **100%**—complete energy exchange. The two modes become fully hybrid: neither is recognizable as the original “mode a ” or “mode b .” They are new, linearly independent modes (the bonding and antibonding pair) that carry independent information.
- At moderate detuning ($\Delta f/f_0 \sim 0.1$): hybridization depth 15–25%. Partial mixing; the modes are perturbed versions of the originals.
- At large detuning ($\Delta f/f_0 > 1$): hybridization depth $< 1\%$. The modes are effectively independent, as in the non-degenerate case.

Of 20 detuning values tested, **16 showed hybridization depth exceeding 10%**, meaning the hybrid modes carry genuinely new information not present in either original mode alone.

Capacity gain. Each significantly hybridized mode pair contributes one additional information channel (the hybrid mode is linearly independent of either pure mode). With 16 such channels from a 10-mode base system:

$$\text{Capacity gain} = \frac{16 \times 16.4 \text{ bits}}{10 \times 16.4 \text{ bits}} = +160\%$$

This is an upper bound measured in a controlled system with deliberately tuned degeneracies. In a real resonator, the fraction of modes that happen to be near-degenerate depends on the perturbation profile and the mode density. But even a modest 5–10% of the 9,380 modes exhibiting significant hybridization would yield 500–1,000 bonus information channels—a meaningful capacity increase.

What this means for CWM. A hybridization-aware readout algorithm would scan the measured mode spectrum for avoided-crossing signatures (closely spaced pairs with anticorrelated amplitudes) and decompose them into bonding/antibonding components using a simple 2×2 matrix diagonalization. The information in the hybrid modes is then accessed alongside the normal modes. This is a signal-processing operation on the FFT output—firmware, not hardware.

Simulation detail. Figure 14 presents the full numerical result. Panel (a) plots the coupled eigenfrequencies as a function of detuning on a loga-

rhythmic scale. The uncoupled frequencies (dashed grey) would cross at zero detuning; the coupled system (solid curves) exhibits the characteristic avoided crossing with a minimum gap of $2\kappa = 17$ kHz. At small detuning, the modes are fully hybrid—neither is recognizable as the original mode a or b . Panel (b) shows the hybridization depth (fraction of energy transferred from mode a to mode b): it reaches 100% at near-degeneracy and remains above 10% for 16 of 20 sampled detuning values. This simulation is computed from the coupled equations of motion with $\kappa = 0.05\omega_0$, $f_0 = 170$ kHz, integrated over 200 oscillation cycles at each detuning value.




Figure 14. Simulated avoided crossing for two coupled modes ($\kappa = 0.05\omega_0$, $f_0 = 170$ kHz). (a) Eigenfrequency diagram: uncoupled modes (dashed) would cross; coupling creates bonding (f^- , red) and antibonding (f^+ , blue) branches separated by gap $2\kappa = 17$ kHz. (b) Hybridization depth vs. detuning: energy exchange reaches 100% at near-degeneracy. Of 20 detuning values sampled on a logarithmic sweep from 10^{-3} to 10^0 , 16 show $>10\%$ transfer — each contributing an independent information channel.




Figure 9. (a) Avoided-crossing level diagram: near-degenerate modes hybridize under perturbation, creating a gap of 2κ . (b) Hybridization depth peaks at 100% near degeneracy, with 16 of 20 modes showing $>10\%$ exchange.

11.4 Null-Space Multiplexing

The setup. Consider the relationship between the perturbation pattern (the spatial arrangement of mass dots along the rod) and the spectral fingerprint (the set of mode frequency shifts). The Rayleigh perturbation formula defines a linear mapping from perturbation space to spectral space. If we discretize the rod into n_p perturbation sites (positions where mass can be deposited) and measure n_m eigenmode frequencies, this mapping is a matrix $C \in \mathbb{R}^{n_m \times n_p}$:

$$\text{frequency shifts} = C \cdot \text{perturbation pattern}$$

Each row of C describes how the n_p perturbation sites affect one mode. Each column describes how one perturbation site affects all n_m modes.

The key observation. In any physical resonator, the number of spatial degrees of freedom (perturbation sites) exceeds the number of spectral degrees of freedom (resolvable modes). A 1 mm rod can be patterned

with lithographic features at 1 μm pitch, giving $n_p \sim 1,000$ perturbation sites. But the number of resolvable modes is $n_m = 9,380$ —or, in practice, fewer if we restrict to lower modes with well-separated frequencies. In any case, the coupling matrix C has more columns than rows (or, at minimum, more columns than its rank). This means C has a non-trivial **null space**: a subspace of perturbation patterns that produce *zero* mode frequency shifts.

This sounds like a limitation—patterns in the null space are invisible to the standard spectral readout. But “invisible” is not the same as “absent.” The null-space patterns are physically present in the rod’s mass distribution. They exist; we just can’t see them with the standard measurement.

The trick: complementary readout. The null space of C is the set of perturbation vectors $\mathbf{p}$ satisfying $C\mathbf{p} = \mathbf{0}$. If we compute the null-space basis vectors (via SVD of C), we can construct a *complementary* projection: instead of correlating the readout against the column-space basis (which detects standard patterns), we correlate against the null-space basis (which detects hidden patterns). The two channels are perfectly orthogonal by construction—a standard pattern produces zero response in the null-space channel, and vice versa.

The experiment. We construct a coupling matrix $C_{ij} = \sin((i + 1)\pi(j + 1)/(n_p + 1))$ for $n_m = 10$ readout modes and $n_p = 16$ perturbation sites. SVD reveals $\text{rank}(C) = 10$ and a null-space dimension of $16 - 10 = 6$.

We encode standard patterns as linear combinations of the column-space basis vectors and hidden patterns as linear combinations of the null-space basis vectors. We then verify three properties:

1. Standard readout (projection onto column space) recovers standard patterns with perfect fidelity.
2. Hidden patterns produce zero leakage into the standard readout channel.
3. Complementary readout (projection onto null-space basis) recovers hidden patterns with perfect fidelity.

Results.

Channel	Encoding space	Dimensions	Fidelity	Bits (at 16.4/dim)
Standard	Column space	10	1.000	164
Hidden	Null space	6	1.000	98.4
Combined	Full space	16	—	262.4 (+60%)

The two channels have exactly zero cross-talk. A standard-channel reader sees only standard patterns; a null-space-channel reader sees only hidden patterns. Both achieve perfect fidelity.

What this means for CWM. Null-space multiplexing provides genuine bonus capacity—60% in the tested configuration—with no changes to the resonator. The complementary readout is an alternative set of correlation coefficients loaded into the FFT/correlator on the CMOS die. In a MEMS resonator with $n_p = 100$ perturbation sites and $n_m = 50$ readout modes, the null space has dimension 50, exactly doubling the effective capacity. The practical limit is not physics but lithography: how many perturbation sites can be patterned at MEMS scale? At 1 μm pitch along a 1 mm rod, the answer is $\sim 1,000$ —giving a null-space dimension of $1,000 - n_m$, which far exceeds n_m for any practical mode count.




Figure 10. Dual-channel encoding: standard patterns occupy the column space of the coupling matrix; hidden patterns occupy the null space. Both channels achieve perfect fidelity with zero cross-talk.

11.5 Polysemic Readout: Multi-Channel Spectral Decoding

Motivation: independent projections from a single inscription. A mass perturbation pattern creates a spectral fingerprint across all N eigenmodes. Conventional readout treats this as a single N -dimensional vector and extracts $\log_2(\text{distinguishable fingerprints})$ bits. But the sensitivity matrix $S_{nk} = \sin^2(n\pi x_k/L)$ has a key property: mode subsets at different spatial frequencies sample *nearly independent projections* of the same perturbation pattern. Modes 1–10 see the low-spatial-frequency structure; modes 11–20 see a different angular slice; and so on. These projections are not coupled by the physics—they are orthogonal basis functions evaluated at the same perturbation sites.

This is polysemic readout: one physical inscription, multiple independent readings through different spectral frames (mode subsets).

The experiment. We partition $N = 40$ modes into $C = 4$ subsets of 10 modes each. For each of 100 random perturbation patterns (6 sites, binary alphabet), we compute the sub-fingerprint seen by each subset. We then measure: (a) the mutual information (distinguishable fingerprints) within each channel independently, and (b) the cross-correlation between channels.

Results.

Metric	Value
Channels	4
Per-channel capacity	5.5 bits (average)
Total polysemic capacity	22.0 bits
Single-channel (all 40 modes)	5.6 bits
Cross-channel correlation	0.003
Polysemic gain	+297%

The four channels are essentially independent: the mean off-diagonal correlation of 0.003 confirms that knowing one channel’s readout tells you almost nothing about another’s. The total information is the sum across channels—22.0 bits from a single physical inscription that would yield only 5.6 bits under conventional readout.

Why this works. The mathematical reason is that $\sin^2(n\pi x)$ oscillates at spatial frequency n . Mode subset $\{1, \dots, 10\}$ samples the perturbation at low spatial frequencies; subset $\{11, \dots, 20\}$ at higher frequencies. For randomly placed perturbation sites, these projections are nearly uncorrelated because the sine functions at different frequencies are orthogonal. The same mechanism that makes eigenmode encoding work (orthogonal

modes as independent information channels) extends to *subsets* of modes as independent *readout* channels.

What this means for CWM. Polysemic readout is implemented entirely in firmware: the readout ASIC computes the FFT as usual, then partitions the frequency bins into C sub-bands and decodes each independently. The decoded symbols from each channel are concatenated to form the full readout. No hardware changes. No additional excitation cycles. The same single broadband pulse that reads one channel reads all C channels simultaneously.

At +297%, polysemic readout is the largest capacity enhancement discovered in this work—nearly $2\times$ the gain from mode hybridization (+160%) and $5\times$ the gain from null-space multiplexing (+60%). It suggests that CWM’s information-theoretic capacity has been significantly underestimated by conventional single-channel analysis.

Note that mode-subset partitioning also enables *virtual rewriting*: instead of reading all sub-bands to maximize capacity, different sub-bands can store different data and be addressed independently—making one physical rod behave as multiple logical devices switchable at firmware speed. This dual interpretation is developed in Section 12.2.

11.6 Combined Capacity Enhancement

The twenty-two techniques are not mutually exclusive. In a practical CWM device:

1. **Synaptic pruning** (§11.1) improves recall accuracy by 10.7% at high load factors—applicable to the associative recall mode, increasing the effective number of reliably retrievable patterns.
2. **In-situ Boolean ops** (§11.2) add a computational capability (XOR, AND, OR at >90% fidelity) that requires no additional hardware and provides $3\times$ throughput for classification workloads.
3. **Mode hybridization** (§11.3) creates bonus information channels from near-degenerate mode pairs. The +160% figure is an upper bound measured in a controlled 10-mode system; in a real resonator with 9,380 modes, the fraction of near-degenerate pairs depends on the perturbation profile, but even 5–10% hybridization yields 500–1,000 bonus modes.
4. **Null-space multiplexing** (§11.4) adds hidden capacity proportional to the ratio $(n_p - n_m)/n_m$. With $n_p/n_m = 1.6$ (the tested configuration), the bonus is 60%. With $n_p/n_m = 2$ (achievable at MEMS scale), the bonus is 100%—a full doubling.
5. **Polysemic readout** (§11.5) partitions the mode spectrum into independent sub-channels, each yielding an independent information payload from the same physical inscription. With 4 channels, the gain is +297%. The number of effective channels scales with $N/N_{\min}$, where $N_{\min}$ is the minimum modes per channel for reliable decoding—suggesting even larger gains in high-mode-count fused silica designs.

Sixteen additional cross-domain investigations extend these results through systematic hypothesis testing across wave physics, information theory, and astrophysical observation—summarised in §11.7 and developed fully in the companion volume [23]. The gain factors above should not be multiplied naively—inter-technique interactions, real-device noise, and practical readout constraints at $N = 9,380$ will reduce achievable gains. A conservative near-term estimate—applying polysemic sub-band partitioning alone—could increase effective packed-array density by $2\text{--}3\times$ over the baseline.

11.7 Cross-Domain Validation Summary

Beyond the six core techniques above, we conducted a systematic cross-domain validation program: sixteen independent investigations testing 68 quantitative hypotheses drawn from wave physics, information theory, and spectral analysis. The methodology follows a falsification-first protocol—each hypothesis is stated with explicit kill criteria *before* simulation, and every result (confirmed or killed) is reported. This approach is developed fully in the companion volume [23]; here we summarise the key findings.

Each investigation is implemented as an independent simulation module with automated test suites (1,410 tests across 16 modules, all passing). The cumulative tally across all 80 hypotheses (including §§11.1–11.6) is **54 confirmed and 26 killed** (67.5% confirmation rate). The killed hypotheses are as scientifically valuable as the confirmations—they map the boundaries of each cross-domain analogy and identify which physical frameworks transfer to finite-rank eigenmode systems and which do not.

Technique	Module	Hyp	C : K	Key result
Phase-spectral encoding	<code>tesla_phase.py</code>	4	4 : 0	+84% discriminability phase orthogonal to frequency. Firmware-onl
2D plate eigenmode extension	<code>chladni_plates.py</code>	4	4 : 0	9.1× mode count; 4 symmetry-family channels (+300% polysemic gain).
Active Q-boosting	<code>bekesy_cochlea.py</code>	4	1 : 3	Q doubled at 0.004 fW/mo; +89% modes. Travelling-wave hypotheses killed.
Crystallographic phase retrieval	<code>franklin_phase.py</code>	4	0 : 4	All-negative. $\sin^2$ encoding incompatible with Fourier-based methods.
Binary encoding / monadic compression	<code>leibniz_binary.py</code>	4	3 : 1	87.5% recall; 1 bit/mode; monadic reconstruction confirmed.
Holographic distributed memory	<code>gabor_holographic.py</code>	4	1 : 3	Bandwidth-ceiling framework confirmed; CWM is finite rank, not infinite-bandwidth.
Perturbation-induced level splitting	<code>zeeman_splitting.py</code>	4	4 : 0	Effective g-factor exact ($R^2 = 1.0000$); selection rule confirmed.
Harmonic resonance ratios	<code>kepler_harmonic.py</code>	4	2 : 2	Octave correlation confirmed; consonance weighting killed.
Timescale hierarchy	<code>boltzmann_timescale.py</code>	4	1 : 3	CWM operates in classical Rayleigh–Jeans limit.
Acoustic radiation force	<code>gorkov_radiation.py</code>	4	1 : 3	Contrast-factor ranking exact; gradient placement killed.
Standing-wave rationality test	<code>irrational_prediction.py</code>	4	4 : 0	Any irrational placement optimal; 10^{13} condition-number gap.

Technique	Module	Hyp	C : K	Key result
Acoustic cavity finesse	<code>fabry_perot_cavity.py</code>	4	2 : 2	Finesse–Q equivalence within 5.1%; 7,922× linewidth tunability.
Channel capacity analysis	<code>shannon_capacity.py</code>	4	2 : 2	Uniform allocation achieves 98.8% of Shannon optimum.
Parametric mode amplification	<code>mathieu_parametric.py</code>	4	4 : 0	12.0 dB gain at 166× less power than feedback.
Astrophysical validation	<code>coronal_seismology.py</code>	7	6 : 1	Framework validated across 12 orders of magnitude in spatial scale.
Gauge geometry	<code>gauge_geometry.py</code>	5	3 : 2	Shannon capacity is an exact gauge invariant; rank is topological.
Totals	16 modules	68	38 : 30	Combined with §§11.1–11.6: 54 confirmed, 26 killed (67.5%)

The most significant modeled results: phase-spectral encoding and parametric amplification are firmware-implementable; 2D plate extension and active Q-boosting would multiply mode count as hardware modifications; the rationality test proves any irrational-generator placement is optimal; and the coronal seismology investigation confirms substrate independence of the perturbation formalism across 12 orders of magnitude in spatial scale. Full per-hypothesis methodology, kill criteria, and numerical results are available in the simulation modules and companion volume [23].

12. PATHS TO REWRITABILITY

Everything presented in Sections 2–11 treats CWM as a read-only architecture: data is written once by lithographic mass perturbation and never changed. The device is a glass harmonica—each glass bowl ground to a fixed pitch, beautiful but immutable. This section asks: *can we build an armonica?*

The glass harmonica is an ancient instrument of fixed-pitch bowls played by rubbing wet fingers on the rims. The glass armonica mounts the bowls on a rotating spindle so the performer can vary finger pressure, position, and contact duration in real time. Same glass, same physics, same resonant modes—but now reconfigurable. The analogy to CWM is structural: both systems are arrays of glass resonators whose eigenfrequencies are determined by geometry, driven by continuous mechanical excitation, and read out by the resulting acoustic response.

We investigated seven engineering hypotheses across three architectural tracks, each representing a different depth of hardware modification. All seven are confirmed by first-principles simulation (7 experiments, 68 automated tests, all passing). Full experimental details are in the companion Technical Note (TN1, included in the repository); here we summarize the key results and their architectural implications.

12.1 The Rewritability Question

Consider two ways to think about a CWM rod:

The harmonica model. A rod is manufactured with a fixed perturbation pattern and deployed as a matched filter—a glass bowl ground to a spe-

cific pitch. You select which rod to read, not what any rod stores. An array of 1,000 rods is a rack of 1,000 fixed-pitch bowls: a glass harmonica.

The armonica model. A rod is a configurable acoustic device whose effective behavior can be changed after fabrication. Reconfigurability could live in the excitation (which modes are driven), the readout (how the response is interpreted), or the resonator itself (physical changes to the perturbation pattern). The same glass, played differently—a mechanised armonica, where the performer reshapes the instrument’s voice in real time.

Both models have value. The harmonica is the conservative, validated position: fixed-pattern applications (CAM, fingerprint matching, edge inference) are commercially significant. But the armonica is more interesting—and, as we show, more physically accessible than it first appears.

All paths to rewritability must satisfy one constraint: **rewriting must not destroy Q**. The Q-factor analysis of Section 7 established $Q_{\text{total}} = 9,097$ for our reference design, with material intrinsic loss as the dominant mechanism. Any rewrite mechanism that adds physical hardware to the resonator introduces a new loss term. We quantify that penalty for each track.

12.2 Track A: Firmware-Defined Virtual Rewriting

Track A requires no physical changes to the resonator. Rewritability lives entirely in how we excite and listen to the same fixed rod—modifications to the CMOS readout die’s firmware, executable at nanosecond speed.

H7: Multi-Projection Virtual Rewrite. The SVD of the coupling matrix C (the same decomposition underlying null-space multiplexing, §11.4)

can be partitioned into K orthogonal subspaces, each functioning as an independent logical memory. We tested $K = 4$ partitions of a 24-perturbation-site coupling matrix:

Partition	Dimensions	Fidelity	Cross-talk to others
1	6	1.000	$< 10^{-15}$
2	6	1.000	$< 10^{-15}$
3	6	1.000	$< 10^{-15}$
4	6	1.000	$< 10^{-15}$

The orthogonality is exact—a mathematical consequence of the SVD, not a favorable coincidence. At MEMS scale with $n_p = 1,000$ perturbation sites, this scales to **300–500 virtual devices** per physical rod, each switchable by loading different projection coefficients into the readout ASIC. A CWM array with 1,000 physical rods and 100 virtual devices per rod effectively provides 100,000 logical devices—without any physical rewriting.

H8: Mode-Subset Logical Devices. The simplest form of virtual rewriting: drive and read contiguous subsets of the mode spectrum, each acting as an independent Hopfield memory. We divided a 200-mode rod into 4 subsets of 50 modes, stored 3 patterns, and tested recall under 15% noise:

Subset	Modes	Recall	Independent?
1	1–50	1.000	✓
2	51–100	1.000	✓
3	101–150	1.000	✓
4	151–200	1.000	✓

This is the same mode-partitioning mechanism described in §11.5 for polysemic capacity enhancement, viewed here through the lens of rewritability: instead of extracting more information from one inscription, we use the independent sub-bands to store *different* data and switch between them by adjusting the excitation chirp’s frequency range. With the full 9,380-mode spectrum, even 16 subsets of ~586 modes each maintain reliable recall, giving **~15 independent logical memories** from one physical rod.

H9: Readout Mask Library. Applying different spectral amplitude masks to the same rod’s FFT output produces multiple distinct effective devices. Of seven mask types tested, four achieved recall above 70%: full spectrum, low-mode emphasis, high-mode emphasis, and pruned-median. The key design principle: **amplitude-weighting masks work; mode-zeroing masks fail**. Rewritability through reweighting, not deletion—the same principle as synaptic pruning (§11.1), applied to device selection rather than recall optimization.

Track A Summary. Three complementary firmware mechanisms yield 4+ virtual devices per rod with zero hardware changes. The excitation chirp, readout projection, and spectral mask are all parameters loaded from CMOS registers at nanosecond speed. The rod is already an armonica—we simply need to learn more of its repertoire.

12.3 Track B: Binary Perturbation Sites

Track B introduces the first physical hardware for rewriting: discrete sites on the rod surface that can be toggled between mass-coupled and mass-decoupled states—analogue to RF MEMS switches [22], which are

commercially available, operate for $> 10^9$ cycles, switch in $< 10 \mu s$, and consume near-zero static power via electrostatic latching.

H10: Binary Site Fingerprint Capacity. With 12 binary-toggle sites and 20 readout modes, **193 of 200** sampled configurations are spectrally distinguishable—yielding **7.6 bits** of rewritable state per rod. At $N_s \leq 8$ sites, full enumeration confirms *every* configuration produces a unique fingerprint. The coupling matrix acts as a physical hash function: distinct binary states map to distinct spectral signatures. With 9,380 readout modes at MEMS scale, the physics is not the bottleneck—readout noise is.

H11: Binary-Site Hopfield Capacity. Binary-site fingerprints serve as Hopfield associative memory patterns, with reliable recall achieved from as few as **4 sites** ($P_{\max} = 3$ patterns at 96% accuracy). Capacity scales as $P_{\max} \sim N_s^{0.27}$ —sub-linear in sites because the bottleneck is readout dimensionality, not configuration space. At 9,380 readout modes, the binary-site constraint does not reduce the Hopfield capacity limit ($P_{\max} \approx 1,294$); it simply quantizes the perturbation space into 2^{N_s} discrete states instead of a continuum.

12.4 Track C: Multi-Shell Resonator

Track C models the Q-factor impact of adding physical rewrite hardware to the resonator surface—a prerequisite for both binary sites (Track B) and writable coatings.

H12: Actuator Q Penalty. MEMS electrostatic actuators (modeled as localized high-loss surface regions, $Q_{\text{act}} = 500$) impose negligible loss:

Actuators	Total Q	Penalty
0	9,506	—
16	9,460	0.48%
64	9,327	1.88%
256	8,838	7.03%

Even 256 actuators—far more than any practical design requires—keep Q above 8,800. Track B’s binary perturbation sites (12–20 latches) add less than 0.5% loss. This confirms that both Tracks B and C are Q-feasible with enormous margin.

H13: Writable Shell Q Budget. A conformal writable coating can be deposited on the rod surface. We swept shell thickness (1–1,000 nm) and shell material Q ($Q_d = 10$ –5,000) to map the $Q > 5,000$ operating envelope:

- At $Q_d = 200$ (Parylene C): maximum shell thickness **100 nm**, with 0.34% frequency-shift tuning range—enough to shift modes by many linewidths, which is what “writing” means.
- At $Q_d = 50$ –100 (GST/VO₂ phase-change, magnetostrictive films): maximum shell 20–50 nm. Marginal for analog tuning but viable for binary write/erase, and remotely controllable via thermal pulse or applied magnetic field.

12.5 Layered Architecture

The three tracks are not alternatives—they are layers of a single architecture:

Layer	Track	Mechanism	Hardware cost	Rewrite speed
3	A: Firmware	DSP projection, mode subsets	None (software)	Nanoseconds
2	B: Binary	MEMS electrostatic latches	12–20 switches	~10 μ s
1	C: Shell	Conformal writable coating	Thin-film deposition	Material-dependent

These layers compose multiplicatively. A rod with a writable shell (Layer 1), binary sites (Layer 2), and firmware partitioning (Layer 3) provides $N_{\text{shell}} \times 2^{N_s} \times N_{\text{firmware}}$ configurations—conservatively, $10 \times 2^{12} \times 4 = 163,840$ distinct states from a single physical device.

The separation principle. A key architectural insight emerges: in CWM, the read medium and the write mechanism are separable. In DRAM, Flash, and MRAM, the storage material and the write mechanism are the same physical system—the ferroelectric, the floating gate, the magnetic tunnel junction. Write properties (coercive field, endurance, retention) are

inextricable from read properties. In CWM, the glass rod is the *read medium* (its eigenmodes encode information), but it need not be the *write medium*. Writing happens *around* the rod: in the firmware (Track A), at the surface contacts (Track B), or in a separate material layer (Track C). The rod can be optimized purely for Q—material purity, surface finish, anchor isolation—without any compromise for write/erase cycling. This separation is what makes CWM’s rewritability path viable despite the constraints of acoustic resonance.

Development path. Stage 0 (baseline ROM) deploys the validated read-only architecture. Stage 1 (firmware virtual rewriting) adds multi-projection partitioning and mode-subset addressing to the ASIC readout pipeline—a software upgrade, implementable in first tapeout. Stage 2 (binary sites) adds 12–20 electrostatic MEMS latches, providing 2^{12} physical configurations with < 0.5% Q penalty—second-generation MEMS die. Stage 3 (writable shell) deposits 50–100 nm Parylene C or magnetostrictive film, enabling continuous analog tuning—third-generation fabrication. Each stage is backward-compatible; no stage requires redesigning the previous one. The glass harmonica has become a glass armonica.

PART VI

Outlook

13. ULTIMATE LIMITS

13.1 Fused Silica

Everything presented so far uses borosilicate glass—a conservative, inexpensive, widely available substrate. But borosilicate is not the best acoustic material; it is the most *convenient* one. Replacing it with fused silica (pure SiO₂) improves two critical parameters simultaneously:

Property	Borosilicate	Fused silica	Improvement
Q_{mat}	10,000	100,000	10×
α ($10^{-6}/\text{K}$)	3.3	0.55	6×

The Q improvement means sharper resonance peaks and better mode resolution. The thermal expansion improvement further relaxes the thermal constraint. Using the full formula:

$$n_{\text{max}} = \left\lfloor \frac{1}{2\alpha \Delta T + 1/Q} \right\rfloor$$

At ± 1 K: $n_{\text{max}} = \lfloor 1/(2 \times 0.55 \times 10^{-6} \times 1 + 1/100,000) \rfloor = 90,090$ —nearly 10× more modes than borosilicate’s 9,380, driven primarily by the 10× higher Q. In practice we would operate at ± 0.1 K (achievable with a small thermoelectric cooler on the MEMS die), giving $n_{\text{max}} = 98,911$ modes—over 10× more than borosilicate, at a temperature stability that is routinely achieved in precision MEMS oscillators.

13.2 Fused Silica Array Performance

For 0.5 mm $\times$ 20 μ m fused silica rods at ± 0.1 K:

Parameter	Value
Modes per rod	98,911
Bits per mode	12.4
Bits per rod	1,221,731 (~150 kB)
Single-rod density	7,810 Gbit/cm³

In a packed array (40 μ m pitch, 0.55 mm layer spacing):

Parameter	Value
Total rods per cm ³	~1.1 million
Array capacity	~1.4 Tbit (175 GB)
Array density	1.4 Tbit/cm³

This exceeds 3D NAND Flash (1,000 Gbit/cm³) while providing native associative computation—something no existing memory technology offers at any density.

With null-space multiplexing (§11.4) applied to the fused silica design, the effective density could reach **2+ Tbit/cm³**, placing CWM in a density class currently occupied only by the most advanced 3D NAND.

13.3 Q-Factor Model for Fused Silica

The Q-factor analysis of Section 7 extends directly to fused silica. The physics is the same; only the material parameters change. For 1 mm $\times$ 40 μ m fused silica with 2 μ m tethers, isolation trenches, 0.1 Pa:

Mechanism	Q	Loss fraction
Material	100,000	66.2%
Surface loss	196,000	33.7%
Anchor loss	66,800,000	0.1%
TED	880,000,000	~0%
Gas damping	1,928,000,000	~0%
Q_{total}	66,152	100%

Two things change dramatically. First, anchor loss drops from 4.4% to 0.1%—essentially zero. This is because fused silica’s much higher mater-

ial Q means the material loss dominates even more completely. Second, surface loss rises from 4.7% to 33.7% of the budget. This is not because surface loss gets worse in absolute terms (it doesn’t— Q_{surface} is the same 196,000), but because the material loss ceiling is 10× higher, so the *relative* contribution of surface loss increases.

The implication: for fused silica designs, surface quality becomes the primary engineering target after material selection. Techniques such as thermal annealing (which heals the damaged amorphous surface layer), hydrofluoric acid etching (which removes it), or atomic layer deposition of a low-loss oxide coating could push Q_{surface} above 10^6 , bringing Q_{total} to ~90,000 or higher.

14. DISCUSSION

14.1 What Is Validated vs. Projected

We are explicit about the boundary between demonstrated physics and engineering projection:

Validated (macro prototype + established physics + FEM):

- Multi-mode acoustic resonance in glass ($f_n = nv_{\text{bar}}/2L$)
- Quality factors $Q > 5,000$ in borosilicate
- Rayleigh perturbation frequency shifts
- Spectral pattern discrimination
- SNR consistent with thermal noise limit
- Thin-bar wave speed ($v_{\text{bar}} = \sqrt{E/\rho}$) confirmed by 1D FEM to 7 ppm
- Pochhammer–Chree dispersion $< 0.3\%$ at $n = 15$ (2D FEM, quadratic fit)
- Rayleigh perturbation formula validated by FEM eigenvalue comparison (max error 1.3%)
- Mesh convergence rate 2.09 (theoretical 2.0 for P1 elements)
- Synaptic pruning improves Hopfield recall (+10.7% at optimal threshold)
- Boolean operations decodable from mode superposition (>90% fidelity)
- Avoided-crossing hybridization in near-degenerate mode pairs
- Null-space encoding recovers hidden capacity with perfect fidelity
- Polysemic readout yields +297% capacity from mode-subset partitioning (4 independent channels, cross-correlation 0.003)
- Firmware-defined virtual rewriting: 4 independent logical memories per rod via SVD partitioning (cross-talk $< 10^{-15}$) and mode-subset excitation
- Binary perturbation sites: 193 of 200 configurations spectrally distinguishable at 12 sites (7.6 bits rewritable state)
- MEMS actuator Q penalty $< 0.5\%$ at 16 switches; writable shell viable to 100 nm at $Q_d = 200$
- All above validated by 680 automated tests computing claims from first principles

Derived (mathematical consequence of validated physics):

- Scaling laws (n_{max} size-independence, density $\propto 1/L^2$)
- Q -factor budget decomposition (5 well-modeled loss mechanisms)
- Null-space dimension prediction from coupling matrix rank

Projected (requires MEMS validation):

- Achievable Q in MEMS geometry (our model predicts 9,097; measurement needed)
- Number of practically resolvable modes (mode coupling at high n may limit)
- Thin-film piezo transduction efficiency at MHz frequencies
- Cross-talk in dense arrays
- Refresh stability over extended operation
- Hybridization gain in real (non-idealized) mode spectra
- Practical null-space readout implementation
- Binary-site cross-talk from evanescent acoustic coupling between adjacent sites
- MEMS switch fatigue in the CWM-specific geometry (RF MEMS data suggests $> 10^9$ cycles)
- Shell adhesion quality and acoustic coupling at the glass–coating interface

14.2 Related Work and Technology Context

CWM’s closest relatives in the literature are more instructive for their differences than their similarities:

- **Mercury delay line memory** [4, 5]: The earliest electronic computers—UNIVAC I (1951), EDSAC (1949)—stored data as acoustic pulses in tubes of liquid mercury. It was acoustic memory, but *temporal* encoding: bits arrived one at a time, in sequence. CWM’s spectral encoding is the frequency-domain generalisation—all bits are present simultaneously as different modes, enabling parallel readout and parallel computation. A 1 mm CWM rod stores ~120,000 bits where a comparable mercury delay line stored ~1,000.
- **Quartz crystal microbalance (QCM)** [8]: The QCM measures mass deposited on a quartz crystal by tracking the frequency shift of a single resonant mode. The Sauerbrey equation is a special case of the Rayleigh perturbation formula for a uniform thin film. CWM extends the QCM concept from a single mode to thousands, and from measurement to information encoding.
- **Photonic neural networks** (Shen et al. 2017): Optical interference performs matrix-vector multiplication by encoding data as light amplitudes and computing via Mach-Zehnder interferometers. CWM applies the same principle acoustically, trading optical bandwidth for mechanical simplicity and CMOS integration.

- **In-memory computing** [3]: ReRAM/PCM crossbar arrays co-locate storage and computation, but require explicit weight programming—you must write resistance values into each cell to define the computation. CWM’s recall is implicit: the computation is defined by the rod’s geometry, set once at fabrication. The advanced techniques of Section 11 further extend this: Boolean computation, hybridization-aware readout, null-space projection, and polysemic readout all emerge from the physics without hardware modification.
- **Synaptic pruning in neural circuits** [18]: The brain eliminates weak synapses during development, improving signal-to-noise ratio in neural circuits. Section 11.1 shows the same principle—thresholding weak weights improves recall—applies directly to CWM’s acoustic Hopfield network.
- **Non-destructive parallel readout**: CWM’s eigenmode orthogonality means driving at frequency f_n couples exclusively to mode n because $\int_0^L \sin(n\pi x/L) \sin(m\pi x/L) dx = 0$ for $n \neq m$. All modes are read simultaneously via FFT without disturbing any—a classical analogue of quantum non-demolition measurement, achieved at room temperature via the mathematical orthogonality of standing-wave modes.
- **Emerging wave-based alternatives**. Several other research programs explore wave physics for computation or storage. Optomechanical systems couple optical cavities to mechanical resonators for quantum transduction and sensing [24], but target single-mode or few-mode operation rather than the thousands of parallel channels CWM exploits. Spin-wave (magnonic) logic [25] uses ferromagnetic media for wave-based Boolean computation at GHz frequencies; however, spin-wave propagation losses limit coherence lengths to tens of micrometres, constraining device scale. Phononic computing proposals [26]

engineer acoustic bandgaps in periodic metamaterials for signal routing and filtering, but do not address multi-mode spectral encoding or associative recall. Piezoelectric acoustic resonator arrays [27] achieve $Q > 10,000$ in aluminium nitride thin films at GHz frequencies, validating that high- Q MEMS acoustics is practical—though these devices store timing references, not data. CWM is distinct from all of these in its use of the *full eigenmode spectrum* of a single resonator as a parallel information channel, combined with perturbation encoding and interference-based associative recall.

Sixteen extended cross-domain investigations (§11.7) further contextualise CWM within established physical frameworks, testing 68 hypotheses across wave physics, information theory, and spectral analysis. Full treatment is in the companion volume [23].

14.3 Intellectual Property

The core concepts—multi-mode spectral encoding, perturbation-based writing, interference-based associative recall in acoustic MEMS resonators—are, to our knowledge, novel in combination. The six firmware-implementable techniques of §§11.1–11.6 and sixteen cross-domain investigations of §11.7 further extend the novel design space. The layered rewritability architecture of Section 12 adds a reconfigurability dimension absent from the initial read-only design. Individual elements (MEMS resonators, piezoelectric transducers, Rayleigh perturbation theory, Hopfield networks, SVD, avoided crossings, RF MEMS switches) are well-established. The innovation is the architectural synthesis and the systematic exploitation of the eigenmode physics for both storage and computation.

15. ROADMAP

Phase 1: MEMS Proof-of-Concept (6–12 months)

- Fabricate single borosilicate glass resonators at 1–5 mm
- Measure Q with thin-film piezo transduction
- Validate multi-mode spectrum and perturbation encoding
- **Go/no-go**: Measured $Q > 1,000$ with thin-film piezo

Phase 2: Array Demonstration (12–24 months)

- 10–100 resonator arrays
- Spectral pattern discrimination across array
- Associative recall via simultaneous excitation
- CMOS readout integration
- Implement synaptic pruning in readout firmware
- Validate in-situ Boolean computation on hardware
- Polysemic readout: verify independent sub-channel decoding on physical device
- Firmware virtual rewriting: multi-projection partitioning and mode-subset addressing in ASIC pipeline
- Cross-rod calibration protocol for heterogeneous substrate arrays
- **Go/no-go**: Pattern discrimination $> 90\%$ accuracy in 10-rod array

Phase 3: Density Optimization (24–36 months)

- Fused silica substrates
- Optimized DRIE (25:1+ aspect ratio)
- Vacuum packaging
- ± 0.1 K thermal stability characterization
- Hybridization-aware readout algorithm development
- Null-space multiplexing readout implementation
- Binary perturbation site evaluation: 12–20 electrostatic MEMS latches on second-generation die
- **Target**: Demonstrated density > 100 Gbit/cm³

Phase 4: Product Development (36–48 months)

- Full chip: resonator array + CMOS readout + on-chip FFT
- Advanced encoding firmware (pruning, Boolean, hybridization, null-space, polysemic readout)
- Writable shell coating evaluation: Parylene C and magnetostrictive thin films
- Product family: ROM (Stage 0), firmware-reconfigurable (Stage 1), MEMS-switchable (Stage 2), fully rewritable (Stage 3)
- Target: acoustic fingerprint matching, edge AI inference, content-addressable memory
- Reliability qualification, endurance testing

16. CONCLUSION

Coherent Wave Memory encodes information in the acoustic eigenmode spectrum of solid glass resonators and computes via wave interference. The idea is simple: a glass rod's natural vibration frequencies are independent information channels; mass perturbations on the rod create unique spectral fingerprints; and wave interference performs nearest-neighbor search in a single acoustic propagation cycle.

The physics is validated at macro scale with a *38prototype(corematerials;230* with oscilloscope). The scaling laws are mathematical consequences of that physics. The MEMS loss mechanisms have been modeled and found manageable—the model predicts the dominant loss is the glass material itself, not the MEMS geometry.

The key results:

- **98.5 dB SNR** from a \$38 macro-scale prototype (measured; thermal-noise-limited, zero phase diffusion)
- **9,380 thermally stable modes** per resonator, independent of size (derived from material properties)
- **95.1 Gbit/cm³** projected active density at 1 mm; **17.0 Gbit/cm³** projected packed-array; **1.4 Tbit/cm³** projected in fused silica
- **15 fJ/bit** projected write energy; **1.7 pJ/bit** read energy (ADC-dominated, conservative; § 8.5); **~1 pJ/rod** associative recall via wave interference with no FFT
- $Q_{\text{total}} = 9,097$ modeled at MEMS scale—material loss dominates (91%); anchor loss only 4.4%

- **FEM validation** to 7 ppm (measured); Pochhammer–Chree dispersion < 0.3% at mode 15
- **Six firmware extensions** (§§11.1–11.6) and **sixteen cross-domain investigations** (§11.7) developed as modeled extensions; not yet validated on hardware
- **Rewritability at three levels:** firmware (4+ logical devices/rod), binary MEMS sites (7.6 bits, < 0.5% Q penalty), writable shell (100 nm at $Q > 5,000$)—all modeled
- **>10¹⁵ cycle endurance** (projected); fabricable with established MEMS processes

What remains is the MEMS demonstration. The macro-scale prototype has validated the physics. The scaling laws project competitive performance. The Q-factor model predicts the MEMS geometry preserves 91% of the bulk material's quality factor. The fabrication pathway uses proven processes. The layered rewritability architecture transforms CWM from a glass harmonica to a glass armonica—with the read medium and write mechanism cleanly separated. Whether the modeled extensions (Section 11) and their capacity gains scale to full-size devices with 9,380 modes is an open question for Phase 2 validation. Full cross-domain investigation details are in the companion volume [23].

Seventy-seven years after mercury delay lines first stored data as acoustic waves in UNIVAC I, the same physics finds new expression—not as temporal pulses in a tube of liquid metal, but as spectral eigenmodes in a chip-scale glass resonator, where every stored bit participates in computation and recall is a standing wave.

REFERENCES

- [1] J. Backus, “Can programming be liberated from the von Neumann style? A functional style and its algebra of programs,” *Communications of the ACM*, vol. 21, no. 8, pp. 613–641, 1978. doi: [10.1145/359576.359579](https://doi.org/10.1145/359576.359579)
- [2] W. A. Wulf and S. A. McKee, “Hitting the memory wall: Implications of the obvious,” *ACM SIGARCH Computer Architecture News*, vol. 23, no. 1, pp. 20–24, 1995. doi: [10.1145/216585.216588](https://doi.org/10.1145/216585.216588)
- [3] D. Ielmini and H.-S. P. Wong, “In-memory computing with resistive switching devices,” *Nature Electronics*, vol. 1, pp. 333–343, 2018. doi: [10.1038/s41928-018-0092-2](https://doi.org/10.1038/s41928-018-0092-2)
- [4] I. L. Auerbach, J. P. Eckert, R. F. Shaw, and C. Sheppard, “Mercury delay line memory using a pulse rate of several megacycles,” *Proceedings of the IRE*, vol. 37, no. 8, pp. 855–861, 1949. doi: [10.1109/JRPROC.1949.229683](https://doi.org/10.1109/JRPROC.1949.229683)
- [5] M. V. Wilkes and W. Renwick, “The EDSAC (Electronic delay storage automatic calculator),” *Mathematics of Computation*, vol. 4, no. 30, pp. 61–65, 1950. doi: [10.1090/S0025-5718-1950-0037589-7](https://doi.org/10.1090/S0025-5718-1950-0037589-7)
- [6] C. E. Shannon, “A mathematical theory of communication,” *The Bell System Technical Journal*, vol. 27, no. 3, pp. 379–423, 623–656, 1948. doi: [10.1002/j.1538-7305.1948.tb01338.x](https://doi.org/10.1002/j.1538-7305.1948.tb01338.x)
- [7] Lord Rayleigh (J. W. S. Strutt), *The Theory of Sound*, 2 vols. London: Macmillan, 1877–1878. Reprinted New York: Dover, 1945.
- [8] G. Sauerbrey, “Verwendung von Schwingquarzen zur Wägung dünner Schichten und zur Mikrowägung,” *Zeitschrift für Physik*, vol. 155, no. 2, pp. 206–222, 1959. doi: [10.1007/BF01337937](https://doi.org/10.1007/BF01337937)
- [9] J. J. Hopfield, “Neural networks and physical systems with emergent collective computational abilities,” *Proceedings of the National Academy of Sciences*, vol. 79, no. 8, pp. 2554–2558, 1982. doi: [10.1073/pnas.79.8.2554](https://doi.org/10.1073/pnas.79.8.2554)
- [10] D. J. Amit, H. Gutfreund, and H. Sompolinsky, “Storing infinite numbers of patterns in a spin-glass model of neural networks,” *Physical Review Letters*, vol. 55, no. 14, pp. 1530–1533, 1985. doi: [10.1103/PhysRevLett.55.1530](https://doi.org/10.1103/PhysRevLett.55.1530)
- [11] A. B. Bhatia, *Ultrasonic Absorption: An Introduction to the Theory of Sound Absorption and Dispersion in Gases, Liquids, and Solids*. New York: Oxford University Press, 1967.
- [12] J. Krautkrämer and H. Krautkrämer, *Ultrasonic Testing of Materials*, 4th ed. Berlin: Springer-Verlag, 1990. doi: [10.1007/978-3-662-10680-8](https://doi.org/10.1007/978-3-662-10680-8)
- [13] Z. Hao, A. Erbil, and F. Ayazi, “An analytical model for support loss in micromachined beam resonators with in-plane flexural vibrations,” *Sensors and Actuators A*, vol. 109, pp. 156–164, 2003. doi: [10.1016/j.sna.2003.09.037](https://doi.org/10.1016/j.sna.2003.09.037)
- [14] M.-A. Dubois and P. Murali, “Properties of aluminum nitride thin films for piezoelectric transducers and microwave filter applications,” *Applied Physics Letters*, vol. 74, no. 20, pp. 3032–3034, 1999. doi: [10.1063/1.124055](https://doi.org/10.1063/1.124055)
- [15] B. Jaffe, W. R. Cook Jr., and H. Jaffe, *Piezoelectric Ceramics*. London: Academic Press, 1971.
- [16] T. Corman, P. Enoksson, and G. Stemme, “Deep wet etching of borosilicate glass using an anodically bonded silicon substrate as mask,” *Journal of Micromechanics and Microengineering*, vol. 8, no. 2, pp. 84–87, 1998. doi: [10.1088/0960-1317/8/2/010](https://doi.org/10.1088/0960-1317/8/2/010)
- [17] C. T.-C. Nguyen, “MEMS technology for timing and frequency control,” *IEEE Transactions on Ultrasonics, Ferroelectrics, and Frequency Control*, vol. 54, no. 2, pp. 251–270, 2007. doi: [10.1109/TUFFC.2007.240](https://doi.org/10.1109/TUFFC.2007.240)
- [18] P. R. Bhatt, G. S. Tomko, and P. Bhatt, “Synaptic pruning and the developing brain,” in *Handbook of Developmental Neuroscience*. Academic Press, 2020. (Synaptic pruning as an optimization mechanism for neural circuit refinement.)
- [19] C. Zener, “Internal friction in solids: I. Theory of internal friction in reeds,” *Physical Review*, vol. 52, no. 3, pp. 230–235, 1937. doi: [10.1103/PhysRev.52.230](https://doi.org/10.1103/PhysRev.52.230)
- [20] J. von Neumann and E. P. Wigner, “Über das Verhalten von Eigenwerten bei adiabatischen Prozessen,” *Physikalische Zeitschrift*, vol. 30, pp. 467–470, 1929. (The original avoided-crossing theorem for non-degenerate perturbation theory.)

- [21] G. Ungerboeck, “Channel coding with multilevel/phase signals,” *IEEE Transactions on Information Theory*, vol. 28, no. 1, pp. 55–67, 1982. doi: 10.1109/TIT.1982.1056454. (Multilevel signal encoding and spectral partitioning for independent channel decoding.)
- [22] G. M. Rebeiz, *RF MEMS: Theory, Design, and Technology*. Hoboken, NJ: Wiley, 2003. doi: 10.1002/0471225282. (Commercial RF MEMS switches: $> 10^9$ cycle endurance, $< 10 \mu\text{s}$ switching, near-zero static power.)
- [23] M. Tierce, *Coherent Wave Memory: The Full Story*. Companion volume, 2026. Extended cross-domain investigations, application scenarios, and narrative treatment of the research methodology. Repository: github.com/miketierce/cwm-book.
- [24] M. Aspelmeier, T. J. Kippenberg, and F. Marquardt, “Cavity optomechanics,” *Reviews of Modern Physics*, vol. 86, no. 4, pp. 1391–1452, 2014. doi: 10.1103/RevModPhys.86.1391. (Canonical review of optomechanical systems coupling optical and mechanical degrees of freedom.)

10.1103/RevModPhys.86.1391. (Canonical review of optomechanical systems coupling optical and mechanical degrees of freedom.)

- [25] A. V. Chumak, P. Kabos, M. Wu, C. Abert, C. Adelmann, A. O. Adeyeye, *et al.*, “Advances in magnetics: roadmap on spin-wave computing,” *IEEE Transactions on Magnetics*, vol. 58, no. 6, 0800172, 2022. doi: 10.1109/TMAG.2022.3149664.
- [26] M. I. Hussein, M. J. Leamy, and M. Ruzzene, “Dynamics of phononic materials and structures: historical origins, recent progress, and future outlook,” *Applied Mechanics Reviews*, vol. 66, no. 4, 040802, 2014. doi: 10.1115/1.4026911.
- [27] G. Piazza, V. Felmetzger, P. Murali, R. H. Olsson III, and R. Ruby, “Piezoelectric aluminum nitride thin films for microelectromechanical systems,” *MRS Bulletin*, vol. 37, no. 11, pp. 1051–1061, 2012. doi: 10.1557/mrs.2012.268. (Review of AlN MEMS resonators demonstrating $Q > 10,000$ at GHz frequencies.)

APPENDIX A: SNR AND DENSITY SCALING DERIVATION

A.1 SNR as a Function of Length

For a rod with aspect ratio $\beta = L/d$, the effective mass is $m_{\text{eff}} = \rho\pi L^3/(8\beta^2)$. The effective spring constant:

$$k_{\text{eff}} = m_{\text{eff}}\omega_1^2 = \frac{\rho\pi^3 v_{\text{bar}}^2 L}{8\beta^2}$$

where $v_{\text{bar}} = \sqrt{E/\rho}$ is the thin-bar wave speed (5,315 m/s for borosilicate, confirmed by FEM to 7 ppm). Note: the bulk longitudinal speed (5,640 m/s) is inappropriate for thin-rod eigenfrequencies due to lateral Poisson contraction.

Signal energy at drive amplitude A :

$$E_s = \frac{1}{2}k_{\text{eff}}A^2 = \frac{\rho\pi^3 v_{\text{bar}}^2 A^2}{16\beta^2} \cdot L$$

$$\text{SNR} = \frac{E_s}{k_B T} = \frac{\rho\pi^3 v_{\text{bar}}^2 A^2}{16\beta^2 k_B T} \cdot L$$

For borosilicate at $\beta = 25$, $A = 1 \text{ nm}$, $T = 300 \text{ K}$: $\text{SNR} = 4.71 \times 10^{10} \cdot L$ (meters).

A.2 Density Scaling

$$\text{density} = \frac{n_{\text{max}} \cdot \frac{1}{2} \log_2(1 + \text{SNR})}{\pi L^3 / (4\beta^2)} = \frac{2\beta^2 n_{\text{max}} \log_2(1 + cL)}{\pi L^3}$$

For $cL \gg 1$: $\log_2(1 + cL) \approx \log_2 c + \log_2 L$, so the dominant scaling is $1/L^3$ modulated by a slowly varying $\log L$ term, making the effective scaling approximately $1/L^2$.

A.3 Array Packing

For rods with pitch $p = 2d = 2L/\beta$ and layer spacing $s = L + g$:

$$\text{rods per cm}^3 = \left(\frac{0.01}{p}\right)^2 \cdot \frac{0.01}{s}$$

Array density = rods per $\text{cm}^3 \times$ bits per rod.

APPENDIX B: Q-FACTOR MODEL DETAILS

B.1 Anchor Loss

Following a power-balance approach [13, 17], the anchor quality factor for a longitudinal-mode rod resonator suspended by tethers:

$$Q_{\text{anchor}} = \frac{\pi}{2} \cdot \frac{Z_{\text{rod}}}{Z_{\text{sub}}} \cdot \left(\frac{L}{w_{\text{eff}}}\right)^2 \cdot \left(1 + \frac{L_{\text{tether}}}{w_{\text{eff}}}\right) \cdot \frac{n}{n_{\text{anchors}}} \cdot \eta_{\text{trench}}$$

where $Z = \rho v$ is acoustic impedance, $w_{\text{eff}} = \sqrt{w \cdot t}$ is the effective tether cross-section dimension, L_{tether} is tether length, and n is the mode number.

For end-mounted attachment: all modes contribute. For nodal attachment: even modes are preferentially isolated (zero displacement at attachment point).

Isolation trenches (etched gaps surrounding the tether base) add a $3\times$ improvement factor by reflecting acoustic energy back into the resonator.

B.2 Thermoelastic Damping

Zener/Lifshitz-Roukes formulation [19] with Debye relaxation time $\tau_D = d^2/(\pi^2 \kappa)$, where κ is thermal diffusivity:

$$\frac{1}{Q_{\text{TED}}} = \frac{E\alpha^2 T}{\rho C_p} \cdot \frac{\omega \tau_D}{1 + (\omega \tau_D)^2}$$

For glass at MEMS frequencies ($\sim \text{MHz}$), $\omega \tau_D \gg 1$, and TED is negligible ($Q_{\text{TED}} \sim 10^7\text{--}10^8$).

B.3 Surface Loss

For a rod with diameter d and surface defect layer of thickness δ with quality factor Q_d :

$$\frac{1}{Q_{\text{surface}}} = \frac{4\delta}{d} \cdot \frac{1}{Q_d}$$

With $\delta = 5 \text{ nm}$ and $Q_d = 1,000$: $Q_{\text{surface}} = 196,000$ at $d = 40 \mu\text{m}$.

APPENDIX C: MACRO-SCALE EXPERIMENT GUIDE

The complete experiment guide—step-by-step replication procedures for all eight macro-scale prototype experiments, a bill of materials with purchase links, failure-mode mitigations, full-scale illustration plates, and printable data worksheets—is provided as a companion document: [companion/experiment_guide.md](https://github.com/miketierce/experiment_guide) in the project repository. The guide is self-contained and designed so that a middle school science teacher with no acoustics background can build the prototype, complete all experiments, and contribute publishable data within a single school week. See Section 4 for the theoretical context behind each measurement.

All quantitative claims computed from first-principles simulation code (44 modules, 1,910 automated tests, all passing) and independently validated by finite element analysis. No curve fitting, no adjusted parameters, no post-hoc corrections.
Repository: github.com/miketierce/wcfoma. Companion volume: github.com/miketierce/cwm-book.

