

scripts/run-helixqa-provider-qa.sh

Revision: 1 Last modified: 2026-06-08T00:00:00Z

Overview

Thin Lava glue that runs **HelixQA** against the Lava Android app for a given provider (or all), feeding the matching Lava test bank, using the **claude CLI as the LLM/Vision model bridge** (HelixQA's BridgedCLIPProvider — no API key needed). It is the per-provider companion to `scripts/run-genymotion-challenges.sh`.

Prerequisites

- HelixQA buildable: submodules/helixqa + its 5 own-org dep submodules (doc_processor, llm_orchestrator, llm_provider, llms_verifier, vision_engine — added 2026-06-08; see docs/qa/helixqa-dependency-submodules.md). `go build ./cmd/helixqa → v0.2.0`.
- Lava banks present: `lava-api-go/qa/banks/lava-<provider>-journey.yaml` (7 banks, 32 cases).
- go (1.24+), adb, and the claude CLI on PATH.
- **A reachable device** — the Genymotion VM at `127.0.0.1:6555` (boot it first) or a physical device with the Lava app (`digital.vasic.lava.client.dev`) installed.

Usage

```
# explicit per-provider bank run (default mode)
scripts/run-helixqa-provider-qa.sh --provider rutor --serial
127.0.0.1:6555
# every provider
scripts/run-helixqa-provider-qa.sh --all
# doc-driven autonomous QA session instead of explicit banks
scripts/run-helixqa-provider-qa.sh --provider kinozal --autonomous
```

Exit codes (anti-bluff)

- 0 — QA run completed.
- 2 — **honest BLOCKED**: no adb device in device state (or adb missing). NOT a pass (§6.AH/§11.4.3). Boot the Genymotion VM / attach a device, then re-run.

- 3 — helixqa build failed (check the dep submodules).
- 1 — QA run reported failures.

Internal behaviour

1. Honest device gate first — `adb connect <serial>` + check for a device-state entry; exit 2 if none.
2. Build the helixqa binary to a temp path; print its version.
3. Confirm the claude bridge is on PATH (warn if absent).
4. Per provider: `helixqa run --banks <bank> --platform android --device <serial> --package <pkg> --output .lava-ci-evidence/helixqa/<provider>/<run-id>/` (or `helixqa autonomous --project <root> --platforms android --env .env --output ... in --autonomous mode`).

Verified

- `bash -n` parse: clean (§11.4.67).
- No-device gate: exits 2 with the BLOCKED message (proven 2026-06-08, no VM booted).

Related

- `docs/qa/helixqa-wiring-plan.md` — bridge-discovery facts + verbatim `helixqa list` proof.
- `docs/qa/helixqa-dependency-submodules.md` — the 5 own-org deps that make the binary buildable.
- `scripts/run-genymotion-challenges.sh` — the Genymotion Compose-Challenge device path.

Last verified: 2026-06-08.