

EmbedUno
Variant: 5V/3V3

08/01/2021
V1I1

RELEASED 08-JAN-2020

Page	Index	Page	Index	Page	Index	Page	Index
1	COVER PAGE	11		21		31	
2	BLOCK DIAGRAM	12		22		32	
3	EMBEDUNO SCHEMATIC	13		23		33	
4	REVISION HISTORY	14		24		34	
5		15		25		35	
6		16		26		36	
7		17		27		37	
8		18		28		38	
9		19		29		39	
10		20		30		40	

DESIGN CONSIDERATIONS

DESIGN NOTE:
Example text for informational
design notes.

DESIGN NOTE:
Example text for cautionary
design notes.

DESIGN NOTE:
Example text for debug notes.

DESIGN NOTE:
Example text for critical
design notes.


LAYOUT NOTE:
Example text for critical
layout guidelines.

Cannot open file C:\Users\Obed\Desktop\Fedevel
Academy\DesignFiles\EmbedUno_V1I1\embedsystems.png

Embedsystem		http://www.fedevel.com/academy	
Title:	EmbedUno	Variant:	5V/3V3
Page Contents:	[01] - COVER PAGE.SchDoc		Checked by
Size:	DWG NO		Revision: VIII
Date:	08/01/2021	Embedsystem	Sheet 1 of 5

EmbedUno

(Block Diagram)




Cannot open file C:\Users\Obed\Desktop\Fedevel
Academy\DesignFiles\EmbedUno_VIII\embedsystems.png


Embedsystem			
Title:		Variant: 5V/3V3	
Page Contents:		[02] - BLOCK DIAGRAM.SchDoc	
Size:	DWG NO		Revision: VIII
Date: 08/01/2021	Designed by embedsystems		Sheet 2 Checked by

EMBEDUNO - SCHEMATIC


Micro USB




POWER




POWER LED




USER LED




RESET (16U2)



RESET (328P)



USER BUTTON




DESIGN NOTE:
This board supports 5V or 3V3 voltage level on the IO pins:
1) 5V IO - Fit everything as defined in this schematic. NF means, do not fit this component.
2) 3.3V IO - Remove R27, Fit R28, *Replace Y1 (change from 16MHz to 10MHz), *Replace Y2 (change from 16MHz to 8MHz).
3) Both 5V and 3V3, selected through JP4 - Remove R27, Remove R28, Fit JP4, *Replace Y1 (change from 16MHz to 10MHz), *Replace Y2 (change from 16MHz to 8MHz).
*Note: The 16MHz crystals are not recommended for 3.3V operation. We need to adjust their values, that's why the change.
IMPORTANT: Once you change the crystal value, you may need to re-compile your source code.


DESIGN NOTE:
About JP3:
1) DebugWire support - Short 1&2. This was added to support possible debugWire debugging (programming?) of 328P through 16U2. In this case, the 16U2 needs to have a correct firmware and has to behave as a debugWire tool.
2) ISP programmer mode - Short 2&3. In this case, take a cable and connect J5 & J6 together. Upload AVRISP MKII firmware into 16U2 and you can program 328P. Example of AVRISP MKII firmware can be found at LUFA projects: <http://www.fourwalledcubicle.com/LUFA.php> (Tip: remap LEDs of the default AVRISP MKII LUFA project to the RX and TX LEDs on the 28Pin board)
3) ISP header - Short 3 & 4. In this mode, the ICSP1 header is used as a standard ISP header to program 16U2 through ISP interface by an ISP programmer.

DESIGN NOTE:
About JP1:
1) Autoreset Enabled - Short 1&2. In this case, 16U2 is used to reset 328P when firmware inside 328P is updated from Arduino IDE.
2) 16U2 DFU mode Enabled - Short 2&3. 16U2 HWB pin is sampled by 16U2 during RESET. If pulled low, then after Reset the 16U2 will go into DFU mode (it's the mode when you can flash 16U2 firmware through USB and Atmel Flip software: <http://www.atmel.com/tools/flip.aspx>).

3V3 LDO




Power Selection



DESIGN NOTE:
This board can be powered from micro USB connector (J7) or a single +3.3V power rail (through J1 pin 4). If +3.3V is used, fit R26 and R28. In this case, JP4 & R27 must NOT be fitted, otherwise the board may be damaged.

328P



1	2	3	4	5	6	7	8																																				
A	<h1>REVISION HISTORY</h1>							A																																			
B								B																																			
C								C																																			
D	<div>Cannot open file C:\Users\Obed\Desktop\Fedevel Academy\DesignFiles\EmbedUno_VIII\embedsystems.png</div> <table><tr><td colspan="2">Embedsystem</td><td colspan="5">http://www.fedevel.com/academy</td></tr><tr><td>Title:</td><td colspan="2">EmbedUno</td><td colspan="4">Variant: 5V/3V3</td></tr><tr><td>Page Contents:</td><td colspan="5">[04] - REVISION HISTORY.SchDoc</td><td>Checked by</td></tr><tr><td>Size:</td><td colspan="5">DWG NO</td><td>Revision: VIII</td></tr><tr><td>Date:</td><td colspan="3">08/01/2021</td><td>Sheet</td><td>4</td><td>of 5</td></tr></table>							Embedsystem		http://www.fedevel.com/academy					Title:	EmbedUno		Variant: 5V/3V3				Page Contents:	[04] - REVISION HISTORY.SchDoc					Checked by	Size:	DWG NO					Revision: VIII	Date:	08/01/2021			Sheet	4	of 5	D
Embedsystem		http://www.fedevel.com/academy																																									
Title:	EmbedUno		Variant: 5V/3V3																																								
Page Contents:	[04] - REVISION HISTORY.SchDoc					Checked by																																					
Size:	DWG NO					Revision: VIII																																					
Date:	08/01/2021			Sheet	4	of 5																																					
1	2	3	4	5	6	7	8																																				

1	2	3	4	5	6	7	8																					
A	<div>Designator [01] - COVER PAGE.SchDoc</div> <div>Designator [02] - BLOCK DIAGRAM.SchDoc</div> <div>Designator [03] - EmbedUno_Schematic.SchDoc</div> <div>Designator [04] - REVISION HISTORY.SchDoc</div>							A																				
B								B																				
C								C																				
D	<div><div>NOTES</div><div>Mark Not Fitted Components as NF</div><div>DRAFT - Very early stage of schematic, ignore details.</div><div>PRELIMINARY - Close to final schematic.</div><div>CHECKED - There should not be any mistakes. Tell the engineer if you find one.</div><div>RELEASED - A board with this schematic has been sent to production.</div></div> <div>Cannot open file C:\Users\Obed\Desktop\Fedevel Academy\DesignFiles\EmbedUno_VIII\embedsystems.png</div> <table><tr><td colspan="2">Embedsystem</td><td colspan="2">embedsystems</td></tr><tr><td>Title:</td><td>EmbedUno</td><td>Variant:</td><td>5V/3V3</td></tr><tr><td>Page Contents:</td><td>EmbedUno.SchDoc</td><td colspan="2">Checked by</td></tr><tr><td>Size:</td><td colspan="2">DWG NO</td><td>Revision: VIII</td></tr><tr><td>Date:</td><td>08/01/2021</td><td>Designed by embedsystem</td><td>Sheet 5 of 5</td></tr></table>							Embedsystem		embedsystems		Title:	EmbedUno	Variant:	5V/3V3	Page Contents:	EmbedUno.SchDoc	Checked by		Size:	DWG NO		Revision: VIII	Date:	08/01/2021	Designed by embedsystem	Sheet 5 of 5	D
Embedsystem		embedsystems																										
Title:	EmbedUno	Variant:	5V/3V3																									
Page Contents:	EmbedUno.SchDoc	Checked by																										
Size:	DWG NO		Revision: VIII																									
Date:	08/01/2021	Designed by embedsystem	Sheet 5 of 5																									
1	2	3	4	5	6	7	8																					