

Advanced Concepts in Time-Shifting and Discrete-Time Signals

Prof. Mehdi Pirahandeh

May 1, 2024

1 Overview

Discrete-time signals are digital signals processed by digital systems. The concept of time-shifting is pivotal in understanding signal manipulation and system responses. Time-shifting involves shifting a signal in the time domain either to the right (delaying) or to the left (advancing). This lecture expands on the basic concepts of discrete-time signals and time-shifting. We will explore the mathematical foundations, practical applications, and implications of these concepts in modern digital signal processing.

2 Discrete-Time Signal Properties

Discrete-time signals are fundamental to digital signal processing. Unlike continuous-time signals, they are defined only at discrete time intervals. This section explores key properties such as periodicity, symmetry, and energy.

2.1 Periodicity

A discrete-time signal $x[n]$ is periodic with period N if

$$x[n] = x[n + N] \quad \text{for all } n$$

We will examine how the period affects the frequency components of a signal.

2.2 Symmetry

Signals can be even or odd:

- An **even signal** satisfies $x[n] = x[-n]$.
- An **odd signal** satisfies $x[n] = -x[-n]$.

Understanding symmetry helps in simplifying Fourier transforms of signals.

2.3 Energy and Power

The energy E of a discrete-time signal is defined as

$$E = \sum_{n=-\infty}^{\infty} |x[n]|^2$$

Power signals, on the other hand, have finite power:

$$P = \lim_{N \rightarrow \infty} \frac{1}{2N+1} \sum_{n=-N}^N |x[n]|^2$$

3 Time-Shifting and its Effects

Time-shifting is a fundamental operation in signal processing. It involves altering the time index of a signal, which has profound implications in systems design and analysis.

3.1 Mathematical Representation

A time-shifted signal $y[n]$ can be represented as:

$$y[n] = x[n - k]$$

where k is the shift factor. Positive k delays the signal, while negative k advances it.

3.2 Practical Implications

Time-shifting can affect system response, filter design, and synchronization in communication systems. For instance, in echo generation, a signal is delayed and added back to the original to create an echo effect.

4 MATLAB Demonstration Continued

Building on the previous examples, let's analyze how time-shifting affects different types of signals and their spectral properties using MATLAB.

4.1 Signal Analysis

```
1 % Analyzing the effect of time-shifting on signal spectra
2 N = 512; % Number of points in FFT
3 f = linspace(-0.5, 0.5, N); % Frequency vector
4 X = fftshift(fft(x, N)); % FFT of the original signal
5 Y = fftshift(fft(y, N)); % FFT of the time-shifted signal
6
7 % Plot the magnitude spectra of both signals
```

```

8 figure;
9 subplot(2,1,1); plot(f, abs(X));
10 title('Original Signal Spectrum');
11 subplot(2,1,2); plot(f, abs(Y));
12 title('Time-Shifted Signal Spectrum');

```

5 MATLAB Demonstration

The MATLAB script below demonstrates how to plot time-shifted discrete-time signals using synthetic data. The script also includes drawing a Cartesian plane to help visualize shifts.

5.1 Code Description

```

1 % Define the time shift
2 tt = -3; % A negative shift implies advancing the signal.
3
4 % Define the coordinates for the signals
5 xx1 = 0:10; yy1 = sin(xx1); % Sine wave data for signal 1
6 xx2 = 0:10; yy2 = cos(xx2); % Cosine wave data for signal 2
7 xx3 = 0:10; yy3 = xx3.^2; % Quadratic data for signal 3
8
9 % Cartesian coordinates for drawing a cross
10 tts1 = [0 0]; % Vertical line X-coordinates
11 tts2 = [-1 2.5]; % Vertical line Y-coordinates
12 tts3 = [(-5-tt) (5-tt)]; % Horizontal line X-coordinates
13 tts4 = [0 0]; % Horizontal line Y-coordinates
14
15 % Plot each signal in a separate subplot
16 figure;
17 subplot(2,2,1); stem(xx1-tt, yy1, 'filled');
18 subplot(2,2,2); stem(xx2-tt, yy2, 'filled');
19 subplot(2,2,3); stem(xx3-tt, yy3, 'filled');
20 subplot(2,2,4); plot([tts1 tts3], [tts2 tts4], 'k', 'LineWidth', 1)
    ;

```

5.2 Line-by-Line Explanation

- **Lines 1-3:** Define a negative time shift, indicating that the signals are to be advanced.
- **Lines 5-7:** Setup arrays representing the x-coordinates and y-coordinates for three different signals. These include a sine wave, cosine wave, and a quadratic signal.
- **Lines 9-12:** Establish coordinates for drawing a cross in the plots to help illustrate the concept of the time axis and zero crossing.
- **Lines 14-19:** Each 'subplot' function call creates a section of the figure window to plot one of the signals, ensuring that all signals are visible

simultaneously. The ‘stem’ function plots discrete data points, and the ‘plot’ function is used to draw straight lines (the Cartesian cross).

Exercise 1: Time-Shifting and Signal Characteristics (20 Minutes)

Objective: Explore the effects of time-shifting on different signal characteristics.

Task:

- Generate a discrete-time signal $x[n] = \sin(2\pi fn)$ where $f = 0.1$.
- Time-shift this signal by +10, -10, and +30 samples.
- Plot the original and each shifted signal on the same graph with different colors.
- Describe how the time-shift affects the signal in terms of phase and alignment.

Questions: 1. What happens to the signal as it is shifted forwards and backwards? 2. How does the phase of the signal change with each shift?

Exercise 2: System Response to Time-Shifting (20 Minutes)

Objective: Analyze the system response to a time-shifted input using a simple system.

Task:

- Consider a system $y[n] = x[n] - 0.5x[n - 1]$.
- Generate a unit pulse signal $x[n] = \delta[n]$ and apply it to the system.
- Shift the unit pulse by 10 samples, apply it to the same system, and plot the output.
- Compare the output of the shifted input to the original output.

Questions: 1. How does shifting the input affect the output of the system?
2. What implications does this have for real-time signal processing applications?

Exercise 3: Frequency Domain Analysis of Time-Shifted Signals (20 Minutes)

Objective: Understand the impact of time-shifting on the frequency domain representation of signals.

Task:

- Use the signal $x[n] = \sin(2\pi fn) + \cos(2\pi 2fn)$ where $f = 0.05$.
- Compute and plot the Fast Fourier Transform (FFT) of the signal.
- Time-shift the signal by +50 and -50 samples and compute the FFT for each.
- Plot the magnitude spectrum of the original and shifted signals on the same graph.

Questions: 1. What changes occur in the magnitude spectrum of the signal when it is time-shifted? 2. How does time-shifting affect the phase spectrum of the signal?

6 Exercise 4: Time-Shift Interaction (20 Minutes)

Objective: Modify the provided MATLAB code to allow dynamic input for the time shift value 'tt'. Plot the results for different values of 'tt' entered by the user.

6.1 Instructions

1. Add a prompt to let the user input a time shift value.
2. Based on the input, plot the time-shifted signals dynamically.
3. Include comments to explain how changing 'tt' affects each plot.

7 Conclusion

In this lecture, we explored deeper into the intricacies of discrete-time signals and time-shifting. These fundamental concepts are critical for students aspiring to excel in signal processing fields.