

QUIZ 2 (A)

NAME: _____

SECTION _____

STUDENT ID: _____

1. Consider following data declaration and fill memory in HEX. ASCII for **A= 41h**.Data memory start at **4000**

DATA (fill given memory for declaration given below)																
<pre> .data v1 DB 2,3, 0ABh,0CDh BYTE 4 v1s = \$-v1 align WORD align 4 v2 DW 'AB','CD',0ABCDh WORD 1 v2c DB 1 ALIGN DWORD ALIGN 2 bptr LABEL Byte wptr LABEL word v3 DD 0ABCDH,'ABCD' DWORD 1 v3ptr DD v3 counter=2 v4 DB counter DUP(counter DUP('A')) counter=1 v1ptr DWORD v1 </pre>																
CODE (fill register & change in memory after every instruction)												Register				
<pre> counter=6 mov al, TYPE v3 mov ah, SIZEOF v2 mov bl,LENGTHOF v1 mov cx,wptr xchg cx,[v2+6] mov esi,v1ptr mov al,[esi+1] inc esi inc BYTE PTR[esi] mov edi,OFFSET v2 mov cx,[edi+3] mov al, bptr mov bx, wptr mov cx, WORD ptr [v3+1] mov cl, counter </pre>																
												al				
												ah				
												bl				
												cx				
												esi				
												al				
												add				
												mem				
												edi				
												cx				
												al				
bx																
cx																
cl																
	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
4000																
4010																
4020																
4030																

QUIZ 2 (A)

NAME: _____

SECTION _____

STUDENT ID: _____

2. Consider following declaration write a code that copy string1 in reverse order to string2 using indirect addressing. **NOTE:** str1ptr hold address of string1 you are supposed to use it to access the address of string1

```
string1 DB "string of characters"
string1size=$-string1
string2 DW string1size DUP(?)
str1ptr DD OFFSET string1
```

3. Consider following code fill registers and memory accordingly. Data memory start at **0100**

DATA																
<pre>num1 DB 1,2,3 n1=2 v1 EQU 2*n1 v2 EQU <5*n1> v3 TEXTEQU %5*n1 n1=3 ary DW v1,v2,v3,n1</pre>																
CODE											REGISTER					
<pre>mov al,num1+2 mov bl,n1 mov cx,ary+1 mov dl,BYTE PTR ary+2 mov esi,DWORD PTR ary</pre>											al					
											bl					
											cx					
											dl					
											esi					
	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0100																
0110																
0120																