Kalman Filter Theory and Applications Equation Drilldown

Michael L. Carroll

October 31, 2020

©2020 by Michael L. Carroll

Part I
The Basic Kalman Equations
Topics

- Understanding the Equations: Heuristic Introduction

- Understanding the Equations: Heuristic Introduction
- **Equation Drilldown: Taking the Equations Apart**

- Understanding the Equations: Heuristic Introduction
- **Equation Drilldown: Taking the Equations Apart**
- State Space Concepts

- Understanding the Equations: Heuristic Introduction
- **Equation Drilldown: Taking the Equations Apart**
- State Space Concepts

- **Mathematical Formulation of the Problem**

- **Mathematical Formulation of the Problem**
- Drilldown on State Dynamics

- **Mathematical Formulation of the Problem**
- Drilldown on State Dynamics
- Kalman Filter Solution: The Five Equations

- **Mathematical Formulation of the Problem**
- Drilldown on State Dynamics
- Kalman Filter Solution: The Five Equations
- Examples

- **Mathematical Formulation of the Problem**
- Drilldown on State Dynamics
- Kalman Filter Solution: The Five Equations
- Examples
- Exercises

- **Mathematical Formulation of the Problem**
- Drilldown on State Dynamics
- Kalman Filter Solution: The Five Equations
- Examples
- Exercises

- Given two models:

- Given two models:
  - State Dynamics Model
    (sometimes called the System or Process Model)

- Given two models:
  - State Dynamics Model
    (sometimes called the System or Process Model)
  - Measurement Model
    (sometimes called the Observation Model)

- Given two models:
  - State Dynamics Model
    (sometimes called the System or Process Model)
  - Measurement Model
    (sometimes called the Observation Model)
- Calculate:

- Given two models:
  - State Dynamics Model
    (sometimes called the System or Process Model)
  - Measurement Model
    (sometimes called the Observation Model)
- Calculate:
  - the optimal **linear** gain $K(k)$ with which to weight the measurement residual (or innovation) and

- Given two models:
  - State Dynamics Model
    (sometimes called the System or Process Model)
  - Measurement Model
    (sometimes called the Observation Model)
- Calculate:
  - the optimal **linear** gain $K(k)$ with which to weight the measurement residual (or innovation) and
  - update the state estimate *recursively and incrementally* by adding in the weighted residual

- Given two models:
  - State Dynamics Model
    (sometimes called the System or Process Model)
  - Measurement Model
    (sometimes called the Observation Model)
- Calculate:
  - the optimal **linear** gain $K(k)$ with which to weight the measurement residual (or innovation) and
  - update the state estimate *recursively and incrementally* by adding in the weighted residual

---

Given:

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector
- Measurement Model: $z(k) = h[x(k)] + v(k)$

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector
- Measurement Model: $z(k) = h[x(k)] + v(k)$
  - where z=measurement vector, h=vector-valued measurement function, v=measurement noise

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector
- Measurement Model: $z(k) = h[x(k)] + v(k)$
  - where z=measurement vector, h=vector-valued measurement function, v=measurement noise

Calculate:

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector
- Measurement Model: $z(k) = h[x(k)] + v(k)$
  - where z=measurement vector, h=vector-valued measurement function, v=measurement noise

Calculate:

- Optimal gain $K(k)$ in order to update state estimate:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - h(\hat{x}^-(k))\,]$$

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector
- Measurement Model: $z(k) = h[x(k)] + v(k)$
  - where z=measurement vector, h=vector-valued measurement function, v=measurement noise

Calculate:

- Optimal gain $K(k)$ in order to update state estimate:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - h(\hat{x}^-(k))\,]$$

  - where $\hat{x}^-(k) = f[\hat{x}^+(k-1)]$=extrapolated/predicted estimate, K=gain matrix, $h(\hat{x}^-(k)])$=expected/predicted measurement

Given:

- State Dynamics Model: $x(k) = f[x(k-1)] + w(k)$
  - where x=state vector, f=vector-valued dynamics function, w=process noise vector
- Measurement Model: $z(k) = h[x(k)] + v(k)$
  - where z=measurement vector, h=vector-valued measurement function, v=measurement noise

Calculate:

- Optimal gain $K(k)$ in order to update state estimate:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - h(\hat{x}^-(k))\,]$$

  - where $\hat{x}^-(k) = f[\hat{x}^+(k-1)]$=extrapolated/predicted estimate, K=gain matrix, $h(\hat{x}^-(k)])$=expected/predicted measurement

- Original Kalman filter was derived for linear (or linearized) system dynamics and linear measurement model

- Original Kalman filter was derived for linear (or linearized) system dynamics and linear measurement model
  - Assume now that vector-valued f is realized as simple multiplication by matrix Φ
    (also assume for now that Φ does not vary with time);
    we call Φ the **state transition matrix**

- Original Kalman filter was derived for linear (or linearized) system dynamics and linear measurement model
  - Assume now that vector-valued f is realized as simple multiplication by matrix Φ
    (also assume for now that Φ does not vary with time);
    we call Φ the **state transition matrix**
  - Assume also that h is realized as a matrix multiplier H

- Original Kalman filter was derived for linear (or linearized) system dynamics and linear measurement model
  - Assume now that vector-valued f is realized as simple multiplication by matrix Φ
    (also assume for now that Φ does not vary with time);
    we call Φ the **state transition matrix**
  - Assume also that h is realized as a matrix multiplier H
- Find a gain $K(k)$ in form of multiplier (i.e., a gain matrix)

- Original Kalman filter was derived for linear (or linearized) system dynamics and linear measurement model
  - Assume now that vector-valued f is realized as simple multiplication by matrix Φ
    (also assume for now that Φ does not vary with time);
    we call Φ the **state transition matrix**
  - Assume also that h is realized as a matrix multiplier H
- Find a gain $K(k)$ in form of multiplier (i.e., a gain matrix)

Given:

Given:

- Discrete-Time State Dynamics Model:

$$x(k) = \Phi x(k-1) + w(k)$$

Given:

- Discrete-Time State Dynamics Model:

$$x(k) = \Phi x(k-1) + w(k)$$

  - x=state vector, Φ=state transition matrix, w=process noise vector

Given:

- Discrete-Time State Dynamics Model:
$$x(k) = \Phi x(k-1) + w(k)$$
  - x=state vector, Φ=state transition matrix, w=process noise vector
- Measurement Model: $z(k) = H\,x(k) + v(k)$
  - where z=measurement vector, H=measurement matrix (assumed constant), v=measurement noise vector

Given:

- Discrete-Time State Dynamics Model:
$$x(k) = \Phi x(k-1) + w(k)$$
  - x=state vector, Φ=state transition matrix, w=process noise vector
- Measurement Model: $z(k) = H\,x(k) + v(k)$
  - where z=measurement vector, H=measurement matrix (assumed constant), v=measurement noise vector

Calculate:

Given:

- Discrete-Time State Dynamics Model:
$$x(k) = \Phi x(k-1) + w(k)$$
  - x=state vector, Φ=state transition matrix, w=process noise vector
- Measurement Model: $z(k) = H\,x(k) + v(k)$
  - where z=measurement vector, H=measurement matrix (assumed constant), v=measurement noise vector

Calculate:

- An optimal gain matrix $K(k)$ and new state estimate:
$$\hat{x}^-(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,]$$

Given:

- Discrete-Time State Dynamics Model:
$$x(k) = \Phi x(k-1) + w(k)$$
  - x=state vector, Φ=state transition matrix, w=process noise vector
- Measurement Model: $z(k) = H\,x(k) + v(k)$
  - where z=measurement vector, H=measurement matrix (assumed constant), v=measurement noise vector

Calculate:

- An optimal gain matrix $K(k)$ and new state estimate:
$$\hat{x}^-(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,]$$
  - where $\hat{x}^-(k) = \Phi\hat{x}^+(k-1)$ extrapolates previous estimate, and $H\hat{x}^-(k)$ is the expected/predicted measurement

Given:

- Discrete-Time State Dynamics Model:
$$x(k) = \Phi x(k-1) + w(k)$$
  - x=state vector, Φ=state transition matrix, w=process noise vector
- Measurement Model: $z(k) = H\,x(k) + v(k)$
  - where z=measurement vector, H=measurement matrix (assumed constant), v=measurement noise vector

Calculate:

- An optimal gain matrix $K(k)$ and new state estimate:
$$\hat{x}^-(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,]$$
  - where $\hat{x}^-(k) = \Phi\hat{x}^+(k-1)$ extrapolates previous estimate, and $H\hat{x}^-(k)$ is the expected/predicted measurement

- Reminder: To distinguish prior (extrapolated) estimate from updated estimate, we use the $+/-$ hat notation:
  $\hat{x}^-(k) := \Phi\hat{x}^+(k-1) =$ predicted estimate
  and $\hat{x}^+(k) =$ updated estimate

- Reminder: To distinguish prior (extrapolated) estimate from updated estimate, we use the $+/-$ hat notation:
  $\hat{x}^-(k) := \Phi\hat{x}^+(k-1) =$ predicted estimate
  and $\hat{x}^+(k) =$ updated estimate
- The term $\hat{x}^-(k) := \Phi\hat{x}^+(k-1)$ is the extrapolated or predicted state estimate computed using the state transition matrix Φ prior to making the measurement update or correction

- Reminder: To distinguish prior (extrapolated) estimate from updated estimate, we use the +/- hat notation:
  $\hat{x}^-(k) := \Phi\hat{x}^+(k-1) =$ predicted estimate
  and $\hat{x}^+(k) =$ updated estimate
- The term $\hat{x}^-(k) := \Phi\hat{x}^+(k-1)$ is the extrapolated or predicted state estimate computed using the state transition matrix Φ prior to making the measurement update or correction
- Sometimes we'll use $\hat{z}(k)$ to denote the expected/predicted measurment $H\hat{x}^-(k)$

- Reminder: To distinguish prior (extrapolated) estimate from updated estimate, we use the +/- hat notation:
  $\hat{x}^-(k) := \Phi\hat{x}^+(k-1) =$ predicted estimate
  and $\hat{x}^+(k) =$ updated estimate
- The term $\hat{x}^-(k) := \Phi\hat{x}^+(k-1)$ is the extrapolated or predicted state estimate computed using the state transition matrix Φ prior to making the measurement update or correction
- Sometimes we'll use $\hat{z}(k)$ to denote the expected/predicted measurment $H\hat{x}^-(k)$

- Thus, the solution we seek looks like this:

- Thus, the solution we seek looks like this:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,] \tag{1}$$

- Thus, the solution we seek looks like this:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,] \tag{1}$$

where $\hat{x}^-(k) = \Phi\hat{x}^+(k-1)$

- Thus, the solution we seek looks like this:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,] \tag{1}$$

  where $\hat{x}^-(k) = \Phi\hat{x}^+(k-1)$

- This now looks a lot like the running average problem!

- Thus, the solution we seek looks like this:

$$\hat{x}^+(k) = \hat{x}^-(k) + K(k)\,[\,z(k) - H\hat{x}^-(k)\,] \tag{1}$$

  where $\hat{x}^-(k) = \Phi\hat{x}^+(k-1)$

- This now looks a lot like the running average problem!

- But what happened to the process noise $w(k)$ and the measurement noise $v(k)$?
  They don't seem to appear in the solution

- But what happened to the process noise $w(k)$ and the measurement noise $v(k)$?
  They don't seem to appear in the solution
- As mentioned in last playlist, the statistics (covariances) associated with these processes enter into the computation of the Kalman gain

- But what happened to the process noise $w(k)$ and the measurement noise $v(k)$?
  They don't seem to appear in the solution
- As mentioned in last playlist, the statistics (covariances) associated with these processes enter into the computation of the Kalman gain
- Using the Kalman gain, we will also be able to update the **estimation uncertainty**, otherwise known as the **estimation error covariance**

- But what happened to the process noise $w(k)$ and the measurement noise $v(k)$?
  They don't seem to appear in the solution
- As mentioned in last playlist, the statistics (covariances) associated with these processes enter into the computation of the Kalman gain
- Using the Kalman gain, we will also be able to update the **estimation uncertainty**, otherwise known as the **estimation error covariance**
- Likewise, we'll be able to use Φ to predict the change over time in estimation uncertainty

---

- Where are we?

- Where are we?
  - We've formulated the linear discrete problem

- Where are we?
  - We've formulated the linear discrete problem
  - We've indicated the form of the solution: the recursive estimating algorithm with a matrix-valued Kalman gain

- Where are we?
  - We've formulated the linear discrete problem
  - We've indicated the form of the solution: the recursive estimating algorithm with a matrix-valued Kalman gain
- What's next?

- Where are we?
  - We've formulated the linear discrete problem
  - We've indicated the form of the solution: the recursive estimating algorithm with a matrix-valued Kalman gain
- What's next?
  - Drill down further on the state dynamics and determine how noise/uncertainty statistics change over time and how both estimation uncertainty and measurment noise uncertainty are used to calculate the Kalman gain
  - When we arrive at the general solution, we'll get an added benefit: While trying to come up with $\hat{x}^+(k)$ and $K(k)$, we'll also end up with a recursive estimate of our estimation uncertainty

- Where are we?
  - We've formulated the linear discrete problem
  - We've indicated the form of the solution: the recursive estimating algorithm with a matrix-valued Kalman gain
- What's next?
  - Drill down further on the state dynamics and determine how noise/uncertainty statistics change over time and how both estimation uncertainty and measurment noise uncertainty are used to calculate the Kalman gain
  - When we arrive at the general solution, we'll get an added benefit: While trying to come up with $\hat{x}^+(k)$ and $K(k)$, we'll also end up with a recursive estimate of our estimation uncertainty