

USED MEDIAS LLC

EMBEDDED SYSTEMS DIVISION

Display Driver

UM-CYDOS-015

DOCUMENT	REVISION	STATUS	CLASSIFICATION
UM-CYDOS-015	1.1 · 2026-08-15	**Complete, verified on hardware** — §5 added, driver moved to the SPI2 peripheral	Internal

1. Abstract

cyd-os drives the CYD's ILI9341 panel: 240×320, 16-bit colour, filled regions and text, driven from a native task showing live kernel state.

There is **no framebuffer anywhere in the system**. UM-CYDOS-010 §7.2 argued that one should not exist — the panel holds the image in its own GRAM, so a host copy is a redundant 153,600 B against a 158,000 B heap. This report is that argument implemented: every pixel is rendered through a **480-byte** span buffer.

Confirmed on the physical panel: header bar, live numeric fields, an advancing marker, and a strip of colour primaries.

§5 (revision 1.1) replaces the bit-banged transport with the SPI2 peripheral, taking a full-screen fill from 387 ms to 78 ms. The staging that §3 argues for is what made that change safe to attempt, and §5.3 records why the speedup is 5× rather than the 12× this report originally predicted.

2. Pin map

Taken from the vendor project's active `TFT_eSPI/User_Setup.h` rather than from recollection. On a board where a wrong pin and a wrong init sequence produce an identical symptom, the difference between reading and remembering is the difference between a first-try success and an afternoon.

Signal	GPIO	Note
SCLK	14	
MOSI	13	
MISO	12	unused — the driver never reads the panel
CS	15	
DC	2	low = command, high = data
BL	21	active high
RST	—	not wired to a GPIO; follows the ESP32's own reset

Because RST is not under software control, the only reset available after boot is the panel's `0x01 SWRESET`.

3. Why bit-banged SPI

Deliberate, and deliberately temporary.

Hardware SPI2 requires DPORT peripheral clock-enable bits and GPIO matrix signal routing. Every mistake in either produces **exactly the same symptom** as a wiring error, a wrong pin, or a bad init sequence: a black screen with no diagnostic. Bringing up four uncertain subsystems at once and then bisecting them from a single bit of output is how M2 consumed nine build cycles (UM-CYDOS-009 §6).

Bit-banging touches only GPIO registers, which `gpio.h` covers completely. A failure could therefore only be the panel, the pins, or the commands — three candidates instead of seven.

3.1 Measured cost

```
153,600 bytes in 387 ms ≈ 397 kB/s ≈ 3.2 MHz effective clock
```

The estimate written into the source first was ~150 ms, wrong by a factor of 2.6. A store to a peripheral register costs considerably more than the "few cycles" assumed. The figure is now measured at init and reported over UART, because throughput is the number that decides whether SPI2 is worth the risk, and an assertion would have decided it wrongly.

2.6 full screens per second is ample for a status display and useless for animation. Partial updates are what make it comfortable: redrawing six numeric fields costs a few hundred spans rather than 76,800 pixels.

4. Rendering without a framebuffer

`display_fill_rect()` composes one row into `g_line[240]` — 480 bytes — sets the panel's address window once, then pushes that span `h` times. `display_text()` does the same per glyph row.

The panel's GRAM is the framebuffer. Setting a window and streaming into it is not a workaround for having too little RAM; it is how the device is designed to be driven, and the 153,600 B figure in UM-CYDOS-010 §7 was only ever the cost of declining to use it.

4.1 The font is free

A 5×8 column-encoded font, 95 glyphs, 475 bytes, in `.rodata`. Since UM-CYDOS-011 that is mapped from flash through the data cache and costs **zero DRAM**. This is the first consumer of that work, and the reason it was scheduled before M4 rather than after.

4.2 Guarded by a mutex

The span buffer and the panel's current address window are both shared state. Two tasks drawing concurrently would interleave pixel streams into a single window and produce garbage.

`display.c` takes a recursive mutex around `fill_rect` and `text` — the first use of UM-CYDOS-014's primitive outside its own self-test. Recursive matters here: `display_clear()` draws through `display_fill_rect()`, so a non-recursive lock would deadlock on the first clear.

5. Hardware SPI2

Added in revision 1.1.

5.1 The deferral was the point

§3 argues for bit-banging first because a wrong DPORT clock bit or a wrong IOMUX selection produces a black screen — the same symptom as a wrong pin, a bad init sequence, or an unseated flex. Bringing up four uncertain subsystems together and bisecting them from one bit of output is how M2 consumed nine build cycles.

That argument is what made this change cheap when it came. Panel, pins, command sequence and colour order were already known good, so the only thing under test was the transport. A black screen could mean exactly one thing.

5.2 What it took

The CYD's display pins are the ESP32's **native HSPI pads**, so IOMUX routes SCLK and MOSI straight to the peripheral — no GPIO matrix, and none of the 40 MHz ceiling the matrix imposes.

CS and DC stay ordinary GPIOs. The driver holds CS asserted across a window command *and* its entire pixel stream (§4), which is not a shape the peripheral's CS automation expresses.

Two details worth keeping:

- **The DPORT write is read-modify-write, never a plain store.** Bit 1 of the same register clocks the flash controller this kernel executes from.
- **Both configuration registers are read back.** `clk=0x00001001` confirms the `sysclk/2` divisor took; `dport` bit 6 confirms the peripheral clock gate stuck. A register that silently fails to take is the difference between a fast display and a black one, and this report's whole staging argument is about not having to guess which.

The bit-banged path is retained behind `DISPLAY_USE_SPI2 0`, and both backends now route through a single `spi_tx()` entry point so a switch cannot leave a stray direct-transport call behind.

5.3 Measured, and why the estimate was wrong

387 ms -> 78 ms full-screen fill

5×, against the ~12× this report predicted in revision 1.0.

At 40 MHz the theoretical floor for 153,600 bytes is about 31 ms, so roughly 2.5× of what remains is per-transaction overhead. The FIFO holds 64 bytes, so a 480-byte span costs eight transactions — sixteen register writes, a start and a poll each — and a full screen is **2,560 of them**.

The original estimate treated the clock rate as the only variable. It is the transaction count that dominates, and that is precisely what DMA exists to remove. The gap between the estimate and the measurement is more useful than either number alone, which is why both are recorded.

5.4 Clock choice

`sysclk/2` is deliberate and conservative. 80 MHz is one register bit away (`SPI_CLK_EQU_SYSCLK`), but the practical limit here is the flex cable and the board layout rather than the controller, so raising it is a change to make against a measurement rather than on spec-sheet optimism.

6. Verification

Visual confirmation on the panel: the status screen renders, values update, and the colour strip shows distinct primaries.

The colour strip exists as a diagnostic rather than decoration. Eight primaries in a known order make a pixel-format or byte-order fault immediately visible; a garbled or monochrome strip would have said which of the two was wrong, without inference from a photograph.

Colour order confirmed. Red renders leftmost, matching the intended `RED, GREEN, BLUE, YELLOW, CYAN, MAGENTA, WHITE, GREY`. That validates the BGR bit in `MADCTL 0x48`: had the panel's red and blue channels been transposed, the strip would have read blue-first and every colour in the system would have been mirrored while still looking entirely plausible in isolation. Distinct primaries alone would not have caught it — only their **order** does, which is why the strip is drawn in a known sequence rather than as arbitrary swatches.

The advancing marker block is the same idea applied to liveness: a display whose numbers all look plausible but never change is otherwise indistinguishable from a working one.

```
display : init ok, bytes=153634 fullscreen=387 ms
tasks   : report=0 a=1 b=2 vm=3 apps=4 shell=5 disp=6
```

`153,634` is $240 \times 320 \times 2$ for the initial clear plus 34 command bytes — the exact figure a correct full-screen fill produces, which is what made it usable as a check before anything was known to be visible.

Regression. Eight native tasks now scheduling. M3, M4, M5 and locking self-tests all still passing.

7. Metrics

Quantity	Value
Resolution	240×320, RGB565
Framebuffer	none
Span buffer	480 B
Font	475 B, in flash
Full-screen fill	78 ms via SPI2 (387 ms bit-banged)
SPI clock	40 MHz (<code>sysclk/2</code>); ~3.2 MHz bit-banged
Transactions per full screen	2,560 (64-byte FIFO)
Theoretical floor at 40 MHz	~31 ms
Bytes for init + clear	153,634
Native tasks	8
Image size	18,896 B

8. What this does not establish

- **No DMA.** 2,560 CPU-driven transactions per full screen account for most of the remaining time (§5.3). DMA would remove them and is the next real speedup available.
- **No 80 MHz.** One register bit, but unmeasured against this board's flex and layout (§5.4).
- **No read phase.** The driver is write-only; `MISO` is wired but unused, so the panel is never interrogated.
- **No touch.** The CYD's XPT2046 is on separate pins and entirely untouched.
- **No orientation control.** `MADCTL` is fixed at `0x48`. Rotation is not implemented.
- **No clipping of text.** A string running past the right edge stops at the panel boundary rather than wrapping.
- **No damage tracking.** Callers decide what to redraw; nothing computes dirty regions.
- **No display access from applications.** There is no syscall for drawing, so bytecode cannot reach the screen. That is the obvious next step and would be the first VM syscall to carry a pointer, which needs the same bounds discipline as everything else in UM-CYDOS-012 §3.
- **No gamma correction.** The gamma tables (`0xE0` / `0xE1`) are left at panel defaults, so colours are correct in channel but not calibrated in response.

9. References

- UM-CYDOS-010 §7.2 — why no framebuffer, and the 153,600 B it would have cost
- UM-CYDOS-011 — flash-mapped `.rodata`, which the font depends on
- UM-CYDOS-014 — the mutex guarding the span buffer
- UM-CYDOS-009 §6 — the multi-variable bring-up this driver's staging avoids

- `kernel/gpio.h` — the two layers that must agree before a pin drives anything
- `kernel/display.c` — SPI, init sequence, span rendering, font