

Touchscreen, and a Verification Method That Failed Three Times

UM-CYDOS-017

DOCUMENT	REVISION	STATUS	CLASSIFICATION
UM-CYDOS-017	1.0 · 2026-08-15	**Complete, verified on hardware**	Internal

1. Abstract

The CYD's XPT2046 resistive touchscreen works: contact is detected through the controller's PENIRQ line, and both axes are mapped to panel coordinates by measurement rather than by reasoning.

The driver took four attempts, and only one of the four failures was in the driver. Two were in `gpio.h`, and the fourth — the one worth reading this report for — was in **how the results were being read**. §5 documents a serial capture that rebooted the board and erased the evidence before printing it, and the two conclusions recorded as fact on the strength of it.

This is the third time in two sessions that an instrument reported its own reading invalid and the number beside it was believed anyway. §6 treats that as the finding.

2. Hardware

Signal	GPIO	Note
CLK	25	
MOSI	32	second GPIO bank
MISO	39	input-only pin, second bank
CS	33	second bank
IRQ (PENIRQ)	36	input-only pin, second bank

Pins and calibration extremes are the board's, taken from the vendor driver.

A separate bus from the display, which matters. The display driver leaves CS asserted between a window command and its pixel stream (UM-CYDOS-015 §4), so a shared bus would mean either interleaving touch traffic into an open window or serialising every touch read behind a 387 ms full-screen fill. Neither is acceptable for a pointer.

Bit-banged, for the same reason the display is: it needs only GPIO registers, so a failure can only be the panel, the pins, or the protocol.

3. Two defects that made a broken driver look plausible

3.1 `gpio.h` only ever handled pins 0–31

Pins 32–39 have entirely separate registers — `OUT1`, `ENABLE1`, `IN1` — and **nothing complains when the wrong bank is used**. A shift of 39 on a 32-bit register is undefined and reads zero in practice.

So MISO on GPIO 39 read a constant 0, and MOSI and CS on 32 and 33 were never driven at all. Every accessor now selects its bank from the pin number, so a caller never has to know the split exists.

This bug was latent from the moment `gpio.h` was written for the display, whose pins are all below 32. It would have broken **any** peripheral above pin 31.

3.2 Silence read as maximum pressure

Pressure was computed as $z = z1 + 4095 - z2$. A controller returning zeros on both channels yields **4095** — full scale. A dead bus therefore presented as a permanent hard press, and the first run reported `s/e=10/10`: every sample a touch, on a screen nobody was touching.

An all-zero reading is now rejected outright. The general point is worth keeping: **a formula whose failure mode is a plausible extreme is worse than one that fails to an obvious value**, because the first requires interpretation and the second announces itself.

3.3 The first conversion is the one that matters

The control bytes originally set `PD1:PD0 = 00`, powering down the ADC and its reference between every conversion. The first conversion after power-up is specified as inaccurate — and `z1`, the channel that decides whether a touch exists, is the first conversion after CS goes low on every single read.

The burst now uses `PD=11` to keep the reference powered, with a throwaway conversion absorbing the inaccurate reading, and a final `PD=00` to power down and re-enable PENIRQ.

4. Detection: PENIRQ, not pressure

Both routes work. Measured under a real touch:

```
irq=17   z1max=1123   z2min=2992   zmax=2065
```

PENIRQ asserted 17 times, matching the event count exactly, and computed pressure peaked at 2065 against a threshold of 300.

PENIRQ is used because it is a direct electrical indication from the panel, needing no ADC, no threshold and no calibration. It is read *before* CS is asserted, since the pin is only meaningful while the controller is idle.

Pressure is still recorded despite no longer being the detector. A channel that never moves is itself evidence, and hiding it would only make the next person repeat the measurement.

5. The capture was destroying its own data

5.1 Symptom

Three consecutive runs, across different builds and different user actions, reported **exactly 150 samples**.

A counter that lands on an identical value every time is not accumulating. It is measuring a fixed window.

5.2 Cause

Opening a serial port asserts DTR/RTS, which is wired to the ESP32's reset and boot pins. Configuring them *after* opening still glitches EN. Every capture described as "no reset" was rebooting the board, waiting for it to boot, and then reading roughly twelve seconds of a system nobody was touching.

Setting `dtr` and `rts` **before** `open()` fixes it. The same read then reports 647,406 samples and no boot banner.

5.3 What it invalidated

Two statements were recorded as findings on data that had already been erased:

- *"pressure never exceeds 1 under a firm press"* — actual value **1123**
- *"PENIRQ never asserts across two full drags"* — actual count **17**

Both were measured on a board that had rebooted seconds earlier. The `PD=11` fix of §3.3 had already worked when it was declared a failure.

Worse, the user reported that dots were following their finger, and that report was overridden as "almost certainly leftovers" on the strength of the broken measurement. **The human observation was the better evidence.**

5.4 Why it was hard to see

The reboot was invisible in every way that was being checked. Output looked normal, because a booting kernel prints a full banner and then healthy report lines. Values looked plausible, because they were real readings — of the wrong interval. Only the sample counter carried the contradiction, and it was printed in the same line as the values that were being trusted.

6. The finding

Three times across two sessions, an instrument reported its own reading invalid and the value beside it was believed anyway:

Instrument	What it said	What was believed instead
Marker block (UM-CYDOS-016 §3.4)	Frozen — the system is halted	The colour bars, which a frozen screen renders identically
<code>s/e=150</code> , three runs	This counter is not accumulating	The pressure values printed beside it
Boot banner in the capture	The board just restarted	The counters, as though continuous

The peripherals were largely fine. The verification method was what kept failing, and it failed in the same shape each time: **a signal that the measurement was invalid, sitting next to a number that looked reasonable.**

What broke the deadlock, every time, was the same move — **latch the quantity so timing cannot lie about it**, then feed the system a controlled input rather than interpret an uncontrolled one. §7 is that method applied deliberately.

7. Calibration by controlled input

Watching a trail follow a finger can say *"the dots go the wrong way"*. It cannot distinguish a **swapped** axis from a **flipped** one, and several build cycles were spent guessing between those two before that was noticed.

Instrumenting the raw span of each channel answers both at once. Two drags, each along one screen axis:

Drag	<code>rx</code> span	<code>ry</code> span
Left → right	486–3536 (3050)	2499–2862 (363)
Top → bottom	675–1518 (843)	432–3204 (2772)

The mirror image is the result. Each drag swept one channel across most of its range while the other barely moved, which is precisely what a correct axis assignment looks like.

Direction falls out of the endpoints: the horizontal drag ended at `rx=3527` against a maximum of 3536, so raw X increases left to right. The vertical drag ran from `ry=586` to `ry=2171`, so raw Y increases downward. Neither axis needs a flip.

The original code had the axes transposed, on the reasoning that a portrait display must swap a landscape-calibrated panel. **That reasoning was wrong**, and no amount of looking at the screen would have said so.

8. Metrics

Quantity	Value
Detection	PENIRQ, GPIO 36
Poll rate	~100 Hz (once per tick)
Conversions per read	11, including one throwaway
Peak pressure measured	2065 (threshold 300)
z1 under touch	1123, against 0 idle
z2 under touch	2992, against ~4090 idle
Raw span, horizontal drag	3050 counts
Raw span, vertical drag	2772 counts
Axis flips required	0
Native tasks	10
Image size	21,888 B
Attempts before working	4
Conclusions retracted	2

9. What this does not establish

- **No multi-touch.** A resistive panel cannot report two points; a second finger produces a reading somewhere between them.
- **No IRQ-driven wakeup.** PENIRQ is polled, not wired to an interrupt. Doing so would let the system idle until touched instead of sampling at 100 Hz.
- **No debounce or gesture recognition.** Every sample is independent; there is no tap, hold, drag or double-tap concept.
- **No touch access from applications.** There is no syscall, so bytecode cannot read the pointer. That is the natural counterpart to the display syscalls of UM-CYDOS-016 and would make applications interactive.
- **Calibration is the vendor's, not this board's.** The extremes were taken from the vendor driver and the measured spans are consistent with them, but no per-unit calibration pass has been run.
- **The cursor leaves a black square** where it has been, because nothing records what was underneath. Fixing that needs either a panel read-back this hardware does not reliably support, or damage tracking the display layer does not have.

10. References

- UM-CYDOS-015 — the display driver, and the shared-bus problem avoided here
- UM-CYDOS-016 §3.4 — the frozen marker, the first instance of the §6 pattern

- `kernel/gpio.h` — the two-bank split of §3.1
- `kernel/touch.c` — PENIRQ detection, PD handling, and the measured mapping