

Aria Doorbell Cam — Owner's Manual

Aria Home · SKU ARIA-DBELL · camera · \$179

This manual covers the Aria Doorbell Cam (model ARIA-DBELL) only. Other Aria products have their own manuals; procedures and error codes are not interchangeable between models.

1. Specifications

Video	1536×1536 head-to-toe view, HDR, 30 fps
Field of view	150° horizontal, 150° vertical
Night vision	colour night vision with ambient light; infrared below 1 lux
Audio	two-way talk with noise cancellation
Storage	cloud via Aria Video plan; 3 hours of event history without a plan
Operating temperature	-5 °F to 120 °F

2. In the box

Doorbell, mounting bracket, 15° wedge, USB-C cable, screws, diode for chime kits.

3. Setup

1. Charge the internal battery with the USB-C cable until the light is solid green (about 5 hours).
2. Mount the bracket at 48 inches from the ground; use the wedge if the door is at an angle.
3. For wired mode, connect the existing doorbell wires to the two terminals; 16–24 V AC is required.
4. Scan the QR code inside the battery cover in the Aria app.

4. Status light

Solid blue ring: streaming or two-way talk.

Pulsing white: pairing.

Solid green (while charging): charged.

Flashing red: battery under 10 percent.

5. Power and battery

Aria Doorbell Cam: Internal 6,040 mAh battery, 3 to 6 months per charge, or hardwired 16–24 V AC.

6. Troubleshooting

Aria Doorbell Cam — Battery drains in a few days. Motion sensitivity is too high or the zone includes a street; reduce Motion zones to the porch only. Expected life is 3 to 6 months per charge in battery mode.

Aria Doorbell Cam — Existing chime does not ring. Install the supplied diode on the chime's Front terminal, then enable Mechanical chime in device settings.

Aria Doorbell Cam — Video is delayed or stutters. Wi-Fi RSSI below -70 dBm; move the router or add an Aria Hub as an extender.

Aria Doorbell Cam — Motion alerts but no video recorded. Event recording needs the Aria Video plan or the 3-hour history; check the plan status in Account.

7. Error codes

Aria Doorbell Cam error D-01: Battery temperature out of range — charging pauses below 32 °F.

Aria Doorbell Cam error D-06: Chime voltage too low (under 16 V AC) — use battery mode or upgrade the transformer.

Aria Doorbell Cam error D-14: Storage sync failed — the doorbell keeps recording locally for 3 hours and retries.

8. Factory reset

To factory reset the Aria Doorbell Cam: Hold the setup button under the faceplate for 20 seconds until the ring flashes white three times.

9. Warranty and compatibility

The Aria Doorbell Cam carries a two-year standard warranty covering manufacturing defects, from the delivery date. Unwanted returns follow the Aria Home returns policy: 14 days from delivery for the Aria Doorbell Cam (security devices have a 14-day window). Damage caused by the customer is handled as a warranty repair, not a refund.

Works with: Aria app, Aria Video plan, Google Home, Amazon Alexa (Echo Show live view).