

Aria Hub — Owner's Manual

Aria Home · SKU ARIA-HUB · hub · \$79

This manual covers the Aria Hub (model ARIA-HUB) only. Other Aria products have their own manuals; procedures and error codes are not interchangeable between models.

1. Specifications

Radios	Zigbee 3.0, Thread border router, Bluetooth LE, Wi-Fi 2.4/5 GHz, Ethernet
Devices	up to 128 Zigbee/Thread devices
Backup	internal battery for 4 hours; optional LTE via USB dongle
Local automation	runs schedules and alarms with no internet

2. In the box

Hub, power adapter, Ethernet cable.

3. Setup

1. Connect Ethernet for the most reliable link; Wi-Fi is the fallback.
2. The ring turns solid white once online; then add sensors and locks through the Hub.

4. Status light

White: online.

Amber: no internet — local automation still runs.

Red: no power, on battery.

5. Power and battery

Aria Hub: 5 V 3 A USB-C adapter. Internal backup battery runs the Hub for 4 hours.

6. Troubleshooting

Aria Hub — Sensors drop offline at the far end of the house. Zigbee range is about 60 feet indoors; add an Aria Smart Plug between the Hub and the sensors as a repeater.

Aria Hub — Hub reboots every few minutes. USB dongle drawing too much power; use the supplied adapter, not a TV USB port.

7. Error codes

Aria Hub error H-01: Zigbee network full — remove unused devices.

Aria Hub error H-09: Thread border router conflict — only one Aria Hub can be primary.

8. Factory reset

To factory reset the Aria Hub: Hold the recessed button for 20 seconds until the ring flashes red; all paired devices are removed.

9. Warranty and compatibility

The Aria Hub carries a two-year standard warranty covering manufacturing defects, from the delivery date. Unwanted returns follow the Aria Home returns policy: 30 days from delivery for the Aria Hub (most devices have a 30-day window). Damage caused by the customer is handled as a warranty repair, not a refund.

Works with: Aria app, Matter, Apple Home, Google Home, Amazon Alexa.