

Aria Motion Sensor — Owner's Manual

Aria Home · SKU ARIA-SENSE · sensor · \$39

This manual covers the Aria Motion Sensor (model ARIA-SENSE) only. Other Aria products have their own manuals; procedures and error codes are not interchangeable between models.

1. Specifications

Detection	passive infrared, 40 feet, 110° horizontal
Pet immunity	ignores animals under 40 lb when mounted at 7 feet
Radio	Zigbee 3.0 via the Aria Hub
Battery	1 × CR123A lithium, about 2 years
Extras	temperature and light level reporting

2. In the box

Motion Sensor, mounting bracket, CR123A battery, adhesive strip.

3. Setup

1. Pull the battery tab; the light blinks green.
2. Mount in a corner at 7 feet, angled down, away from heaters and windows.
3. In the Aria app tap Add device, Motion Sensor, then press the button on the sensor once.

4. Status light

Green blink: motion detected (first 30 minutes after pairing only).

Red blink every 30 seconds: battery low.

Green triple blink: pairing.

5. Power and battery

Aria Motion Sensor: 1 × CR123A lithium, about 2 years. Alkaline cells are not supported.

6. Troubleshooting

Aria Motion Sensor — Shows Not reporting / no signal in the app. The battery is flat or the sensor lost the hub. Replace the CR123A (about 2 years of life), then press the button once; if it still does not report, it is more than 60 feet from the Hub — add an Aria Smart Plug as a repeater.

Aria Motion Sensor — Triggered by the dog. Pet immunity only works when mounted at 7 feet pointing down; lower mounting or a cat on furniture will trigger it. Set Sensitivity to Low.

Aria Motion Sensor — False alerts near a window. Sunlight and HVAC vents look like motion to PIR; move it out of direct sun and away from vents.

7. Error codes

Aria Motion Sensor error S-01: Tamper — the sensor was removed from its bracket.

Aria Motion Sensor error S-03: Battery under 10 percent — replace within 7 days.

8. Factory reset

To factory reset the Aria Motion Sensor: Hold the button for 5 seconds until the light blinks red, release, then press once to pair.

9. Warranty and compatibility

The Aria Motion Sensor carries a two-year standard warranty covering manufacturing defects, from the delivery date. Unwanted returns follow the Aria Home returns policy: 30 days from delivery for the Aria Motion Sensor (most devices have a 30-day window). Damage caused by the customer is handled as a warranty repair, not a refund.

Works with: Aria app, Aria Hub (required).