

KW007: Ultra-Low Power 5.8GHz Microwave Radar Sensor

Motion Detection with Intelligent Doppler Engine

Programming Guide

Version 1.8


March 2026

Key Operational Characteristics:

KW007 Doppler Radar Software Procedure

The **KW007** Doppler radar sensor can operate via a standard **I²C interface**. Upon power-up, the device must perform the following initialization sequence to ensure stable operation and optimal detection performance.

1. **Initialization Settings:** Write the fundamental chip configuration parameters to initialize the device.
2. **Application Settings:** Configure the sensing parameters based on specific application requirements. This includes setting the detection range, and Doppler filter corners.
3. **Automatic Operation:** Once the configuration is applied, the radar operates automatically. The host MCU periodically reads the radar parameters at set intervals for subsequent application processing.



Standard I²C Write/Read Interface Description for KW007

Supported Modes: Standard-mode (100 kHz) / Fast-mode (400 kHz)

Device Address: 7-bit addressing

Data Format: 8-bit Data, MSB First

KW007 Write/Read Address

The KW007 uses an addressing scheme consisting of a fixed 7-bit slave address ID followed by a read/write (R/W) bit.

◆ **Slave address ID:** The fixed 8-bit slave address ID is **00110010b (0x32h)**.

◆ **Read/Write Control:** The address is followed by a R/W bit:

☐ '0' for **Write** operations. (8bit: 0011001**0**b, 0x32h)

☐ '1' for **Read** operations. (8bit: 0011001**1**b, 0x33h)

KW007 Write mode Write format is shown as follow:




Figure 1. KW007 I²C Write Mode Timing Diagram

KW007 Read mode Read format is shown as follow:




Figure 2. KW007 I²C Read Mode Timing Diagram

Register Descriptions

Register	Function	Access	Value	Bits	Description	
Reg 0	R0	R	-	[7:0]	Reserved	
Reg 1	VCO Bank	R	-	[5:0]	VCO Bank (Read Only, factory burned)	
Reg 2 Reg 4	R2 R4	R	-	[7:0]	Reserved	
Reg 5	RSSI	R	-	[7:0]	RSSI Output (Read Only, 0-255)	
Reg 6	Detection Flag: Day/Night & Approach & Leaving	R	-	[3]	Day/Night Flag 0: Night 1: Day	
				[2]	Flag Forward/Approach 0: No object approaching 1: Object approaching	
				[1]	Flag Backward/Leaving 0: No object leaving 1: Object leaving	
Reg 7	R7	R	-		Reserved	
Reg 8	R8	W/R	0xFC	[7:0]	Reserved	
Reg 9	Manual Mode	W/R	0x30	[5]	[5]: Efuse mode 0: FUSE 1: I2C	
Reg 10	R10	W/R	0x88	[7:0]	Reserved	
Reg 11	R11	W/R	0x03	[7:0]	Reserved	
Reg 12	Sampling Rate	W/R	0x54	[7]	Sampling Rate: 0=1kHz, 1=500Hz	
		W/R		[5:0]	VCO Bank (Set during initialization)	
Reg 13 Reg 18	R13 R18	W/R	-	[7:0]	Reserved	
Reg 19	Amp1_Gain	W/R	0xEA	[7:5]	Amplifier 1 Gain: 000: 8 db 001: 12 db 010: 16 db 011: 19 db 100: 21 db 101: 24 db 110: 28 db 111: 32 db	Total Gain = Amp1_Gain + Amp2_Gain + Amp3_Gain (Ex. 24+24+0 = 48db)
Reg 20	Amp3_Gain	W/R	0xF7	[4:3]	Amplifier 3 Gain: 00: 0 db 01: 4 db 10: 8 db 11: 12 db	
	Amp2_Gain	W/R		[2:0]	Amplifier 2 Gain: 000: 8 db 001: 12 db 010: 16 db 011: 19 db 100: 21 db 101: 24 db 110: 28 db 111: 32 db	

Register	Function	Access	Value	Bits	Description
Reg 21	Slow Speed Detection	W/R	0x5F	[5]	High-pass Corner: (Default = 0) 0: Low (Allows slow-moving signals.) 1: High (Cuts off slow-moving signals.)
Reg 22 Reg 23	R22 R23	W/R	-	[7:0]	Reserved
Reg 24	Enhanced Mode	W/R	0xA0	[6]	Enhanced Range Mode: 0: Off (Normal mode) 1: On (Enhanced mode)
Reg 25 Reg 26	R25 R26	W/R	-	[7:0]	Reserved
Reg 27	Valid Decision Magnitude Threshold	W/R	0x30	[7:0]	Decision Magnitude Threshold 00000000: 0 00000001: 1 00000010: 2 ... 11111111: 255
Reg 28	R28	W/R	0x55	[7:0]	Reserved
Reg 29	GPO Delay	W/R	0x75	[2:1]	GPO Delay: (Default = 10) SE/L S 00: 16s 4s 01: 32s 2s 10: 1s 1s 11: 64s 64s
	High Speed Detection	W/R		[0]	Low-pass Corner: (Default = 1) 0: Low (Filters out ultra-fast signals.) 1: High (allow faster objects to detect.)
Reg 30 Reg 31	R30 R31	W/R	-	[7:0]	Reserved

KW007 Recommended Register Configuration:

Address	Value (Hex)	Address	Value (Hex)	Address	Value (Hex)	Address	Value (Hex)
Reg 0	0x00	Reg 8	0xFC	Reg 16	0x98	Reg 24	0xA0
Reg 1	0x00	Reg 9	0x30	Reg 17	0xA0	Reg 25	0x20
Reg 2	0x00	Reg 10	0x88	Reg 18	0x00	Reg 26	0x9A
Reg 3	0x00	Reg 11	0x03	Reg 19	0xEA	Reg 27	0x30
Reg 4	0x00	Reg 12	0x54	Reg 20	0xF7	Reg 28	0x55
Reg 5	0x00	Reg 13	0x4B	Reg 21	0x5F	Reg 29	0x75
Reg 6	0x00	Reg 14	0x68	Reg 22	0x02	Reg 30	0x42
Reg 7	0x00	Reg 15	0x55	Reg 23	0x30	Reg 31	0x00

Note: Reg9 = 0x30 (manual mode), Reg12[5:0] will be set to VCO bank value.

KW007 Radar Sensor


Official Website: <https://keywavetech.co.uk/>

Initialization Flow


Follow these steps in order:

1. **Write REG9 = 0x10** (Efuse mode) to enable reading the factory-burned VCO bank value
2. **Read REG1[5:0]** to obtain the VCO bank value (factory calibrated for each chip)
3. **Set REG12[5:0] = VCO bank value** in your initialization register array
4. **Write all 32 registers (R0-R31)** with REG9 = 0x30 (I²C manual mode)

Write Reg9 = 0x10



Read Reg1[5:0]



Set Reg12[5:0] = VCO bank

Write all 32 Registers



1. Functional Description

The detection range is determined by the three-stage amplifier gain (AmpX_Gain), the decision magnitude threshold. Increasing the amplifier gain and reducing the magnitude threshold will extend the detection range; however, these settings also increase susceptibility to false triggers.

Three-stage Amplifier Gain:

Amp1_Gain R19[7:5]:

(000=8dB, 001=12dB, 010=16dB, 011=19dB, 100=21dB, 101=24dB, 110=28dB, 111=32dB)

Amp2_Gain R20[2:0]:

(000=8dB, 001=12dB, 010=16dB, 011=19dB, 100=21dB, 101=24dB, 110=28dB, 111=32dB)

Amp3_Gain R20[4:3]:

(000=0dB, 001=4dB, 010=8dB, 011=12dB)

For example, to set gain to 48 dB:

Write amp1_gain 32dB, write amp2_gain 16dB, write amp3_gain 0dB.

Total gain:

$$32 + 16 + 0 = 48 \text{ dB}$$

(We suggested using higher gain in the previous stage for better signal/noise quality.)

Mag Threshold:

Reg27 sets the signal threshold after the three-stage amplifier, and the signal needs to be larger than mag threshold to do the detection algorithm. (Range 0~255).

Note: If gain is too small or too high, the signal strength saturates to 0 or 255 and the algorithm does not work well.

Enhance Range Mode:

When Reg24[6] = 1, the detection range will increase.

Doppler Filter High-Pass Corner

The Reg21[5] defines the high-pass corner frequency of the Doppler filter.

☐ 0: Low corner frequency.

Allows low-frequency signals to pass; capable of detecting subtle movements (e.g., breathing).

☐ 1: High corner frequency.

Cuts off slow-moving signals; optimized for detecting rapid motion and filtering out environmental drifts.

Doppler Filter Low-Pass Corner

The Reg29[0] defines the low-pass corner frequency of the Doppler filter.

- ☐ 0: Low corner frequency.
Filters out ultra-fast signals (likely interference) to provide a steady and reliable output.
- ☐ 1: High corner frequency.
Best for speed. It allows the radar to "see" everything instantly, making it highly sensitive to objects moving at extreme speeds.

Sampling Rate:

Sampling rate Reg12[7] will influence filter corner.

Ex. $\text{Corner}_{fs}(1\text{kHz}) = 2 \times \text{Corner}_{fs}(500\text{Hz})$.

*fs = Sampling Frequency.

The detection object speed is determined by the doppler filter **corner** and **sampling rate**. The Doppler low-pass corner filters out fast-moving clutter, but may also attenuate fast-walking human targets. The Doppler high-pass corner is related to slow-motion clutter rejection.

GPO Delay Time

The Reg29[2:1] defines the delay time for the GPO output.

To prevent the output from turning ON and OFF too quickly (chattering) when a target is at the edge of the detection range.

Once motion is detected, the GPO triggers. When the motion stops, the GPO will wait for the **Delay Time** to expire before returning to the "Idle" state.

- ☐ 00: 16 Sec
- ☐ 01: 32 Sec
- ☐ 10: 1 Sec
- ☐ 11: 64 Sec

Approach Flag

The Reg6[2] defines whether an object is moving toward the radar.

Read only.

☐ 0: No object approaching.

☐ 1: Object approaching.

Leaving Flag

The Reg6[1] defines whether an object is moving away from the radar.

Read only.

☐ 0: No object leaving.

☐ 1: Object leaving.

Day/Night Flag

The Reg6[1] defines ambient light conditions.

Read only.

☐ 0: Night.

☐ 1: Day.

Recommended Settings Table

Detection Range (Typical Estimate)	Total Gain Reg19[7:5] + Reg20[4:0] = AMP1 + AMP2 + AMP3	Magnitude Threshold Reg27[7:0]	Enhanced Mode Reg24[6]
Level 1 (15 cm)	19+8+0 = 27 dB	45	OFF
Level 2 (50cm)	24+8+0 = 32dB	64	OFF
Level 3 (1 m)	32+12+0 = 44 dB	90	OFF
Level 4 (3 m)	32+21+0 = 53 dB	90	OFF
Level 5 (5 m)	32+32+0 = 64 dB	90	OFF
Level 6 (7 m)	32+32+4 = 68 dB	64	OFF
Level 7 (10 m)	32+32+12 = 76 dB	32	OFF
Level 8 (13 m)	32+32+12= 76 dB	32	ON

NOTICE & CONFIDENTIALITY STATEMENT

Confidentiality and Proprietary Rights

This document and the information contained herein (including but not limited to register maps, recommended configurations, and functional descriptions) are the proprietary and confidential property of KeywaveTech.

This information is provided to the recipient solely for the purpose of product evaluation and integration.

Any unauthorized use, reproduction, distribution, or disclosure of this document to any third party, in whole or in part, is strictly prohibited without express prior written consent from KeywaveTech.

Revision History	
V1.6	Reg29 0x65 -> 0x75
V1.7	Modify Reg9 Description Update Recommended Table (Level 0~7)
V1.8	Modify Settings Table
V1.9	Modify Register Table

End of Document