

Cypress CyAPI Programmer's Reference

© 2010 Cypress Semiconductor

Table of Contents

Foreword	0
Part I Overview	7
Part II New API	7
Part III Features Not Supported	8
Part IV CCyBulkEndPoint	8
1 BeginDataXfer()	9
2 CCyBulkEndPoint()	10
3 CCyBulkEndPoint()	10
Part V CCyControlEndPoint	11
1 BeginDataXfer()	12
2 CCyControlEndPoint()	13
3 CCyControlEndPoint()	14
4 Direction	14
5 Index	15
6 Read()	16
7 ReqCode	16
8 ReqType	17
9 Target	18
10 Value	19
11 Write()	19
Part VI CCyInterruptEndPoint	20
1 BeginDataXfer()	21
2 CCyInterruptEndPoint()	22
3 CCyInterruptEndPoint()	22
Part VII CCyIsocEndPoint	23
1 BeginDataXfer()	23
2 CCyIsocEndPoint()	25
3 CCyIsocEndPoint()	25
4 CreatePktInfos()	26
Part VIII CCyIsoPktInfo	27

Part IX CCyUSBDevice	28
1 AltIntfc().....	29
2 AltIntfcCount().....	29
3 bHighSpeed.....	29
4 BcdDevice.....	30
5 BcdUSB.....	30
6 BulkInEndPt.....	30
7 BulkOutEndPt.....	31
8 CCyUSBDevice().....	32
9 ~CCyUSBDevice().....	34
10 Close().....	34
11 Config().....	35
12 ConfigAttrib.....	35
13 ConfigCount().....	35
14 ConfigValue.....	36
15 ControlEndPt.....	36
16 DevClass.....	36
17 DeviceCount().....	37
18 DeviceHandle().....	37
19 DeviceName.....	38
20 DevProtocol.....	38
21 DevSubClass.....	38
22 DriverGUID().....	38
23 DriverVersion.....	38
24 EndPointCount().....	39
25 EndPointOf().....	39
26 EndPoints.....	40
27 FriendlyName.....	41
28 GetDeviceDescriptor().....	41
29 GetConfigDescriptor().....	41
30 GetIntfcDescriptor().....	42
31 GetUSBConfig().....	42
32 Interface().....	43
33 InterruptInEndPt.....	44
34 InterruptOutEndPt.....	44
35 IntfcClass.....	45
36 IntfcCount().....	45
37 IntfcProtocol.....	46
38 IntfcSubClass.....	46

39	IsocInEndPt.....	46
40	IsocOutEndPt.....	47
41	IsOpen().....	47
42	Manufacturer.....	48
43	MaxPacketSize.....	48
44	MaxPower.....	48
45	NtStatus.....	48
46	Open().....	49
47	PowerState().....	50
48	Product.....	50
49	ProductID.....	50
50	ReConnect().....	51
51	Reset().....	51
52	Resume().....	51
53	SerialNumber.....	51
54	SetConfig().....	52
55	SetAltIntfc().....	52
56	StrLangID.....	52
57	Suspend().....	53
58	USBAddress.....	53
59	USBDIVersion.....	53
60	UsbdStatus.....	53
61	UsbdStatusString().....	54
62	VendorID.....	54

Part X CCyUSBConfig 55

1	AltInterfaces.....	57
2	bConfigurationValue.....	57
3	bDescriptorType.....	57
4	bLength.....	57
5	bmAttributes.....	58
6	bNumInterfaces.....	58
7	CCyUSBConfig().....	58
8	CCyUSBConfig().....	58
9	CCyUSBConfig().....	59
10	~CCyUSBConfig.....	59
11	iConfiguration.....	59
12	Interfaces.....	60
13	wTotalLength.....	61

Part XI CCyUSBEndPoint	61
1 Abort().....	62
2 Address	62
3 Attributes.....	63
4 BeginDataXfer().....	64
5 bIn	65
6 CCyUSBEndPoint().....	66
7 CCyUSBEndPoint().....	66
8 CCyUSBEndPoint().....	67
9 DscLen.....	67
10 DscType.....	67
11 GetXferSize().....	68
12 FinishDataXfer().....	68
13 hDevice	69
14 Interval.....	70
15 MaxPktSize	70
16 NtStatus.....	70
17 Reset().....	71
18 SetXferSize().....	71
19 TimeOut	71
20 UsbdStatus.....	72
21 WaitForXfer().....	72
22 XferData().....	73
Part XII CCyUSBInterface	74
1 bAlternateSetting.....	76
2 bAltSettings	76
3 bDescriptorType.....	77
4 CCyUSBInterface().....	77
5 CCyUSBInterface().....	77
6 bInterfaceClass	78
7 bInterfaceNumber.....	78
8 bInterfaceProtocol.....	78
9 bInterfaceSubClass.....	79
10 bLength.....	79
11 bNumEndpoints.....	79
12 EndPoints.....	80
13 iInterface.....	81

Index**82**

1 Overview

Overview

[Top](#) [Next](#)

Library Overview

[Top](#) [Next](#)

CyAPI.lib provides a simple, powerful C++ programming interface to USB devices. More specifically, it is a C++ class library that provides a high-level programming interface to the **CyUsb.sys** device driver. The library is only able to communicate with USB devices that are served by (i.e. matched to) this driver.

Rather than communicate with the driver via Windows API calls such as *SetupDiXxxx* and *DeviceIoControl*, applications call simpler CyAPI methods such as [Open](#), [Close](#), and [XferData](#) to communicate with USB devices.

To use the library, you need to include the header file, **CyAPI.h**, in files that access the **CCyUSBDevice** class. In addition, the statically linked **CyAPI.lib** file must be linked to your project. Versions of the .lib file are available for use with Microsoft Visual Studio 2008 and Borland C++ Builder 6.0.

The library employs a **Device and EndPoints** use model. To use the library you must [create an instance](#) of the **CCyUSBDevice** class using the **new** keyword. A **CCyUSBDevice** object knows [how many USB devices](#) are attached to the **CyUsb.sys** driver and can be made to abstract any one of those devices at a time by using the [Open](#) method. An instance of **CCyUSBDevice** exposes several methods and data members that are device-specific, such as [DeviceName](#), [DevClass](#), [VendorID](#), [ProductID](#), and [SetAltIntfc](#).

When a **CCyUSBDevice** object is open to an attached USB device, its [endpoint](#) members provide an interface for performing data transfers to and from the device's endpoints. Endpoint-specific data members and methods such as [MaxPktSize](#), [Timeout](#), [bIn](#), [Reset](#) and [XferData](#) are only accessible through endpoint members of a **CCyUSBDevice** object.

In addition to its simplicity, the class library facilitates creation of sophisticated applications as well. The **CCyUSBDevice** [constructor](#) automatically registers the application for Windows USB Plug and Play event notification. This allows your application to support "hot plugging" of devices. Also, the asynchronous [BeginDataXfer](#)/[WaitForXfer](#)/[FinishDataXfer](#) methods allow queueing of multiple data transfer requests on a single endpoint, thus enabling data streaming from the application level.

2 New API

New API

[Top](#) [Previous](#) [Next](#)

bool XferData(PUCHAR buf, LONG &bufLen, CCyIsoPktInfo* pktInfos, **bool** pktMode);

XferData() method of CCyUSBEndPoint is overloaded such that it can be used for partial IN transfer.

if pktMode = true, partial data transfer is enabled or else calls the **bool** XferData(PUCHAR buf, LONG &len, CCyIsoPktInfo* pktInfos = NULL) where partial data is discarded.

This parameter has no effect on Out endpoint.

Code snippet:

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
char buf[12] = "hello world";
LONG length = 11;
if (USBDevice->BulkOutEndPt)
USBDevice->BulkOutEndPt->XferData(buf, length, NULL, false);
if (USBDevice->BulkInEndPt)
USBDevice->BulkInEndPt->XferData(buf, length, NULL, true);
```

3 Features Not Supported

Features Not Supported

[Top](#) [Previous](#) [Next](#)

The Following features are not supported by CyAPI.lib

1. SET ADDRESS Feature

The SET ADDRESS Request cannot be implemented through control endpoint.

2. SYNC FRAME

The SYNC FRAME Request cannot be implemented through Control Endpoint.

4 CCyBulkEndPoint

CCyBulkEndPoint

[Top](#) [Previous](#) [Next](#)

CCyBulkEndPoint Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

CCyBulkEndPoint is a subclass of the CCyUSBEndPoint abstract class. CCyBulkEndPoint exists to implement a bulk-specific [BeginDataXfer\(\)](#) function.

Normally, you should not need to construct any of your own instances of this class. Rather, when an instance of CyUSBDevice is created, instances of this class are automatically created for all bulk endpoints as members of that class. Two such members of CyUSBDevice are [BulkInEndPt](#) and [BulkOutEndPt](#).

Example

```
// Find bulk endpoints in the EndPoints[]
array
CCyBulkEndPoint *BulkInEpt = NULL;
CCyBulkEndPoint *BulkOutEpt = NULL;

CCyUSBDevice *USBDevice = new
CCyUSBDevice(Handle);
int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]-
>Address & 0x80;
    bool bBulk = (USBDevice->EndPoints
[i]->Attributes == 2);
    if (bBulk && bIn) BulkInEpt =
(CCyBulkEndPoint *) USBDevice->EndPoints
[i];
    if (bBulk && !bIn) BulkOutEpt =
(CCyBulkEndPoint *) USBDevice->EndPoints
[i];
}
```

4.1 BeginDataXfer()

BeginDataXfer()

[Top](#) [Previous](#) [Next](#)

PUCHAR CCyBulkEndPoint::BeginDataXfer(
PCHAR buf, LONG len, OVERLAPPED *ov)

[Previous](#) [Top](#) [Next](#)

Description

BeginDataXfer is an advanced method for performing asynchronous IO. This method sets-up all the parameters for a data transfer, initiates the transfer, and immediately returns, not waiting for the transfer to complete.

BeginDataXfer allocates a complex data structure and returns a pointer to that structure. [FinishDataXfer](#) de-allocates the structure. Therefore, it is imperative that each BeginDataXfer call have exactly one matching FinishDataXfer call.

You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

Example

```
// This example assumes that the device automatically sends back,
// over its bulk-IN endpoint, any bytes that were received over its
```

```

// bulk-OUT endpoint (commonly referred to as a loopback function)

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

OVERLAPPED outOvLap, inOvLap;
outOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_OUT");
inOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_IN");

char inBuf[128];
ZeroMemory(inBuf, 128);

char buffer[128];
LONG length = 128;

// Just to be cute, request the return data before initiating the loopback
UCHAR *inContext = USBDevice->BulkInEndPt->BeginDataXfer(inBuf, length,
&inOvLap);
UCHAR *outContext = USBDevice->BulkOutEndPt->BeginDataXfer(buffer, length,
&outOvLap);

USBDevice->BulkOutEndPt->WaitForXfer(&outOvLap, 100);
USBDevice->BulkInEndPt->WaitForXfer(&inOvLap, 100);

USBDevice->BulkOutEndPt->FinishDataXfer(buffer, length, &outOvLap, outContext);
USBDevice->BulkInEndPt->FinishDataXfer(inBuf, length, &inOvLap, inContext);

CloseHandle(outOvLap.hEvent);
CloseHandle(inOvLap.hEvent);

```

4.2 CCyBulkEndPoint()

CCyBulkEndPoint()

[Top](#) [Previous](#) [Next](#)
CCyBulkEndPoint::CCyBulkEndPoint (void)
[Previous](#) [Top](#) [Next](#)

Description

This is the default constructor for the CCyBulkEndPoint class.

The resulting instance has most of it's member variables initialized to zero. The two exceptions are [hDevice](#), which gets set to INVALID_HANDLE_VALUE and [TimeOut](#) which is set to 10,000 (10 seconds).

4.3 CCyBulkEndPoint()

CCyBulkEndPoint()

[Top](#) [Previous](#) [Next](#)

CCyBulkEndPoint::CCyBulkEndPoint (HANDLE
h, USB_ENDPOINT_DESCRIPTOR
pEndPointDescriptor)

[Previous](#) [Top](#) [Next](#)

Description

This constructor creates a legitimate CCyBulkEndPoint object through which bulk transactions can be performed on the endpoint.

The constructor is called by the library, itself, in the process of performing the [Open](#)() method of the CCyUSBDevice.

You should never need to invoke this constructor. Instead, you should use the CCyBulkEndPoint objects created for you by the CCyUSBDevice class and accessed via its [EndPoints](#), [BulkInEndPoint](#) and [BulkOutEndPoint](#) members.

5 CCyControlEndPoint

CCyControlEndPoint

[Top](#) [Previous](#) [Next](#)

CCyControlEndPoint Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

CCyControlEndPoint is a subclass of the CCyUSBEndPoint abstract class.

Instances of this class can be used to perform control transfers to the device.

Control transfers require 6 parameters that are not needed for bulk, isoc, or interrupt transfers. These are:

[Target](#)
[ReqType](#)
[Direction](#)
[ReqCode](#)
[Value](#)
[Index](#)

All USB devices have at least one Control endpoint, endpoint zero. Whenever an instance of CCyUSBDevice successfully performs its [Open](#)() function, an instance of CCyControlEndPoint called [ControlEndPoint](#) is created. Normally, you will use this [ControlEndPoint](#) member of CCyUSBDevice to perform all your Control endpoint data transfers.

Example

```

CCyUSBDevice *USBDevice = new
CCyUSBDevice(Handle);

// Just for typing efficiency

CCyControlEndPoint *ept = USBDevice-
>ControlEndPt;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);

```

5.1 BeginDataXfer()

BeginDataXfer()

[Top](#) [Previous](#) [Next](#)

PCHAR CCyControlEndPoint::BeginDataXfer
(PCHAR buf, LONG len, OVERLAPPED *ov)

[Previous](#) [Top](#) [Next](#)

Description

BeginDataXfer is an advanced method for performing asynchronous IO.

This method sets-up all the parameters for a data transfer, initiates the transfer, and immediately returns, not waiting for the transfer to complete.

BeginDataXfer allocates a complex data structure and returns a pointer to that structure. [FinishDataXfer](#) de-allocates the the structure. Therefore, it is imperative that each BeginDataXfer call have exactly one matching FinishDataXfer call. You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

Control transfers require 6 parameters that are not needed for bulk, isoc, or interrupt transfers. These are:

[Target](#)
[ReqType](#)
[Direction](#)

[ReqCode](#)
[Value](#)
[Index](#)

Be sure to set the value of these CCyControlEndPoint members before invoking the BeginDataXfer or [XferData](#) methods.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

OVERLAPPED OvLap;
OvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_CTL");

char buffer[128];
LONG length = 128;
ept->Target = TGT_DEVICE;
ept->ReqType = REQ_VENDOR;
ept->Direction = DIR_TO_DEVICE;
ept->ReqCode = 0x05;
ept->Value = 1;
ept->Index = 0;

PUCHAR Context = ept->BeginDataXfer(buffer, length, &OvLap);
ept->WaitForXfer(&OvLap, 100);
ept->FinishDataXfer(buffer, length, &OvLap, Context);

CloseHandle(OvLap.hEvent);
```

5.2 CCyControlEndPoint()

CCyControlEndPoint()

[Top](#) [Previous](#) [Next](#)

```
CCyControlEndPoint::CCyControlEndPoint(void
)
```

[Previous](#) [Top](#) [Next](#)

Description

This is the default constructor for the CCyControlEndPoint class.

It sets the class' data members to:

```

Target      = TGT_DEVICE
ReqType     = REQ_VENDOR
Direction   = DIR_TO_DEVICE
ReqCoe      = 0
Value       = 0
Index       = 0

```

5.3 CCyControlEndPoint()

CCyControlEndPoint()

[Top](#) [Previous](#) [Next](#)

CCyControlEndPoint::CCyControlEndPoint(
HANDLE h, USB_ENDPOINT_DESCRIPTOR
pEndPointDescriptor)

[Previous](#) [Top](#) [Next](#)

Description

This is the primary constructor for the CCyControlEndPoint class.

It sets the class' data members to:

```

Target      = TGT_DEVICE
ReqType     = REQ_VENDOR
Direction   = DIR_TO_DEVICE
ReqCoe      = 0
Value       = 0
Index       = 0

```

5.4 Direction

Direction

[Top](#) [Previous](#) [Next](#)

CTL_XFER_DIR_TYPE CCyControlEndPoint::
Direction

[Previous](#) [Top](#) [Next](#)

Description

Direction is one of the essential parameters for a Control transfer and a data member of the CCyControlEndPoint class.

Legitimate values for the Direction member are DIR_TO_DEVICE and DIR_FROM_DEVICE.

Unlike Bulk, Interrupt and ISOC endpoints, which are uni-directional (either IN or OUT), the Control endpoint is bi-directional. It can be used to send data to the device or read data from the device. So, the direction of the transaction is one of the fundamental parameters required for each Control transfer.

Direction is automatically set to DIR_TO_DEVICE by the [Write\(\)](#) method. It is automatically set to DIR_FROM_DEVICE by the [Read\(\)](#) method.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);
```

5.5 Index

Index

[Top](#) [Previous](#) [Next](#)

WORD CCyControlEndPoint::Index

[Previous](#) [Top](#) [Next](#)

Description

Index is one of the essential parameters for a Control transfer and a data member of the CCyControlEndPoint class.

Index values typically depend on the specific ReqCode that is being sent in the Control transfer.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;
```

```
ept->XferData(buf, buflen);
```

5.6 Read()

Read()

[Top](#) [Previous](#) [Next](#)

```
bool CCyControlEndPoint::Read( PCHAR buf,
LONG &len)
```

[Previous](#) [Top](#) [Next](#)

Description

Read() sets the CyControlEndPoint [Direction](#) member to DIR_FROM_DEVICE and then calls [CCyUSBEndPoint::XferData\(\)](#).

The **buf** parameter points to a memory buffer where the read bytes will be placed.

The **len** parameter tells how many bytes are to be read.

Returns **true** if the read operation was successful.

Passes-back the actual number of bytes transferred in the **len** parameter.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target = TGT_DEVICE;
ept->ReqType = REQ_VENDOR;
ept->ReqCode = 0x07;
ept->Value = 1;
ept->Index = 0;

char buf[512];
LONG bytesToRead = 64;

ept->Read(buf, bytesToRead);
```

5.7 ReqCode

ReqCode

[Top](#) [Previous](#) [Next](#)

```
UCHAR CCyControlEndPoint::ReqCode
```

[Previous](#) [Top](#) [Next](#)

Description

ReqCode is one of the essential parameters for a Control transfer and a data member of the CCyControlEndPoint class.

ReqCode values indicate, to the USB chip, a particular function or command that the chip should perform. They are usually documented by the USB chip manufacturer.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);
```

5.8 ReqType

ReqType

[Top](#) [Previous](#) [Next](#)

CTL_XFER_REQ_TYPE CCyControlEndPoint::
ReqType

[Previous](#) [Top](#) [Next](#)

Description

ReqType is one of the essential parameters for a Control transfer and a data member of the CCyControlEndPoint class.

Legitimate values for the ReqType member are **REQ_STD**, **REQ_CLASS** and **REQ_VENDOR**.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;
```

```

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);

```

5.9 Target

Target

[Top](#) [Previous](#) [Next](#)

CTL_XFER_TGT_TYPE CCyControlEndPoint::
Target

[Previous](#) [Top](#) [Next](#)

Description

Target is one of the essential parameters for a Control transfer and a data member of the CCyControlEndPoint class.

Legitimate values for the Target member are **TGT_DEVICE**, **TGT_INTFC**, **TGT_ENDPT** and **TGT_OTHER**.

Example

```

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);

```

5.10 Value

Value

[Top](#) [Previous](#) [Next](#)

WORD CCyControlEndPoint::Value

[Previous](#) [Top](#) [Next](#)

Description

Value is one of the essential parameters for a Control transfer and a data member of the CCyControlEndPoint class.

Values typically depend on the specific ReqCode that is being sent in the Control transfer.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);
```

5.11 Write()

Write()

[Top](#) [Previous](#) [Next](#)

bool CCyControlEndPoint::Write(PCHAR buf, LONG &len)

[Previous](#) [Top](#) [Next](#)

Description

Write() sets the CyControlEndPoint [Direction](#) member to DIR_TO_DEVICE and then calls [CCyUSBEndPoint::XferData\(\)](#).

The **buf** parameter points to a memory buffer where the read bytes will be placed.

The **len** parameter tells how many bytes are to be read.

Returns **true** if the write operation was successful.

Passes-back the actual number of bytes transferred in the **len** parameter.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPt;

ept->Target    = TGT_DEVICE;
ept->ReqType   = REQ_VENDOR;
ept->ReqCode   = 0x07;
ept->Value     = 1;
ept->Index     = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG bytesToSend = 128;

ept->Write(buf, bytesToSend);
```

6 CCyInterruptEndPoint

CCyInterruptEndPoint

[Top](#) [Previous](#) [Next](#)

CCyInterruptEndPoint Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

CCyInterruptEndPoint is a subclass of the [CCyUSBEndPoint](#) abstract class.

CCyInterruptEndPoint exists to implement a interrupt-specific [BeginDataXfer\(\)](#) function.

Normally, you should not need to construct any of your own instances of this class. Rather, when an instance of [CyUSBDevice](#) is created, instances of this class are automatically created as members of that class. Two such members of CyUSBDevice are [InterruptInEndPt](#) and [InterruptOutEndPt](#).

Example

```
// Find interrupt endpoints in the EndPoints[] array
CCyInterruptEndPoint *IntInEpt = NULL;
CCyInterruptEndPoint *IntOutEpt = NULL;
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
```

```

int eptCount = USBDevice->EndPointCount();
for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->Endpoints[i]->Address & 0x80;
    bool bInt = (USBDevice->Endpoints[i]->Attributes == 3);

    if (bInt && bIn) IntInEpt = (CCyInterruptEndPoint *) USBDevice->Endpoints[i];
    if (bInt && !bIn) IntOutEpt = (CCyInterruptEndPoint *) USBDevice->Endpoints[i];
}

```

6.1 BeginDataXfer()

BeginDataXfer()

[Top](#) [Previous](#) [Next](#)

PUCHAR CCyInterruptEndPoint::
BeginDataXfer(PCHAR buf, LONG len,
OVERLAPPED *ov)

[Previous](#) [Top](#) [Next](#)

Description

BeginDataXfer is an advanced method for performing asynchronous IO. This method sets-up all the parameters for a data transfer, initiates the transfer, and immediately returns, not waiting for the transfer to complete.

BeginDataXfer allocates a complex data structure and returns a pointer to that structure. [FinishDataXfer](#) de-allocates the structure. Therefore, it is imperative that each BeginDataXfer call have exactly one matching FinishDataXfer call.

You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

Example

```

// This example assumes that the device automatically sends back,
// over its bulk-IN endpoint, any bytes that were received over its
// bulk-OUT endpoint (commonly referred to as a loopback function)

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

OVERLAPPED outOvLap, inOvLap;
outOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_OUT");
inOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_IN");

char inBuf[128];
ZeroMemory(inBuf, 128);

char buffer[128];
LONG length = 128;

// Just to be cute, request the return data before initiating the loopback

```

```

    UCHAR *inContext = USBDevice->BulkInEndPt->BeginDataXfer(inBuf, length,
&inOvLap);
    UCHAR *outContext = USBDevice->BulkOutEndPt->BeginDataXfer(buffer, length,
&outOvLap);

    USBDevice->BulkOutEndPt->WaitForXfer(&outOvLap,100);
    USBDevice->BulkInEndPt->WaitForXfer(&inOvLap,100);

    USBDevice->BulkOutEndPt->FinishDataXfer(buffer, length, &outOvLap,outContext);
    USBDevice->BulkInEndPt->FinishDataXfer(inBuf, length, &inOvLap,inContext);

    CloseHandle(outOvLap.hEvent);
    CloseHandle(inOvLap.hEvent);

```

6.2 CCyInterruptEndPoint()

CCyInterruptEndPoint()

[Top](#) [Previous](#) [Next](#)

CCyInterruptEndPoint::CCyInterruptEndPoint (void)

[Previous](#) [Top](#) [Next](#)

Description

This is the default constructor for the CCyInterruptEndPoint class.

The resulting instance has most of it's member variables initialized to zero. The two exceptions are [hDevice](#), which gets set to INVALID_HANDLE_VALUE and [TimeOut](#) which is set to 10,000 (10 seconds).

6.3 CCyInterruptEndPoint()

CCyInterruptEndPoint()

[Top](#) [Previous](#) [Next](#)

CCyInterruptEndPoint::CCyInterruptEndPoint(HANDLE h,PUSB_ENDPOINT_DESCRIPTOR pEndPtDescriptor)

[Previous](#) [Top](#) [Next](#)

Description

This constructor creates a legitimate CCyInterruptEndPoint object through which interrupt transactions can be performed on the endpoint.

The constructor may be called by the library, itself, in the process of performing the [Open\(\)](#) method of the CCyUSBDevice.

You should never need to invoke this constructor. Instead, you should use the CCyInterruptEndPoint objects created for you by the CCyUSBDevice class and accessed via its [EndPoints,InterruptInEndPt](#) and [InterruptOutEndPt](#) members.

7 CCylsocEndPoint

CCylsocEndPoint

[Top](#) [Previous](#) [Next](#)

CCylsocEndPoint Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

CCylsocEndPoint is a subclass of the [CCyUSBEndPoint](#) abstract class.

CCylsocEndPoint exists to implement a isoc-specific [BeginDataXfer\(\)](#) function.

Normally, you should not need to construct any of your own instances of this class. Rather, when an instance of [CyUSBDevice](#) is created, instances of this class are automatically created as members of that class. Two such members of CyUSBDevice are [IsocInEndPt](#) and [IsocOutEndPt](#).

NOTE: For ISOC transfers, the buffer length and the endpoint's transfers size (see [SetXferSize](#)) must be a multiple of 8 times the endpoint's [MaxPktSize](#).

Example

```
// Find isoc endpoints in the EndPoints[] array
CCylsocEndPoint *IsocInEpt = NULL;
CCylsocEndPoint *IsocOutEpt = NULL;

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bInt = (USBDevice->EndPoints[i]->Attributes == 1);
    if (bInt && bIn) IsocInEpt = (CCylsocEndPoint *) USBDevice->EndPoints[i];
    if (bInt && !bIn) IsocOutEpt = (CCylsocEndPoint *) USBDevice->EndPoints[i];
}
```

7.1 BeginDataXfer()

BeginDataXfer()

[Top](#) [Previous](#) [Next](#)

PUCHAR CCylsocEndPoint::BeginDataXfer (
PCHAR buf, **LONG** len, **OVERLAPPED** *ov)

[Previous](#) [Top](#) [Next](#)

Description

BeginDataXfer is an advanced method for performing asynchronous IO. This method sets-up all the parameters for a data transfer, initiates the transfer, and immediately returns, not waiting for the transfer to complete.

BeginDataXfer allocates a complex data structure and returns a pointer to that structure. [FinishDataXfer](#) de-allocates the structure. Therefore, it is imperative that each BeginDataXfer call have exactly one matching FinishDataXfer call.

You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

NOTE: For ISOC transfers, the buffer length and the endpoint's transfers size (see [SetXferSize](#)) must be a multiple of 8 times the endpoint's [MaxPktSize](#).

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(hWnd);
CCyIsocEndPoint *IsoIn = USBDevice->IsocInEndPt;

if (IsoIn) {

    int pkts = 16;
    LONG bufSize = IsoIn->MaxPktSize * pkts;

    PCHAR context;
    OVERLAPPED inOvLap;
    PCHAR buffer = new UCHAR[bufSize];
    CCyIsoPktInfo *isoPktInfos = new CCyIsoPktInfo[pkts];

    IsoIn->SetXferSize(bufSize);

    inOvLap.hEvent = CreateEvent(NULL, false, false, NULL);

    // Begin the data transfer
    context = IsoIn->BeginDataXfer(buffer, bufSize, &inOvLap);

    // Wait for the xfer to complete.
    if (!IsoIn->WaitForXfer(&inOvLap, 1500)) {
        IsoIn->Abort();
        // Wait for the stalled command to complete
        WaitForSingleObject(inOvLap.hEvent, INFINITE);
    }

    int complete = 0;
    int partial = 0;

    // Must always call FinishDataXfer to release memory of contexts[i]
    if (IsoIn->FinishDataXfer(buffer, bufSize, &inOvLap, context, isoPktInfos)) {

        for (int i=0; i< pkts; i++)
```



```

        if (isoPktInfos[i].Status)
            partial++;
        else
            complete++;

    } else
        partial++;

    delete buffer;
    delete [] isoPktInfos;
}

```

7.2 CCylsocEndPoint()

CCylsocEndPoint()

[Top](#) [Previous](#) [Next](#)
CCylsocEndPoint::CCylsocEndPoint (void)
[Previous](#) [Top](#) [Next](#)

Description

This is the default constructor for the CCylsocEndPoint class.

The resulting instance has most of it's member variables initialized to zero. The two exceptions are [hDevice](#), which gets set to INVALID_HANDLE_VALUE and [TimeOut](#) which is set to 10,000 (10 seconds).

7.3 CCylsocEndPoint()

CCylsocEndPoint()

[Top](#) [Previous](#) [Next](#)
**CCylsocEndPoint::CCylsocEndPoint(HANDLE
h, USB_ENDPOINT_DESCRIPTOR
pEndPointDescriptor)**
[Previous](#) [Top](#) [Next](#)

Description

This constructor creates a legitimate CCylsocEndPoint object through which isochronous transactions can be performed on the endpoint.

The constructor is called by the library, itself, in the process of performing the [Open\(\)](#) method of the CCyUSBDevice.

You should never need to invoke this constructor. Instead, you should use the CCylsocEndPoint objects created for you by the CCyUSBDevice class and accessed via its [EndPoints](#), [IsocInEndPt](#) and [IsocOutEndPt](#) members.

7.4 CreatePktInfos()

CreatePktInfos()

[Top](#) [Previous](#) [Next](#)

**CCyIsoPktInfo* CCyIsocEndPoint::
CreatePktInfos(LONG bufLen, int &packets)**

[Previous](#) [Top](#) [Next](#)

Description

The **CreatePktInfos** method is provided for convenience.

It creates an array of [CCyIsoPktInfo](#) objects to be used in calls to [XferData](#) and [FinishDataXfer](#) for Isoc endpoints.

CreatePktInfos calculates the number of isoc packets that the driver will use to transfer a data buffer of **bufLen** bytes. This number is returned in the **packets** parameter.

CreatePktInfos also dynamically constructs an array of [CCyIsoPktInfo](#) objects and returns a pointer to the first element of that array. There are **packets** elements in the array.

After using the array of CCyPktInfo objects you must delete the array of objects yourself by calling **delete []**.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice();
CCyIsocEndPoint *IsoIn = USBDevice->IsocInEndPt;

if (IsoIn) {

    LONG    bufSize = 4096;
    UCHAR buffer = new UCHAR[bufSize];

    CCyIsoPktInfo *isoPktInfos;
    int          pkts;

    // Allocate the IsoPktInfo objects, and find-out how many were allocated
    isoPktInfos = IsoIn->CreatePktInfos(bufSize, pkts);

    if (IsoIn->XferData(buffer, bufSize, isoPktInfos)) {

        LONG recvdBytes = 0;

        for (int i=0; i<pkts; i++)
            if (isoPktInfos[i].Status == 0)
                recvdBytes += isoPktInfos[i].Length;

    }
}
```

```
        delete [] buffer;
        delete [] isoPktInfos;

    }
```

8 CCyIsoPktInfo

CCyIsoPktInfo

[Top](#) [Previous](#) [Next](#)

CCyIsoPktInfo

[Previous](#) [Top](#) [Next](#)

The **CCyIsoPktInfo** class is defined as:

```
class CCyIsoPktInfo {
public:
    LONG Status;
    LONG Length;
};
```

When an Isoc transfer is performed, the data buffer passed to [XferData](#) or [BeginDataXfer](#) is logically partitioned, by the driver, into multiple packets of data. The driver returns status and length information for each of those packets.

The [XferData](#) and [FinishDataXfer](#) methods of [CCyUSBEndPoint](#) accept an optional parameter that is a pointer to an array of **CCyIsoPktInfo** objects. If this parameter is not NULL, the array will be filled with the packet status and length information returned by the driver.

If the value returned in the **Status** field is zero (USB_STATUS_SUCCESS) all the data in the packet is valid. Other non-zero values for the Status field can be found in the DDK include file, USBDI.H.

The value returned in the **Length** field indicates the number of bytes transferred in the packet. In ideal conditions, this number will be bufferLength / numPackets (which is the maximum capacity of each packet). However, fewer bytes could be transferred.

An array of **CCyIsoPktInfo** objects can be easily created by invoking the [CCyUSBIsocEndPoint::CreatePktInfos](#) method.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice();
CCyIsocEndPoint *IsoIn = USBDevice->IsocInEndPt;

if (IsoIn) {

    LONG    bufSize = 4096;
    UCHAR  buffer = new UCHAR[bufSize];

    CCyIsoPktInfo *isoPktInfos;
```

```

    int          pkts;

    // Allocate the IsoPktInfo objects, and find-out how many were allocated
    isoPktInfos = IsoIn->CreatePktInfos(bufSize, pkts);

    if (IsoIn->XferData(buffer, bufSize, isoPktInfos)) {

        LONG recvdBytes = 0;

        for (int i=0; i<pkts; i++)
            if (isoPktInfos[i].Status == 0)
                recvdBytes += isoPktInfos[i].Length;

    }

    delete [] buffer;
    delete [] isoPktInfos;

}

```

9 CCyUSBDevice

CCyUSBDevice

[Top](#) [Previous](#) [Next](#)

CCyUSBDevice Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

The CCyUSBDevice class is the primary entry point into the library. All the functionality of the library should be accessed via an instance of CCyUSBDevice.

Create an instance of CCyUSBDevice using the **new** keyword.

An instance of CCyUSBDevice is aware of all the USB devices that are attached to the USB driver and can selectively communicate with any ONE of them by using the [Open\(\)](#) method.

Example

```

// Look for a device having VID = 0547, PID = 1002

USBDevice = new CCyUSBDevice(Handle); // Create an instance of CCyUSBDevice

int  devices = USBDevice->DeviceCount();

int  vID, pID;
int  d = 0;

```

```

do {
    USBDevice->Open(d);    // Open automatically calls Close() if necessary
    vID = USBDevice->VendorID;
    pID = USBDevice->ProductID
    d++;
} while ((d < devices) && (vID != 0x0547) && (pID != 0x1002));

```

9.1 AltIntfc()

AltIntfc()

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::AltIntfc(void)

[Previous](#) [Top](#) [Next](#)

Description

This function returns the current alternate interface setting for the device.

A return value of 255 (0xFF) indicates that the driver failed to return the current alternate interface setting.

Call [SetAltIntfc\(\)](#) to select a different alternate interface (changing the AltSetting).

Call [AltIntfcCount\(\)](#) to find-out how many alternate interfaces are exposed by the device.

9.2 AltIntfcCount()

AltIntfcCount()

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::AltIntfcCount(void)

[Previous](#) [Top](#) [Next](#)

Description

This function returns the number of alternate interfaces exposed by the device.

The primary interface (AltSetting == 0) is not counted as an alternate interface.

Example

A return value of 2 means that there are 2 alternate interfaces, in addition to the primary interface. Legitimate parameter values for calls to [SetAltIntfc\(\)](#) would then be 0, 1 and 2.

9.3 bHighSpeed

bHighSpeed

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::bHighSpeed

[Previous](#) [Top](#) [Next](#)

Description

bHighSpeed indicates whether or not the device is a high speed USB device.

If the USB device represented is a high speed device, **bHighSpeed** will be **true**. Otherwise, **bHighSpeed** will be **false**.

This property is only valid on systems running Windows 2K SP4 (and later) or WindowsXP. On earlier versions of Windows, a high speed device will not be detected as such and **bHighSpeed** will incorrectly have a value of **false**.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

if (USBDevice->bHighSpeed) {
    .
    // Do something
    .
}
```

9.4 BcdDevice

BcdDevice
[Top](#) [Previous](#) [Next](#)
USHORT CCyUSBDevice::BcdDevice
[Previous](#) [Top](#) [Next](#)
Description

This data member contains the value of the **bcdDevice** member from the device's USB descriptor structure.

9.5 BcdUSB

BcdUSB
[Top](#) [Previous](#) [Next](#)
USHORT CCyUSBDevice::BcdUSB
[Previous](#) [Top](#) [Next](#)
Description

This data member contains the value of the **bcdUSB** member from the device's USB descriptor structure.

9.6 BulkInEndPt

BulkInEndPt
[Top](#) [Previous](#) [Next](#)

CCyBulkEndPoint* CCyUSBDevice::BulkInEndPt

[Previous](#) [Top](#) [Next](#)

Description

BulkInEndPt is a pointer to an object representing the first BULK IN endpoint enumerated for the selected interface.

The selected interface might expose additional BULK IN endpoints. To discern this, one would need to traverse the [Endpoints](#) array, checking the [Attributes](#) and [Address](#) members of each [CCyUSBEndPoint](#) object referenced in the array.

If no BULK IN endpoints were enumerated by the device, BulkInEndPt will be set to NULL.

Example

```
// Find a second bulk IN endpoint in the EndPoints[] array

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyBulkEndPoint *BulkIn2 = NULL;

int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->bIn;
    bool bBulk = (USBDevice->EndPoints[i]->Attributes == 2);

    if (bBulk && bIn) BulkIn2 = (CCyBulkEndPoint *) USBDevice->EndPoints[i];
    if (BulkIn2 == USBDevice->BulkInEndPt) BulkIn2 = NULL;
}
```

9.7 BulkOutEndPt

BulkOutEndPt

[Top](#) [Previous](#) [Next](#)

CCyBulkEndPoint* CCyUSBDevice::BulkOutEndPt

[Previous](#) [Top](#) [Next](#)

Description

BulkOutEndPt is a pointer to an object representing the first BULK OUT endpoint enumerated for the selected interface.

The selected interface might expose additional BULK OUT endpoints. To discern this, one would need to traverse the [Endpoints](#) array, checking the [Attributes](#) and [Address](#) members of each [CCyUSBEndPoint](#) object referenced in the array.

If no BULK OUT endpoints were enumerated by the device, BulkInEndPt will be set to NULL.

Example

```
// Find a second bulk OUT endpoint in the EndPoints[] array
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyBulkEndPoint *BulkOut2 = NULL;

int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bBulk = (USBDevice->EndPoints[i]->Attributes == 2);

    if (bBulk && !bIn) BulkOut2 = (CCyBulkEndPoint *) USBDevice->EndPoints[i];
    if (BulkOut2 == USBDevice->BulkOutEndPt) BulkOut2 = NULL;
}
```

9.8 CCyUSBDevice()**CCyUSBDevice()**[Top](#) [Previous](#) [Next](#)

CCyUSBDevice::CCyUSBDevice(HANDLE hnd =
NULL, GUID guid = CYUSBDRV_GUID)

[Previous](#) [Top](#) [Next](#)**Description**

This is the constructor for the CCyUSBDevice class.

It registers the window of *hnd* to receive USB Plug and Play messages when devices are connected or disconnected to/from the driver.

The object created serves as the programming interface to the driver whose GUID is passed in the *guid* parameter.

The constructor initializes the class members and then calls the [Open](#)(0) method to open the first device that is attached to the driver.

Parameters***hnd***

hnd is a handle to the application's main window (the window whose WndProc function will process USB PnP events).

If you are building a console application or don't want your window to receive PnP events, you may omit the *hnd* parameter.

guid

guid is the GUID defined in the [Strings] section of the CyUsb.inf file (or your own named copy). If this parameter is omitted, *guid* defaults to CYUSBDRV_GUID.

If you don't want to register for PnP events, but you do want to pass your own driver GUID to the constructor, you will need to pass NULL as the *hnd* parameter.

Example 1

```
void __fastcall TMainForm::FormCreate(TObject *Sender)
{
    USBDevice = new CCyUSBDevice(Handle);
    CurrentEndPt = USBDevice->ControlEndPt;
}

// Overload MainForm's WndProc method to watch for PnP messages
// Requires #include <dbt.h>
void __fastcall TMainForm::WndProc(TMessage &Message)
{
    if (Message.Msg == WM_DEVICECHANGE) {

        // Tracks DBT_DEVICEARRIVAL followed by DBT_DEVNODES_CHANGED
        if (Message.WParam == DBT_DEVICEARRIVAL) {
            bPnP_Arrival = true;
            bPnP_DevNodeChange = false;
        }

        // Tracks DBT_DEVNODES_CHANGED followed by DBT_DEVICEREMOVECOMPLETE
        if (Message.WParam == DBT_DEVNODES_CHANGED) {
            bPnP_DevNodeChange = true;
            bPnP_Removal = false;
        }

        if (Message.WParam == DBT_DEVICEREMOVECOMPLETE) {
            bPnP_Removal = true;

            PDEV_BROADCAST_HDR bcastHdr = (PDEV_BROADCAST_HDR) Message.LParam;
            if (bcastHdr->dbch_devicetype == DBT_DEVTYP_HANDLE) {

                PDEV_BROADCAST_HANDLE pDev = (PDEV_BROADCAST_HANDLE) Message.LParam;
                if (pDev->dbch_handle == USBDevice->DeviceHandle())
                    USBDevice->Close();
            }
        }

        // If DBT_DEVNODES_CHANGED followed by DBT_DEVICEREMOVECOMPLETE
        if (bPnP_Removal && bPnP_DevNodeChange) {
            Sleep(10);
            DisplayDevices();
        }
    }
}
```

```

        bPnP_Removal = false;
        bPnP_DevNodeChange = false;
    }

    // If DBT_DEVICEARRIVAL followed by DBT_DEVNODES_CHANGED
    if (bPnP_DevNodeChange && bPnP_Arrival) {
        DisplayDevices();
        bPnP_Arrival = false;
        bPnP_DevNodeChange = false;
    }

}

TForm::WndProc(Message);
}

```

Example 2

In the *CyUSB.inf* file :

[Strings]

CyUSB.GUID="{BE18AA60-7F6A-11d4-97DD-00010229B959}"

In some application source (.cpp) file:

```

GUID guid = StringToGUID("{BE18AA60-7F6A-11d4-97DD-00010229B959}");
CCyUSBDevice *USBDevice = new CCyUSBDevice(NULL, guid); // Does not register for
PnP events

```

9.9 ~CCyUSBDevice()

~CCyUSBDevice()

[Top](#) [Previous](#) [Next](#)

CCyUSBDevice::~~CCyUSBDevice(void)

[Previous](#) [Top](#) [Next](#)

Description

This is the destructor for the CCyUSBDevice class. It calls the [Close\(\)](#) method in order to properly close any open handle to the driver and to deallocate dynamically allocated members of the class.

9.10 Close()

Close()

[Top](#) [Previous](#) [Next](#)

void CCyUSBDevice:: Close(void)

[Previous](#) [Top](#) [Next](#)

Description

The Close method closes the handle to the CyUSB driver, if one is open.

Dynamically allocated members of the CCyUSBDevice class are de-allocated. And, all "shortcut" pointers to elements of the [EndPoints](#) array (ControlEndPt, IsoIn/OutEndPt, BulkIn/OutEndPt, InterruptIn/OutEndPt) are reset to NULL.

Close() is called automatically by the [~CCyUSBDevice](#)() destructor. It is also called automatically by the [Open](#)() method, if a handle to the driver is already open.

Therefore, it is rare that you would ever need to call Close() explicitly (though doing so would not cause any problems).

9.11 Config()

Config()

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBDevice::Config(void)**[Previous](#) [Top](#) [Next](#)

Description

This method returns the current configuration index for the device.

Most devices only expose a single configuration at one time. So, this method should almost always return zero.

9.12 ConfigAttrib

ConfigAttrib

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBDevice::ConfigAttrib**[Previous](#) [Top](#) [Next](#)

Description

This data member contains the value of the **bmAttributes** field from the device's current configuration descriptor.

9.13 ConfigCount()

ConfigCount()

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBDevice::ConfigCount(void)**[Previous](#) [Top](#) [Next](#)

Description

This function returns the number of configurations reported by the device in the **bNumConfigurations** field of its device descriptor.

9.14 ConfigValue

ConfigValue

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::ConfigValue

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the value of the **bConfigurationValue** field from the device's current configuration descriptor.

9.15 ControlEndPoint

ControlEndPoint

[Top](#) [Previous](#) [Next](#)

CCyControlEndPoint* CCyUSBDevice::ControlEndPoint

[Previous](#) [Top](#) [Next](#)

Description

ControlEndPoint points to an object representing the primary Control endpoint, endpoint 0.

ControlEndPoint should always be the same value as [EndPoints](#)[0].

Before calling the [XferData](#)() method for ControlEndPoint, you should set the object's control properties.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Just for typing efficiency
CCyControlEndPoint *ept = USBDevice->ControlEndPoint;

ept->Target      = TGT_DEVICE;
ept->ReqType     = REQ_VENDOR;
ept->Direction   = DIR_TO_DEVICE;
ept->ReqCode     = 0x05;
ept->Value       = 1;
ept->Index       = 0;

char buf[512];
ZeroMemory(buf, 512);
LONG buflen = 512;

ept->XferData(buf, buflen);
```

9.16 DevClass

DevClass

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::DevClass[Previous](#) [Top](#) [Next](#)**Description**

This data member contains the value of the **bDeviceClass** field from the open device's Device Descriptor.

9.17 DeviceCount()**DeviceCount()**[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBDevice::DeviceCount(void)**[Previous](#) [Top](#) [Next](#)**Description**

Returns the number of devices attached to the USB driver.

The value returned can be used to discern legitimate parameters for the [Open\(\)](#) method.

Example

```
// Look for a device having VID = 0547, PID = 1002

USBDevice = new CCyUSBDevice(Handle);
int devices = USBDevice->DeviceCount( );

int vID, pID;

int d = 0;
do
{
    USBDevice->Open(d);    // Open automatically calls Close( ) if necessary
    vID = USBDevice->VendorID;
    pID = USBDevice->ProductID;
    d++;
} while ((d < devices) && (vID != 0x0547) && (pID != 0x1002));
```

9.18 DeviceHandle()**DeviceHandle()**[Top](#) [Previous](#) [Next](#)**HANDLE CCyUSBDevice::DeviceHandle(void)**[Previous](#) [Top](#) [Next](#)**Description**

Returns the handle to the driver if the CCyUSBDevice is opened to a connected USB device. If no device is currently open, DeviceHandle() returns INVALID_HANDLE_VALUE.

9.19 DeviceName

DeviceName

[Top](#) [Previous](#) [Next](#)

```
char CCyUSBDevice::DeviceName
[USB_STRING_MAXLEN]
```

[Previous](#) [Top](#) [Next](#)

Description

DeviceName is an array of characters containing the product string indicated by the device descriptor's iProduct field.

9.20 DevProtocol

DevProtocol

[Top](#) [Previous](#) [Next](#)

```
UCHAR CCyUSBDevice::DevProtocol
```

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the value of the **bDeviceProtocol** field from the open device's Device Descriptor.

9.21 DevSubClass

DevSubClass

[Top](#) [Previous](#) [Next](#)

```
UCHAR CCyUSBDevice::DevSubClass
```

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the value of the **bDeviceSubClass** field from the open device's Device Descriptor.

9.22 DriverGUID()

DriverGUID()

[Top](#) [Previous](#) [Next](#)

```
GUID CCyUSBDevice::DriverGUID(void)
```

[Previous](#) [Top](#) [Next](#)

Description

Returns the Global Unique Identifier of the USB driver attached to the CCyUSBDevice.

See also: [CCyUSBDevice\(\)](#)

9.23 DriverVersion

DriverVersion

[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBDevice::DriverVersion[Previous](#) [Top](#) [Next](#)**Description**

DriverVersion contains 4 bytes representing the version of the driver that is attached to the CCyUSBDevice.

9.24 EndPointCount()**EndPointCount()**[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBDevice::EndPointCount(void)**[Previous](#) [Top](#) [Next](#)**Description**

Returns the number of endpoints exposed by the currently selected interface (or Alternate Interface) plus 1.

The default Control endpoint (endpoint 0) is included in the count.

Example

```
// Find bulk endpoints in the EndPoints[] array
CCyBulkEndPoint *BulkInEpt = NULL;
CCyBulkEndPoint *BulkOutEpt = NULL;

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
int eptCount = USBDevice->EndPointCount();

// Skip EndPoints[0], which we know is the control endpoint
for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bBulk = (USBDevice->EndPoints[i]->Attributes == 2);

    if (bBulk && bIn) BulkInEpt = (CCyBulkEndPoint *) USBDevice->EndPoints[i];
    if (bBulk && !bIn) BulkOutEpt = (CCyBulkEndPoint *) USBDevice->EndPoints[i];
}
```

9.25 EndPointOf()**EndPointOf()**[Top](#) [Previous](#) [Next](#)**CCyUSBEndPoint* CCyUSBDevice::EndPointOf
(UCHAR addr)**[Previous](#) [Top](#) [Next](#)**Description**

Returns a pointer to the endpoint object in the EndPoints array whose [Address](#) property is equal to **addr**.

Returns NULL If no endpoint with Address = **addr** is found.

Example

```
UCHAR eptAddr = 0x82;
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
CCyUSBEndPoint *EndPt = USBDevice->EndPointOf(eptAddr);
if (EndPt) EndPt->Reset( );
```

9.26 EndPoints

EndPoints

[Top](#) [Previous](#) [Next](#)

CCyUSBEndPoint**CCyUSBDevice::EndPoints

[Previous](#) [Top](#) [Next](#)

Description

EndPoints is a list of up to MAX_ENDPTS (16) pointers to endpoint objects.

The objects pointed to represent all the USB endpoints reported for the current USB interface/Alt interface of the device.

EndPoints[0] always contains a pointer to a [CCyControlEndPoint](#) representing the primary Control Endpoint (endpoint 0) of the device.

Unused entries in EndPoints are set to NULL.

Use [EndPointCount](#)() to find-out how many entries in EndPoints are valid.

EndPoints is re-initialized each time [Open](#)() or [SetAltIntfc](#)() is called.

NOTE:

[CCyUSBEndPoint](#) is an abstract class, having a pure virtual function [BeginDataXfer](#)().

The objects pointed to by EndPoints** are, therefore, actually instances of [CCyControlEndPoint](#), [CCyBulkEndPoint](#), [CCylsocEndPoint](#) or [CCyInterruptEndPoint](#).

Calling EndPoints[n]->XferData() automatically results in the correct XferData() function being invoked.

Example

```
// Count the bulk-in endpoints
```

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
```



```
int epCnt = USBDevice->EndPointCount();

bool bBulk, bIn;
int blkInCnt = 0;

for (int e=0; e<epCnt; e++) {
    bBulk = USBDevice->EndPoints[e]->Attributes == 2;
    bIn    = USBDevice->EndPoints[e]->Address & 0x80;

    if (bBulk && bIn) blkInCnt++;
}
```

9.27 FriendlyName

FriendlyName

[Top](#) [Previous](#) [Next](#)

```
char CCyUSBDevice::FriendlyName
[USB_STRING_MAXLEN]
```

[Previous](#) [Top](#) [Next](#)

Description

FriendlyName is an array of characters containing the device description string for the open device which was provided by the driver's .inf file.

9.28 GetDeviceDescriptor()

GetDeviceDescriptor()

[Top](#) [Previous](#) [Next](#)

```
void CCyUSBDevice::GetDeviceDescriptor(
PUSB_DEVICE_DESCRIPTOR descr)
```

[Previous](#) [Top](#) [Next](#)

Description

This function copies the current device's device descriptor into the memory pointed to by **descr** .

9.29 GetConfigDescriptor()

GetConfigDescriptor()

[Top](#) [Previous](#) [Next](#)

```
void CCyUSBDevice::GetConfigDescriptor(
PUSB_CONFIGURATION_DESCRIPTOR descr)
```

[Previous](#) [Top](#) [Next](#)

Description

This function copies the current device's configuration descriptor into the memory pointed to by **descr**.

9.30 GetIntfcDescriptor()

GetIntfcDescriptor()

[Top](#) [Previous](#) [Next](#)

```
void CCyUSBDevice::GetIntfcDescriptor(
PUSB_INTERFACE_DESCRIPTOR descr)
```

[Previous](#) [Top](#) [Next](#)

Description

This function copies the currently selected interface descriptor into the memory pointed to by **descr** .

9.31 GetUSBConfig()

GetUSBConfig()

[Top](#) [Previous](#) [Next](#)

```
CCyUSBConfig CCyUSBDevice::GetUSBConfig
(int index)
```

[Previous](#) [Top](#) [Next](#)

Description

This function returns a copy of the [CCyUSBConfig](#) object indicated by **index** .

The **index** parameter must be less than [CCyUSBDevice::ConfigCount](#)().

Example

```
// This code lists all the endpoints reported
//     for all the interfaces reported
//     for all the configurations reported
//     by the device.

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

String s;

for (int c=0; c<USBDevice->ConfigCount(); c++) {
    CCyUSBConfig cfg = USBDevice->GetUSBConfig(c);

    s.printf("bLength: 0x%x",cfg.bLength); EZOutputMemo->Lines->Add(s);
    s.printf("bDescriptorType: %d",cfg.bDescriptorType); EZOutputMemo->Lines->Add
(s);
    s.printf("wTotalLength: %d (0x%x)",cfg.wTotalLength,cfg.wTotalLength);
EZOutputMemo->Lines->Add(s);
    s.printf("bNumInterfaces: %d",cfg.bNumInterfaces); EZOutputMemo->Lines->Add
(s);
    s.printf("bConfigurationValue: %d",cfg.bConfigurationValue); EZOutputMemo-
>Lines->Add(s);
    s.printf("iConfiguration: %d",cfg.iConfiguration); EZOutputMemo->Lines->Add
(s);
    s.printf("bmAttributes: 0x%x",cfg.bmAttributes); EZOutputMemo->Lines->Add(s);
    s.printf("MaxPower: %d",cfg.MaxPower); EZOutputMemo->Lines->Add(s);
```

```

EZOutputMemo->Lines->Add("*****");

for (int i=0; i<cfg.AltInterfaces; i++) {
    CCyUSBInterface *ifc = cfg.Interfaces[i];
    EZOutputMemo->Lines->Add("Interface Descriptor:" + String(i+1));
    EZOutputMemo->Lines->Add("-----");
    s.sprintf("bLength: 0x%x", ifc->bLength); EZOutputMemo->Lines->Add(s);
    s.sprintf("bDescriptorType: %d", ifc->bDescriptorType); EZOutputMemo->Lines-
>Add(s);
    s.sprintf("bInterfaceNumber: %d", ifc->bInterfaceNumber); EZOutputMemo->Lines-
>Add(s);
    s.sprintf("bAlternateSetting: %d", ifc->bAlternateSetting); EZOutputMemo-
>Lines->Add(s);
    s.sprintf("bNumEndpoints: %d", ifc->bNumEndpoints); EZOutputMemo->Lines->Add
(s);
    s.sprintf("bInterfaceClass: %d", ifc->bInterfaceClass); EZOutputMemo->Lines-
>Add(s);

    for (int e=0; e<ifc->bNumEndpoints; e++) {
        CCyUSBEndPoint *ept = ifc->EndPoints[e+1];
        EZOutputMemo->Lines->Add("EndPoint Descriptor: " + String(e+1));
        EZOutputMemo->Lines->Add("-----");
        s.sprintf("bLength: 0x%x", ept->DscLen); EZOutputMemo->Lines->Add(s);
        s.sprintf("bDescriptorType: %d", ept->DscType); EZOutputMemo->Lines->Add(s);
        s.sprintf("bEndpointAddress: 0x%x", ept->Address); EZOutputMemo->Lines->Add
(s);
        s.sprintf("bmAttributes: 0x%x", ept->Attributes); EZOutputMemo->Lines->Add
(s);
        s.sprintf("wMaxPacketSize: %d", ept->MaxPktSize); EZOutputMemo->Lines->Add
(s);
        s.sprintf("bInterval: %d", ept->Interval); EZOutputMemo->Lines->Add(s);
        EZOutputMemo->Lines->Add("*****");
    }
}
}

```

9.32 Interface()

Interface()

[Top](#) [Previous](#) [Next](#)
UCHAR CCyUSBDevice::Interface(void)
[Previous](#) [Top](#) [Next](#)

Description

Interface returns the index of the currently selected device interface.

Because Windows always represents different reported interfaces as separate devices, the CyUSB driver is only shown devices that have a single interface. This causes the Interface() method to always return zero.

9.33 InterruptInEndPt

InterruptInEndPt

[Top](#) [Previous](#) [Next](#)

**CCyInterruptEndPoint* CCyUSBDevice::
InterruptInEndPt**

[Previous](#) [Top](#) [Next](#)

Description

InterruptInEndPt is a pointer to an object representing the first INTERRUPT IN endpoint enumerated for the selected interface.

The selected interface might expose additional INTERRUPT IN endpoints. To discern this, one would need to traverse the [EndPoints](#) array, checking the [Attributes](#) and [Address](#) members of each [CCyUSBEndPoint](#) object referenced in the array.

If no INTERRUPT IN endpoints were enumerated by the device, InterruptInEndPt will be set to NULL.

Example

```
// Find a second Interrupt IN endpoint in the EndPoints[] array

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyInterruptEndPoint *IntIn2 = NULL;
int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bInt = (USBDevice->EndPoints[i]->Attributes == 3);

    if (bInt && bIn) IntIn2 = (CCyInterruptEndPoint *) USBDevice->EndPoints[i];
    if (IntIn2 == USBDevice->InterruptInEndPt) IntIn2 = NULL;
}
```

9.34 InterruptOutEndPt

InterruptOutEndPt

[Top](#) [Previous](#) [Next](#)

**CCyInterruptEndPoint* CCyUSBDevice::
InterruptOutEndPt**

[Previous](#) [Top](#) [Next](#)

Description

InterruptOutEndPt is a pointer to an object representing the first INTERRUPT OUT endpoint enumerated for the selected interface.

The selected interface might expose additional INTERRUPT OUT endpoints. To discern this, one would need to traverse the [EndPoints](#) array, checking the [Attributes](#) and [Address](#) members of each [CCyUSBEndPoint](#) object referenced in the array.

If no INTERRUPT OUT endpoints were enumerated by the device, InterruptOutEndPt will be set to NULL.

Example

```
// Find a second Interrupt OUT endpoint in the EndPoints[] array
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyInterruptEndPoint *IntOut2 = NULL;
int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bInt = (USBDevice->EndPoints[i]->Attributes == 3);

    if (bInt && !bIn) IntOut2 = (CCyInterruptEndPoint *) USBDevice->EndPoints[i];
    if (IntOut2 == USBDevice->InterruptInEndPt) IntOut2 = NULL;
}
```

9.35 IntfcClass

IntfcClass

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::IntfcClass

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the bInterfaceClass field from the currently selected interface's interface descriptor.

9.36 IntfcCount()

IntfcCount()

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::IntfcCount(void)

[Previous](#) [Top](#) [Next](#)

Description

Returns the bNumInterfaces field of the current device's configuration descriptor.

This number does not include alternate interfaces that might be part of the current configuration.

Because Windows always represents different reported interfaces as separate devices, the CyUSB driver is only shown devices that have a single interface. This causes the IntfcCount() method to always return 1.

9.37 IntfcProtocol

IntfcProtocol

[Top](#) [Previous](#) [Next](#)
UCHAR CCyUSBDevice::IntfcProtocol
[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bInterfaceProtocol** field from the currently selected interface's interface descriptor.

9.38 IntfcSubClass

IntfcSubClass

[Top](#) [Previous](#) [Next](#)
UCHAR CCyUSBDevice::IntfcSubClass
[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bInterfaceSubClass** field from the currently selected interface's interface descriptor.

9.39 IsocInEndPt

IsocInEndPt

[Top](#) [Previous](#) [Next](#)
**CCyIsocEndPoint* CCyUSBDevice::
IsocInEndPt**
[Previous](#) [Top](#) [Next](#)

Description

IsocInEndPt is a pointer to an object representing the first ISOCHRONOUS IN endpoint enumerated for the selected interface.

The selected interface might expose additional ISOCHRONOUS OUT endpoints. To discern this, one would need to traverse the [EndPoints](#) array, checking the [Attributes](#) and [Address](#) members of each [CCyUSBEndPoint](#) object referenced in the array.

If no ISOCHRONOUS IN endpoints were enumerated by the device, IsocInEndPt will be set to NULL.

Example

```
// Find a second Isoc IN endpoint in the EndPoints[] array

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyIsocEndPoint *IsocIn2 = NULL;

int eptCount = USBDevice->EndPointCount();
```

```

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bIsoc = (USBDevice->EndPoints[i]->Attributes == 1);

    if (bIsoc && bIn) IsocIn2 = (CCyIsocEndPoint *) USBDevice->EndPoints[i];
    if (IsocIn2 == USBDevice->IsocInEndPt) IsocIn2 = NULL;
}

```

9.40 IsocOutEndPt

IsocOutEndPt

[Top](#) [Previous](#) [Next](#)

**CCyIsocEndPoint* CCyUSBDevice::
IsocOutEndPt**

[Previous](#) [Top](#) [Next](#)

Description

IsocOutEndPt is a pointer to an object representing the first ISOCHRONOUS OUT endpoint enumerated for the selected interface.

The selected interface might expose additional ISOCHRONOUS OUT endpoints. To discern this, one would need to traverse the [EndPoints](#) array, checking the [Attributes](#) and [Address](#) members of each [CCyUSBEndPoint](#) object referenced in the array.

If no ISOCHRONOUS OUT endpoints were enumerated by the device, IsocOutEndPt will be set to NULL.

Example

```

// Find a second Isoc OUT endpoint in the EndPoints[] array
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyIsocEndPoint *IsocOut2 = NULL;
int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->EndPoints[i]->Address & 0x80;
    bool bIsoc = (USBDevice->EndPoints[i]->Attributes == 1);

    if (bIsoc && !bIn) IsocOut2 = (CCyIsocEndPoint *) USBDevice->EndPoints[i];
    if (IsocOut2 == USBDevice->IsocOutEndPt) IsocOut2 = NULL;
}

```

9.41 IsOpen()

IsOpen()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::IsOpen(void)

[Previous](#) [Top](#) [Next](#)

Description

IsOpen() returns **true** if CCyUSBDevice object has a valid handle to a device attached to the CyUSB driver.

When IsOpen() is **true** , the CCyUSBDevice object is ready to perform IO operations via its [EndPoints](#) members.

9.42 Manufacturer

Manufacturer[Top](#) [Previous](#) [Next](#)

wchar_t CCyUSBDevice::Manufacturer
[USB_STRING_MAXLEN]

[Previous](#) [Top](#) [Next](#)**Description**

Manufacturer is an array of wide characters containing the manufacturer string indicated by the device descriptor's **iManufacturer** field.

9.43 MaxPacketSize

MaxPacketSize[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::MaxPacketSize

[Previous](#) [Top](#) [Next](#)**Description**

This data member contains the value of the **bMaxPacketSize0** field from the open device's Device Descriptor structure.

9.44 MaxPower

MaxPower[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::MaxPower

[Previous](#) [Top](#) [Next](#)**Description**

This data member contains the value of the **MaxPower** field of the open device's selected configuration descriptor.

9.45 NtStatus

NtStatus[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBDevice::NtStatus

[Previous](#) [Top](#) [Next](#)**Description**

The `NtStatus` member contains the `NTSTATUS` returned by the driver for the most recent call to a non-endpoint IO method (`SetAltIntfc`, `Open`, `Reset`, etc.)

More often, you will want to access the [NtStatus](#) member of the `CCyUSBEndPoint` objects.

9.46 Open()

Open()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::Open(UCHAR dev)

[Previous](#) [Top](#) [Next](#)

Description

The `Open()` method is one of the main workhorses of the library.

When `Open()` is called, it first checks to see if the `CCyUSBDevice` object is already opened to one of the attached devices. If so, it calls [Close\(\)](#), then proceeds.

`Open()` calls [DeviceCount\(\)](#) to determine how many devices are attached to the USB driver.

`Open()` creates a valid handle to the device driver, through which all future access is accomplished by the library methods.

`Open()` calls the driver to gather the device, interface, endpoint and string descriptors.

`Open()` results in the [EndPoints](#) array getting properly initialized to pointers of the default interface's endpoints.

`Open()` initializes the [ControlEndPt](#) member to point to an instance of [CCyControlEndPoint](#) that represents the device's endpoint zero.

`Open()` initializes the [BulkInEndPt](#) member to point to an instance of `CCyBulkEndPoint` representing the first Bulk-IN endpoint that was found. Similarly, the [BulkOutEndPt](#), [InterruptInEndPt](#), [InterruptOutEndPt](#), [IsocInEndPt](#) and [IsocOutEndPt](#) members are initialized to point to instances of their respective endpoint classes if such endpoints were found.

After `Open()` returns **true**, all the properties and methods of `CCyUSBDevice` are legitimate.

`Open()` returns **false** if it is unsuccessful in accomplishing the above activities. However, if `Open()` was able to obtain a valid handle to the driver, the handle will remain valid even after `Open()` returns **false**. (When open fails, it does not automatically call `Close()`.) This allows the programmer to call the [Reset\(\)](#) or [ReConnect\(\)](#) methods and then call `Open()` again. Sometimes this will allow a device to open properly.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

// Attempt to open device #0
if (USBDevice->DeviceCount() && !USBDevice->Open(0)) {
```

```

        USBDevice->Reset();
        USBDevice->Open(0);
    }

    if (! USBDevice->IsOpen()) return false;

```

9.47 PowerState()

PowerState()

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::PowerState(void)

[Previous](#) [Top](#) [Next](#)

This method returns the current power state of the device.

A return value of 1 indicates a power state of D0 (Device fully on).

A return value of 4 indicates a power state of D3 (Device fully asleep).

9.48 Product

Product

[Top](#) [Previous](#) [Next](#)

**wchar_t CCyUSBDevice::Product
[USB_STRING_MAXLEN]**

[Previous](#) [Top](#) [Next](#)

Description

Product is an array of wide characters containing the product string indicated by the device descriptor's **iProduct** field.

9.49 ProductID

ProductID

[Top](#) [Previous](#) [Next](#)

USHORT CCyUSBDevice::ProductID

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the value of idProduct from the open device's Device Descriptor structure.

Example

```

// Look for a device having VID = 0547, PID = 1002

USBDevice = new CCyUSBDevice(Handle); // Create an instance of CCyUSBDevice
int devices = USBDevice->DeviceCount();
int vid, pid;
int d = 0;

```

```

do {
    USBDevice->Open(d);    // Open automatically calls Close() if necessary
    vID = USBDevice->VendorID;
    pID = USBDevice->ProductID;
    d++;
} while ((d < devices) && (vID != 0x0547) && (pID != 0x1002));

```

9.50 ReConnect()

ReConnect()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::ReConnect(void)

[Previous](#) [Top](#) [Next](#)

Description

ReConnect() calls the USB device driver to cause the currently open USB device to be logically disconnected from the USB bus and re-enumerated.

9.51 Reset()

Reset()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::Reset(void)

[Previous](#) [Top](#) [Next](#)

Description

Reset() calls the USB device driver to cause the currently open USB device to be reset.

This call causes the device to return to its initial power-on configuration.

9.52 Resume()

Resume()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::Resume(void)

[Previous](#) [Top](#) [Next](#)

The Resume() method sets the device power state to D0 (Full on).

The method returns true if successful and false if the command failed.

9.53 SerialNumber

SerialNumber

[Top](#) [Previous](#) [Next](#)

**wchar_t CCyUSBDevice::SerialNumber
[USB_STRING_MAXLEN]**

[Previous](#) [Top](#) [Next](#)

Description

SerialNumber is an array of wide characters containing the serial number string indicated by the device descriptor's **iSerialNumber** field.

9.54 SetConfig()

SetConfig()

[Top](#) [Previous](#) [Next](#)

void CCyUSBDevice::SetConfig(UCHAR cfg)

[Previous](#) [Top](#) [Next](#)

Description

This method will set the current device configuration to **cfg**, if **cfg** represents an existing configuration.

In practice, devices only expose a single configuration. So, while this method exists for completeness, it should probably never be invoked with a **cfg** value other than 0.

9.55 SetAltIntfc()

SetAltIntfc()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::SetAltIntfc(UCHAR alt)

[Previous](#) [Top](#) [Next](#)

Description

SetAltIntfc() calls the driver to set the active interface of the device to **alt** .

If **alt** is not a valid alt interface setting, the method does nothing.

Legitimate values for **alt** are 0 to [AltIntfcCount\(\)](#).

Calling SetAltIntfc() causes all the [EndPoints](#) members of CCyUSBDevice to be re-assigned to objects reflecting the endpoints of the new alternate interface.

Returns **true** if the alternate interface was successfully set to **alt** .

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

int lastIntfc = USBDevice->AltIntfcCount( );

// Select the last Alternate Interface
USBDevice->SetAltIntfc(lastIntfc);
```

9.56 StrLangID

StrLangID

[Top](#) [Previous](#) [Next](#)

USHORT CCyUSBDevice::StrLangID

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the value of **bString** field from the open device's first String Descriptor.

This value indicates the language of the other string descriptors.

If multiple languages are supported in the string descriptors and English is one of the supported languages, StrLangID is set to the value for English (0x0409).

9.57 Suspend()

Suspend()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBDevice::Suspend(void)

[Previous](#) [Top](#) [Next](#)

The Suspend() method sets the device power state to D3 (Full asleep).

The method returns true if successful and false if the command failed.

9.58 USBAddress

USBAddress

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBDevice::USBAddress

[Previous](#) [Top](#) [Next](#)

Description

USBAddress contains the bus address of the currently open USB device.

This is the address value used by the Windows USBDI stack. It is not particularly useful at the application level.

9.59 USBDIVersion

USBDIVersion

[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBDevice::USBDIVersion

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the version of the USB Host Controller Driver in BCD format.

9.60 UsbdStatus

UsbdStatus

[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBDevice::UsbdStatus

[Previous](#) [Top](#) [Next](#)

Description

The `UsbdStatus` member contains the `USB_D_STATUS` returned by the driver for the most recent call to a non-endpoint IO method (SetAltIntfc, Open, Reset, etc.)

More often, you will want to access the [UsbdStatus](#) member of the `CCyUSBEndPoint` objects.

9.61 UsbdStatusString()**UsbdStatusString()**
[Top](#) [Previous](#) [Next](#)

void CCyUSBDevice::UsbdStatusString(ULONG
stat, PCHAR s)

[Previous](#) [Top](#) [Next](#)
Description

The `UsbdStatusString` method returns a string of characters in **s** that represents the `UsbdStatus` error code contained in **stat**.

The **stat** parameter should be the [UsbdStatus](#) member or a `CCyUSBEndPoint::UsbdStatus` member.

The format of the returned string, **s**, is:

"[state=SSSSSS status=TTTTTTTT]"

where SSSSSS can be "SUCCESS", "PENDING", "STALLED", or "ERROR".

Note:

There is no endpoint equivalent for this method. To interpret the `UsbdStatus` member of an endpoint object, call this method (`CCyUSBDevice::UsbdStatusString`) passing the `UsbdStatus` member of the endpoint.

9.62 VendorID**VendorID**
[Top](#) [Previous](#) [Next](#)

USHORT CCyUSBDevice::VendorID

[Previous](#) [Top](#) [Next](#)
Description

This data member contains the value of `idVendor` from the open device's Device Descriptor structure.

Example

```
// Look for a device having VID = 0547, PID = 1002

USBDevice = new CCyUSBDevice(Handle); // Create an instance of CCyUSBDevice
```

```

int devices = USBDevice->DeviceCount();
int vID, pID;

int d = 0;
do {
    USBDevice->Open(d);    // Open automatically calls Close() if necessary
    vID = USBDevice->VendorID;
    pID = USBDevice->ProductID;
    d++;
} while ((d < devices) && (vID != 0x0547) && (pID != 0x1002));

```

10 CCyUSBConfig

CCyUSBConfig

[Top](#) [Previous](#) [Next](#)

CCyUSBConfig Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

CCyUSBConfig represents a USB device configuration. Such configurations have one or more interfaces each of which exposes one or more endpoints.

When [CCyUSBDevice::Open\(\)](#) is called, an instance of CCyUSBConfig is constructed for each configuration reported by the open device's device descriptor. (Normally, there is just one.)

In the process of construction, CCyUSBConfig creates instances of [CCyUSBInterface](#) for each interface exposed in the device's configuration descriptor. In turn, the CCyUSBInterface class creates instances of [CyUSBEndPoint](#) for each endpoint descriptor contained in the interface descriptor. In this iterative fashion, the entire structure of Configs->Interfaces->EndPoints gets populated from a single construction of the CCyUSBConfig class.

The following example code shows how you might use the CCyUSBConfig class in an application.

Example

```

// This code lists all the endpoints reported
// for all the interfaces reported
// for all the configurations reported
// by the device.

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

String s;

for (int c=0; c<USBDevice->ConfigCount(); c++) {

```

```

CCyUSBConfig cfg = USBDevice->GetUSBConfig(c);

s.printf("bLength: 0x%x",cfg.bLength); EZOutputMemo->Lines->Add(s);
s.printf("bDescriptorType: %d",cfg.bDescriptorType); EZOutputMemo->Lines->Add
(s);
s.printf("wTotalLength: %d (0x%x)",cfg.wTotalLength, cfg.wTotalLength);
EZOutputMemo->Lines->Add(s);
s.printf("bNumInterfaces: %d",cfg.bNumInterfaces); EZOutputMemo->Lines->Add
(s);
s.printf("bConfigurationValue: %d",cfg.bConfigurationValue); EZOutputMemo-
>Lines->Add(s);
s.printf("iConfiguration: %d",cfg.iConfiguration); EZOutputMemo->Lines->Add
(s);
s.printf("bmAttributes: 0x%x",cfg.bmAttributes); EZOutputMemo->Lines->Add(s);
s.printf("MaxPower: %d",cfg.MaxPower); EZOutputMemo->Lines->Add(s);
EZOutputMemo->Lines->Add("*****");

for (int i=0; i<cfg.AltInterfaces; i++) {
    CCyUSBInterface *ifc = cfg.Interfaces[i];
    EZOutputMemo->Lines->Add("Interface Descriptor: " + String(i+1));
    EZOutputMemo->Lines->Add("-----");
    s.printf("bLength: 0x%x",ifc->bLength); EZOutputMemo->Lines->Add(s);
    s.printf("bDescriptorType: %d",ifc->bDescriptorType); EZOutputMemo->Lines-
>Add(s);
    s.printf("bInterfaceNumber: %d",ifc->bInterfaceNumber); EZOutputMemo->Lines-
>Add(s);
    s.printf("bAlternateSetting: %d",ifc->bAlternateSetting); EZOutputMemo-
>Lines->Add(s);
    s.printf("bNumEndpoints: %d",ifc->bNumEndpoints); EZOutputMemo->Lines->Add
(s);
    s.printf("bInterfaceClass: %d",ifc->bInterfaceClass); EZOutputMemo->Lines-
>Add(s);

    for (int e=0; e<ifc->bNumEndpoints; e++) {
        CCyUSBEndPoint *ept = ifc->EndPoints[e+1];
        EZOutputMemo->Lines->Add("EndPoint Descriptor: " + String(e+1));
        EZOutputMemo->Lines->Add("-----");
        s.printf("bLength: 0x%x",ept->DscLen); EZOutputMemo->Lines->Add(s);
        s.printf("bDescriptorType: %d",ept->DscType); EZOutputMemo->Lines->Add(s);
        s.printf("bEndpointAddress: 0x%x",ept->Address); EZOutputMemo->Lines->Add
(s);
        s.printf("bmAttributes: 0x%x",ept->Attributes); EZOutputMemo->Lines->Add
(s);
        s.printf("wMaxPacketSize: %d",ept->MaxPktSize); EZOutputMemo->Lines->Add
(s);
        s.printf("bInterval: %d",ept->Interval); EZOutputMemo->Lines->Add(s);
        EZOutputMemo->Lines->Add("*****");
    }
}
}

```


10.1 AltInterfaces

AltInterfaces

[Top](#) [Previous](#) [Next](#)**CCyUSBConfig::AltInterfaces**[Previous](#) [Top](#) [Next](#)

Description

AltInterfaces contains the total number of interfaces exposed by the configuration (including the default interface). This value is the number of interface descriptors contained in the current configuration descriptor.

Because the [CCyUSBDevice::AltIntfcCount\(\)](#) method does not count the primary interface, it returns CCyUSBConfig::AltInterfaces - 1.

10.2 bConfigurationValue

bConfigurationValue

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBConfig::bConfigurationValue**[Previous](#) [Top](#) [Next](#)

Description

bConfigurationValue contains value of the **bConfigurationValue** field from the selected configuration descriptor.

10.3 bDescriptorType

bDescriptorType

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBConfig::bDescriptorType**[Previous](#) [Top](#) [Next](#)

Description

bDescriptorType contains value of the **bDescriptorType** field from the selected configuration descriptor.

10.4 bLength

bLength

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBConfig::bLength**[Previous](#) [Top](#) [Next](#)

Description

bLength contains value of the **bLength** field from the selected configuration descriptor.

10.5 bmAttributes

bmAttributes

[Top](#) [Previous](#) [Next](#)
UCHAR CCyUSBConfig::bmAttributes
[Previous](#) [Top](#) [Next](#)

Description

bmAttributes contains value of the **bmAttributes** field from the selected configuration descriptor.

10.6 bNumInterfaces

bNumInterfaces

[Top](#) [Previous](#) [Next](#)
UCHAR CCyUSBConfig::bNumInterfaces
[Previous](#) [Top](#) [Next](#)

Description

bNumInterfaces contains value of the **bNumInterfaces** field from the selected configuration descriptor.

10.7 CCyUSBConfig()

CCyUSBConfig()

[Top](#) [Previous](#) [Next](#)
CCyUSBConfig::CCyUSBConfig(void)
[Previous](#) [Top](#) [Next](#)

Description

This is the default constructor for the CCyUSBConfig class.

This constructor simply sets all it's data members to zero.

10.8 CCyUSBConfig()

CCyUSBConfig()

[Top](#) [Previous](#) [Next](#)
**CCyUSBConfig::CCyUSBConfig(HANDLE
handle, PUSB_CONFIGURATION_DESCRIPTOR
pConfigDescr)**
[Previous](#) [Top](#) [Next](#)

Description

This constructor creates a functional CCyUSBConfig object, complete with a populated Interfaces[] array.

During construction, the pConfigDescr structure is traversed and all interface descriptors are read, creating CCyUSBInterface objects.

This constructor is called automatically as part of the [CCyUSBDevice::Open\(\)](#) method. You should never need to call this constructor yourself.

10.9 CCyUSBConfig()

CCyUSBConfig()

[Top](#) [Previous](#) [Next](#)

CCyUSBConfig::CCyUSBConfig(
CCyUSBConfig& cfg)

[Previous](#) [Top](#) [Next](#)

Description

This is the *copy* constructor for the CCyUSBConfig class.

This constructor copies all of the simple data members of **cfg**. Then, it walks through **cfg** 's list of [CCyUSBInterface](#) objects and makes copies of them, storing pointers to the new interface objects in a private, internal data array. (This is accomplished by calling the [copy constructor](#) for CCyUSBInterface.)

You should usually not call the copy constructor explicitly. Instead, use the [GetUSBConfig\(\)](#) method of the CCyUSBDevice class.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);  
CCyUSBConfig cfg = USBDevice->GetUSBConfig(0);
```

10.10 ~CCyUSBConfig

~CCyUSBConfig

[Top](#) [Previous](#) [Next](#)

CCyUSBConfig::~~CCyUSBConfig(void)

[Previous](#) [Top](#) [Next](#)

Description

This is the destructor for the CCyUSBConfig class.

The destructor deletes all the dynamically constructed [CCyUSBInterface](#) objects that were created during construction of the object.

10.11 iConfiguration

iConfiguration

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBConfig::iConfiguration

[Previous](#) [Top](#) [Next](#)

Description

iConfiguration contains value of the **iConfiguration** field from the selected configuration descriptor.

10.12 Interfaces

Interfaces

[Top](#) [Previous](#) [Next](#)

**CCyUSBInterface* CCyUSBConfig::Interfaces
[MAX_INTERFACES]**

[Previous](#) [Top](#) [Next](#)

Description

Interfaces is an array of pointers to [CCyUSBInterface](#) objects. One valid pointer exists in Interfaces[] for each alternate interface exposed by the configuration (including alt setting 0).

The [AltInterfaces](#) member tells how many valid entries are held in Interfaces.

Use [CCyUSBDevice::AltIntfcCount\(\)](#) and [CCyUSBDevice::SetAltIntfc\(\)](#) to access a configuration's alternate interfaces.

Example

```
// This code lists all the endpoints reported
//     for all the interfaces reported
//         for all the configurations reported
//     by the device.

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

String s;

for (int c=0; c<USBDevice->ConfigCount(); c++) {
    CCyUSBConfig cfg = USBDevice->GetUSBConfig(c);

    s.printf("bLength: 0x%x",cfg.bLength); EZOutputMemo->Lines->Add(s);
    s.printf("bDescriptorType: %d",cfg.bDescriptorType); EZOutputMemo->Lines->Add
(s);
    s.printf("wTotalLength: %d (0x%x)",cfg.wTotalLength,cfg.wTotalLength);
EZOutputMemo->Lines->Add(s);
    s.printf("bNumInterfaces: %d",cfg.bNumInterfaces); EZOutputMemo->Lines->Add
(s);
    s.printf("bConfigurationValue: %d",cfg.bConfigurationValue); EZOutputMemo-
>Lines->Add(s);
    s.printf("iConfiguration: %d",cfg.iConfiguration); EZOutputMemo->Lines->Add
(s);
    s.printf("bmAttributes: 0x%x",cfg.bmAttributes); EZOutputMemo->Lines->Add(s);
    s.printf("MaxPower: %d",cfg.MaxPower); EZOutputMemo->Lines->Add(s);
EZOutputMemo->Lines->Add("*****");

    for (int i=0; i<cfg.AltInterfaces; i++) {
        CCyUSBInterface *ifc = cfg.Interfaces[i];
        EZOutputMemo->Lines->Add("Interface Descriptor:" + String(i+1));
        EZOutputMemo->Lines->Add("-----");
        s.printf("bLength: 0x%x",ifc->bLength); EZOutputMemo->Lines->Add(s);
        s.printf("bDescriptorType: %d",ifc->bDescriptorType); EZOutputMemo->Lines-
```

```

>Add(s);
    s.sprintf("bInterfaceNumber: %d", ifc->bInterfaceNumber); EZOutputMemo->Lines-
>Add(s);
    s.sprintf("bAlternateSetting: %d", ifc->bAlternateSetting); EZOutputMemo-
>Lines->Add(s);
    s.sprintf("bNumEndpoints: %d", ifc->bNumEndpoints); EZOutputMemo->Lines->Add
(s);
    s.sprintf("bInterfaceClass: %d", ifc->bInterfaceClass); EZOutputMemo->Lines-
>Add(s);

    for (int e=0; e<ifc->bNumEndpoints; e++) {
        CCyUSBEndPoint *ept = ifc->EndPoints[e+1];
        EZOutputMemo->Lines->Add("EndPoint Descriptor: " + String(e+1));
        EZOutputMemo->Lines->Add("-----");
        s.sprintf("bLength: 0x%x", ept->DscLen); EZOutputMemo->Lines->Add(s);
        s.sprintf("bDescriptorType: %d", ept->DscType); EZOutputMemo->Lines->Add(s);
        s.sprintf("bEndpointAddress: 0x%x", ept->Address); EZOutputMemo->Lines->Add
(s);
        s.sprintf("bmAttributes: 0x%x", ept->Attributes); EZOutputMemo->Lines->Add
(s);
        s.sprintf("wMaxPacketSize: %d", ept->MaxPktSize); EZOutputMemo->Lines->Add
(s);
        s.sprintf("bInterval: %d", ept->Interval); EZOutputMemo->Lines->Add(s);
        EZOutputMemo->Lines->Add("*****");
    }
}

```

10.13 wTotalLength

wTotalLength

[Top](#) [Previous](#) [Next](#)

USHORT CCyUSBConfig::wTotalLength

[Previous](#) [Top](#) [Next](#)

Description

wTotalLength contains value of the **wTotalLength** field from the selected configuration descriptor.

11 CCyUSBEndPoint

CCyUSBEndPoint

[Top](#) [Previous](#) [Next](#)

CCyUSBEndPoint Class

[Previous](#) [Top](#) [Next](#)

Header

CyUSB.h

Description

CCyUSBEndPoint is an abstract class, having a pure virtual method, [BeginDataXfer\(\)](#). Therefore, instances of CCyUSBEndPoint cannot be constructed. [CCyControlEndPoint](#), [CCyBulkEndPoint](#),

[CCyIsocEndPoint](#), and [CCyInterruptEndPoint](#) are all classes derived from [CCyUSBEndPoint](#).

All USB data traffic is accomplished by using instances of the endpoint classes.

When a [CCyUSBDevice](#) is opened, a list of all the [EndPoint](#)s for the current alt interface is generated. This list is populated with viable [CCyUSBEndPoint](#) objects, instantiated for the appropriate type of endpoint. Data access is then accomplished via one of these [CCyUSBEndPoint](#) objects.

11.1 Abort()

Abort()

[Top](#) [Previous](#) [Next](#)

void CCyUSBEndPoint::Abort(void)

[Previous](#) [Top](#) [Next](#)

Description

Abort sends an IOCTL_ADAPT_ABORT_PIPE command to the USB device, with the endpoint address as a parameter. This causes an abort of pending IO transactions on the endpoint.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

USBDevice->ControlEndPt->Abort();
```

11.2 Address

Address

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBEndPoint::Address

[Previous](#) [Top](#) [Next](#)

Description

Address contains the value of the **bEndpointAddress** field of the endpoint descriptor returned by the device.

Addresses with the high-order bit set (0x8_) are IN endpoints.

Addresses with the high-order bit cleared (0x0_) are OUT endpoints.

The default control endpoint ([ControlEndPt](#)) has Address = 0.

Example

```
// Find a second bulk IN endpoint in the EndPoints[] array

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);
```

```

CCyBulkEndPoint *BulkIn2 = NULL;

int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->Endpoints[i]->Address & 0x80;
    bool bBulk = (USBDevice->Endpoints[i]->Attributes == 2);

    if (bBulk && bIn) BulkIn2 = (CCyBulkEndPoint *) USBDevice->Endpoints[i];
    if (BulkIn2 == BulkInEndPt) BulkIn2 = NULL;
}

```

11.3 Attributes

Attributes

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBEndPoint::Attributes

[Previous](#) [Top](#) [Next](#)

Description

Attributes contains the value of the **bmAttributes** field of the endpoint's descriptor.

The Attributes member indicates the type of endpoint per the following list.

- 0: Control
- 1: Isochronous
- 2: Bulk
- 3: Interrupt

Example

```

// Find a second bulk IN endpoint in the EndPoints[] array

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyBulkEndPoint *BulkIn2 = NULL;

int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool bIn = USBDevice->Endpoints[i]->bIn;
    bool bBulk = (USBDevice->Endpoints[i]->Attributes == 2);

    if (bBulk && bIn) BulkIn2 = (CCyBulkEndPoint *) USBDevice->Endpoints[i];
    if (BulkIn2 == BulkInEndPt) BulkIn2 = NULL;
}

```

11.4 BeginDataXfer()

BeginDataXfer()

[Top](#) [Previous](#) [Next](#)

```
virtual PCHAR CCyUSBEndPoint::
BeginDataXfer(PCHAR buf, LONG len,
OVERLAPPED *ov) = 0
```

[Previous](#) [Top](#) [Next](#)

Description

Note that the CCyUSBEndPoint version of this method is a pure virtual function. There is no implementation body for this function in the CCyUSBEndPoint class. Rather, all the classes derived from CCyUSBEndPoint provide their own special implementation of this method.

BeginDataXfer is an advanced method for performing asynchronous IO. This method sets-up all the parameters for a data transfer, initiates the transfer, and immediately returns, not waiting for the transfer to complete.

BeginDataXfer allocates a complex data structure and returns a pointer to that structure. [FinishDataXfer](#) de-allocates the structure. Therefore, it is imperative that each BeginDataXfer call have exactly one matching FinishDataXfer call.

You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

Example

```
// This example assumes that the device automatically sends back,
// over its bulk-IN endpoint, any bytes that were received over its
// bulk-OUT endpoint (commonly referred to as a loopback function)

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

OVERLAPPED outOvLap, inOvLap;
outOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_OUT");
inOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_IN");

char inBuf[128];
ZeroMemory(inBuf, 128);

char buffer[128];
LONG length = 128;

// Just to be cute, request the return data before initiating the loopback
UCHAR *inContext = USBDevice->BulkInEndPt->BeginDataXfer(inBuf, length,
&inOvLap);
UCHAR *outContext = USBDevice->BulkOutEndPt->BeginDataXfer(buffer, length,
&outOvLap);

USBDevice->BulkOutEndPt->WaitForXfer(&outOvLap, 100);
USBDevice->BulkInEndPt->WaitForXfer(&inOvLap, 100);
```



```

USBDevice->BulkOutEndPt->FinishDataXfer(buffer, length, &outOvLap, outContext);
USBDevice->BulkInEndPt->FinishDataXfer(inBuf, length, &inOvLap, inContext);

```

```

CloseHandle(outOvLap.hEvent);
CloseHandle(inOvLap.hEvent);

```

11.5 bIn

bIn

[Top](#) [Previous](#) [Next](#)

bool CCyUSBEndPoint::bIn

[Previous](#) [Top](#) [Next](#)

Description

bIn indicates whether or not the endpoint is an IN endpoint.

IN endpoints transfer data from the USB device to the Host (PC).

Endpoint addresses with the high-order bit set (0x8_) are IN endpoints. Endpoint addresses with the high-order bit cleared (0x0_) are OUT endpoints.

bIn is not valid for [CCyControlEndPoint](#) objects (such as CCyUSBDevice->ControlEndPt).

Example

```

// Find a second bulk IN endpoint in the EndPoints[] array

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyBulkEndPoint *BulkIn2 = NULL;

int eptCount = USBDevice->EndPointCount();

for (int i=1; i<eptCount; i++) {
    bool In = USBDevice->EndPoints[i]->bIn;
    bool bBulk = (USBDevice->EndPoints[i]->Attributes == 2);

    if (bBulk && In) BulkIn2 = (CCyBulkEndPoint *) USBDevice->EndPoints[i];
    if (BulkIn2 == USBDevice->BulkInEndPt) BulkIn2 = NULL;
}

```

11.6 CCyUSBEndPoint()

CCyUSBEndPoint()

[Top](#) [Previous](#) [Next](#)**CCyUSBEndPoint::CCyUSBEndPoint(void)**[Previous](#) [Top](#) [Next](#)

Description

This is the default constructor for the CCyUSBEndPoint class.

Because CCyUSBEndPoint is an abstract class, you cannot instantiate an object of CCyUSBEndPoint. That is, the statement

```
new CCyUSBEndPoint ( );
```

would result in a compiler error.

The default constructor initializes most of its data members to zero. It sets the default endpoint Timeout to 10 seconds. It sets bln to false, and sets hDevice to INVALID_HANDLE_VALUE.

11.7 CCyUSBEndPoint()

CCyUSBEndPoint()

[Top](#) [Previous](#) [Next](#)**CCyUSBEndPoint::CCyUSBEndPoint(HANDLE
h, USB_ENDPOINT_DESCRIPTOR
pEndPointDescriptor)**[Previous](#) [Top](#) [Next](#)

Description

This is the primary constructor for the CCyUSBEndPoint class.

Because CCyUSBEndPoint is an abstract class, you cannot instantiate an object of CCyUSBEndPoint. That is, the statement

```
new CCyUSBEndPoint (h, pEndPointDesc);
```

would result in a compiler error.

However, the constructor does get called (automatically) in the process of constructing derived endpoint classes.

This constructor sets most of its data members to their corresponding fields in the **pEndPointDescriptor** structure. It sets the default endpoint Timeout to 10 seconds. It sets its hDevice member to **h**.

11.8 CCyUSBEndPoint()

CCyUSBEndPoint()

[Top](#) [Previous](#) [Next](#)

CCyUSBEndPoint::CCyUSBEndPoint(
CCyUSBEndPoint& ept)

[Previous](#) [Top](#) [Next](#)

Description

This is the *copy* constructor for the CCyUSBEndPoint class.

This constructor copies all of the simple data members of ept.

Because CCyUSBEndPoint is an abstract class, you cannot invoke this constructor explicitly. Instead, it gets called as a side effect of invoking the copy constructors for [CCyControlEndPoint](#), [CCyBulkEndPoint](#), [CCyIsocEndPoint](#), and [CCyInterruptEndPoint](#).

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyControlEndPoint *ctlEpt = new CCyControlEndPoint(*USBDevice->ControlEndPt);
```

11.9 DscLen

DscLen

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBEndPoint::DscLen

[Previous](#) [Top](#) [Next](#)

Description

DscLen contains the length of the endpoint descriptor as reported in the **bLength** field of the USB_ENDPOINT_DESCRIPTOR structure that was passed to the endpoint object's constructor. (Because the passed descriptor was an endpoint descriptor, this value should always be 0x07.)

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

11.10 DscType

DscType

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBEndPoint::DscType

[Previous](#) [Top](#) [Next](#)

Description

DscType contains the type of the endpoint descriptor as reported in the **bDescriptorType** field of the

USB_ENDPOINT_DESCRIPTOR structure that was passed to the endpoint object's constructor. (Because the passed descriptor was an endpoint descriptor, this value should always be 0x05.)

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

11.11 GetXferSize()

GetXferSize()

[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBEndPoint::GetXferSize(void)

[Previous](#) [Top](#) [Next](#)

Description

Each non-control endpoint has a transfer size that is some multiple of its MaxPacketSize. This transfer size can be adjusted programmatically.

The transfer size establishes the size of internal buffers used by the USB driver stack for performing data transfers. Larger values for the transfer size enable data transfers involving fewer transactions. However, those larger buffers also consume more available memory.

GetXferSize() returns the current transfer size setting for the endpoint.

11.12 FinishDataXfer()

FinishDataXfer()

[Top](#) [Previous](#) [Next](#)

**bool CCyUSBEndPoint::FinishDataXfer(PCHAR
buf, LONG &len, OVERLAPPED *ov, PCHAR
pXmitBuf, CCyIsoPktInfo* pktInfos = NULL)**

[Previous](#) [Top](#) [Next](#)

Description

FinishDataXfer is an advanced method for performing asynchronous IO.

FinishDataXfer transfers any received bytes into **buf** . It sets the **len** parameter to the actual number of bytes transferred. Finally, FinishDataXfer frees the memory associated with the **pXmitBuf** pointer. This pointer was returned by a previous corresponding call to [BeginDataXfer](#).

The pointer to an OVERLAPPED structure, passed in the **ov** parameter, should be the same one that was passed to the corresponding BeginDataXfer method.

The **pktInfos** parameter is optional and points to an array of [CCyIsoPktInfo](#) objects. It should only be used for Isochronous endpoint transfers.

You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

Example

```

// This example assumes that the device automatically sends back,
// over its bulk-IN endpoint, any bytes that were received over its
// bulk-OUT endpoint (commonly referred to as a loopback function)

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

OVERLAPPED outOvLap, inOvLap;
outOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_OUT");
inOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_IN");

char inBuf[128];
ZeroMemory(inBuf, 128);

char buffer[128];
LONG length = 128;

// Just to be cute, request the return data before initiating the loopback
UCHAR *inContext = USBDevice->BulkInEndPoint->BeginDataXfer(inBuf, length,
&inOvLap);
UCHAR *outContext = USBDevice->BulkOutEndPoint->BeginDataXfer(buffer, length,
&outOvLap);

USBDevice->BulkOutEndPoint->WaitForXfer(&outOvLap, 100);
USBDevice->BulkInEndPoint->WaitForXfer(&inOvLap, 100);

USBDevice->BulkOutEndPoint->FinishDataXfer(buffer, length, &outOvLap, outContext);
USBDevice->BulkInEndPoint->FinishDataXfer(inBuf, length, &inOvLap, inContext);

CloseHandle(outOvLap.hEvent);
CloseHandle(inOvLap.hEvent);

```

11.13 hDevice

hDevice

[Top](#) [Previous](#) [Next](#)

HANDLE CCyUSBEndPoint::hDevice

[Previous](#) [Top](#) [Next](#)

Description

hDevice contains a handle to the USB device driver, through which all the IO is carried-out. The handle is created by the [Open\(\)](#) method of a [CCyUSBDevice](#) object.

The only reason to access this data member would be to call the device driver explicitly, bypassing the API library methods. *This is not recommended.*

You should never call `CloseHandle(hDevice)` directly. Instead, call the [Close\(\)](#) method of a [CCyUSBDevice](#) object.

Note that an instance of CCyUSBDevice will contain several [CCyUSBEndPoint](#) objects. Each of those will have the same value for their hDevice member. Also, the endpoint's hDevice member will be identical to its container CCyUSBDevice object's private hDevice member (accessed via the [DeviceHandle\(\)](#) method).

11.14 Interval

Interval

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBEndPoint::Interval

[Previous](#) [Top](#) [Next](#)

Description

Interval contains the value reported in the **Interval** field of the USB_ENDPOINT_DESCRIPTOR structure that was passed to the endpoint object's constructor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

11.15 MaxPktSize

MaxPktSize

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBEndPoint::MaxPktSize

[Previous](#) [Top](#) [Next](#)

Description

MaxPktSize contains the value indicated by the **wMaxPacketSize** field of the USB_ENDPOINT_DESCRIPTOR structure that was passed to the endpoint object's constructor.

MaxPktSize is calculated by multiplying the low-order 11 bits of **wMaxPacketSize** by the value represented by 1 + the next 2 bits (bits 11 and 12) .

NOTE: For ISOC transfers, the buffer length and the endpoint's transfers size (see [SetXferSize](#)) must be a multiple of 8 times the endpoint's [MaxPktSize](#).

Example

If wMaxPacketSize is 0x1400 (binary = 0001 0100 0000 0000)

MaxPktSize = [100 0000 0000 binary] * [10 binary + 1] = 1024 * 3 = 3072

11.16 NtStatus

NtStatus

[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBEndPoint::NtStatus[Previous](#) [Top](#) [Next](#)**Description**

NtStatus member contains the error code returned from the last call to the XferData or BeginDataXfer methods.

11.17 Reset()

Reset()[Top](#) [Previous](#) [Next](#)**bool CCyUSBEndPoint::Reset(void)**[Previous](#) [Top](#) [Next](#)**Description**

The Reset method resets the endpoint, clearing any error or stall conditions on that endpoint.

Pending data transfers are not cancelled by the Reset method.

Call [Abort\(\)](#) for the endpoint in order force completion of any transfers in-process.

11.18 SetXferSize()

SetXferSize()[Top](#) [Previous](#) [Next](#)**void CCyUSBEndPoint::SetXferSize(ULONG
xfer)**[Previous](#) [Top](#) [Next](#)**Description**

Each non-control endpoint has a transfer size that is some multiple of its [MaxPktSize](#). This transfer size can be adjusted programmatically.

The transfer size establishes the size of internal buffers used by the USB driver stack for performing data transfers. Larger values for the transfer size enable data transfers involving fewer transactions. However, those larger buffers also consume more available memory.

SetXferSize() sets the current transfer size setting for the endpoint. It automatically sets the transfer size to a multiple of the endpoint's [MaxPktSize](#) property that is greater or equal to the requested **xfer** size.

NOTE: For ISOC transfers, the buffer length and the endpoint's transfers size (see [SetXferSize](#)) must be a multiple of 8 times the endpoint's [MaxPktSize](#).

11.19 TimeOut

TimeOut[Top](#) [Previous](#) [Next](#)**ULONG CCyUSBEndPoint::TimeOut**[Previous](#) [Top](#) [Next](#)

Description

TimeOut limits the length of time that a [XferData](#)() call will wait for the transfer to complete.

The units of **TimeOut** is milliseconds.

NOTE : For [CCyControlEndPoint](#), the **TimeOut** is rounded down to the nearest 1000 ms, except for values between 0 and 1000 which are rounded up to 1000. Also, for [CCyControlEndPoint](#), a **TimeOut** of zero will wait forever unless the transaction completes. **TimeOut** has no effect on Isoc endpoints since they will always transfer data or fail immediately.

Example

```
char buffer[128];
LONG length = 128;

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

USBDevice->BulkOutEndPoint->TimeOut = 1000; // 1 sec timeout
USBDevice->BulkOutEndPoint->XferData(buf, length);
```

11.20 UsbdStatus

UsbdStatus

[Top](#) [Previous](#) [Next](#)

ULONG CCyUSBEndPoint::UsbdStatus

[Previous](#) [Top](#) [Next](#)

Description

UsbdStatus member contains an error code returned from the last call to the [XferData](#) or [BeginDataXfer](#) methods.

UsbdStatus can be decoded by passing the value to the [CCyUSBDevice::UsbdStatusString](#)() method.

11.21 WaitForXfer()

WaitForXfer()

[Top](#) [Previous](#) [Next](#)

bool CCyUSBEndPoint::WaitForXfer(
OVERLAPPED *ov, ULONG tOut)

[Previous](#) [Top](#) [Next](#)

Description

This method is used in conjunction with [BeginDataXfer](#) and [FinishDataXfer](#) to perform asynchronous IO.

The **ov** parameter points to the OVERLAPPED object that was passed in the preceding [BeginDataXfer](#) call.

tOut limits the time, in milliseconds, that the library will wait for the transaction to complete.

You will usually want to use the synchronous [XferData](#) method rather than the asynchronous BeginDataXfer/WaitForXfer/FinishDataXfer approach.

Example

```
// This example assumes that the device automatically sends back,
// over its bulk-IN endpoint, any bytes that were received over its
// bulk-OUT endpoint (commonly referred to as a loopback function)

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

OVERLAPPED outOvLap, inOvLap;
outOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_OUT");
inOvLap.hEvent = CreateEvent(NULL, false, false, "CYUSB_IN");

char inBuf[128];
ZeroMemory(inBuf, 128);

char buffer[128];
LONG length = 128;

// Just to be cute, request the return data before initiating the loopback
UCHAR *inContext = USBDevice->BulkInEndPoint->BeginDataXfer(inBuf, length,
&inOvLap);
UCHAR *outContext = USBDevice->BulkOutEndPoint->BeginDataXfer(buffer, length,
&outOvLap);

USBDevice->BulkOutEndPoint->WaitForXfer(&outOvLap, 100);
USBDevice->BulkInEndPoint->WaitForXfer(&inOvLap, 100);

USBDevice->BulkOutEndPoint->FinishDataXfer(buffer, length, &outOvLap, outContext);
USBDevice->BulkInEndPoint->FinishDataXfer(inBuf, length, &inOvLap, inContext);

CloseHandle(outOvLap.hEvent);
CloseHandle(inOvLap.hEvent);
```

11.22 XferData()

XferData()

[Top](#) [Previous](#) [Next](#)

```
bool CCyUSBEndPoint::XferData(PCHAR buf,
LONG &len, PUCCHAR pktInfos = NULL)
```

[Previous](#) [Top](#) [Next](#)

Description

XferData sends or receives **len** bytes of data from / into **buf**.

This is the primary IO method of the library for transferring data. Most data transfers should occur by invoking the **XferData** method of an instantiated endpoint object.

XferData calls the appropriate [BeginDataXfer](#) method for the instantiated class (one of [CCyBulkEndPoint](#), [CCyControlEndPoint](#), [CCyInterruptEndPoint](#), or [CCyIsocEndPoint](#)). It then waits for the transaction to complete (or until the endpoint's [TimeOut](#) expires), and finally calls the [FinishDataXfer](#) method to complete the transaction. It call [Abort\(\)](#) method internally if operation fail.

For all non-control endpoints, the direction of the transfer is implied by the endpoint itself. (Each such endpoint will either be an IN or an OUT endpoint.)

For control endpoints, the [Direction](#) must be specified, along with the other control-specific parameters.

XferData performs synchronous (i.e. blocking) IO operations. It does not return until the transaction completes or the endpoint's TimeOut has elapsed.

Returns **true** if the transaction successfully completes before TimeOut has elapsed.

Note that the **len** parameter is a reference, meaning that the method can modify its value. The number of bytes actually transferred is passed back in **len**.

The **pktInfos** parameter is optional and points to an array of [CCyIsoPktInfo](#) objects. It should only be used for Isochronous endpoint transfers.

NOTE: For ISOC transfers, the buffer length and the endpoint's transfers size (see [SetXferSize](#)) must be a multiple of 8 times the endpoint's [MaxPktSize](#).

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

char buf[12] = "hello world";
LONG length = 11;

if (USBDevice->BulkOutEndPt)
    USBDevice->BulkOutEndPt->XferData(buf, length);
```

12 CCyUSBInterface

CCyUSBInterface

[Top](#) [Previous](#) [Next](#)

CCyUSBInterface Class

[Previous](#) [Top](#) [Next](#)

Header
CyUSB.h

Description

CCyUSBInterface represents a USB device interface. Such interfaces have one or more endpoints.

When [CCyUSBDevice::Open\(\)](#) is called, an instance of [CCyUSBConfig](#) is constructed for each configuration reported by the open device's device descriptor. (Normally, there is just one.)

In the process of construction, CCyUSBConfig creates instances of CCyUSBInterface for each interface exposed in the device's configuration descriptor. In turn, the CCyUSBInterface class creates instances of [CyUSBEndPoint](#) for each endpoint descriptor contained in the interface descriptor. In this iterative fashion, the entire structure of Configs->Interfaces->EndPoints gets populated from a single construction of the CCyUSBConfig class.

The below example code shows how you might use the CCyUSBInterface class in an application.

Example

```
// This code lists all the endpoints reported
// for all the interfaces reported
// for all the configurations reported
// by the device.

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

String s;

for (int c=0; c<USBDevice->ConfigCount(); c++) {
    CCyUSBConfig cfg = USBDevice->GetUSBConfig(c);

    s.sprintf("bLength: 0x%x",cfg.bLength); EZOutputMemo->Lines->Add(s);
    s.sprintf("bDescriptorType: %d",cfg.bDescriptorType); EZOutputMemo->Lines->Add
(s);
    s.sprintf("wTotalLength: %d (0x%x)",cfg.wTotalLength, cfg.wTotalLength);
EZOutputMemo->Lines->Add(s);
    s.sprintf("bNumInterfaces: %d",cfg.bNumInterfaces); EZOutputMemo->Lines->Add
(s);
    s.sprintf("bConfigurationValue: %d",cfg.bConfigurationValue); EZOutputMemo-
>Lines->Add(s);
    s.sprintf("iConfiguration: %d",cfg.iConfiguration); EZOutputMemo->Lines->Add
(s);
    s.sprintf("bmAttributes: 0x%x",cfg.bmAttributes); EZOutputMemo->Lines->Add(s);
    s.sprintf("MaxPower: %d",cfg.MaxPower); EZOutputMemo->Lines->Add(s);
    EZOutputMemo->Lines->Add("*****");

    for (int i=0; i<cfg.AltInterfaces; i++) {
        CCyUSBInterface *ifc = cfg.Interfaces[i];
        EZOutputMemo->Lines->Add("Interface Descriptor: " + String(i+1));
        EZOutputMemo->Lines->Add("-----");
        s.sprintf("bLength: 0x%x",ifc->bLength); EZOutputMemo->Lines->Add(s);
        s.sprintf("bDescriptorType: %d",ifc->bDescriptorType); EZOutputMemo->Lines-
>Add(s);
        s.sprintf("bInterfaceNumber: %d",ifc->bInterfaceNumber); EZOutputMemo->Lines-
>Add(s);
```

```

        s.sprintf("bAlternateSetting: %d", ifc->bAlternateSetting); EZOutputMemo->Lines->Add(s);
        s.sprintf("bNumEndpoints: %d", ifc->bNumEndpoints); EZOutputMemo->Lines->Add(s);
        s.sprintf("bInterfaceClass: %d", ifc->bInterfaceClass); EZOutputMemo->Lines->Add(s);

        for (int e=0; e<ifc->bNumEndpoints; e++) {
            CCyUSBEndPoint *ept = ifc->EndPoints[e+1];
            EZOutputMemo->Lines->Add("EndPoint Descriptor: " + String(e+1));
            EZOutputMemo->Lines->Add("-----");
            s.sprintf("bLength: 0x%x", ept->DscLen); EZOutputMemo->Lines->Add(s);
            s.sprintf("bDescriptorType: %d", ept->DscType); EZOutputMemo->Lines->Add(s);
            s.sprintf("bEndpointAddress: 0x%x", ept->Address); EZOutputMemo->Lines->Add(s);

            s.sprintf("bmAttributes: 0x%x", ept->Attributes); EZOutputMemo->Lines->Add(s);

            s.sprintf("wMaxPacketSize: %d", ept->MaxPktSize); EZOutputMemo->Lines->Add(s);

            s.sprintf("bInterval: %d", ept->Interval); EZOutputMemo->Lines->Add(s);
            EZOutputMemo->Lines->Add("*****");
        }
    }
}

```

12.1 bAlternateSetting

bAlternateSetting

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBInterface::bAlternateSetting

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bAlternateSetting** field from the currently selected interface's interface descriptor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.2 bAltSettings

bAltSettings

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBInterface::bAltSettings

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the number of valid alternate interface settings exposed by this interface.

For an interface that exposes a primary interface and two alternate interfaces, this value would be 3.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

See [CCyUSBDevice::AltIntfcCount\(\)](#).

12.3 bDescriptorType

bDescriptorType

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBInterface::bDescriptorType

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bDescriptorType** field of the USB_INTERFACE_DESCRIPTOR structure that was passed to the interface object's constructor. (Because the passed descriptor was an interface descriptor, this value should always be 0x04.)

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.4 CCyUSBInterface()

CCyUSBInterface()

[Top](#) [Previous](#) [Next](#)

CCyUSBInterface::CCyUSBInterface:(HANDLE
h, USB_INTERFACE_DESCRIPTOR
pIntfcDescriptor)

[Previous](#) [Top](#) [Next](#)

Description

This is the constructor for the [CCyUSBInterface](#) class.

It reads [bNumEndpoint](#) endpoint descriptors and creates the appropriate type of endpoint object for each one, saving a pointer to each new endpoint in the class's [EndPoints](#) array.

12.5 CCyUSBInterface()

CCyUSBInterface()

[Top](#) [Previous](#) [Next](#)

CCyUSBInterface::CCyUSBInterface:(
CCyUSBInterface& intfc)

[Previous](#) [Top](#) [Next](#)

Description

This is the *copy* constructor for the [CCyUSBInterface](#) class.

This constructor copies all of the simple data members of **intfc**. It then walks through **intfc**'s [EndPoints](#) array, making copies of every endpoint referenced there and storing pointers to the new copies in its own EndPoints array.

You should usually not call the copy constructor explicitly. It is called by the copy constructor for [CCyUSBConfig](#) when [CCyUSBDevice::GetUSBConfig\(\)](#) is called.

The below example shows how you could create a copy of the first interface exposed by a device.

Example

```
CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

CCyUSBConfig cfg = USBDevice->GetUSBConfig(0);

CCyUSBInterface iface = new CCyUSBInterface(*cfg.Interfaces[0]);
```

12.6 bInterfaceClass

bInterfaceClass

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBInterface::bInterfaceClass

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bInterfaceClass** field from the currently selected interface's interface descriptor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.7 bInterfaceNumber

bInterfaceNumber

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBInterface::bInterfaceNumber

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bInterfaceNumber** field from the currently selected interface's interface descriptor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.8 bInterfaceProtocol

bInterfaceProtocol

[Top](#) [Previous](#) [Next](#)

UCHAR CCyUSBInterface::bInterfaceProtocol

[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bInterfaceProtocol** field from the currently selected interface's interface descriptor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.9 bInterfaceSubClass

bInterfaceSubClass

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBInterface::bInterfaceSubClass**[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bInterfaceSubClass** field from the currently selected interface's interface descriptor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.10 bLength

bLength

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBInterface::bLength**[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bLength** field from the currently selected interface's interface descriptor. It indicates the length of the interface descriptor. (Because the descriptor is an interface descriptor, this value should always be 0x09.)

12.11 bNumEndpoints

bNumEndpoints

[Top](#) [Previous](#) [Next](#)**UCHAR CCyUSBInterface::bNumEndpoints**[Previous](#) [Top](#) [Next](#)

Description

This data member contains the **bNumEndpoints** field from the currently selected interface's interface descriptor. It indicates how many endpoint descriptors are returned for the selected interface.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

12.12 EndPoints

EndPoints

[Top](#) [Previous](#) [Next](#)

CCyUSBEndPoint* CCyUSBInterface::EndPoints
[MAX_ENDPTS]

[Previous](#) [Top](#) [Next](#)

Description

This is the key data member of the CCyUSBInterface class. It is an array of pointers to CCyUSBEndPoint objects that represent the endpoint descriptors returned, by the device, for the interface.

The [CCyUSBDevice::EndPoints](#) member is actually a pointer to the currently selected interface's EndPoints array.

Example

```
// This code lists all the endpoints reported
// for all the interfaces reported
// for all the configurations reported
// by the device.

CCyUSBDevice *USBDevice = new CCyUSBDevice(Handle);

String s;

for (int c=0; c<USBDevice->ConfigCount(); c++) {
    CCyUSBConfig cfg = USBDevice->GetUSBConfig(c);

    s.sprintf("bLength: 0x%x",cfg.bLength); EZOutputMemo->Lines->Add(s);
    s.sprintf("bDescriptorType: %d",cfg.bDescriptorType); EZOutputMemo->Lines->Add
(s);
    s.sprintf("wTotalLength: %d (0x%x)",cfg.wTotalLength,cfg.wTotalLength);
EZOutputMemo->Lines->Add(s);
    s.sprintf("bNumInterfaces: %d",cfg.bNumInterfaces); EZOutputMemo->Lines->Add
(s);
    s.sprintf("bConfigurationValue: %d",cfg.bConfigurationValue); EZOutputMemo-
>Lines->Add(s);
    s.sprintf("iConfiguration: %d",cfg.iConfiguration); EZOutputMemo->Lines->Add
(s);
    s.sprintf("bmAttributes: 0x%x",cfg.bmAttributes); EZOutputMemo->Lines->Add(s);
    s.sprintf("MaxPower: %d",cfg.MaxPower); EZOutputMemo->Lines->Add(s);
    EZOutputMemo->Lines->Add("*****");

    for (int i=0; i<cfg.AltInterfaces; i++) {
        CCyUSBInterface *ifc = cfg.Interfaces[i];
        EZOutputMemo->Lines->Add("Interface Descriptor:" + String(i+1));
        EZOutputMemo->Lines->Add("-----");
        s.sprintf("bLength: 0x%x",ifc->bLength); EZOutputMemo->Lines->Add(s);
        s.sprintf("bDescriptorType: %d",ifc->bDescriptorType); EZOutputMemo->Lines-
>Add(s);
```



```

        s.printf("bInterfaceNumber: %d", ifc->bInterfaceNumber); EZOutputMemo->Lines-
>Add(s);
        s.printf("bAlternateSetting: %d", ifc->bAlternateSetting); EZOutputMemo-
>Lines->Add(s);
        s.printf("bNumEndpoints: %d", ifc->bNumEndpoints); EZOutputMemo->Lines->Add
(s);
        s.printf("bInterfaceClass: %d", ifc->bInterfaceClass); EZOutputMemo->Lines-
>Add(s);

        for (int e=0; e<ifc->bNumEndpoints; e++) {
            CCyUSBEndPoint *ept = ifc->EndPoints[e+1];
            EZOutputMemo->Lines->Add("EndPoint Descriptor: " + String(e+1));
            EZOutputMemo->Lines->Add("-----");
            s.printf("bLength: 0x%x", ept->DscLen); EZOutputMemo->Lines->Add(s);
            s.printf("bDescriptorType: %d", ept->DscType); EZOutputMemo->Lines->Add(s);
            s.printf("bEndpointAddress: 0x%x", ept->Address); EZOutputMemo->Lines->Add
(s);
            s.printf("bmAttributes: 0x%x", ept->Attributes); EZOutputMemo->Lines->Add
(s);
            s.printf("wMaxPacketSize: %d", ept->MaxPktSize); EZOutputMemo->Lines->Add
(s);
            s.printf("bInterval: %d", ept->Interval); EZOutputMemo->Lines->Add(s);
            EZOutputMemo->Lines->Add("*****");
        }
    }
}

```

12.13 iInterface

iInterface

[Top](#) [Previous](#)
UCHAR CCyUSBInterface::iInterface
[Previous](#) [Top](#)

Description

This data member contains the **iInterface** field from the currently selected interface's interface descriptor.

This data member exists for completeness and debugging purposes. You should normally never need to access this data member.

Index

- D -

Data Transfers

Asynchronous Transfers 64

Synchronous Transfers 73

Descriptors

Configuration 41

Device 41

Endpoint 61

Interface 74

Listing Descriptor Contents 55

Devices

Finding USB Devices 28

Manufacturer 48

Product 50

Serial Number 51

- E -

Endpoints 40

Bulk Endpoints 31

Control Endpoints 36

Interrupt Endpoints 44

Isochronous Endpoints 47

- I -

Interfaces

Alternate Interfaces 52