J1

3V3	1	3V3
3V3	2	3V3
	3	
	4	
I2S_LRCK	5	I2S_LRCK
I2S_DIN	6	I2S_DIN
I2S_BCK	7	I2S_BCK
	8	
SD_CS	9	SD_CS
SPI_MOSI	10	SPI_MOSI
SPI_MISO	11	SPI_MISO
SPI_SCK	12	SPI_SCK
	13	
	14	
TFT_DC	15	TFT_DC
TFT_RST	16	TFT_RST
TFT_CS	17	TFT_CS
	18	
	19	
	20	
5V	21	5V
GND	22	GND

ESP32-S3 J1 (gauche)

J3

GND	1	GND
	2	
	3	
VBAT_ADC	4	VBAT_ADC
	5	
BTN_MENU	6	BTN_MENU
BTN_PLAY	7	BTN_PLAY
ENC_A	8	ENC_A
ENC_B	9	ENC_B
ENC_SW	10	ENC_SW
	11	
	12	
	13	
	14	
	15	
	16	
	17	
	18	
	19	
	20	
GND	21	GND
GND	22	GND

ESP32-S3 J3 (droite)

J4

3V3	1	3V3
GND	2	GND
TFT_CS	3	TFT_CS
TFT_RST	4	TFT_RST
TFT_DC	5	TFT_DC
SPI_MOSI	6	SPI_MOSI
SPI_SCK	7	SPI_SCK
3V3	8	3V3
	9	
	10	
	11	
	12	
	13	
	14	

ILI9341 VCC GND CS RST DC MOSI SCK LED(=3V3) SDO ...

J5

SD_CS	1	SD_CS
SPI_MOSI	2	SPI_MOSI
SPI_MISO	3	SPI_MISO
SPI_SCK	4	SPI_SCK

SD du module ecran

J6

3V3	1	3V3
GND	2	GND

alim breakout microSD: 3V3 GND

J7

GND	1	GND
I2S_BCK	2	I2S_BCK
I2S_DIN	3	I2S_DIN
I2S_LRCK	4	I2S_LRCK
GND	5	GND
3V3	6	3V3

PCM5102A: SCK BCK DIN LCK GND VIN

ENC1

ENC_A	A	ENC_A
ENC_B	B	ENC_B
GND	C	GND
ENC_SW	S1	ENC_SW
GND	S2	GND

EC11

SW1

BTN_MENU	1	BTN_MENU
GND	2	GND

MENU

SW2

BTN_PLAY	1	BTN_PLAY
GND	2	GND

PLAY

J8

BATP	1	BATP
GND	2	GND

LiPo JST-PH

J9

BATP	1	BATP
GND	2	GND

TP4056 B+ B-

J10

TPOUT	1	TPOUT
GND	2	GND

TP4056 OUT+ OUT-

JP1

TPOUT	1	TPOUT
VSW	2	VSW

INTER

J11

VSW	1	VSW
GND	2	GND

MT3608 IN+ IN-

J12

5VB	1	5VB
GND	2	GND

MT3608 OUT+ OUT-

D1

5V	1	5V
5VB	2	5VB

1N5819

R4

VSW	1	VSW
VBAT_ADC	2	VBAT_ADC

100k

R5

VBAT_ADC	1	VBAT_ADC
GND	2	GND

100k

C1

5V	1	5V
GND	2	GND

470uF

C2

VBAT_ADC	1	VBAT_ADC
GND	2	GND

100nF

C3

3V3	1	3V3
GND	2	GND

10uF

C4

3V3	1	3V3
GND	2	GND

100nF

ESP32-S3-DevKitC-1 N16R8 + ILI9341 + SD SPI + PCM5102A

Sheet: /
File: ipod_v7.kicad_sch

Title: iPod OK Computer – carte de test V7

Size: A2	Date:	**Rev:**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/1