

C-band telemetry transmitter

(V) Variable Rate, auto-scaling of deviation and filter BW

(C) 4400 MHz to 4950 MHz Tuning in 0.5 MHz steps

(R) RS-422, 120 ohms differential

(2) RS-232, 57,600 baud rate

(1) ARTM Tier 0 (PCM/FM), 0.05 - 14 Mbps: YES

(1) ARTM Tier I (SOQPSK-TG), 0.1 - 28 Mbps: YES

(0) ARTM Tier II (Multi-h CPM), 0.1 - 28 Mbps: NO

(0) BPSK, QPSK, OQPSK 0.05 - 14 Mbps: NO

(20) RF Output: 20 Watts (+43.0 dBm Minimum)

(54) Pin Out Configuration

(07BN) Package: 2" x 3" x 1.11" = 6.66 inches³

Primary Connector: Female MDM-15

RF Output Connector: SMA Female

Input Power: On Primary

Options selected:

(PM) Parallel Mode Select Option

(DSWBX) Parallel frequency and mode switching via digital switchbox. The switchbox can also select LDPC codes when either the -LD or -LD6 option is ordered. Includes switchbox and wiring harness to connect to MDM-9 on accessory board

(P9) MDM-9 on accessory board

(PF) Parallel Frequency Select Option

(DP) Dual Power (64 settings, user selects one for "high" and one for "low," chosen via baseband connector pin)

Primary Connector (Female MDM-15) Pins

1. DC Power In
2. DC Power Return
3. No Connection
4. Differential Clock Positive
5. Differential Data Positive
6. Serial Control Ground
7. RF On/Off
8. Serial Control Reply from Transmitter
9. DC Power In
10. DC Power Return
11. No Connection
12. Differential Clock Negative
13. Differential Data Negative
14. Dual Power
15. Serial Control Input to Transmitter

Other Connector Male MDM-9 Pins

1. Ground
2. XDC Control Ground (only with option XD)
3. CH1 XDC Control Out (only with option XD)
4. No Connection
5. Transmitter Replies to Switchbox (only with options PF/PM)
6. 3.3VDC + Output
7. No Connection
8. CH2 XDC Control Out (only with option XD)
9. Switchbox Commands to Transmitter (only with options PF/PM)