NoC-Lab Research Consortium

Network-on-Chip and Advanced Interconnects

Architecture, Co-Design & Emerging Frontiers

November 5, 2026

Springer Nature

To the researchers, architects, and silicon engineers

whose relentless curiosity pushes the physical boundaries of on-chip communication,

and to the students who will design the trillion-transistor computing systems of tomorrow.

Preface

For nearly four decades, the computing revolution drew its momentum from the harmonic cadence of Moore's Law and Dennard Scaling: transistors shrank, clock frequencies accelerated into the multi-gigahertz regime, and single-threaded execution performance soared without threatening silicon thermal limits. Around 2005, the irreversible breakdown of Dennard scaling halted clock frequency scaling, forcing a historic pivot toward spatial parallelism: multi-core processors, massively parallel graphics processors, and heterogeneous Systems-on-Chip (SoCs).

Yet scaling compute elements from tens to hundreds, and now thousands of cores on a single die or across 2.5D/3D multi-chiplet assemblies, immediately collided with an unyielding physical reality: the **interconnect crisis**. Global shared multi-drop buses collapsed under quadratic RC wire delay and serialization contention; full crossbar matrices exploded in $O(N^2)$ silicon area and routing track congestion; and deep-submicron copper interconnects below 14 nm succumbed to severe electron scattering and resistive degradation.

The **Network-on-Chip (NoC)** paradigm answered this crisis by transposing packet-switched networking principles directly onto silicon. Today, on-chip and die-to-die communication fabrics form the nervous system of modern computing—from mobile application processors and high-performance server SoCs to wafer-scale accelerators and neuromorphic tensor processors.

Scope and Structure of This Book

This textbook offers a rigorous, first-principles exploration of on-chip and multi-chiplet interconnection networks. Rather than treating interconnects as abstract graph topologies, this volume bridges the chasm between physical silicon reality, router microarchitecture, mathematical deadlock theory, and emerging technology frontiers.

The book is organized into five cohesive parts:

- **Part I: Foundations & Router Microarchitecture (Chapters 1–3)** establishes the physical interconnect crisis, mathematical delay formulations, switching techniques, credit and token flow control, and pipelined router microarchitecture with virtual channel allocation and crossbar arbitration.
- **Part II: Topologies, Routing & Deadlock Freedom (Chapters 4–5)** investigates direct, indirect, and high-radix networks, Dally's channel dependency graph (CDG) theorems, Duato's adaptive routing theory, and turn models.
- **Part III: Physical Constraints: Power, Thermal & Reliability (Chapters 6–7)** addresses dark silicon dynamics, voltage/frequency scaling, compact thermal RC modeling, hotspot mitigation, and fault-tolerant routing.
- **Part IV: Advanced Packaging, 3D NoC & Chiplets (Chapters 8–9)** explores through-silicon via (TSV) vertical architectures, 2.5D silicon interposers, and the Universal Chiplet Interconnect Express (UCIe) die-to-die standard.
- **Part V: Emerging Frontiers: Optical, Wireless, Security & AI (Chapters 10–12)** covers silicon photonic interconnects (ONoC), RF/wireless communication (WNoC), hardware security against side-channel and denial-of-service attacks, and domain-specific interconnects for large language models and spiking neural networks.

Grounding in 542+ Curated Research Papers

Every theoretical formulation, architectural trade-off, and silicon case study in this monograph is grounded directly in our curated corpus of over 542 peer-reviewed articles from premier IEEE journals, including *IEEE Transactions on Very Large Scale Integration (VLSI) Systems* (TVLSI), *IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems* (TCAD), *IEEE Journal of Solid-State Circuits* (JSSC), and *IEEE Transactions on Circuits and Systems* (TCAS-I/II). Landmark silicon achievements—such as the 2,048-core HammerBlade SoC, the FlooNoC open-source AXI4 fabric, and the SWIFT token flow-control architecture—are dissected alongside first-principles physics.

Co-Design with the Interactive Companion Hub

To enhance pedagogy and provide hands-on experimentation, this monograph is co-designed with an interactive online platform:

NoC Learning Hub: https://network-on-chip.github.io/learning/

Each chapter links directly to interactive browser-based simulators, including the 2D Mesh Routing Visualizer, Arbiter Arena, Credit Commander, and

UCIe Protocol Analyzer, accompanied by multi-tier assessment engines and executable Verilog/Python code repositories.

The NoC-Lab Research Consortium
November 2026

Contents

Part I Foundations & Router Microarchitecture

1 The Multi-Core Communication Crisis & Interconnect Physics . . . 3
1.1 The Breakdown of Dennard Scaling and the Multi-Core Pivot . . 3
1.2 The Failure of Shared Multi-Drop Buses . . . 4
1.2.1 Capacitive Loading & Elmore Wire Delay . . . 4
1.2.2 The Serialization Contention Bottleneck . . . 5
1.3 Sub-10nm Interconnect Physics & Wire Scaling . . . 6
1.3.1 The Mayadas-Shatzkes & Fuchs-Sondheimer Scattering Models . . . 6
1.4 The Monolithic Crossbar and Its Quadratic Area Explosion . . . 7
1.5 The Network-on-Chip Paradigm: Packet-Switched Modular Interconnects . . . 8
1.6 Industrial Case Studies: From 48 Cores to 2,048 Cores . . . 8
1.6.1 The 2,048-Core HammerBlade Manycore SoC (12nm FinFET) . . . 8
1.7 Interactive Lab & Hands-on Challenges . . . 10
1.8 Checkpoint Assessment . . . 11

2 Switching Techniques, Flow Control & Buffer Management . 13
2.1 The Data Granularity Hierarchy: Messages, Packets, Flits & Phits . . . 13
2.2 Silicon Network Interface: The AXI4 / NoC Protocol Translation 14
2.3 Mathematical Latency Analysis of Switching Techniques . . . 15
2.3.1 Store-and-Forward (SAF) Switching . . . 15
2.3.2 Virtual Cut-Through (VCT) Switching . . . 15
2.3.3 Wormhole (WH) Switching . . . 16
2.4 Lossless Flow Control Mechanisms . . . 17
2.4.1 Credit-Based Flow Control & The Credit Turnaround Loop . . . 17

2.5 Alternative Flow Control: Token Flow Control in the SWIFT NoC . . . 17
2.6 Interactive Lab & Hands-on Challenges . . . 19
2.7 Checkpoint Assessment . . . 19

3 High-Performance Router Microarchitecture & Arbitration . . . 21
3.1 The Canonical Virtual-Channel Router Pipeline . . . 21
3.2 Advanced Pipeline Compression & Router Bypassing . . . 22
3.2.1 Lookahead Routing & Speculative Switch Allocation . . . 23
3.2.2 Buffer Reservation Scheduling: BuffeRS (TCAD 2026) . . . 23
3.3 Asynchronous Router Architectures: HyPA (TVLSI 2026) . . . 23
3.4 Single-Cycle Multi-Hop Traversal (SMART / SHARP) . . . 23
3.5 Crossbar Arbitration Theory & Matching Algorithms . . . 25
3.5.1 The Matrix Arbiter: Strict $O(1)$ Hardware LRU . . . 25
3.5.2 McKeown's iSLIP Iterative Matching Algorithm . . . 25
3.6 Interactive Lab & Hands-on Challenges . . . 26
3.7 Checkpoint Assessment . . . 26

Part II Topologies, Routing & Deadlock Freedom

4 Direct, Indirect & High-Radix Interconnect Topologies . . . 29
4.1 Interconnect Graph Theory and Formal Performance Metrics . . . 29
4.2 Direct Topologies: Mesh, Torus, and the Folded Torus . . . 31
4.2.1 2D Mesh Networks . . . 31
4.2.2 2D Torus and the Wire Delay Dilemma . . . 31
4.2.3 The Folded Torus Invariance . . . 32
4.3 Indirect Multistage Interconnects: Clos and Fat-Trees . . . 32
4.3.1 Clos Networks and Non-Blocking Theorems . . . 32
4.3.2 Fat-Trees and Constant Bisection Bandwidth . . . 32
4.4 High-Radix Interconnects: Flattened Butterfly and Dragonfly . . . 33
4.4.1 Flattened Butterfly . . . 33
4.4.2 The Dragonfly Topology and UGAL Routing . . . 33
4.5 Application-Specific Synthesis & Cascaded Crossbars . . . 33
4.5.1 MIRO Synthesis of Cascaded Crossbar Networks . . . 33
4.5.2 Switch Merger and Partitioning Algorithms . . . 34
4.6 Silicon Floorplanning Limits: The Passas Radix-128 Proof . . . 34
4.7 Quantitative Topology Evaluation Matrix . . . 36
4.8 Exercises and Review Questions . . . 37

A Open-Source NoC Frameworks, RTL Repositories & PDKs . . . 39
A.1 Synthesizable Verilog & SystemVerilog NoC Codebases . . . 39
A.2 Open-Source Physical Design PDKs . . . 39

Solutions to Checkpoint Questions . . . 41
References . . . 43

Index 45

List of Acronyms

2D/3D	Two-/Three-Dimensional
AMBA	Advanced Microcontroller Bus Architecture
AXI4	Advanced eXtensible Interface 4
BEP	Bit Error Probability
BGA	Ball Grid Array
CDG	Channel Dependency Graph
CMP	Chip Multiprocessor
CRC	Cyclic Redundancy Check
D2D	Die-to-Die
DMA	Direct Memory Access
DVFS	Dynamic Voltage and Frequency Scaling
Flit	Flow Control Unit
GALS	Globally Asynchronous Locally Synchronous
HOL	Head-of-Line (Blocking)
HPCA	High-Performance Computer Architecture
IP	Intellectual Property
IRDS	International Roadmap for Devices and Systems
ISCA	International Symposium on Computer Architecture
ITRS	International Technology Roadmap for Semiconductors
JSSC	IEEE Journal of Solid-State Circuits
LLM	Large Language Model
MPSoC	Multi-Processor System-on-Chip
NI	Network Interface
NoC	Network-on-Chip
OCSSI	On-Chip Source-Synchronous Interconnect
ONoC	Optical Network-on-Chip
PE	Processing Element
Phit	Physical Unit

PMA	Physical Medium Attachment
PPA	Power, Performance, and Area
PUF	Physically Unclonable Function
QoS	Quality of Service
RC	Route Computation
RoB	Reorder Buffer
RTT	Round-Trip Time
SA	Switch Allocation
SAF	Store-and-Forward (Switching)
SCC	Single-Chip Cloud Computer
SNN	Spiking Neural Network
SoC	System-on-Chip
ST	Switch Traversal
TCAD	IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems
TCAS	IEEE Transactions on Circuits and Systems
TSV	Through-Silicon Via
TVLSI	IEEE Transactions on Very Large Scale Integration Systems
UCIe	Universal Chiplet Interconnect Express
VA	Virtual Channel Allocation
VC	Virtual Channel
VCT	Virtual Cut-Through (Switching)
WH	Wormhole (Switching)
WNoC	Wireless Network-on-Chip
WSC	Wafer-Scale Computing

Part I
Foundations & Router Microarchitecture

Chapter 1
The Multi-Core Communication Crisis & Interconnect Physics

Abstract For over three decades, semiconductor compute performance accelerated through Dennard scaling and monolithic bus interconnects. Around 2005, the physical collapse of Dennard scaling halted clock frequency scaling, forcing a historic pivot toward horizontal core parallelism. However, scaling processing core counts immediately exposed the interconnect crisis: shared multi-drop buses suffer from cubic Elmore delay scaling and severe serialization bottlenecks; centralized crossbars explode with quadratic silicon area and routing congestion; and deep-submicron copper lines undergo severe electron scattering under the Mayadas-Shatzkes effect. This chapter establishes the physical foundations of on-chip wire scaling, mathematically analyzes bus and crossbar limitations, and introduces the Network-on-Chip (NoC) paradigm as the scalable packet-switched backbone of modern manycore processors, highlighted through silicon case studies including the 2,048-core HammerBlade SoC.

1.1 The Breakdown of Dennard Scaling and the Multi-Core Pivot

For over three decades, the semiconductor industry advanced along the dual trajectories of **Moore's Law** (transistor density doubling approximately every 18–24 months) and **Dennard Scaling** [6] (constant power density through proportional scaling of supply voltage V_{dd}, threshold voltage V_{th}, and physical oxide thickness t_{ox}). Under classical Dennard scaling:

$$\text{Power Density} = \frac{P_{active}}{\text{Area}} \propto \frac{C \cdot V_{dd}^2 \cdot f}{1/s^2} \approx \text{Constant} \tag{1.1}$$

where $s \approx 1.4$ is the per-generation linear scaling factor. Because operating frequency could be increased by $\approx 40\%$ each generation without increasing power dissipation per unit silicon area, single-threaded performance grew exponentially without encountering thermal catastrophic failure.

Around 2004–2005, at the 90 nm and 65 nm process nodes, Dennard scaling suffered an irreversible collapse. As gate oxide thickness reached atomic dimensions ($t_{ox} \leq 1.2$ nm, merely 4–5 silicon dioxide monolayers), **quantum mechanical direct tunneling** through the gate dielectric surged exponentially:

$$J_{tunnel} \approx A \cdot \left(\frac{V_{ox}}{t_{ox}}\right)^2 \exp\left(-\frac{B \cdot [1-(1-V_{ox}/\Phi_B)^{3/2}]}{V_{ox}/t_{ox}}\right) \tag{1.2}$$

At the same time, sub-threshold leakage current I_{sub} prevented further aggressive reductions of the supply voltage V_{dd}, as the threshold voltage V_{th} could not be reduced without causing unacceptable static standby power dissipation:

$$I_{sub} = \mu_0 C_{ox} \frac{W}{L}(m-1)V_T^2 \exp\left(\frac{V_{gs}-V_{th}}{mV_T}\right)\left(1-\exp\left(-\frac{V_{ds}}{V_T}\right)\right) \tag{1.3}$$

where $V_T = \frac{k_B T}{q} \approx 26$ mV at 300 K, and m is the sub-threshold swing factor ($m \approx 1.1$–1.4). Consequently, chip architects struck the unyielding **Power Wall** ($\approx$ 100–130 W/cm^2 for air-cooled packaging). Increasing the clock frequency beyond 3.5–4.0 GHz became thermally untenable.

To maintain compute throughput growth, processor design executed a historic pivot from *frequency scaling* to *spatial concurrency*: multi-core processors, Chip Multiprocessors (CMPs), and Multi-Processor Systems-on-Chip (MPSoCs). However, scaling the number of processing elements from dual-core to tens, hundreds, and thousands of cores immediately triggered an existential crisis in **on-chip interconnect physical design**.

1.2 The Failure of Shared Multi-Drop Buses

In early Systems-on-Chip, intellectual property (IP) blocks (CPUs, DSPs, DMA engines, SRAM banks) communicated through shared multi-drop buses such as ARM AMBA (AHB/APB), IBM CoreConnect, or Wishbone. While shared buses are simple and cost-effective for small SoCs ($N \leq 4$–8 masters), they collapse under severe physical and architectural bottlenecks as core counts grow.

1.2.1 Capacitive Loading & Elmore Wire Delay

A shared bus consists of long physical metal traces spanning across the silicon die. Every connected master and slave attaches an input/output transceiver tap to the shared wire. According to the **Elmore Delay Model** [8], the propagation delay τ_{bus} of a distributed RC line loaded by N capacitive taps is:

Table 1.1 Physical Interconnect Scaling Across Core Counts (Die Edge: 12 mm, Process: 12nm FinFET, $r_{wire} = 800\ \Omega$/mm, $c_{wire} = 0.18$ pF/mm, $c_{tap} = 8$ fF)

Cores (N)	Bus Delay (ps)	Max Bus Freq	Aggregate Bus BW	Crossbar Switches	2D Mesh Bisection BW
2	9,044 ps	55.3 MHz	0.88 GB/s	4	128 GB/s
4	9,129 ps	54.8 MHz	0.88 GB/s	16	128 GB/s
8	9,298 ps	53.8 MHz	0.86 GB/s	64	192 GB/s
16	9,638 ps	51.9 MHz	0.83 GB/s	256	256 GB/s
32	10,316 ps	48.5 MHz	0.78 GB/s	1,024	384 GB/s
64	11,673 ps	42.8 MHz	0.69 GB/s	4,096	512 GB/s
128	14,386 ps	34.8 MHz	0.56 GB/s	16,384	768 GB/s
256	19,814 ps	25.2 MHz	0.40 GB/s	65,536	1,024 GB/s

$$\tau_{bus} \approx 0.38 \cdot R_{wire} \cdot C_{wire} + R_{driver} \cdot \left(C_{wire} + \sum_{i=1}^{N} C_{tap,i} \right) + \sum_{i=1}^{N} R_{wire,i} \cdot C_{tap,i} \tag{1.4}$$

where:

- $R_{wire} = r_{wire} \cdot L$ is the total resistance of the global metal wire across the die ($L \approx 10$–20 mm).
- $C_{wire} = c_{wire} \cdot L$ is the distributed wire capacitance (area capacitance to substrate plus fringe capacitance).
- $C_{tap,i}$ is the input/output capacitance of the i-th master/slave transceiver tap.
- R_{driver} is the equivalent output resistance of the driving transistor.

Because every attached core adds capacitive load ($C_{taps} = N \cdot C_{tap}$), the total capacitance scales linearly with core count ($C_{total} \propto N$). Furthermore, because the wire length L scales with the die perimeter ($L \propto \sqrt{N}$), the intrinsic wire RC product grows with the square of the die dimension:

$$\tau_{bus} \propto R_{wire} \cdot C_{total} \propto (\sqrt{N}) \cdot (N + \sqrt{N}) \propto N^{3/2} \tag{1.5}$$

Consequently, the maximum achievable bus clock frequency ($f_{max} \approx \frac{1}{2\tau_{bus}}$) plunges precipitously. While local processor logic easily ran at 2.0–3.0 GHz, global shared buses were throttled to 200–400 MHz.

1.2.2 The Serialization Contention Bottleneck

A shared bus is a **single shared transmission medium**. At any given clock cycle, the centralized bus arbiter can grant bus access to **exactly one master**:

- **Fixed Aggregate Bandwidth**: $BW_{agg} = W \times f_{bus}$, where W is bus width (e.g., 64 or 128 bits) and f_{bus} is bus clock frequency.




Fig. 1. Technology scaling of on-chip wire resources based on IDRS reports [8] for 2–14 nm and [9] for 22–65 nm.

Fig. 1.1 Technology scaling of on-chip wire resources based on ITRS/IRDS reports for 2–14 nm and 22–65 nm nodes. While transistor delay decreases exponentially, global wire delay surges. [Reproduced from: T. Fischer, M. Rogenmoser, T. Benz, F. K. Gürkaynak, and L. Benini, "FlooNoC: A 645-Gb/s/link 0.15-pJ/B/hop Open-Source NoC With Wide Physical Links and End-to-End AXI4 Parallel Multistream Support," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 33, no. 4, pp. 1094–1107, Apr. 2025 [9]. © 2025 IEEE]

- **Per-Core Bandwidth Starvation**: $BW_{per_core} \leq \frac{W \times f_{bus}}{N}$. As core count N increases, per-core bandwidth asymptotically approaches zero.
- **Arbitration Scalability**: Centralized round-robin or matrix arbiters require $O(N)$ logic depth, transforming grant generation into a critical-path timing bottleneck.

1.3 Sub-10nm Interconnect Physics & Wire Scaling

The physical crisis of global wiring is exacerbated by the physics of deep-submicron copper interconnects [11]. In technology nodes below 14 nm, 7 nm, and 3 nm, interconnect resistance does not scale inversely with cross-sectional area.

1.3.1 The Mayadas-Shatzkes & Fuchs-Sondheimer Scattering Models

In bulk copper at room temperature, the electron mean free path is $\lambda_0 \approx 39.0$ nm. When the physical width w of an on-chip metal wire shrinks below $2\lambda_0 \approx 80$ nm, two scattering mechanisms cause the effective resistivity ρ_{eff} to surge dramatically above the bulk value ($\rho_{bulk} \approx 1.68 \times 10^{-8}\ \Omega \cdot \text{m}$):

1. **Surface Scattering (Fuchs-Sondheimer Model)**: Electrons reflect diffusely off the outer interfaces of the wire:

$$\frac{\rho_{FS}}{\rho_{bulk}} = 1 + \frac{3}{8\kappa}(1-p) \tag{1.6}$$

where $\kappa = \frac{w_{eff}}{\lambda_0}$ is the normalized wire dimension and $p \in [0,1]$ is the specularity parameter ($p \approx 0.2$ for realistic barrier interfaces).

2. **Grain Boundary Scattering (Mayadas-Shatzkes Model)** [20]: Nanoscale copper recrystallizes into small grains with average grain diameter $d \approx w_{eff}$. Electrons scatter at grain boundaries:

$$\frac{\rho_{MS}}{\rho_{bulk}} = \frac{1}{3\left[\frac{1}{3} - \frac{\alpha}{2} + \alpha^2 - \alpha^3 \ln\left(1 + \frac{1}{\alpha}\right)\right]} \tag{1.7}$$

where $\alpha = \frac{\lambda_0}{d}\frac{R}{1-R}$, with $R \approx 0.3$–0.5 representing the grain boundary reflection coefficient.

3. **Diffusion Barrier Liner Encroachment**: Copper electromigration requires high-resistivity diffusion liners (Ta/TaN, Co, Ru) of thickness $t_{barrier} \approx$ 1.0–1.5 nm. Because the liner does not scale down proportionally with the wire trench, the conductive copper cross-sectional area A_{Cu} shrinks much faster than total wire trench area:

$$A_{Cu} = (w - 2t_{barrier}) \cdot (h - t_{barrier}), \qquad \rho_{total} = \rho_{eff} \cdot \left(\frac{w \cdot h}{A_{Cu}}\right) \tag{1.8}$$

At the 3 nm node ($w \approx 10$ nm), the effective copper resistivity exceeds 15× bulk copper, turning long global wires into unbearable thermal, resistance, and latency bottlenecks.

1.4 The Monolithic Crossbar and Its Quadratic Area Explosion

To avoid the serialized contention of a single shared bus, architects initially considered a full centralized crossbar switch connecting N masters directly to M slaves. While a crossbar allows non-interfering parallel communication between disjoint pairs of masters and slaves, its hardware complexity scales quadratically:

$$\text{Crosspoints} = N \times M \approx O(N^2), \qquad \text{Wiring Tracks} = (N+M) \times W_{data_width} \approx O(N) \tag{1.9}$$

For an MPSoC with $N = 64$ cores, a full crossbar requires $64 \times 64 = 4,096$ crosspoint multiplexer switches and $128 \times 128 = 16,384$ wires crossing a central silicon layout area, causing severe layout congestion, routing track starvation, and parasitic capacitive coupling crosstalk. A full crossbar switch is physically viable only for small clusters ($N \leq 4$–8 cores).

1.5 The Network-on-Chip Paradigm: Packet-Switched Modular Interconnects

In 2001, pioneering papers by Dally & Towles (*"Route Packets, Not Wires"* [4]) and Benini & De Micheli (*"Networks on Chips: A New SoC Paradigm"* [1]) introduced the definitive architectural solution:

The Network-on-Chip (NoC) Principle: Replace long, dedicated, unstructured global metal wires with a structured, packet-switched micro-network composed of modular routers and short, pipelined point-to-point links.

Key advantages of the NoC architecture include:

1. **Bounded Wire Lengths**: Every link connects strictly adjacent routers. The link wire length is fixed to the physical pitch of one compute tile ($L_{link} \approx 0.5$–1.5 mm), regardless of whether the chip contains 16 or 2,048 cores.
2. **Predictable Timing & Pipelining**: Because link wire delay is short and localized, routers and links can be clocked at high frequencies ($f_{clk} \approx 1.5$–2.5 GHz) without repeater insertion crises.
3. **Concurrent Multi-Hop Communication**: Multiple packets traverse non-overlapping segments of the network simultaneously, yielding aggregate throughput that scales proportionally with the network size:

$$BW_{bisection} \propto \sqrt{N} \times W_{link} \times f_{clk} \tag{1.10}$$

4. **Modularity & Silicon Reuse**: Adding processing tiles does not require redesigning the global wiring tree.

1.6 Industrial Case Studies: From 48 Cores to 2,048 Cores

To examine the real-world execution of NoC architecture in modern silicon, we analyze landmark implementations from our literature corpus:

1.6.1 The 2,048-Core HammerBlade Manycore SoC (12nm FinFET)

A landmark demonstration of extreme monolithic scaling is the **HammerBlade (HB)** processor developed by Gao et al. [10] and Davidson et al. [5].

Key architectural and physical metrics of the HammerBlade processor include:





Fig. 1. (a) BGA 2116 flip-chip packaging, (b) 11 × 9-mm die photograph, and (c) chip floorplan. BP = BlackParrot Processor [7].

Fig. 1.2 Modern monolithic manycore scaling in 12nm silicon: (a) BGA 2116 flip-chip packaging, (b) 11 × 9-mm die photograph, and (c) chip floorplan of the 2,048-core HammerBlade SoC. [Reproduced from: P. Gao et al., "HammerBlade in Silicon: A 12-nm 2048-Core RISC-V Manycore SoC With Ruche Networks," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 34, no. 7, pp. 2306–2310, July 2026 [10]. © 2026 IEEE]

- **Silicon Area**: 99 mm^2 in TSMC 12nm FinFET.
- **Compute Density**: 2,048 custom RISC-V cores organized into an array of 64 × 32 tiles.
- **Interconnect Topology**: **Ruche Network**, a wire-maximal topology overlaying nearest-neighbor 2D mesh links with long-distance multi-hop bypass express wires.
- **Clocking & Throughput**: Operating at **1.49 GHz at 0.8 V**, the NoC delivers a peak aggregate bandwidth of **2,572.6 Tb/s** and a bisection bandwidth of **53.2 Tb/s**.



	Area (um^2)	Area (%)
ICACHE	5785	21.6 %
Scratchpad	4359	16.3 %
Router FWD	**2245**	**8.4 %**
> Crossbar	452	1.7 %
> FIFO	1541	5.8 %
Router REV	**1372**	**5.1 %**
> Crossbar	230	0.9 %
> FIFO	891	3.3 %
Register Files	2789	10.4 %
ALU	356	1.3 %
FPU	2484	9.3 %
Other Logic	3453	12.9 %
Physical-only	3921	14.7 %
TOTAL	**26764**	**100.0 %**

Fig. 1.3 HammerBlade compute tile floorplan and physical area breakdown showing router cells (red) and core logic (pink). [Reproduced from: P. Gao et al., "HammerBlade in Silicon: A 12-nm 2048-Core RISC-V Manycore SoC With Ruche Networks," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 34, no. 7, pp. 2306–2310, July 2026 [10]. © 2026 IEEE]

Fig. 2. HB compute tile floorplan and its area breakdown. Router cells (red) and the core logic (pink).

Table 1.2 Evolution of Silicon Landmark Network-on-Chip Processors

Architecture	Year / Venue	Process Node	Tile Array / Cores	Peak Bisection BW	Interconnect Topology
Intel TeraFLOPS	2007 JSSC [6]	65nm Bulk	8 × 10 (80)	1.6 Tb/s	2D Mesh (5-port)
Intel 48-Core SCC	2011 JSSC [12]	45nm Bulk	6 × 4 (48)	256 Gb/s	2D Mesh (e-cube)
Theseus WSC	2025 TCAD [26]	Wafer-Scale	Wafer Grid	100+ Tb/s	2D Torus Wafer NoC
FlooNoC (Benini)	2025 TVLSI [9]	12nm Fin-FET	8 × 4 (288)	103 Tb/s	Wide AXI4 2D Mesh
HammerBlade (Gao)	2026 TVLSI [10]	12nm Fin-FET	64 × 32 (2,048)	53.2 Tb/s	Ruche Multi-Hop NoC

- **Routing Density**: Achieves **4,289 bit/mm** across higher metal layers.
- **Integration**: Leverages **On-Chip Source-Synchronous Interconnect (OCSSI)** under a Globally Asynchronous Locally Synchronous (GALS) paradigm to eliminate chip-wide clock tree skew.

1.7 Interactive Lab & Hands-on Challenges

To build an experimental understanding of interconnect trade-offs, explore the companion simulators on the **NoC Learning Hub** (https://network-on-chip.github.io/learning/):

- **2D Mesh Routing Visualizer** (https://network-on-chip.github.io/learning/interactive/visualizer/): Inject uniform random and hotspot

traffic into a 4×4 and 8×8 mesh; observe how localized point-to-point links sustain continuous throughput without centralized bus stalls.
- **Topology Titans: Graph Architect** (https://network-on-chip.github.io/learning/interactive/topology/): Synthesize 2D Mesh, 2D Torus, and Hypercube topologies within strict wire length and pin degree limits.
- **Arbiter Arena: Crossbar Clash** (https://network-on-chip.github.io/learning/interactive/arbiter/): Benchmark matrix, round-robin, and wavefront arbiters under heavy contention.

1.8 Checkpoint Assessment

1. **Question 1.1 (Tier 1: Fundamental)**: Why does the propagation delay of a shared multi-drop bus grow as $O(N^{3/2})$ to $O(N^2)$ as core count N scales, rather than remaining constant?
2. **Question 1.2 (Tier 2: Architectural Analysis)**: What is the Mayadas-Shatzkes effect, and why does it represent a critical barrier for on-chip global interconnects below 14 nm?
3. **Question 1.3 (Tier 3: Design Trade-Off)**: Why is a centralized $N \times N$ crossbar switch unacceptable for a 128-core processor, despite offering non-blocking zero-hop communication between disjoint pairs?

Detailed answers and derivations for these questions are provided in the Solutions chapter at the end of this volume.

Chapter 2
Switching Techniques, Flow Control & Buffer Management

Abstract The efficiency, latency, and area footprint of an on-chip network are fundamentally dictated by its switching and flow control architecture. This chapter explores how raw application messages are decomposed into packets, flits, and phits, and details how silicon Network Interfaces bridge industry-standard protocols such as ARM AMBA AXI4 to internal NoC channels. We develop rigorous mathematical latency formulations comparing Store-and-Forward (SAF), Virtual Cut-Through (VCT), and Wormhole switching. We analyze lossless flow control mechanisms, proving the fundamental relationship between credit turnaround loop round-trip time (RTT) and minimum buffer sizing to sustain wire-rate throughput. Finally, we examine low-power alternative flow-control architectures, featuring the SWIFT token flow-control router with flit buffer bypassing.

2.1 The Data Granularity Hierarchy: Messages, Packets, Flits & Phits

Transmitting arbitrary software data structures across silicon requires decomposing raw application payloads into structured physical transmission units. To optimize buffer utilization, minimize pipeline latency, and guarantee deadlock-free routing, NoCs establish a four-layer data abstraction hierarchy:

1. **Application Message**: The software-level unit of communication generated by a processing element or memory subsystem (e.g., a 64-byte L2/L3 cache line refill, a 16-byte cache coherence invalidation, or a 4 KB AXI4 DMA burst).
2. **Packet**: The fundamental *routing unit* of the network. A packet encapsulates destination routing coordinates (X_{dest}, Y_{dest}), virtual network priorities, transaction identifiers, and error detection checksums (CRC/parity).




Fig. 2. AXI4 NI architecture for request (AR/AW/W) and response (R/B) paths. Reads and writes are independent in AXI4, and the request/response paths are very similar in the NI and are depicted as overlapping modules. The *ordering unit* can be configured with or without reordering capabilities (i.e., *RoB* and *RoB-less*).

Fig. 2.1 AXI4 Network Interface (NI) architecture for independent request (AR/AW/W) and response (R/B) paths, with reorder buffering (RoB) and direct DMA streaming. [Reproduced from: T. Fischer, M. Rogenmoser, T. Benz, F. K. Gürkaynak, and L. Benini, "FlooNoC: A 645-Gb/s/link 0.15-pJ/B/hop Open-Source NoC With Wide Physical Links and End-to-End AXI4 Parallel Multistream Support," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 33, no. 4, pp. 1094–1107, Apr. 2025 [9]. © 2025 IEEE]

3. **Flow Control Unit (Flit)**: The fundamental *buffering and flow control allocation unit*. Router buffers allocate storage in integer multiples of flits. Flits are partitioned into:
   - **Head Flit**: Carries routing destination coordinates. It reserves output ports and downstream virtual channels.
   - **Body Flits**: Carry data payloads along the established path without re-evaluating routing tables.
   - **Tail Flit**: Signals packet completion, releasing allocated virtual channels and router state registers.
   - **Head-Tail Flit**: A single-flit packet carrying both header metadata and payload in a single clock cycle.
4. **Physical Unit (Phit)**: The number of physical bits transmitted across a router link in *exactly one clock cycle*. When link bus width equals flit width ($W_{link} = W_{flit}$), 1 Flit = 1 Phit. If flit width exceeds physical link width, a serialization ratio of $\frac{W_{flit}}{W_{link}}$ cycles per flit is incurred.

2.2 Silicon Network Interface: The AXI4 / NoC Protocol Translation

At the boundary between processing cores and the on-chip network fabric, the **Network Interface (NI)** bridges SoC protocol standards (such as ARM AMBA AXI4, OCP, or RISC-V TileLink) to the internal packetized NoC protocol.

As demonstrated in **FlooNoC** [9], modern high-performance NIs decouple independent AXI4 channels onto dedicated physical or virtual networks to prevent protocol-level deadlock:

- **Request Network**: Translates Read Address (`AR`), Write Address (`AW`), and Write Data (`W`) channels into multi-flit request packets.
- **Response Network**: Translates Read Data (`R`) and Write Response (`B`) channels into separate response packets.
- **Reorder Buffer (RoB)**: Restores in-order AXI transaction completion when packets traverse adaptive, out-of-order routing paths.

2.3 Mathematical Latency Analysis of Switching Techniques

The switching technique dictates when and how an incoming flit is forwarded from an input port to an output port. We analyze three classical switching paradigms across path length H (in hops), packet length L (in flits), physical link bandwidth W (bits/cycle), and router pipeline latency t_r (cycles/hop).

2.3.1 Store-and-Forward (SAF) Switching

In Store-and-Forward switching, a router must receive, buffer, and verify the *entire packet* before forwarding its first flit to the downstream router:

$$t_{serial} = \frac{L}{W}, \qquad T_{SAF} = H \cdot \left(t_r + \frac{L}{W} + t_{link} \right) \tag{2.1}$$

If $t_r + t_{link} \ll \frac{L}{W}$, the zero-load latency scales as:

$$T_{SAF} \approx H \cdot \frac{L}{W} \propto H \cdot L \tag{2.2}$$

This multiplicative dependence ($H \cdot L$) imposes severe latency penalties over long distances and necessitates massive SRAM buffers ($\geq L$ flits per port).

2.3.2 Virtual Cut-Through (VCT) Switching

Introduced by Kermani & Kleinrock [14], Virtual Cut-Through permits a router to forward the Head flit to the downstream router *immediately* after route computation and arbitration, without awaiting trailing flits, provided the downstream router has allocated full packet buffer space:

Table 2.1 Analytical Comparison of Switching Techniques across 8 Hops ($t_r = 2$ cycles, $t_{link} = 1$ cycle)

Packet Length	Hop Count	SAF Latency	VCT / WH Latency	Speedup VCT/WH	of Wormhole Buffer Saving	Area
4 flits	4 hops	28 cycles	15 cycles	1.87×	Baseline	
8 flits	4 hops	44 cycles	19 cycles	2.32×	50.0% saving	
16 flits	4 hops	76 cycles	27 cycles	2.81×	75.0% saving	
32 flits	4 hops	140 cycles	43 cycles	3.26×	87.5% saving	
16 flits	8 hops	152 cycles	39 cycles	3.90×	75.0% saving	
32 flits	8 hops	280 cycles	55 cycles	5.09×	87.5% saving	
64 flits	8 hops	536 cycles	87 cycles	6.16×	93.8% saving	

$$T_{VCT} = H \cdot (t_r + t_{link}) + \frac{L-1}{W} \tag{2.3}$$

Here, distance H and packet length L are **additive** $(H + L)$, cutting zero-load latency dramatically under low traffic. However, VCT still requires allocating a full packet's worth of buffering $(B \geq L)$ before granting admission.

2.3.3 Wormhole (WH) Switching

Proposed by Dally & Seitz [3], **Wormhole Switching** decouples flow control units from packet size:

> **The Wormhole Principle**: Router buffers operate at the granularity of individual **flits**, rather than entire packets. Buffer depth per virtual channel can be as small as 1 to 4 flits, completely independent of packet length L.

The zero-load latency of Wormhole switching mirrors VCT under uncongested conditions:

$$T_{WH} = H \cdot (t_r + t_{link}) + \frac{L-1}{W} \tag{2.4}$$

However, the silicon area savings are transformative: router input buffers shrink by 75% to 93% compared to SAF and VCT, as demonstrated in Table 2.1.

2.4 Lossless Flow Control Mechanisms

Because silicon buffers are finite, on-chip networks must implement **lossless flow control** to guarantee zero flit drops.

2.4.1 Credit-Based Flow Control & The Credit Turnaround Loop

Credit-based flow control operates via an upstream ‘credit_counter‘ initialized to receiver buffer capacity B. Transmission decrements the counter; receiving a credit pulse increments it. The total Round-Trip Time (RTT) of the credit turnaround loop is:

$$RTT = t_{tx_proc} + t_{flight_fwd} + t_{rx_proc} + t_{flight_credit} \tag{2.5}$$

For adjacent routers clocked synchronously:

$$RTT = 1 + 1 + 1 + 1 = 4 \text{ cycles} \tag{2.6}$$

The Fundamental Throughput Theorem: To sustain 100% wire-rate throughput without pipeline stall bubbles, the downstream buffer depth B must satisfy:

$$B_{min} \geq RTT \times \text{Peak Injection Rate} = RTT \text{ flits} \tag{2.7}$$

Table 2.2 illustrates the severe bandwidth degradation that occurs when buffer depth $B < RTT$.

2.5 Alternative Flow Control: Token Flow Control in the SWIFT NoC

In high-performance low-power interconnects, **Token Flow Control** [24] routes tokens ahead of data flits to achieve flit buffer bypassing.

Key innovations of the SWIFT architecture include:

1. **Flit Buffer Bypassing**: Tokens reserve crossbar paths in advance; data flits cut straight through the crossbar into the link without writing into input SRAM FIFO cells.
2. **Buffer Power Reduction**: Dynamic FIFO write power is slashed by 38% at saturation and 25% at low load.

Table 2.2 Buffer Depth vs. Achievable Link Utilization ($RTT = 4$ cycles, 100-cycle injection simulation)

Buffer Depth (B)	RTT (Cycles)	Link Utilization	Flits Transferred	Pipeline Stall State
$B = 1$ flit	4 cycles	20.0%	20 flits	Severe Underflow Stall
$B = 2$ flits	4 cycles	40.0%	40 flits	Severe Underflow Stall
$B = 3$ flits	4 cycles	60.0%	60 flits	Moderate Stall
$B = 4$ flits	4 cycles	80.0%	80 flits	Boundary Stall Bubble
$B = 5$ flits	4 cycles	100.0%	100 flits	100% Full Wire-Rate
$B = 8$ flits	4 cycles	100.0%	100 flits	100% Wire-Rate (Safe Margin)




Fig. 1. Overview of SWIFT NoC versus a baseline NoC and ideal communication. (a) Ideal communication. (b) Baseline NoC. (c) SWIFT NoC.

Fig. 2.2 Overview of SWIFT NoC versus baseline multi-stage NoC: (a) Ideal single-cycle communication, (b) Baseline multi-stage NoC, and (c) SWIFT NoC with token-based flit buffer bypassing. [Reproduced from: J. Postman, T. Krishna, C. Edmonds, L.-S. Peh, and P. Chiang, "SWIFT: A Low-Power Network-On-Chip Implementing the Token Flow Control Router Architecture With Swing-Reduced Interconnects," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 21, no. 8, pp. 1432–1446, Aug. 2013 [24]. © 2013 IEEE]

Fig. 2.3 SWIFT NoC microarchitecture: (a) Routing using tokens, (b) Token distribution, (c) Bypass flow control using lookahead signals, and (d) 1-cycle router plus 1-cycle link traversal. [Reproduced from: J. Postman et al., *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, Aug. 2013 [24]. © 2013 IEEE]




Fig. 2. SWIFT NoC architecture. (a) Routing using tokens. (b) Token distribution. (c) Bypass flow-control using lookaheads. (d) One-cycle router+ one-cycle LT.

3. **Swing-Reduced Interconnects**: Reduced-swing transceivers on physical links substantially diminish dynamic energy dissipation.

2.6 Interactive Lab & Hands-on Challenges

Explore the interactive flow-control simulators on the **NoC Learning Hub** (https://network-on-chip.github.io/learning/):

- **Credit Commander: Flow Control** (https://network-on-chip.github.io/learning/interactive/credits/): Experiment with buffer depth B and round-trip time RTT to observe credit stalls and pipeline bubbles in real time.
- **Packet Master: Routing Puzzle** (https://network-on-chip.github.io/learning/interactive/puzzle/): Coordinate Head, Body, and Tail flit traversal across congested wormhole channels.

2.7 Checkpoint Assessment

1. **Question 2.1 (Tier 1: Fundamental)**: What is the critical hardware advantage of Wormhole Switching compared to Store-and-Forward and Virtual Cut-Through?
2. **Question 2.2 (Tier 2: Core Engineering)**: In credit-based flow control, if link flight takes 1 cycle, receiver buffer write/read takes 1 cycle, and credit return takes 1 cycle, what occurs if the receiver buffer capacity is only 2 flits?
3. **Question 2.3 (Tier 3: Silicon Mastery)**: How does Token Flow Control in the SWIFT NoC achieve up to 38% power reduction compared to canonical wormhole routers?

Detailed answers and derivations for these questions are provided in the Solutions chapter at the end of this volume.

Chapter 3
High-Performance Router Microarchitecture & Arbitration

Abstract At the core of every packet-switched on-chip network is the router datapath and its allocation logic. This chapter dissects the canonical five-stage virtual-channel router pipeline (Buffer Write, Route Computation, VC Allocation, Switch Allocation, and Switch Traversal) and details modern pipeline compression techniques including Lookahead Routing, Speculative Switch Allocation, and deterministic buffer reservation bypassing (BuffeRS). We examine asynchronous router design paradigms in GALS-based SoCs, featuring the domino-logic HyPA router, and analyze the physical clock constraints of single-cycle multi-hop traversal (SMART/SHARP). Finally, we formalize bipartite maximum matching arbitration, proving the $O(1)$ hardware LRU properties of the Matrix Arbiter and the 100% throughput convergence theorems of McKeown's iSLIP algorithm.

3.1 The Canonical Virtual-Channel Router Pipeline

At the heart of every packet-switched on-chip network is the **Virtual-Channel (VC) Router**. In a canonical synchronous architecture [23], processing each packet traverses a five-stage pipeline:

1. **Buffer Write (BW)**: The incoming flit arrives from an adjacent router or local network interface and is written into the input FIFO buffer corresponding to its assigned `VC_ID`.
2. **Route Computation (RC)**: Evaluates the routing function $R : (C_{curr}, C_{dest}) \rightarrow P_{out}$ to determine the set of permissible output physical ports. In Dimension-Order Routing (DOR), RC is computed via combinational comparators:

$$\Delta X = X_{dest} - X_{curr}, \qquad \Delta Y = Y_{dest} - Y_{curr} \tag{3.1}$$




Fig. 1. (a) Multicycle router pipeline and (b) BuffeRS router pipeline.

Fig. 3.1 Pipeline comparison: (a) Multicycle router pipeline (BW, RC, VA, SA, ST, LT) versus (b) Low-latency BuffeRS router pipeline with buffer reservation bypassing. [Reproduced from: Z. Liu, X. Wu, and Y. Ye, "BuffeRS: A Buffer Reservation Scheduling Strategy for Router Bypassing in NoCs and Multichiplet Networks," *IEEE Trans. Comput.-Aided Design Integr. Circuits Syst.*, vol. 45, no. 6, pp. 2635–2648, June 2026 [19]. © 2026 IEEE]

3. **Virtual Channel Allocation (VA)**: The Head flit arbitrates for a free downstream Virtual Channel at the designated output port using a two-phase separable allocator (Input Arbitration followed by Output Arbitration).
4. **Switch Allocation (SA)**: Flits with valid downstream VCs arbitrate for crossbar switch input and output ports using a two-stage separable allocator.
5. **Switch Traversal (ST)**: Granted flits traverse the crossbar multiplexer fabric to reach the output link registers.
6. **Link Traversal (LT)**: Flits traverse the inter-router physical metal link wires to the downstream router.

3.2 Advanced Pipeline Compression & Router Bypassing

Because per-hop pipeline latency compounds linearly with network diameter ($T_{net} = H \cdot t_r$), minimizing router latency from 5 cycles to 1 cycle has been a central focus of on-chip network research.

3.2.1 Lookahead Routing & Speculative Switch Allocation

- **Lookahead Routing**: Router N computes the output port for Router $N+1$ and encodes it into the flit header, stripping the RC stage from intermediate hops and saving 1 cycle per hop.
- **Speculative Switch Allocation** [23]: Flits request switch allocation in parallel with virtual channel allocation. Under low-to-medium contention, speculative requests succeed, compressing the pipeline to 2 cycles (or 1 cycle with crossbar bypassing).

3.2.2 Buffer Reservation Scheduling: BuffeRS (TCAD 2026)

As formulated by Liu et al. [19], **BuffeRS** introduces a coordinated time-division buffer reservation protocol that reserves destination buffer slots in advance across router groups, providing deterministic contention-free bypass paths across both monolithic dies and 2.5D multi-chiplet packaging boundaries.

3.3 Asynchronous Router Architectures: HyPA (TVLSI 2026)

In large-scale Multi-Processor Systems-on-Chip (MPSoCs), distributing a single low-skew global clock across a 20 mm $\times$ 20 mm die incurs prohibitive clock-tree power dissipation and timing closure complexity.

In Globally Asynchronous Locally Synchronous (GALS) systems, asynchronous routers eliminate clock trees entirely:

- **HyPA Router** [25]: Implemented in 65nm CMOS, HyPA employs a hybrid pipeline asynchronous architecture using high-throughput domino logic with one-hot hybrid data encoding.
- **Power and Energy Gains**: Compared to synchronous clock-gated baseline routers, HyPA demonstrates a **62% power reduction** and an **85% reduction in energy-per-flit**, achieving a forward latency of **0.8 ns** and a throughput of **1.65 GFlits/port/s**.

3.4 Single-Cycle Multi-Hop Traversal (SMART / SHARP)

In SMART [17], flits traverse multiple physical router crossbars and links asynchronously within a single clock cycle under low traffic.

Single-cycle traversal is physically bounded by the clock period timing budget:




Fig. 2. Detailed microarchitecture of the proposed asynchronous router.

Fig. 3.2 Detailed microarchitecture of the HyPA asynchronous router featuring a high-throughput domino-logic pipeline template with one-hot hybrid data encoding. [Reproduced from: M. N. Saranya, C. T. Avinash, and R. Rao, "HyPA: A Low-Latency Hybrid Pipeline Asynchronous Router for Network-on-Chip Architectures in GALS-Based SoCs," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 34, no. 8, pp. 2840–2851, 2026 [25]. © 2026 IEEE]

Fig. 3.3 Preemption stopping cases at intermediate routers for contending flows in priority-preemptive single-cycle multi-hop traversal networks under hop limits ($HPC_{max} = 3$). [Reproduced from: *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, vol. 31, no. 10, pp. 1560–1572, Oct. 2023. © 2023 IEEE]




Fig. 2. Two stopping cases at intermediate routers for the analyzed flows f_i and f_j in priority-preemptive SHARP, $HPC_{max} = 3$. (a) Directly contending flow. (b) HPCmax limitation.

$$t_{hop} = t_{crossbar_mux} + t_{wire_propagation} + t_{repeater} \tag{3.2}$$

$$\text{Maximum Traversable Hops per Cycle: } HPC_{max} = \left\lfloor \frac{T_{clk} - t_{setup}}{t_{hop}} \right\rfloor \tag{3.3}$$

At 1.0 GHz ($T_{clk} = 1.0$ ns), HPC_{max} is typically 3 to 5 hops before requiring intermediate latching.

3.5 Crossbar Arbitration Theory & Matching Algorithms

Crossbar allocation resolves contention when multiple input ports simultaneously request the same output port, formalized as the Bipartite Maximum Matching Problem.

3.5.1 The Matrix Arbiter: Strict $O(1)$ Hardware LRU

The **Matrix Arbiter** maintains an $N \times N$ triangular binary priority matrix M:

$$M[i][j] = \begin{cases} 1 & \text{if Client } i \text{ has higher priority than Client } j \\ 0 & \text{if Client } j \text{ has higher priority than Client } i \end{cases} \tag{3.4}$$

Combinational grant generation evaluates in two gate levels:

$$G_i = R_i \cdot \prod_{j \neq i} (\overline{R_j} + M[i][j]) \tag{3.5}$$

When client k wins the grant ($G_k = 1$), it becomes the Least Recently Used (LRU) client via single-cycle register updates:

$$M[k][j] = 0 \quad (\forall j \neq k), \qquad M[i][k] = 1 \quad (\forall i \neq k) \tag{3.6}$$

3.5.2 McKeown's iSLIP Iterative Matching Algorithm

For an $N \times N$ crossbar switch, separable allocators can suffer from up to 50% port under-utilization under heavy traffic. McKeown's **iSLIP** algorithm [21] achieves 100% throughput using iterative matching:

1. **Phase 1 (Request)**: Unmatched inputs request all outputs with queued flits.
2. **Phase 2 (Grant)**: Unmatched outputs arbitrate using round-robin pointers g_j.
3. **Phase 3 (Accept)**: Inputs arbitrate among received grants using accept pointers a_i.
4. **Pointer Update Rule**: Pointers g_j and a_i update *if and only if* the match is accepted in the **first iteration**:

$$g_j = (i+1) \pmod N, \qquad a_i = (j+1) \pmod N \tag{3.7}$$

By restricting updates to iteration 1, iSLIP de-synchronizes the grant arbiters, achieving 100% throughput and maximal matching in $\leq \min(N, \log_2 N)$ iterations.

3.6 Interactive Lab & Hands-on Challenges

Explore the interactive microarchitecture simulators on the **NoC Learning Hub** (https://network-on-chip.github.io/learning/):

- **Arbiter Arena: Crossbar Clash** (https://network-on-chip.github.io/learning/interactive/arbiter/): Step through Matrix, Round-Robin, and Wavefront schedulers under heavy traffic bursts.
- **2D Mesh Routing Visualizer** (https://network-on-chip.github.io/learning/interactive/visualizer/): Inspect crossbar switch allocation states and input buffer queues across an 8×8 mesh.

3.7 Checkpoint Assessment

1. **Question 3.1 (Tier 1: Fundamental)**: What are the canonical 5 pipeline stages of a classic Virtual Channel wormhole router?
2. **Question 3.2 (Tier 2: Core Engineering)**: In a Matrix Arbiter with an $N \times N$ triangular priority matrix M, what is the exact hardware update rule when Client k is granted the resource?
3. **Question 3.3 (Tier 3: Silicon Mastery)**: Why does McKeown's iSLIP algorithm update its round-robin grant and accept pointers ONLY on the first iteration, rather than on every iteration?

Detailed answers and derivations for these questions are provided in the Solutions chapter at the end of this volume.

Part II
Topologies, Routing & Deadlock Freedom

Chapter 4
Direct, Indirect & High-Radix Interconnect Topologies

Abstract The topological organization of an on-chip interconnection network establishes the fundamental trade-offs between zero-load latency, bisection bandwidth, router crossbar complexity, and physical wire routing density. This chapter presents an authoritative, mathematically rigorous analysis of direct, indirect, and high-radix on-chip networks. We derive first-principles formulations for network diameter, average hop distance, bisection bandwidth, and saturation throughput across regular and irregular fabrics. We analyze planar direct topologies (2D Mesh, 2D Torus, and the delay-invariant Folded Torus), indirect multistage architectures (Clos networks, non-blocking theorems, and constant-bisection Fat-Trees), and the modern high-radix paradigm (Flattened Butterfly and Dragonfly networks with adaptive UGAL routing). Furthermore, we examine peer-reviewed silicon methodologies for application-specific cascaded crossbars and review the landmark Passas-Katevenis proofs establishing the area-efficient scalability of monolithic crossbars beyond 100 nodes.

4.1 Interconnect Graph Theory and Formal Performance Metrics

An on-chip interconnection network is formally modeled as a directed graph $G = (V, E)$, where the vertex set V represents the network nodes ($|V| = N$, comprising routers, compute cores, accelerators, and memory controllers), and the edge set E represents the point-to-point physical transmission channels.

The choice of topology defines the structural limits of communication performance:

1. **Router Radix (k)**: The number of physical input/output ports per router:

$$k = \deg_{in}(u) = \deg_{out}(u) \tag{4.1}$$

Because internal crossbar switch area and power scale quadratically ($O(k^2)$), low-radix designs minimize local switch overhead, whereas high-radix switches reduce network traversal hops at the expense of larger crossbars.

2. **Network Diameter (D)**: The maximum shortest-path distance between any pair of nodes in the network:

$$D = \max_{u,v \in V} d(u,v) \tag{4.2}$$

where $d(u,v)$ is the minimum hop count between u and v. Diameter dictates worst-case communication latency.

3. **Average Hop Distance ($\bar{h}$)**: The expected shortest-path distance under a spatial traffic probability distribution $p(u,v)$:

$$\bar{h} = \sum_{u \in V} \sum_{v \neq u} p(u,v) \cdot d(u,v) \tag{4.3}$$

Under Uniform Random (UR) traffic ($p(u,v) = \frac{1}{N(N-1)}$), this reduces to $\bar{h}_{UR} = \frac{1}{N(N-1)} \sum_{u \neq v} d(u,v)$.

4. **Bisection Bandwidth (B_C)**: The minimum bandwidth cut partitioning the vertex set V into two equal disjoint subsets V_1, V_2 ($|V_1| = |V_2| = N/2$):

$$B_C = \min_{V_1,V_2} \sum_{u \in V_1, v \in V_2, (u,v) \in E} C(u,v) \tag{4.4}$$

where $C(u,v)$ denotes link bandwidth. In networks with uniform channel width W bits and clock frequency f_{clk}, bisection bandwidth is expressed as channel count N_C: $B_C = N_C \cdot W \cdot f_{clk}$.

5. **Maximum Channel Load (γ_{max}) and Saturation Throughput (Θ_{sat})**: Let γ_e denote the expected traffic volume traversing physical edge $e \in E$ when each node injects 1 flit per cycle. The maximum channel load is:

$$\gamma_{max} = \max_{e \in E} \gamma_e \tag{4.5}$$

Because each channel can transport at most 1 flit per cycle, the theoretical maximum saturation throughput per node is bounded by:

$$\Theta_{sat} \leq \frac{1}{\gamma_{max}} \leq \frac{2B_C}{N} \quad \text{[flits/node/cycle]} \tag{4.6}$$

6. **Zero-Load Latency (T_0)**: The average latency of an L-flit packet across uncontended routers and links:

$$T_0 = (\bar{h} + 1) \cdot t_{router} + \bar{h} \cdot t_{wire} + \left(\frac{L-1}{\text{Rate}} \right) \tag{4.7}$$

4.2 Direct Topologies: Mesh, Torus, and the Folded Torus

Direct topologies couple every router directly to a compute node, forming regular planar grids well-suited for standard CMOS silicon tiling.

4.2.1 2D Mesh Networks

In a $k \times k$ 2D Mesh ($N = k^2$):

- **Diameter**: Opposing corners require $2(k-1)$ hops: $D_{Mesh} = 2(k-1)$.
- **Average Hop Distance**:

$$\bar{h}_{Mesh} = \frac{2}{3}k \cdot \left(1 - \frac{1}{k^2}\right) \approx \frac{2}{3}k \tag{4.8}$$

- **Bisection Bandwidth**: Bisecting the mesh cuts k bidirectional links ($2k$ directional channels):

$$B_{C,Mesh} = 2k \cdot W \implies \Theta_{Mesh} \leq \frac{4W}{k} \tag{4.9}$$

Under uniform traffic, peripheral nodes route through the center, generating severe center-channel congestion ($\gamma_{max} \approx k/4$).

4.2.2 2D Torus and the Wire Delay Dilemma

A $k \times k$ 2D Torus (k-ary 2-cube) adds periodic wrap-around links. The topology becomes completely edge-symmetric:

$$D_{Torus} = 2\left\lfloor \frac{k}{2} \right\rfloor, \quad \bar{h}_{Torus} \approx \frac{k}{2}, \quad B_{C,Torus} = 4k \cdot W \tag{4.10}$$

A 2D Torus delivers exactly twice the bisection bandwidth and a 25% reduction in average hop count compared to a 2D Mesh.

However, in a naive planar layout, the perimeter wrap-around wire must span the entire die:

$$L_{wrap} = (k-1) \cdot L_0 \tag{4.11}$$

where L_0 is the tile pitch. By the Elmore delay model ($\tau \propto L^2$), an 8×8 torus suffers $49\times$ higher propagation delay on wrap-around wires than on local links, destroying clock frequency unless aggressively pipelined.

4.2.3 The Folded Torus Invariance

The **Folded Torus** topology solves the wrap-around wire crisis by physically interleaving even and odd nodes along each dimension:

$$\text{Physical Placement} : 0, \quad 2, \quad 4, \quad \ldots, \quad k-2, \quad k-1, \quad \ldots, \quad 3, \quad 1 \tag{4.12}$$

Every link in the Folded Torus—including all wrap-around connections—has an identical physical length:

$$L_{link,Folded} = 2 \cdot L_0 \tag{4.13}$$

By trading a constant wire length of $2L_0$ for the elimination of catastrophic $(k-1)L_0$ wires, the Folded Torus achieves high clock frequencies while retaining torus bisection bandwidth and low diameter.

4.3 Indirect Multistage Interconnects: Clos and Fat-Trees

Indirect topologies place processing elements exclusively at the network periphery, interconnecting them through intermediate switching stages.

4.3.1 Clos Networks and Non-Blocking Theorems

A 3-stage Clos network $C(n, m, r)$ comprises r input switches of size $n \times m$, m middle switches of size $r \times r$, and r output switches of size $m \times n$ [2].

- **Strictly Non-Blocking (SNB)**: Any idle input can connect to any idle output without rerouting existing calls if and only if:

$$m \geq 2n - 1 \tag{4.14}$$

- **Rearrangeably Non-Blocking (RNB)**: By the Slepian-Duguid theorem, any input can connect to any output with potential rerouting if:

$$m \geq n \tag{4.15}$$

4.3.2 Fat-Trees and Constant Bisection Bandwidth

Leiserson's Fat-Tree [18] avoids root bottlenecks by progressively increasing channel capacity toward the tree root. At each hierarchical level, the number of parallel channels doubles, preserving constant bisection bandwidth across all horizontal network partitions.

4.4 High-Radix Interconnects: Flattened Butterfly and Dragonfly

Modern sub-10nm CMOS technologies provide vast routing gate density, prompting a shift from low-radix/high-diameter networks to high-radix/low-diameter architectures ($k \geq 16$–$64+$).

4.4.1 Flattened Butterfly

Kim et al. [15] projected multi-stage butterfly switches into a single direct router per tile. In a $k \times k$ Flattened Butterfly, each router connects to all other routers in the same row and column:

$$D_{FBfly} = 2, \quad k_{radix} = 2(k-1) + p \tag{4.16}$$

Any node in the network is reachable in at most 2 hops, slashing router traversal cycles.

4.4.2 The Dragonfly Topology and UGAL Routing

Kim, Dally et al. [16] organized high-radix routers into local fully connected groups (cliques) interconnected by sparse global links. Under **Universal Globally-Adaptive Routing (UGAL)**, packets evaluate queuing delays: if the minimal global link is congested, packets are routed non-minimally through a randomly chosen intermediate group, eliminating hot-spot saturation.

4.5 Application-Specific Synthesis & Cascaded Crossbars

Heterogeneous SoCs exhibit highly non-uniform communication demands. Rigid standard topologies introduce severe silicon area and power waste.

4.5.1 MIRO Synthesis of Cascaded Crossbar Networks

Jun, Yoo, and Chung [13] formulated the synthesis of cascaded crossbar switches to replace power-hungry centralized bus matrices.

Jun et al. proved that while Mixed Integer Linear Programming (MILP) discovers exact optimal topologies, its computational complexity explodes for $|V| > 16$. The MIRO heuristic clusters masters based on communication affini-




Fig. 1. MIRO Process.

Fig. 4.1 The MIRO (Multi-stage Interconnect Reduction and Optimization) process for synthesizing cascaded crossbar networks under bandwidth and latency constraints. [Reproduced from: M. Jun, S. Yoo, and E.-Y. Chung, "Topology Synthesis of Cascaded Crossbar Switches," *IEEE Trans. Comput.-Aided Design Integr. Circuits Syst.*, Vol. 28, No. 6, pp. 926–930, June 2009, DOI: 10.1109/TCAD.2009.2017079. © 2009 IEEE]

ties, achieving **up to 69.5% area reduction** over conventional architectures while satisfying all clock frequency requirements.

4.5.2 Switch Merger and Partitioning Algorithms

Dumitriu and Khan [7] introduced transaction-oriented topology generation using iterative switch merging and partitioning:

By using predictive contention modeling during synthesis, the resulting topologies matched or exceeded regular 2D mesh throughput while utilizing **50% fewer network resources**.

4.6 Silicon Floorplanning Limits: The Passas Radix-128 Proof

A persistent misconception in early literature asserted that full crossbar networks are unviable beyond 32 nodes. Passas, Katevenis, and Pnevmatikatos [22]




Fig. 3. Example of a switch merger.




Fig. 4. Example of the switch partitioning process.

Fig. 4.2 Application-specific topology optimization: (left) switch merger process combining low-traffic routers; (right) switch partitioning process dividing congested routers to meet physical pin and timing constraints. [Reproduced from: V. Dumitriu and G. N. Khan, "Throughput-Oriented NoC Topology Generation and Analysis for High Performance SoCs," *IEEE Trans. Very Large Scale Integr. (VLSI) Syst.*, Vol. 17, No. 10, pp. 1433–1446, October 2009, DOI: 10.1109/TVLSI.2008.2006798. © 2009 IEEE]

refuted this by modeling and fabricating a **radix-128 crossbar in 90 nm CMOS**.




Fig. 1. Die floorplans. (a) Stack of user tiles using side crossbar. (b) Matrix of user tiles using distributed crossbar. (c) Matrix of user tiles using centralized crossbar. (d) Balanced link density of (c) in a "12×12 minus 4×4" matrix of user tiles; *P*s denote processors and *M*s memories.

Fig. 4.3 Die floorplans for crossbar-based on-chip networks. (a) Stack of user tiles with side crossbar. (b) Matrix of user tiles with distributed crossbar. (c) Centralized crossbar. (d) Balanced link density layout in a 12×12 minus 4×4 matrix of tiles. [Reproduced from: G. Passas, M. Katevenis, and D. Pnevmatikatos, "Crossbar NoCs Are Scalable Beyond 100 Nodes," *IEEE Trans. Comput.-Aided Design Integr. Circuits Syst.*, Vol. 31, No. 4, pp. 573–585, April 2012, DOI: 10.1109/TCAD.2011.2176730. © 2012 IEEE]

Passas et al. proved that:

1. With 8+ metal layers, crossbar wiring tracks fit directly **over standard cells** on intermediate metal layers without expanding standard-cell silicon area:

$$\text{Area}_{crossbar} \approx O(N^2 \cdot W), \quad \text{Delay}_{crossbar} \approx O(\sqrt{N \cdot W}) \tag{4.17}$$




Fig. 3. 3-bit radix-8 crossbar.

Fig. 4.4 Standard-cell layout of a 3-bit radix-8 crossbar bit-slice. Multiplexer circuits are routed entirely beneath upper-level metal tracks. [Reproduced from: G. Passas, M. Katevenis, and D. Pnevmatikatos, "Crossbar NoCs Are Scalable Beyond 100 Nodes," *IEEE Trans. Comput.-Aided Design Integr. Circuits Syst.*, Vol. 31, No. 4, pp. 573–585, April 2012, DOI: 10.1109/TCAD.2011.2176730. © 2012 IEEE]

2. In a 150 mm^2 die containing 128 1 mm^2 processor tiles, the radix-128 crossbar occupied **only 11% of total die area** (including repeaters and pipeline flip-flops).
3. Under global and stressed traffic, the monolithic crossbar delivered **up to 3× higher throughput and 2.5× lower latency** than a 2D mesh by eliminating multi-hop queueing stalls.

4.7 Quantitative Topology Evaluation Matrix

Table 4.1 summarizes the mathematical and microarchitectural metrics across major topology classes for an $N = 64$ core system.

Table 4.1 Analytical and Empirical Metric Matrix across Interconnect Topologies ($N = 64$ nodes)

Topology	Radix (k)	Diam (D)	Avg Hops ($\bar{h}$)	Bisect (B_C/W)	T_0 (cyc)	Sat. Thru.
Ring (1D)	2	32	16.00	4	28.00	0.125
2D Mesh (8×8)	4 (avg 3.5)	14	5.33	16	12.00	0.500
2D Torus (8×8)	4	8	4.06	32	10.10	1.000
Folded Torus (8×8)	4	8	4.06	32	10.10	1.000
Hypercube (6-cube)	6	6	3.05	64	8.57	2.000
Fat-Tree (3-level)	4	6	3.80	64	9.70	2.000
Flattened Butterfly (8×8)	14	2	1.78	256	6.67	8.000
Full Crossbar (64×64)	64	1	1.00	2048	5.00	64.000

4.8 Exercises and Review Questions

1. **Bisection Bandwidth Bound**: Prove that under uniform random traffic, the maximum throughput per node is bounded by $\Theta \leq \frac{2B_C}{N}$. What fraction of injected traffic must traverse the bisection cut?
2. **Folded Torus Delay**: For an 8×8 tiled chip with tile pitch $L_0 = 1.2$ mm, compare the wire delay of a naive torus wrap-around link versus a folded torus link under the Elmore delay model.
3. **Clos Non-Blocking Sizing**: For a 3-stage Clos network $C(n, m, r)$ with $N = 64$ and $n = 8$, calculate the minimum m required for strictly non-blocking operation versus rearrangeably non-blocking operation.
4. **High-Radix Trade-Offs**: Explain why high-radix networks become more energy-efficient than low-radix 2D meshes as core counts scale beyond 100 nodes.

Appendix A
Open-Source NoC Frameworks, RTL Repositories & PDKs

A.1 Synthesizable Verilog & SystemVerilog NoC Codebases

To facilitate reproducible experimentation, several landmark academic and industrial NoC architectures have been made open-source:

- **FlooNoC (ETH Zürich / University of Bologna)**: An open-source SystemVerilog Network-on-Chip supporting wide physical links, AXI4 parallel multistreaming, and AXI-Stream virtualization.
  - Repository: https://github.com/pulp-platform/floonoc
  - Key Reference: Fischer et al., *IEEE TVLSI 2025* [9].
- **HammerBlade Manycore (University of Washington / UCSD / Cornell)**: A complete open-source 2,048-core RISC-V compute fabric and Ruche network silicon implementation in 12nm FinFET.
  - Repository: https://github.com/bespoke-silicon-group/bsg_manycore
  - Key Reference: Gao et al., *IEEE TVLSI 2026* [10].
- **OpenPiton & Princeton Piton NoC**: A scalable manycore framework supporting SPARC and RISC-V with a 2D mesh packet-switched interconnect.
  - Repository: https://github.com/PrincetonUniversity/openpiton

A.2 Open-Source Physical Design PDKs

Academic exploration of sub-14nm interconnect physics is supported by open-source process design kits:

- **FreePDK45**: 45nm predictive technology model with 10 metal layers.

- **ASAP7**: 7nm FinFET Predictive Process Design Kit developed by Arizona State University in collaboration with ARM.
- **SkyWater 130nm (SKY130)**: The first fully open-source manufacturable 130nm CMOS foundry PDK.

Solutions to Checkpoint Questions

Chapter 1: The Multi-Core Communication Crisis & Interconnect Physics

Question 1.1 **Answer: B**. According to the Elmore delay formulation (Eq. 1.4), the propagation delay of a shared wire is $\tau \approx 0.38 R_{wire} C_{wire} + R_{driver} \sum C_{tap} + \sum R_{wire} C_{tap}$. Because each attached core introduces transceiver parasitic capacitance ($C_{taps} \propto N$) and the physical wire length across the chip perimeter scales as $L \propto \sqrt{N}$, the total RC product surges as $O(N^{3/2})$, resulting in severe frequency throttling for $N > 8$.

Question 1.2 **Answer: B**. The Mayadas-Shatzkes effect models electron scattering at polycrystalline grain boundaries in nanoscale metal lines. When wire trench width approaches the electron mean free path ($\lambda_0 \approx 39$ nm in bulk copper), grain boundary reflection ($R \approx 0.3$–0.5) and surface diffuse reflection combine with non-conductive barrier liners (Ta/TaN) to surge effective resistivity by $5\times$ to $15\times$ above bulk values, destroying global interconnect RC performance.

Question 1.3 **Answer: A**. An $N \times N$ crossbar requires N^2 crosspoint multiplexer switches and $2N \times W_{data}$ wiring tracks crossing the central layout. For $N = 128$, this dictates 16,384 crosspoints and thousands of parallel global wires, creating insurmountable physical routing track congestion and parasitic crosstalk in silicon layout.

Chapter 2: Switching Techniques, Flow Control & Buffer Management

Question 2.1 **Answer: B**. Wormhole switching operates at the granularity of individual flits rather than entire packets. By allowing body flits to stream across established router paths behind the head flit, input buffer depth can be

reduced to as few as 1–4 flits, reducing router SRAM buffer area by 75%–93% compared to Store-and-Forward and Virtual Cut-Through.

Question 2.2 **Answer: B**. The credit turnaround loop Round-Trip Time is $RTT = t_{tx} + t_{flight_fwd} + t_{rx} + t_{flight_cred} = 4$ cycles. By the Fundamental Throughput Theorem (Eq. 2.7), sustaining 100% wire-rate throughput requires $B \geq RTT = 4$ flits. With $B = 2$, the transmitter exhausts its credits after 2 cycles and is forced to stall during cycles 3 and 4 while waiting for credit feedback, throttling link utilization to 40%–50%.

Question 2.3 **Answer: B**. In the SWIFT NoC, lightweight tokens travel ahead of data flits to reserve crossbar switch allocation in advance. When a token is granted, the incoming data flit cuts directly through the crossbar into the outgoing link without writing into or reading from input FIFO SRAM cells, saving up to 38% of dynamic router power at saturation.

Chapter 3: High-Performance Router Microarchitecture & Arbitration

Question 3.1 **Answer: B**. The canonical synchronous 5-stage router pipeline comprises: Buffer Write (BW), Route Computation (RC), Virtual Channel Allocation (VA), Switch Allocation (SA), and Switch Traversal (ST), followed by inter-router Link Traversal (LT).

Question 3.2 **Answer: A**. When Client k receives a grant ($G_k = 1$), row k is cleared to zero ($M[k][j] = 0\ \forall j \neq k$) and column k is set to one ($M[i][k] = 1\ \forall i \neq k$). This places client k at the lowest priority relative to all other requesters, implementing an exact, single-cycle Least Recently Used (LRU) policy.

Question 3.3 **Answer: B**. Updating round-robin pointers in later iterations would cause output grant arbiters to synchronize into identical priority positions when traffic is heavy. Restricting pointer updates to the first iteration preserves pointer diversity (entropy), preventing cyclic grant lockouts and achieving 100% throughput under uniform traffic.

References

1. Benini, L., Micheli, G.D.: Networks on chips: A new SoC paradigm. IEEE Computer **35**(1), 70–78 (2002). DOI 10.1109/2.976921
2. Clos, C.: A study of non-blocking switching networks. Bell System Technical Journal **32**(2), 406–424 (1953)
3. Dally, W.J., Seitz, C.L.: Deadlock-free message routing in multiprocessor interconnection networks. IEEE Transactions on Computers **C-36**(5), 547–553 (1987). DOI 10.1109/TC.1987.1676939
4. Dally, W.J., Towles, B.: Route packets, not wires: On-chip interconnection networks. In: Proceedings of the 38th Annual Design Automation Conference (DAC), pp. 684–689 (2001). DOI 10.1145/378239.379048
5. Davidson, S., Gao, M., Gao, P., Zhao, C., Li, K., Gilani, F., Richmond, D., Oskin, M., Taylor, M.B.: The HammerBlade manycore: Architecting a 16-nm, 0.45-pj/op, 1.4-ghz, 21.6-tflops/w compute fabric for machine learning and beyond. IEEE Transactions on Very Large Scale Integration (VLSI) Systems **31**(11), 1774–1787 (2023). DOI 10.1109/TVLSI.2023.3308821
6. Dennard, R.H., Gaensslen, F.H., Yu, H.N., Rideout, V.L., Bassous, E., LeBlanc, A.R.: Design of ion-implanted MOSFET's with very small physical dimensions for digital integrated circuits. IEEE Journal of Solid-State Circuits **9**(5), 256–268 (1974). DOI 10.1109/JSSC.1974.1050511
7. Dumitriu, V., Khan, G.N.: Throughput-oriented NoC topology generation and analysis for high performance SoCs. IEEE Transactions on Very Large Scale Integration (VLSI) Systems **17**(10), 1433–1446 (2009). DOI 10.1109/TVLSI.2008.2006798
8. Elmore, W.C.: The transient response of damped linear networks with particular regard to wideband amplifiers. Journal of Applied Physics **19**(1), 55–63 (1948). DOI 10.1063/1.1697872
9. Fischer, T., Rogenmoser, M., Benz, T., Gürkaynak, F.K., Benini, L.: FlooNoC: A 645-gb/s/link 0.15-pj/b/hop open-source NoC with wide physical links and end-to-end AXI4 parallel multistream support. IEEE Transactions on Very Large Scale Integration (VLSI) Systems **33**(4), 1094–1107 (2025). DOI 10.1109/TVLSI.2025.3527225
10. Gao, P., Jung, D.C., Davidson, S., Ruelas-Petrisko, D., Chueh, Y.M., Ruttenberg, M., Li, K., Gilani, F., Richmond, D., Oskin, M., Taylor, M.B.: HammerBlade in silicon: A 12-nm 2048-core RISC-V manycore SoC with ruche networks. IEEE Transactions on Very Large Scale Integration (VLSI) Systems **34**(7), 2306–2310 (2026). DOI 10.1109/TVLSI.2026.3684311
11. Ho, R., Mai, K.W., Horowitz, M.A.: The future of wires. Proceedings of the IEEE **89**(4), 490–504 (2001). DOI 10.1109/5.920580
12. Howard, J., Dighe, S., Hoskote, Y., Vangal, S., Finan, D., Ruhl, G., Jenkins, D., Wilson, H., Borkar, N., Schrom, G., Pailet, F., Jain, S., Jacob, T., Yada, S., Marella, S., Salihundam, P., Erraguntla, V., Konow, M., Riepen, M., Droege, G., Lindemann, J., Gammack, R., Sugihara, O., Cheodukar, R., Sriram, P., Hirpa, B., Chandrasekharan, N., Rao, T., Reddy, K.C.S., Chidambara, B., Wang, H., Bautista, J., Rao, G.B.S., Kulkarni, P., Raman, B.K., Govindaraju, V., Mathew, S., Soumyanath, K.: A 48-core IA-32 message-passing processor with DVFS in 45nm CMOS. IEEE Journal of Solid-State Circuits **46**(1), 173–183 (2011). DOI 10.1109/JSSC.2010.2079496
13. Jun, M., Yoo, S., Chung, E.Y.: Topology synthesis of cascaded crossbar switches. IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems **28**(6), 926–930 (2009). DOI 10.1109/TCAD.2009.2017079
14. Kermani, P., Kleinrock, L.: Virtual cut-through: A new computer communication switching technique. Computer Networks **3**(4), 267–286 (1979). DOI 10.1016/0376-5075(79)90034-7
15. Kim, J., Balfour, J., Dally, W.J.: Flattened butterfly topology for on-chip networks. In: Proceedings of the 40th Annual IEEE/ACM International Symposium on Microarchitecture (MICRO), pp. 172–182 (2007). DOI 10.1109/MICRO.2007.28

16. Kim, J., Dally, W.J., Scott, S., Abts, D.: Technology-driven, highly-scalable dragonfly topology. In: Proceedings of the 35th Annual International Symposium on Computer Architecture (ISCA), pp. 77–88 (2008). DOI 10.1109/ISCA.2008.19
17. Krishna, T., Chen, C.H.O., Kwon, W.C., Peh, L.S.: Single-cycle multi-hop asynchronous repeated traversal: A case for asynchronous logic in on-chip networks. In: Proceedings of the 46th Annual IEEE/ACM International Symposium on Microarchitecture (MICRO), pp. 336–348 (2013). DOI 10.1145/2540708.2540737
18. Leiserson, C.E.: Fat-trees: Universal networks for hardware-efficient supercomputing. IEEE Transactions on Computers **C-34**(10), 892–901 (1985). DOI 10.1109/TC.1985.1676519
19. Liu, Z., Wu, X., Ye, Y.: BuffeRS: A buffer reservation scheduling strategy for router bypassing in NoCs and multichiplet networks. IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems **45**(6), 2635–2648 (2026). DOI 10.1109/TCAD.2025.3624677
20. Mayadas, A.F., Shatzkes, M.: Electrical-resistivity model for polycrystalline films: the case of arbitrary reflection at external surfaces. Physical Review B **1**(4), 1382–1389 (1970). DOI 10.1103/PhysRevB.1.1382
21. McKeown, N.: The iSLIP scheduling algorithm for input-queued switches. IEEE/ACM Transactions on Networking **7**(2), 188–201 (1999). DOI 10.1109/90.769767
22. Passas, G., Katevenis, M., Pnevmatikatos, D.: Crossbar NoCs are scalable beyond 100 nodes. IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems **31**(4), 573–585 (2012). DOI 10.1109/TCAD.2011.2176730
23. Peh, L.S., Dally, W.J.: A delay model and speculative architecture for pipelined routers. In: Proceedings of the 7th International Symposium on High-Performance Computer Architecture (HPCA), pp. 255–266 (2001). DOI 10.1109/HPCA.2001.903268
24. Postman, J., Krishna, T., Edmonds, C., Peh, L.S., Chiang, P.: SWIFT: A low-power network-on-chip implementing the token flow control router architecture with swing-reduced interconnects. IEEE Transactions on Very Large Scale Integration (VLSI) Systems **21**(8), 1432–1446 (2013). DOI 10.1109/TVLSI.2012.2211904
25. Saranya, M.N., Avinash, C.T., Rao, R.: HyPA: A low-latency hybrid pipeline asynchronous router for network-on-chip architectures in GALS-based SoCs. IEEE Transactions on Very Large Scale Integration (VLSI) Systems **34**(8), 2840–2851 (2026). DOI 10.1109/TVLSI.2026.3716692
26. Zhu, J., Xue, C., Chen, Y., Wang, Z., Zhang, C., Shen, Y., Chen, Y., Cheng, Z., Jiang, Y., Wang, T., Lin, Y., Hu, W., Cui, B., Wang, R., Liang, Y., Sun, G.: Theseus: Exploring efficient wafer-scale chip design for large language models. IEEE Transactions on Computer-Aided Design of Integrated Circuits and Systems **44**(11), 3810–3823 (2025). DOI 10.1109/TCAD.2024.3496321

Index

Symbols

2D Mesh 31
2D Torus 31

C

Cascaded Crossbars 33
Clos Network 32
Crossbar Scalability 34

D

Dragonfly 33

F

Fat-Tree 32
Flattened Butterfly 33
Folded Torus 31

H

High-Radix Networks 33

I

Interconnect Graph Theory 29

T

Topological Metrics 29
Topology Synthesis 33