create_net

NAME

create_net
Creates one or more power, ground, tie, or signal nets.

SYNTAX

```
collection create_net
       [-design design]
       [-power | -ground | -tie_high | -tie_low]
       [-cell cell]
       net_names
```

Data Types

```
design         collection
cell           collection
net_names      list
```

ARGUMENTS

-design design
Specifies the design in which to create the nets. If no design is specified, the nets are created in the current design.

-power Specifies that power nets should be created.

-ground
Specifies that ground nets should be created.

-tie_high
Specifies that tie-high nets should be created.

-tie_low
Specifies that tie-low nets show be created.

net_names
Specifies the names of the nets to be created in the design. Each net name must be unique.

-cell cell
Specifies the cell where the net is to be added. The net is created in the cell's reference module. The cell must not reference a library cell, unless this command is executed in the library manager. In the library manager, nets might be created in library cells. When not specified, the net is created in the current module.

DESCRIPTION

The create_net command creates new nets in the current design (unless otherwise specified by -design). It creates only scalar (single-bit) nets. One net is created for each of the names listed.

This command can create PG, tie, or signal nets. If no net type is specified, the command creates signal nets.

Nets connect ports and pins in a design. The create_net command creates nets, but does not connect the nets. To establish this connection, use the connect_net or connect_pg_net commands.

EXAMPLES

The following example creates signal nets named N1, N2, N3, and N4.

```
prompt> create_net {N1 N2 N3 N4}
```

The following example creates a power net named VDD.

```
prompt> create_net -power VDD
```

SEE ALSO

connect_net(2)
disconnect_net(2)
get_nets(2)
remove_nets(2)