

Service Bulletin 07 - Aurora X1

Issue: readings stop after 49 days

Units on firmware 2.4.1 stop sending readings after 49 days of continuous uptime. The status ring stays green and the unit still answers the local API, so the fault shows up only as a gap in the gateway's data.

Fix: update to firmware 2.4.2

Update every affected unit to firmware 2.4.2. Run the update on mains power; updates below twenty percent battery are refused. A soft reset clears the fault until the update is installed and keeps every stored setting.