The Analytical and Geometric Synthesis of the Smith Chart: A Comprehensive Treatise for Microwave Engineering

The advancement of radio frequency (RF) and microwave engineering throughout the 20th century was fundamentally underpinned by the necessity to solve complex wave propagation equations with precision and efficiency. At the center of this evolution lies the Smith Chart, a sophisticated graphical nomogram that remains an essential pillar of the discipline, despite the proliferation of high-speed computational tools.[1] Primarily developed and refined by Phillip Hagar Smith at Bell Telephone Laboratories between 1939 and 1969, the chart provides a bridge between the abstract mathematical world of complex analysis and the physical reality of electromagnetic waves traveling along transmission lines.[1] By utilizing the properties of Möbius transformations, the Smith Chart maps an infinite impedance plane into a finite, circular domain, effectively compactifying the engineer's workspace into a unit disk where wave behavior can be visualized and manipulated with geometric intuition.[5]

Historical Context and the Measurement Challenge

The genesis of the Smith Chart was driven by the practical limitations of early RF measurements. In the era preceding the modern Vector Network Analyzer (VNA), engineers characterized high-frequency circuits using slotted lines.[5] This measurement apparatus consisted of a longitudinal slit in a coaxial transmission line through which a small electric field probe could be moved to detect standing wave patterns.[5] By determining the positions and magnitudes of the voltage maxima (U_{max}) and minima (U_{min}), engineers calculated the Voltage Standing Wave Ratio (VSWR), a scalar indicator of the mismatch between the transmission line and the terminating load.[5]

Translating these physical measurements into the actual complex impedance ($Z_L = R + jX$) of a device under test was a mathematically arduous task, requiring the repeated solution of the transmission line equations involving complex transcendental functions.[5] Phillip Smith recognized that the relationship between the normalized impedance z and the complex reflection coefficient Γ could be represented as a universal coordinate system.[1] Although similar graphical representations were independently explored by researchers such as Mizuhashi in Japan and Volpert in the Soviet Union, the Smith Chart became the global industry standard due to its comprehensive integration of impedance and admittance coordinates and its intuitive mapping of wave propagation.[4]

Contributor	Region	Primary Contribution	Era
Phillip H. Smith	USA	Comprehensive 2D Nomogram, Z-Y Coordinates.[1]	1939–1969
Tosaku Mizuhashi	Japan	Early development of the reflection-impedance chart.[4]	1937
Amiel Volpert	USSR	Independent development of circular impedance diagrams.[4]	1940
Andrei Muller	Europe	Development of the 3D Smith Chart on the Riemann Sphere.[1]	2011–Present

The Mathematical Engine: Möbius Transformations in the Complex Plane

The theoretical foundation of the Smith Chart is rooted in the study of Möbius transformations, also known as bilinear or fractional linear transformations.[5] In complex analysis, a Möbius transformation is a rational function that maps the extended complex plane $\mathbb{C} \cup \{\infty\}$ to itself.[15] The general form of this transformation is given by:

$$f(z) = \frac{az + b}{cz + d}$$

where the coefficients a, b, c, d are complex numbers satisfying the constraint $ad - bc \neq 0$.[15] This transformation is always a bijective holomorphic function, meaning it is a one-to-one mapping that preserves the local structure of the complex plane.[15]

The Smith Chart Mapping Function

The specific transformation used to generate the Smith Chart relates the normalized impedance z to the complex reflection coefficient Γ [5]:

$$\Gamma = \frac{z-1}{z+1}$$

In this expression, z represents the impedance Z of the load normalized to the characteristic impedance Z_0 of the transmission line, such that $z = Z/Z_0 = r + jx$.[4] This normalization is critical because it renders the chart "universal," allowing it to be used for any system impedance, whether it be the standard 50 Ω of RF systems or the 75 Ω used in cable television.[4]

The choice of coefficients in this Möbius transformation ($a = 1, b = -1, c = 1, d = 1$) yields several profound geometric results.[17] Most significantly, it maps the entire right half-plane of the impedance space (where $r \geq 0$) into the interior of the unit circle in the Γ-plane ($|\Gamma| \leq 1$).[1] This mapping is physically essential because passive circuit elements cannot have a negative real part of impedance; therefore, all passive impedances must fall within the boundaries of the chart.[1]

Mapping Specific Topological Points

Understanding the Smith Chart requires tracking the destination of key points from the Cartesian z-plane after the transformation.[6] These mappings define the boundary and orientation of the chart.

Normalized Impedance (z)	Complex Reflection (Γ)	Cartesian (u,v)	Physical Interpretation
$z = 1 +$ (Matched)	$\Gamma =$	$(0, 0)$	Center of the chart; ideal match.[2]
$z = 0 +$ (Short)	$\Gamma =$	$(-1, 0)$	Left edge; zero impedance.[2]

$z \to$ (Open)	$\Gamma =$	$(1, 0)$	Right edge; infinite impedance.[2]
$z = 0+$ (Inductive)	$\Gamma =$	$(0, 1$	Top of the outer circle; pure reactance.[6]
$z = 0-$ (Capacitive)	$\Gamma =$	$(0, -1$	Bottom of the outer circle; pure reactance.[6]

The mapping of the imaginary axis ($r = 0$) is particularly illustrative. Any point on the imaginary axis in the z-plane takes the form $z = jx$. Applying the transformation results in:

$$\Gamma = \frac{jx - 1}{jx + 1}$$

Taking the magnitude, we find $|\Gamma| = \sqrt{(-1)^2 + x^2} / \sqrt{1^2 + x^2} = 1$.[6] Thus, the entire imaginary axis of the Cartesian plane is "wrapped" around the circumference of the unit circle on the Smith Chart.[6]

Rigorous Algebraic Derivation of Chart Contours

The internal grid of the Smith Chart is composed of two families of circles: those representing constant normalized resistance (r) and those representing constant normalized reactance (x).[10] To derive their equations, we let $\Gamma = u + jv$, where u is the real part and v is the imaginary part of the reflection coefficient.[19]

Starting from $\Gamma = (z - 1)/(z + 1)$, we substitute $z = r + jx$ and separate the real and imaginary components [19]:

$$u + jv = \frac{(r - 1) + jx}{(r + 1) + jx}$$

Multiplying by the complex conjugate $(r + 1) - jx$, we obtain:

$$u = \frac{r^2 - 1 + x^2}{(r+1)^2 + x^2}$$

$$v = \frac{2x}{(r+1)^2 + x^2}$$

Constant Resistance Circles

To find the locus of points where r is constant, we eliminate x from the two equations. After algebraic manipulation, this yields the standard form of a circle in the u, v plane [19]:

$$\left(u - \frac{r}{r+1}\right)^2 + v^2 = \left(\frac{1}{r+1}\right)^2$$

This result confirms that constant resistance lines map to circles with centers on the real axis at $(r/(r+1), 0)$ and radii of $1/(r+1)$.[19] These circles are all tangent to each other at the point $(1, 0)$, which corresponds to the open-circuit condition.[10] As the resistance r increases, the center moves further to the right and the radius decreases, reflecting the fact that as impedance becomes very large, the reflection coefficient approaches unity with zero phase.[10]

Constant Reactance Circles

To determine the locus of constant reactance, we eliminate r from the equations for u and v [19]:

$$(u-1)^2 + \left(v - \frac{1}{x}\right)^2 = \left(\frac{1}{x}\right)^2$$

This family of circles has centers at $(1, 1/x)$ and radii of $1/|x|$.[19] Like the resistance circles, they all pass through the point $(1, 0)$.[10] However, only segments of these circles (arcs) are typically drawn within the unit disk.[10] The upper half of the chart represents positive reactance ($x > 0$), corresponding to inductive behavior, while the lower half represents negative

reactance ($x < 0$), corresponding to capacitive behavior.[18]

Conformal Mapping and Geometric Orthogonality

One of the most powerful properties of the Möbius transformation is that it is a conformal mapping.[1] By definition, a conformal map preserves the local angles between intersecting curves.[16] In the Cartesian impedance plane, the lines of constant resistance (vertical) and constant reactance (horizontal) are perpendicular to one another at every intersection.[6]

Because the Smith Chart is generated by a conformal transformation, the resulting r-circles and x-arcs must also intersect at right angles.[6] This orthogonality is not merely a mathematical curiosity; it is a fundamental design feature that allows engineers to move along the grid with an intuitive understanding that changes in resistance and reactance are locally independent.[2] When an engineer adds a series inductor to a circuit, they move clockwise along a constant resistance circle, and the conformality of the chart ensures that this movement is perfectly perpendicular to the local resistance contour.[5]

Analytically, the conformality of the mapping $\Gamma(z)$ is guaranteed because the function is holomorphic (differentiable in the complex sense) at all points except for the pole at $z = -1$.[26] The derivative $\Gamma'(z) = 2/(z+1)^2$ is non-zero throughout the right half-plane, which is the sufficient condition for a mapping to be locally conformal.[26]

Topology and the Riemann Sphere: The 3D Smith Chart

While the standard Smith Chart is restricted to a 2D plane, it is topologically more consistent to view it as a mapping onto the Riemann sphere.[1] The Riemann sphere is a way of visualizing the extended complex plane by performing a stereographic projection from a unit sphere onto a flat plane.[7]

Stereographic Projection Mechanics

In a stereographic projection, a sphere is placed so that its South Pole touches the origin of the complex plane.[7] A straight line is drawn from the North Pole (the point of projection) through a point in the complex plane.[7] The intersection of this line with the surface of the sphere identifies the spherical coordinates of that complex number.[7]

- The **origin** ($z = 0, \Gamma = -1$) maps to the South Pole.[4]

- The **point at infinity** ($z \to \infty, \Gamma = 1$) maps to the North Pole.[4]
- The **unit circle** ($|\Gamma| = 1$) maps to the equator of the sphere.[7]

Expanding to Active Circuits

The conventional 2D Smith Chart is "incomplete" in that it only displays the interior of the unit circle, corresponding to passive loads with $r \geq 0$.[1] However, active circuits, such as amplifiers and oscillators, often exhibit negative resistance ($r <$), resulting in reflection coefficients with magnitudes greater than unity ($|\Gamma| > 1$).[1] On a 2D chart, these points lie outside the boundary and are difficult to visualize as they extend toward infinity.[1]

The 3D Smith Chart, proposed by Andrei Muller and colleagues, solves this by mapping the entire extended reflection coefficient plane onto the Riemann sphere.[1] In this 3D model:

- **Northern Hemisphere:** Hosts all passive circuits ($r >$).[1]
- **Southern Hemisphere:** Becomes the domain for active circuits with negative resistance ($r <$).[7]
- **Greenwich Meridian (and its opposite):** Differentiates inductive (East) and capacitive (West) responses.[13]

This transformation ensures that the "points at infinity" in 2D space are compactified into the South Pole of the sphere, allowing for a mathematically complete and visually bounded representation of all possible electronic loads.[1]

Zone on 3D Smith Chart	Physical Meaning	Reflection Coefficient Magnitude
North Pole	Perfect Match ($z =$)	$
Northern Hemisphere	Passive Load ($r >$)	$0 <
Equator	Purely Reactive ($r =$)	$
Southern Hemisphere	Active Load ($r <$)	$1 <

South Pole	Singular Reflector ($z =$)	$

Hyperbolic Geometry and the Poincaré Disk Connection

A profound insight into the Smith Chart's behavior is found in its relationship with non-Euclidean hyperbolic geometry.[13] The Smith Chart is geometrically equivalent to the Poincaré disk model of the hyperbolic plane.[30] This connection explains why the chart's coordinate lines appear as specific circular arcs.

The Poincaré Disk Paradigm

In hyperbolic geometry, the Parallel Postulate of Euclid is rejected, leading to a space where the shortest path (geodesic) between two points is an arc of a circle perpendicular to the boundary.[30] In the Poincaré disk model, this boundary is the unit circle.[30] The metric of this space is defined such that the distance to the boundary is infinite.[32]

This perfectly describes the Smith Chart: the center of the chart represents the origin of a hyperbolic space, and as one moves toward the outer edge ($|\Gamma| \to 1$), the "hyperbolic distance" (representing the magnitude of the impedance or the VSWR) grows exponentially.[31] The VSWR, when measured in decibels, behaves like a hyperbolic distance metric induced by the invariant cross-ratio of Möbius transformations.[31]

Artistic Synthesis: The Escher Woodcuts

The visual aesthetic of the Smith Chart has a direct mathematical parallel in the work of M.C. Escher, particularly the *Circle Limit* woodcuts.[31] Escher's *Circle Limit IV* (Heaven and Hell) depicts a tessellation of angels and demons where the figures appear to shrink as they approach the edge of the circle.[31] This "shrinking" is actually a Euclidean distortion of a periodic mosaic of constant size in hyperbolic space.[33]

Research comparing *Circle Limit IV* to the Smith Chart reveals that the radial placement of Escher's figures corresponds exactly to the VSWR scale.[31] Both the engineer and the artist are using the same Möbius-driven geometry to represent an infinite reality within a finite, circular boundary.[13]

Practical Navigation and Impedance Matching

The ultimate purpose of the Smith Chart for an EE student is its application as a graphical

calculator for impedance matching.[10] Matching is the process of transforming a load impedance Z_L to match the source impedance Z_0, thereby ensuring maximum power transfer and eliminating signal reflections.[11]

Navigation via Lumped Elements

When components are added in series or shunt (parallel) to a circuit, the impedance point moves along the chart's coordinate lines in predictable ways [5]:

- **Series Reactance:** Movements occur along the constant resistance circles (r-circles).[5] Adding an inductor moves the point clockwise, while adding a capacitor moves it counter-clockwise.[5]
- **Shunt Susceptance:** Movements occur along constant conductance circles (g-circles).[5] Navigation in the shunt plane is most easily performed using an Admittance (Y) chart, which is a mirrored version of the Impedance (Z) chart.[2]

To facilitate complex matching involving both series and parallel elements, engineers utilize the "Immittance" (Z-Y) chart, which overlays both sets of coordinates.[12] This allows the designer to alternate between impedance and admittance movements without manually rotating the chart.[12]

Distributed Elements and Transmission Lines

As frequency increases into the microwave range, "lumped" components (discrete inductors and capacitors) become difficult to implement due to parasitic effects.[11] Instead, engineers use lengths of transmission lines and "stubs" as reactive elements.[10]

Moving along a transmission line of characteristic impedance Z_0 corresponds to a simple rotation around the center of the Smith Chart.[10] The magnitude of the reflection coefficient $|\Gamma|$ remains constant (assuming a lossless line), and the point moves clockwise toward the generator.[10] One full rotation around the chart (360°) represents a transmission line length of exactly half a wavelength ($\lambda/2$).[4]

Component Addition	Chart Used	Geometric Trajectory

Series Inductor	Z-Chart	Clockwise along Constant Resistance.[5]
Series Capacitor	Z-Chart	Counter-Clockwise along Constant Resistance.[5]
Shunt Inductor	Y-Chart	Counter-Clockwise along Constant Conductance.[12]
Shunt Capacitor	Y-Chart	Clockwise along Constant Conductance.[12]
Transmission Line	Z or Y	Clockwise Rotation about the Center.[10]

Distributed Matching: Stub Tuners

The single-stub tuner is a fundamental RF matching technique that employs a parallel branch of transmission line (a "stub") to cancel out reflections.[10] The Smith Chart simplifies this multi-step complex analysis into a geometric routine [38]:

1. **Normalization and Plotting:** The load impedance Z_L is normalized to $z_L = Z_L/Z_0$ and plotted.[38]
2. **Admittance Transformation:** Because the stub is in parallel, the impedance point is transformed to its equivalent admittance y_L by rotating 180° on the chart.[2]
3. **Rotation to the Unit Conductance Circle:** The point is rotated clockwise (moving along the transmission line toward the generator) until it intersects the circle where the real part of the admittance (conductance) equals 1.0.[22] At this point, the admittance is $1 + jb$.[38]
4. **Stub Cancellation:** A shorted or open stub is designed to provide a susceptance of $-jb$.[38] Adding this in parallel brings the total admittance to $1 + j0$, which is the center of the chart and represents a perfect match.[22]

Pedagogical Insights and Common Student Misconceptions

Mastering the Smith Chart requires the student to move beyond rote memorization of movements and toward a conceptual understanding of the underlying physics and math. Several common pitfalls consistently hinder this progress.

Frequency Dependence and Reactance

Students often erroneously treat a point on the Smith Chart as a constant property of a component.[41] However, a component's location on the chart is a "snapshot" at a specific frequency.[4] Since reactance $X_L = \omega L$ and $X_C = -1/(\omega C)$, the point $z = r + jx$ will migrate along a frequency locus as the operating frequency changes.[4] A resistor will remain stationary (ideally), but an inductor will move clockwise toward higher reactance as frequency increases.[21] Understanding this "motion" is critical for designing wideband matching networks that must maintain a low VSWR over a range of frequencies.[4]

Electrical Length and Velocity Factor

A frequent source of error in laboratory exercises is the failure to distinguish between physical length and electrical length.[40] The Smith Chart is graduated in "wavelengths toward generator," where one rotation is 0.5λ.[4] However, the wavelength λ in a transmission line is not the free-space wavelength λ_0.[40] Due to the dielectric constant of the cable, the wave travels at a velocity $v_p = c/\sqrt{\epsilon_r}$.[40] For common coaxial cables like RG-58, the velocity factor is approximately 0.66, meaning the physical length of a 0.5λ stub is only 66% of its free-space value.[40] Students must always adjust their physical measurements by this factor before plotting or implementing their Smith Chart solutions.[40]

Reference Planes and Electrical Delay

When using high-precision instruments like a VNA, the "reference plane" is the point where the device is calibrated.[4] If an additional cable or connector is placed between the VNA and the load, the Smith Chart will display the impedance at the VNA port, not the load.[40] This is perceived as a rotation on the chart.[40] To see the true load impedance, the student must perform "port extension" or "de-embedding," which mathematically rotates the point counter-clockwise back to the load interface.[40]

Advanced RF Analysis and the Chart's Modern Role

While basic matching is the starting point, the Smith Chart is also used for advanced analysis, including stability, noise, and gain circles in amplifier design.[14]

Stability Circles and S-Parameters

For active devices, the scattering parameters (S-parameters) are plotted on the Smith Chart to determine stability.[7] If a transistor's input or output reflection coefficient exceeds unity, the device may oscillate.[7] Engineers plot "stability circles" on the chart to identify forbidden regions

of impedance that would cause such instability.[13] The 3D Smith Chart is particularly useful here, as stability circles that would "overflow" a 2D chart can be viewed in their entirety on the Southern hemisphere of the Riemann sphere.[7]

Noise Figure and Gain Contours

In Low-Noise Amplifier (LNA) design, there is a trade-off between maximum gain and minimum noise.[11] The chart allows designers to overlay "Constant Noise Figure" circles and "Constant Gain" circles.[12] The intersection of these circles allows the engineer to visually select an optimal source impedance that provides acceptable gain while keeping the noise figure within specifications.[11]

Advanced Parameter	Chart Use Case	Visualization Goal
S11 / S22	Impedance Matching	Move toward the center $(0, 0)$.[4]
Stability Circles	Oscillator/Amp Design	Stay outside unstable regions.[21]
Constant Gain Circles	Amplifier Design	Maximize power delivery.[12]
Noise Figure Circles	LNA Design	Minimize system noise floor.[11]

Conclusion: The Enduring Nomogram in a Digital Era

The Smith Chart stands as a unique artifact in the history of engineering—a manual tool that has not only survived the computer age but has been integrated into the very heart of modern digital instrumentation.[1] Its longevity is derived from its perfect alignment with the underlying mathematical structure of electromagnetic wave propagation.[3] By mastering the Möbius transformations that define the chart and the hyperbolic geometry that governs its distances, the student gains more than a calculation tool; they acquire a visual language for the high-frequency world.[14]

Whether used to match a simple dipole antenna or to analyze the stability of a terahertz transistor, the Smith Chart provides a bounded, conformal, and topologically complete workspace.[1] It remains an "analog" oasis of clarity in a sea of digital data, continuing to be the RF engineer's most trusted guide for navigating the complex landscapes of resistance, reactance, and reflection.[3]

Works cited

1. The 3D Smith chart and its journey to reality: from negative resistance to negative capacitance - Infoscience, accessed February 28, 2026, https://infoscience.epfl.ch/bitstreams/56aa5ffc-bdd9-4524-ab7c-ce626288cc3a/download
2. (PDF) RF engineering basic concepts: the Smith chart - ResearchGate, accessed February 28, 2026, https://www.researchgate.net/publication/51990536_RF_engineering_basic_concepts_the_Smith_chart
3. The Enigmatic Smith Chart - RF Engineer's Essential Tool., accessed February 28, 2026, https://www.dynamicengineers.com/content/the-enigmatic-smith-chart-an-rf-engineer-s-essential-tool
4. Smith chart - Wikipedia, accessed February 28, 2026, https://en.wikipedia.org/wiki/Smith_chart
5. RF Engineering Basic Concepts: The Smith Chart - CERN Indico, accessed February 28, 2026, https://indico.cern.ch/event/115334/sessions/5217/attachments/50210/72210/C1_Caspers_Smith_Chart.pdf
6. Mathematical properties of the Smith chart, accessed February 28, 2026, https://www.johndcook.com/blog/2025/10/23/smith-chart/
7. A 3D Smith Chart based on the Riemann Sphere for Active and Passive Microwave Circuits - SciSpace, accessed February 28, 2026, https://scispace.com/pdf/a-3-d-smith-chart-based-on-the-riemann-sphere-for-active-and-3camliur9l.pdf
8. RF Engineering - Basic Concepts: The Smith Chart, accessed February 28, 2026, https://cas.web.cern.ch/sites/default/files/lectures/ebeltoft-2010/caspers-smith-chart.pdf
9. PRACTICAL METHOD FOR DETERMINATION THE WAVEGUIDE IMPEDANCE USING SMITH CHART, accessed February 28, 2026, https://www.upet.ro/annals/electrical/doc/2021/Lucrare%2011_Dobra.pdf
10. Smith Chart Calculations - ARRL, accessed February 28, 2026, https://www.arrl.org/files/file/Antenna%20Book%20Supplemental%20Files/22nd%20Edition/Smith%20Chart%20Supplement%20-%20Corrected%20Jan%202012.pdf
11. Impedance Matching and Smith Chart Impedance - Analog Devices, accessed February 28, 2026, https://www.analog.com/en/resources/technical-articles/impedance-matching-and-smith-chart-impedance-maxim-integrated.html
12. Smith Chart : Basics, Components, Types, Examples and Applications - ElProCus, accessed February 28, 2026, https://www.elprocus.com/what-is-a-smith-chart-basics-types-its-applications/
13. Two Compact Smith Charts: The 3D Smith Chart and a Hyperbolic Disc Model of the Generalized Infinite Smith Chart - ROMJIST, accessed February 28, 2026,

http://www.romjist.ro/content/pdf/12-amuller.pdf
14. What is the 3D Smith Chart? - everything RF, accessed February 28, 2026, https://www.everythingrf.com/community/what-is-the-3d-smith-chart
15. Möbius transformation - Wikipedia, accessed February 28, 2026, https://en.wikipedia.org/wiki/M%C3%B6bius_transformation
16. The Geometry of Möbius Transformations - John Olsen's homepage, accessed February 28, 2026, https://johno.dk/mathematics/moebius.pdf
17. The Geometry of the Smith Chart - Remcycles, accessed February 28, 2026, https://remcycles.net/blog/smith_chart_geometry.html
18. Understanding the Smith chart | Rohde & Schwarz, accessed February 28, 2026, https://www.rohde-schwarz.com/us/products/test-and-measurement/essentials-test-equipment/spectrum-analyzers/understanding-the-smith-chart_257989.html
19. Smith Chart Basics - UC Homepages - University of Cincinnati, accessed February 28, 2026, https://homepages.uc.edu/~ferendam/Courses/EE_611/Smith/Smith1.html
20. Understanding the Smith Chart - Copper Mountain Technologies, accessed February 28, 2026, https://coppermountaintech.com/wp-content/uploads/2023/02/SmithChart.pdf
21. accessed February 28, 2026, https://circuitdigest.com/article/basics-of-smith-chart-and-how-to-use-if-for-impedance-matching
22. 3.3 The Smith Chart - PTC Community, accessed February 28, 2026, https://community.ptc.com/sejnu66972/attachments/sejnu66972/PTCMathcad/192347/1/3.3_The_Smith_Chart.pdf
23. antennas tx/rx - Impedance matching and the Smith chart – The fundamentals., accessed February 28, 2026, https://ieee.li/pdf/essay/smith_chart_fundamentals.pdf
24. The Smith Chart - UTK-EECS, accessed February 28, 2026, https://web.eecs.utk.edu/~ggu1/files/ECE341Notes_7_SmithChart_as%20the%20z-chart_Spring19.pdf
25. What is and how to read the the Smith chart? | Transfer Multisort Elektronik USA - Tme.eu, accessed February 28, 2026, https://www.tme.com/us/en-us/news/library-articles/page/70732/what-is-and-how-to-read-the-the-smith-chart/
26. Conformal Mapping -- from Wolfram MathWorld, accessed February 28, 2026, https://mathworld.wolfram.com/ConformalMapping.html
27. mobius transformation - Proof that Möbius tranformations are conformal, accessed February 28, 2026, https://math.stackexchange.com/questions/1685517/proof-that-m%C3%B6bius-tranformations-are-conformal
28. The 3D Smith Chart: From Theory to Experimental Reality - SciSpace, accessed February 28, 2026, https://scispace.com/pdf/the-3d-smith-chart-from-theory-to-experimental-reality-2xuvzwsleg.pdf

29. (PDF) 3D Smith charts - ResearchGate, accessed February 28, 2026, https://www.researchgate.net/publication/258926877_3D_Smith_charts
30. Hyperbolic geometry - Wikipedia, accessed February 28, 2026, https://en.wikipedia.org/wiki/Hyperbolic_geometry
31. (PDF) Escher's art, Smith chart, and hyperbolic geometry - ResearchGate, accessed February 28, 2026, https://www.researchgate.net/publication/3427377_Escher's_art_Smith_chart_and_hyperbolic_geometry
32. Cross ratio to define a metric on the hyperbolic plane - Applied Mathematics Consulting, accessed February 28, 2026, https://www.johndcook.com/blog/2025/11/26/hyperbolic-metric/
33. The Geometric Viewpoint | Tessellations of the Hyperbolic Plane and M.C. Escher, accessed February 28, 2026, https://web.colby.edu/thegeometricviewpoint/2016/12/21/tessellations-of-the-hyperbolic-plane-and-m-c-escher/
34. Eschers Art, Smith Chart, and Hyperbolic Geometry | PDF - Scribd, accessed February 28, 2026, https://www.scribd.com/document/447185511/Eschers-art-Smith-chart-and-hyperbolic-geometry
35. “L” Matching Networks, accessed February 28, 2026, https://web.ece.ucsb.edu/~long/ece145a/Notes5_Matching_networks.pdf
36. Impedance and Admittance on Smith Chart - Ximera, accessed February 28, 2026, https://ximera.osu.edu/em/electromagnetics/smithChart/digInSmithChartImpedanceAdmittanceExamples
37. impedance matching - Use of Smith charts - Electrical Engineering - Stack Exchange, accessed February 28, 2026, https://electronics.stackexchange.com/questions/97311/use-of-smith-charts
38. Smith Chart - UNH, accessed February 28, 2026, https://unh.edu/ece/ECE603/Acrobat%20Files/Smith%20Chart.pdf
39. Evaluation of Stub Matching Techniques: A systematic review - ResearchGate, accessed February 28, 2026, https://www.researchgate.net/publication/390222621_Evaluation_of_Stub_Matching_Techniques_A_systematic_review
40. Impedance Matching and Smith Charts - USPAS, accessed February 28, 2026, https://uspas.fnal.gov/materials/08UCSC/mml13_matching+smith_chart.pdf
41. Smith Chart for Dummies - Electrical Engineering Stack Exchange, accessed February 28, 2026, https://electronics.stackexchange.com/questions/475531/smith-chart-for-dummies
42. Smith Chart Basics - Microwaves 101, accessed February 28, 2026, https://www.microwaves101.com/encyclopedias/smith-chart-basics
43. The Smith Chart and Its Relation to the Reflection Coefficient and Impedance - Technical Articles - All About Circuits, accessed February 28, 2026, https://www.allaboutcircuits.com/technical-articles/understanding-the-smith-cha

rt-relection-coefficient-and-normalized-impedance/