


AM-5010

User Guide




AM-5010 Dimensions


• Dimensions (mm)



Side



Bottom · mount



Top · propeller side

AM-5010 Specifications

• Basic Specifications

Stator Dimensions	$\Phi 55.6 \times 33.9$ mm
Slots / Poles	24N28P (14 pole pairs)
Motor Weight	177 g
KV Value	KV300
Rated Voltage	22.2 ~ 29.6 V
Max Current	37.7 A
Max Power	916 W
Recommended Prop	15 ~ 16 inch (15×5.5)
Operating Temp	-20 ~ +85 °C

AM-5010 Performance Data

6S LiPo, 20%–100% throttle on static thrust stand. Measured values; rated specs may differ.

• Propeller 15 × 5.5

Throttle	Thrust (g)	Current (A)	Power (W)	Eff. (g/W)	Temp (°C)
20%	160	0.49	12	12.0	21
40%	420	1.51	38	10.8	—
60%	863	4.14	104	8.4	—
80%	1485	8.92	223	6.6	—
100%	2243	16.22	404	5.5	—

AM-5010 Installation



1. **Mounting** — Fix the motor to the arm through the bottom mounting holes. Follow the screw size and spacing on the drawing and use screws that do not reach the windings.
2. **ESC wiring** — Connect the three motor wires to the ESC outputs. To reverse the rotation, swap any two wires or reverse it in the ESC settings.
3. **Spin check** — Without a propeller, run at low throttle and check the direction and for abnormal noise.
4. **Propeller** — Fit a propeller matching the rotation and tighten the nut firmly.
Recommended: 15 ~ 16 inch (15×5.5).

AM-5010 Safety Notes

- Do not exceed the rated voltage. Rated: 22.2 ~ 29.6 V.
- Use an ESC rated with margin above the motor maximum current. Max current: 37.7 A.
- Always remove the propeller while wiring, configuring or bench testing.
- The motor can be hot right after operation; let it cool before touching.
- Keep metal debris away from the magnets; stop using the motor if the shaft is bent or the bearings are noisy.



<Detailed Manual>

novaX