

	1	2	3	4	5	6	7	8
A								
B								
C								
D								
E								
F								

1. Connector & input protection

Field connector, 2-stage bidirectional TVS surge protection, chassis isolation

File: connector.kicad_sch

2. Power

eFuse (reverse/OV/UV), 60V buck to 5V, LDO 3.3V

File: power.kicad_sch

3. MCU

STM32G0B1CCT3, SWD, reset, internal temperature sensor

File: mcu.kicad_sch

4. Measurement

Capacitive humidity sensor (PCAP04) and Pt1000 2-wire (ADS1220)

File: measurement.kicad_sch

5. Analog outputs

2x DAC8760 V/I output with TPS26611 miswiring protection

File: analog_out.kicad_sch

6. RS-485

THVD2450 +/-70V fault-protected transceiver

File: rs485.kicad_sch

DOTECH HMT500 – Oil Moisture Transmitter – Schematic v0.7

v0.5: J1 = JST GH 1.25 mm 8P side entry (SM08B-GHS-TB), harness W-2 to M12 8P; J5 chassis spring contact (was M12 shell pin).

v0.4: J3 = JST SH 1.0 mm 4P (SM04B-SRSS-TB side entry, v0.5) for sensor harness W-1 direct from HTX99R (no feedthrough, mech Rev F); Pt1000 2-wire (Kelvin split at J3 pads).

v0.3: MCU STM32G0B1CCT3 (LQFP48, -40..125 C, in-house part); TPS26600PWP official pinout; single axial PCB 57x23 (mech Rev C).

Signal flow: J1 field connector -> protection -> eFuse -> 5 V buck -> 3.3 V LDO; sensor head J3 -> PCAP04 / ADS1220 -> MCU -> DAC8760 x2 / THVD2450 -> J1

Outputs: RS-485 Modbus RTU + 2x analog (4-20 mA / 0-20 mA / 0-10 V / 0-5 V selectable). Supply 12-30 V DC.

Protection target: any pin pair +/-30 V continuous (miswiring), surge +/-1 kV, ESD +/-8 kV contact.

Power symbols: GND, +3V3, +3V3A (analog 3.3 V), +5V, VIN_P (protected input), CHASSIS. Inter-sheet signals: global labels.

v0.6: parts cleanup (-16: pull-ups R11-15, LED D3/R16, RS-485 R60/61 D60/61, FB2 C19 C11 C2 C6); PCB temperature = ADS1220 + MCU internal sensors.

v0.7: DAC8760 datasheet pinout (HTSSOP-24 PWP); +VSENSE via OPA197 follower (U12/U13); external ISET-R 15k 0.1%; DACs on SPI2 daisy chain, common DAC_LATCH.

VERIFY: LMR36006, PCAP04, TPS26611 pin numbers are placeholders (datasheets not accessible when drawn). TPS2660: RTN link R22 to confirm.

TBD footprints: J5 chassis contact, CMC, GDT, buck inductor, LMR36006, PCAP04, TPS26611.

표기 규칙: 부품번호 = 굵은 글자 (R1, U4) / 부품값 = 보통 글자 (10k, DAC8760) / 전원 네트 = 기울임 글자 (+3V3, VIN_P)

신호 네트 = 테두리 있는 라벨 (SPI_SCK, OUT1_EXT) - 네트 이름은 부품번호·부품명과 겹치지 않게 지음

글자 겹침: 생성기가 부품 몸체·핀·선·라벨·메모와 겹치지 않는 자리에 자동 배치하고, 겹치면 생성 실패로 처리

VERIFY=YES parts: pin numbers LMR36006/PCAP04/TPS26611; TPS2660 R22

Design notes: docs/hw/circuit-design.md

Oil moisture transmitter HMT500 – RS-485 + 2x V/I analog output

DOTECH Co., Ltd.

Sheet: /

File: HMT500.kicad_sch

Title: HMT500 Top

Size: A3

Date: 2026-09-29


Rev: 0.7

KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4

Id: 1/7

FIELD CONNECTOR


J1 JST GH 8P -> W-2 -> M12 8P
EE364 pinout, pin n = pin n



Pins 1, 7: not connected
GH mounting pads (MP): PCB only

INPUT SURGE / REVERSE-POLARITY PROTECTION


TVS bidirectional: -30 V miswiring must not conduct



SMDJ 3 kW (1st) -> R1 -> SMBJ (2nd) -> eFuse on sheet Power

CIRCUIT GND <--> CHASSIS (floating)

회로 GND-외함 분리



PCB-housing creepage >= 2 mm

GDT conducts only on line-to-ground surge

주요 부품 — 역할 · 특징 · 사양

부품번호	부품	역할	특징 · 사양
J1	SM08B-GHS-TB	현장 커넥터 연결	JST GH 1.25 mm 8P 옆 삽입, 하네스 W-2 -> M12 8P, 핀 n = M12 핀 n
L1	CMC 2x1mH 0.3A	전원선 공통모드 노이즈 차단	2 x 1 mH, 0.3 A — 전도 방출-전도 내성 대책
D1	SMDJ36CA	입력 서지 1단 흡수	TVS 양방향 3000 W, 36 V — -30 V 오결선에 도통 안 함
R1	4.7R 1W pulse	1단-2단 서지 분담	MELF 1 W 펄스 내량 저항
D2	SMBJ33CA	입력 서지 2단 클램프	TVS 양방향 600 W, 33 V — eFuse 정격 이하로 제한
GDT1	GDT 230V	회로 GND-외함 서지 방전	230 V 방전관, 선-대지 서지 때만 도통 (평소 절연)
C3, R2	4.7n Y2 / 1M	GND-외함 고주파 결합	Y2 안전 콘덴서 + 1 MΩ 정전기 방전 경로
J5	Chassis contact	PCB-하우징 겹치 점검	SMD 스프링 점검, PCB 가장자리 -> 하우징 Ø27 내면

* 표시 값은 데이터시트로 확인

VERIFY=YES parts: pin numbers LMR36006/PCAP04/TPS26611; TPS2660 R22
Design notes: docs/hw/circuit-design.md
Oil moisture transmitter HMT500 - RS-485 + 2x V/I analog output


DOTECH Co., Ltd.

Sheet: /1. Connector & input protection/
File: connector.kicad_sch

Title: HMT500 Connector & input protection


Size: A3	Date: 2026-09-29	Rev: 0.7
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 2/7

MCU DECOUPLING




100 nF at VDD, VBAT, VREF+ (C20); 4.7 uF bulk

MCU 바이패스




RESET

리셋



Fault lines: MCU pull-ups
(PB3-4, PB11, PC6-7 internal)



MCU NOTES (STM32G0B1)

MCU 설정 메모

BOOT0 shares PA14/SWCLK - no pull-down.

Option bytes: nBOOT_SEL=1, nBOOT0=1

-> boot from flash (RS-485 bootloader 0x08000000).

VDDA = VDD (LQFP48); VREF+ tied to +3V3 (C20).

PCB temp (mid): internal sensor, ADC ch TS + TS_CAL.

Cortex-M0+: no SWO (J2 pin 6 NC).

Same die as DP2000 (G0B1CCT6); T3 = -40..125 C.

주요 부품 — 역할 · 특징 · 사양

부품번호	부품	역할	특징 · 사양
U4	STM32G0B1CCT3	제어·통신·보정 연산	Cortex-M0+ 64 MHz, 플래시 256 KB, RAM 144 KB, -40-125 °C, LQFP48, 내부 온도센서 (PCB 온도), SPI1 = 측정 · SPI2 = DAC 전용
J2	TC2030-IDC-NL	생산 때 펌웨어 기록 (SWD)	PCB 패드만 (부품 없음). 이후 업데이트는 RS-485 부트로더
C21	100n	리셋 노이즈 필터	NRST 핀, 물딩 후 EMC 여유

* 표시 값은 데이터시트로 확인

VERIFY=YES parts: pin numbers LMR36006/PCAP04/TPS26611; TPS2660 R22
Design notes: docs/hw/circuit-design.md
Oil moisture transmitter HMT500 - RS-485 + 2x V/I analog output

DOTECH Co., Ltd.

Sheet: /3. MCU/
File: mcu.kicad_sch






Title: HMT500 MCU

Size: A3
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4

Date: 2026-09-29

Rev: 0.7

Id: 4/7



주요 부품 — 역할 · 특징 · 사양			
부품번호	부품	역할	특징 · 사양
J3	SM04B-SRSS-TB	센서 하네스 W-1 연결	JST SH 1.0 mm 4P 옆 삽입, 1-2 = MK33, 3-4 = Pt1000
U5	PCAP04-AQFM-24	습도 센서 정전용량 측정	정전용량-디지털 변환, 기준 C와 비율 측정, 내부 DSP, SPI*
C22	220p COG 1%	PCAP04 기준 용량	MK33-W mini (200 pF)와 비슷한 값, COG (온도 변화 거의 없음)
U6	ADS1220IPWR	Pt1000 온도 측정	24비트 ADC, PGA, 여가 전류 IDAC, 50/60 Hz 제거, 내부 온도센서 (PCB 온도)
R19	4.02k 0.01% 5ppm	Pt1000 비율 측정 기준저항	IDAC 전류 오차 상쇄, 온도계수 5 ppm/°C
R17, R18, C27	1k / 10n	입력 RC 필터	차동-공통모드 노이즈 제거
* 표시 값은 데이터시트로 확인			

VERIFY=YES parts: pin numbers LMR36006/PCAP04/TPS26611; TPS2660 R22
Design notes: docs/hw/circuit-design.md
Oil moisture transmitter HMT500 - RS-485 + 2x V/I analog output
DOTECH Co., Ltd.


Sheet: /4. Measurement/
File: measurement.kicad_sch

Title: HMT500 Measurement

Size: A3	Date: 2026-09-29	Rev: 0.7
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		
Id: 5/7		

ANALOG OUTPUT CH1 - V/I selectable, miswiring protected -> connector pin 4


아날로그 출력 1



VOUT + IOUT one terminal (datasheet 9.1.1.3). +VSENSE = U12 OPA197 follower of terminal OUT1_EXT (after R30) via R31:
no +VSENSE 60k leakage in current mode, series-R drop corrected in voltage mode. ISET-R = R32 external 15k 0.1%.

CH1 DECOUPLING

채널 1 바이패스



C45: U12 OPA197 V+

DAC SELECTION (decision #10)

DAC 선정

U7/U8 fitted: DAC8760 (16-bit, I + V output).

Drop-in alternates (same pinout, no layout change):

DAC7760 12-bit, I + V (cost-down, V/I kept)

DAC8750 16-bit, I only 4-20/0-20/0-24 mA (EE364-equiv.)


DAC7750 12-bit, I only (-5 uA/step vs EE364 2 uA)

Current-only (x750): VOUT/+VSENSE/-VSENSE absent -

check pin handling before fitting (VERIFY).

ANALOG OUTPUT CH2 - V/I selectable, miswiring protected -> connector pin 5


아날로그 출력 2



VOUT + IOUT one terminal (datasheet 9.1.1.3). +VSENSE = U13 OPA197 follower of terminal OUT2_EXT (after R40) via R41:
no +VSENSE 60k leakage in current mode, series-R drop corrected in voltage mode. ISET-R = R42 external 15k 0.1%.

CH2 DECOUPLING

채널 2 바이패스



C55: U13 OPA197 V+

DAC SPI - SPI2 daisy chain

DAC 전용 SPI

SPI2 for the DACs only (PB13 SCK, PB14 MISO, PB15 MOSI).

DAC_MOSI -> U7 DIN, U7 SDO -> DAC_DAI5Y -> U8 DIN,


U8 SDO -> DAC_MISO (readback / fault status).

One 48-bit frame (U8 word first), then one DAC_LATCH

(PB10) edge: both channels update together.

Init: set DCEN in U7 (24-bit), then in U8 (48-bit).

R33: U8 shifts in NOP (0x00) until U7 SDO is enabled.



주요 부품 - 역할·특징·사양

부품번호	부품	역할	특징·사양
U7, U8	DAC8760IPWP	아날로그 출력 1·2	16비트, 4-20 / 0-20 / 0-24 mA · 0-5 / 0-10 V 선택, 내부 기준, 고장 알람 - 대체 DAC7760/8750/7750
U9, U10	TPS26611	출력 오걸선 보호	출력 단자 과전압·역전압 차단, 전류 제한, 고장 출력 FLT*
R30, R40	10R pulse (2512)	서지 전류 제한	출력 보호기와 TVS 사이 직렬
D30, D40	SMAJ33CA	출력 서지 클램프	TVS 양방향 400 W, 33 V
C41, C51	1n 100V	출력 고주파 필터	케이블로 들어오는 RF 억제
U12, U13	OPA197IDBVR	+VSENSE 버퍼 (이득 1)	36 V, 입출력 레일투레일, 오프셋 100 uV* - 단자 전압을 +VSENSE로, 전류 모드 누설 0
R31, R41	10k	버퍼 입력 보호	R30-R40 뒤 단자 전압을 OPA197 + 입력으로 (서지 전류 제한)
R32, R42	15k 0.1% 25ppm	외부 ISET-R (전류 기준)	내부 저항보다 온도 드리프트 작음 -> 전류 출력 정확도
R33	100k	데이터지 체인 폴다운	U7 SDO 켜기 전 U8에 NOP (0x00) 입력

* 표시 값은 데이터시트로 확인

VERIFY=YES parts: pin numbers LMR36006/PCAP04/TPS26611; TPS2660 R22
Design notes: docs/hw/circuit-design.md
Oil moisture transmitter HMT500 - RS-485 + 2x V/I analog output
DOTTECH Co., Ltd.
Sheet: /5. Analog outputs/
File: analog_out.kicad_sch

Title: HMT500 Analog outputs

Size: A3	Date: 2026-09-29	Rev: 0.7
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 6/7

