1. HDMI TYPE-A SOURCE CONNECTOR



HDMI_HEAC_N remains unused in Rev A; the selected monitor uses video/DDC/CEC/HPD only.

Shell bonds to chassis at the connector. TMDS shield returns use the local digital ground plane.

2. HDMI ESD / LOW-CAPACITANCE SHUNTS







Place all HDMI ESD arrays immediately behind J801 with no stubs on TMDS pairs.

Confirm CMS DDC 5 V tolerance and final pull-up values against the Radxa carrier reference before layout release.

3. DEDICATED IO_5V0 / 2 A BUCK



IO_5V0 feeds CMS ±12-V pin 106, HDMI source 5 V and USB-touch VBUS; no monitor-power sFuse.

4. USB TOUCH HOST PORT



Only USB 2 is allocated from the CM5. A standard USB 3 A-to-B cable still carries USB 2 touch data.

The monitor-side SuperSpeed Type-B receptacle is not duplicated as a device connector on this host carrier.



DISPLAY_12V design load: 2.5 A continuous / 30 W branch, covering the locked 25 W monitor.

No local display eFuse. Use the upstream AUX_12V branch fuse and HOST keyed 18 AWG harness.

5. 12 V / 2.5 A DISPLAY POWER

6. HINGE-EDGE HARNESS BUILD



×20 HDMI, HOST, USB touch, HOST, 12 V; 1000 +/− 25 mm each, with separate retained hinge and service loops.

Acceptance: full lid travel plus 300 mm panel OR / 40 degree tilt; no connector tension or hinge-line bend.

Carrier connectors face down. Store released loops clear of fans, PSU airflow, board keepouts and sharp edges.

No display eFuse: separate fused DISPLAY_12V and DISPLAY_IO_12V branches feed this sheet.
USB-A is the CM5 host end; cable terminates in USB-B SuperSpeed at the monitor.
Carrier connectors face downward at the hinge-edge harness notch
15.6-inch lid monitor: HDMI video, USB 2 touch, 12 V / 2.5 A

ProComm	
Sheet: /	
File: Display-Harness.kicad_sch	
Title: Radxa CM5 ProComm Carrier – Lid Display Harness	
Size: A1	Date: 2026-08-14 — **Rev: A1**
KiCad E.D.A. 10.0.5-rc1	Id: 1/1