


LiPo Charger




External Power Sense

U2



**Fully compatible to Espressif's
ESP32-DevKitC connectors J2&J3!**



Note:

1. When ESP32-WROVER, take in mind that GPIO16<27> and GPIO17<28> are not connected.
2. GPIO6 to GPIO11 are connected to the SPI flash integrated on the module and are not recommended for other uses!


ESP32-WROOM-32D-4MB



Internal Bootstrapping Resistors

MTDI/GPIO12:	Pull-Down
GPI00:	Pull-Up
GPI02:	Pull-Down
GPI04:	Pull-Down
MTDO/GPIO15:	Pull-Up
GPI05:	Pull-Up

ESP_EN



Software Selectable Pins

Interface	Signal	Pin
EMAC	EMAC_MDC_out EMAC_MDIO_in EMAC_MDO_out EMAC_CRS_out EMAC_COL_out	Any GPIO
I2C	I2CEXT0_SCL_in I2CEXT0_SDA_in I2CXT1_SCL_in I2CXT1_SDA_in I2CEXT0_SCL_out I2CEXT0_SDA_out I2CXT1_SCL_out I2CXT1_SDA_out	Any GPIO
General Purpose SPI	HSPIQ_in/_out HSPID_in/_out HSPICLK_in/_out HSPICSO_in/_out HSPICL1_out HSPICL2_out VSPIQ_in/_out VSPID_in/_out VSPICLK_in/_out VSPICSO_in/_out VSPICL1_out VSPICL2_out	Any GPIO

For more information refer to [ESP_WPM332_datasheet_en.pdf](#).

Voltage of Internal LDO(VDD,SDIO)				Bootstrapping Pins Settings
Pin	Default	3.3V	1.8V	
GPIO12/MTDI	Pull-Down	0	1	
Bootling Mode				
Pin	Default	SPI Flash Boot	Download Boot	
GPIO0	Pull-Up	1	0	
GPIO2	Pull-Down	Don't-care	0	
Debugging Log on UOTXD During Bootling				
Pin	Default	UOTXD Toggling	UOTXD Silent	
GPIO15/MTDO	Pull-Up	1	0	
Timing of SDIO Slave				
Pin	Default	Falling-edge:Output	Falling-edge:Input Rising-edge:Output	Rising-edge:Input Rising-edge:Output
GPIO15/MTDO	Pull-Up	0	0	1
GPIO5	Pull-Up	0	1	1



Sheet: /
File: working.kicad_sch



Title: ESP32-DevKit-Lipo

Size: A3	Date: 2020-06-09
KiCad E.D.A. eeschema 7.0.6	

Rev: C
Id: 1/1