Voltage Regulation

VIN Range 2.2V–6.0V

Take care when closing this jumper, it removes the 6V/2A fuse.

RTC

1A/23V/620mV
0.65uA Leakage
0.3V drop at 10mA

300uA Leakage

3A/10V/280mV

1mAhr Capacity
~20 minute charge time

USB Power and Program Processor Board

ZED-F9P USB (u-center)

MicroMod Connector

Close "EN" jumper to allow processor control over 3.3V power.

GPS and PPS Antenna

Co-planar Calculation:
Copper Thickness (1oz): 1.4mil/0.035mm
Board thickness: 1.6mm
Dielectric thickness: 1.46mm
Er: 4.58
No clean process
Polygon Isolation: .3mm
RF Trace Width: 1mm

GPS Module ZED-F9P

Interrupt is not enabled by default.
Check ublox datasheet for more information

Close this jumper to enable SPI.

I2C unshifted 7 bit address: 0x42

ZED-F9P Backup Battery

*Battery Initial Charge: 2.3–2.8V
*Intial Battery Capacity (maH): 800mAH or Greater
*Battery Charge Rate: 1mA MAX
*Voff: 2.0V
*72 hours charge time from 2.0–3.1V

LEDs

Cut jumpers to remove respective LEDs

SWD

Buttons

Testpoints

Headers

Released under the Creative Commons Attribution Share-Alike 4.0 License
https://creativecommons.org/licenses/by-sa/4.0/

TITLE: ${PROJECTNAME}

Design by: Elias Santistevan

REV: >REV

Date: ${CURRENT_DATE}

Sheet: ${#}/${##}

Sheet: /
File: working.kicad_sch

Title:

Size: User | Date: | Rev:

KiCad E.D.A. kicad-cli 7.0.6-7.0.6~ubuntu22.04.1 | Id: 1/1