Certified Robustness for Model-Free PID Tuning by Step-Response Inspection

Pavel Otta[1], Daniel Pachner[1], Jiří Dostál[1] and Vladimír Havlena[2]*†

October 12, 2026

Abstract

The SPIN method tunes a PID controller without a model. After each setpoint step it counts the turns of the control error in three phase portraits and raises the gains until a count exceeds its limit. The limits were calibrated, and nothing guaranteed robustness. We prove two results. First, for any loop, the count of the integral portrait is within half a turn of half the number of setpoint crossings whenever the lobes of the error shrink. On loops that cancel the plant lags, which have a single gain parameter, the lobes always shrink in the relevant range, the sensitivity peak M_s grows strictly with the gain, and the error never crosses the setpoint if and only if $M_s \leq 1.394$. Second, for any stable digital loop with one degree of freedom, the increments of the error after a unit setpoint step are the impulse response of the sensitivity function. From one finite record we derive a lower and an upper bound on M_s that need no model and one assumption on the variation of the error after the record ends, and both converge to M_s. Used as the acceptance test of SPIN, the upper bound certifies every accepted tuning, the same record predicts the effect of lowering any gain, and every run of rejections by the test ends: the test never traps the original rules. Simulations on 19 loops confirm the theory.

1 Introduction

Let $L = CP$ be the loop transfer function and $S = 1/(1+L)$ the sensitivity function. The peak $M_s = \max_\omega |S|$ measures robustness: a value near 1.4 is safe, a value near 2 is close to the limit [2]. Tuning rules reach a chosen M_s with a model [2, 3]. After tuning, plants rarely check M_s, because a check needs a model or a test that disturbs production [5, 6].

1.1 The SPIN method

SPIN [1] tunes a PI or PID controller with gains K_i, K_p, K_d without a model. In each iteration it applies one setpoint step, records the control error e, and forms three phase portraits,

$$\Gamma_0 : (e, \textstyle\sum e), \quad \Gamma_1 : (\Delta e, e), \quad \Gamma_2 : (\Delta^2 e, \Delta e), \tag{1}$$

where $\sum e$ is the running sum of e and Δ the difference between samples. The portraits $\Gamma_0, \Gamma_1, \Gamma_2$ react to the bands of K_i, K_p, K_d, called bands $0, 1, 2$. The turn count N_k is the number of turns that Γ_k makes around its end point before the error stays within a band δ (2% of the step by default). Algorithm 1 gives the rule. SPIN needs no model and no plant-specific setting [1], but its limits $\bar{N}_k$ were chosen by calibration, and nothing guaranteed the robustness of the result. An online simulator lets the reader try SPIN.[1]

Algorithm 1: one iteration of SPIN [1]

```
Apply a setpoint step and record the error e.
if the record does not settle then
    divide K_i, K_p, K_d by 2, 4, 8                (back off)
else
    count the turns N_0, N_1, N_2 of Γ_0, Γ_1, Γ_2
    if N_k ≤ N̄_k for every band k then
        raise all gains by one step                (accept)
    else
        k ← lowest band with N_k > N̄_k
        lower the gain of band k by one step,
        raise the gains of the bands below k by one step
```

One step multiplies or divides a gain by $1/(1-\beta)$. Defaults: $\bar{N} = (0.5, 0.75, 1.0)$, $\delta = 0.02$, $\beta = 0.1$, each gain within $[0.001, 10]$ times its start.

1.2 Contributions

Result 1: what a count means (Section 2). Lemma 1 shows, for any loop, that a portrait turns by exactly half a turn between two zeros of its first coordinate, in any linear coordinates; so the count of Γ_0 is within half a turn of half the number of setpoint crossings when the lobes of the error shrink (Corollary 1). For loops that cancel the plant lags we prove that the lobes shrink, that M_s grows strictly with the loop gain, and that the error crosses the setpoint if and only if $M_s > 1.394$ (Propositions 1, 2). The Lambert-W and $1/e$ facts are classical [10, 11]; their link to the counts is new.

*[1] University Centre for Energy Efficient Buildings (UCEEB), Czech Technical University in Prague, Buštěhrad, Czech Republic. Corresponding author: pavel.otta@cvut.cz

†[2] Department of Control Engineering, Faculty of Electrical Engineering, Czech Technical University in Prague, Czech Republic.

[1] https://robopid-simulator.uceeb.cvut.cz

Result 2: the step certifies M_s (Sections 3, 4). For a digital loop the record gives the sensitivity exactly (Lemma 2). Theorem 1 turns one finite record into certified lower and upper bounds on M_s. Theorem 2 makes them the acceptance test of SPIN: every accepted tuning satisfies $M_s \le M^*$, every run of rejections by the test ends, and no sequence of rejections can return to the same gains. Proposition 3 predicts from the same record the effect of lowering any gain. Section 5 confirms all statements in simulation.

1.3 Related work

Frequency responses have been computed from step and relay responses [7], sensitivity functions and margins from closed-loop data with reference excitation or designed experiments [8, 9]. The setpoint overshoot method tunes PI controllers from one setpoint step [14]. Model-free tuning by repeated experiments [12, 13] or from one data set [15] optimizes performance. Here one normal setpoint step, without special excitation, gives a certified bound on M_s inside a model-free rule.

2 Result 1: What a Turn Count Means

2.1 Half turns

In each portrait (1), the second coordinate q is the running sum of the first, p; in continuous time $\dot q = p$, and the turns are counted around the end point, which we place at the origin. We state the results in continuous time; the sampled counts of SPIN approximate them. For Γ_0 the zeros of $p = e$ are the setpoint crossings, for Γ_1 the extrema of e.

Lemma 1 (Half turns) *Let $\dot q = p$ with p continuous, and let $t_1 < t_2$ be consecutive zeros of p with $q(t_1)q(t_2) < 0$. On $[t_1, t_2]$ the curve (p, q) turns counterclockwise around the origin by exactly half a turn. So does its image under any linear map with positive determinant, such as the whitening of [1].*

Proof: On (t_1, t_2), p keeps one sign, so the curve stays in one open half-plane bounded by the q-axis, and q moves monotonically from $q(t_1)$ to $q(t_2)$, that is from one ray of the q-axis to the opposite ray. In the half-plane the angle lies in an open interval of length π, so it changes by exactly π; for $p > 0$, q increases, and for $p < 0$ it decreases, so the turn is counterclockwise in both cases. A linear map with positive determinant maps the half-plane to a half-plane and the two rays to opposite rays, and it keeps the orientation. □

Corollary 1 (Counts and crossings) *Let p change sign at $t_1 < \cdots < t_m$, $m \ge 1$, before the record settles, let $q(t_j)$ alternate in sign, and let $q(t_1)$ have the sign of p before t_1. Then the turn count of (p, q) lies in $(\frac{m-1}{2}, \frac{m+1}{2})$. For Γ_0, these conditions hold when the areas of the lobes of e between crossings decrease strictly.*

Proof: Each of the $m-1$ intervals adds π (Lemma 1). Before t_1 and after t_m the curve stays in one open half-plane and starts or ends on the ray from which it turns counterclockwise, so each end adds an angle in $(0, \pi)$. For Γ_0, $q(t_j) = -\int_{t_j}^{\infty} e\,dt$ is an alternating sum of lobe areas; when they decrease, it has the sign of its first term. □

2.2 The lag-cancelled loop

Lambda, IMC and SIMC tunings cancel the plant lags [3]: PI $K_c(1 + 1/(T_i s))$ with $T_i = T$ on $Ke^{-sL_d}/(Ts+1)$, or series PID with $T_i = T_1$, $T_d = T_2$ on a plant with two lags. The loop is then

$$L(s) = \frac{k\,e^{-sL_d}}{sL_d}, \qquad k = \frac{KK_cL_d}{T_i}. \tag{2}$$

Proposition 1 (Exact robustness) *The loop (2) is stable for $0 < k < \pi/2$, with gain margin $\pi/(2k)$ and poles $W_j(-k)/L_d$, where W_j are the branches of the Lambert W function [10]. Its peak M_s is a strictly increasing function of k, given by*

$$k = x\sin x - x^2\cos x, \qquad \frac{1}{M_s^2} = 1 - \frac{2k\sin x}{x} + \frac{k^2}{x^2}, \tag{3}$$

where $x = \omega_p L_d \in (0, \pi/2)$ is the normalized peak frequency.

Proof: The phase of L is $-\pi/2 - x$; it reaches $-\pi$ at $x = \pi/2$, where $|L| = 2k/\pi$. The poles solve $sL_de^{sL_d} = -k$. Let $h(x) = |1+L|^2 = 1 - 2k\sin x/x + k^2/x^2$. Then $h'(x) = 2k(\varphi(x) - k)/x^3$ with $\varphi(x) = x\sin x - x^2\cos x$, which increases on $(0, \pi)$ with $\varphi(\pi/2) = \pi/2 > k$. So h has a single minimum $x^* \in (0, \pi/2)$ on $(0, \pi)$. On $[\pi, 2\pi]$, $h \ge 1$; for $x \ge 2\pi$, $h \ge (1 - k/x)^2 > (1 - 2k/\pi)^2 = h(\pi/2)$. So x^* is the global minimum, which gives (3). By the envelope theorem, $\frac{d}{dk}h(x^*) = \frac{2}{x^{*2}}(k - x^*\sin x^*) = -2\cos x^* < 0$. □

SIMC with $\tau_c = L_d$ and $T \le 8L_d$ cancels the lag and gives $k = \frac{1}{2}$, so GM $= \pi$ and $M_s = 1.59$ by (3), exactly the values in [4, Table 2].

After a unit setpoint step, $e = 1$ on $[0, L_d]$ and $\dot e(t) = -(k/L_d)\,e(t - L_d)$. Let $c_1 < c_2 < \ldots$ be the setpoint crossings, $c_0 = 0$, lobe i the interval $[c_i, c_{i+1}]$, and $E_0 = 1$.

Proposition 2 (Crossings) *For the loop (2) with $0 < k < \pi/2$: (a) the error never crosses the setpoint if and only if $k \le 1/e$, that is $M_s \le M_s(1/e) = 1.394$; for $k > 1/e$ it crosses infinitely often. (b) Lobe i contains exactly one extremum E_i, at $c_i + L_d$. (c) $|E_{i+1}| \le r(k)\,|E_i|$, with $r(k) = k^2/2$ for $k \le 1$ and $r(k) = k - \frac{1}{2}$ for $k \ge 1$. (d) For $k < 3/2$ the lobe areas decrease strictly, so Corollary 1 holds for Γ_0: N_0 is within half a turn of half the number of crossings.*

Proof: (a) The record is the fundamental solution of the delay equation. It is positive if and only if $s + (k/L_d)e^{-sL_d} = 0$ has a real root, that is $k \le 1/e$, and for $k > 1/e$ all solutions oscillate [11]; M_s follows from Proposition 1. (b) $\dot e(t)$ has the sign of $-e(t - L_d)$. By induction over the lobes, e moves away from zero on $(c_i, c_i + L_d)$, where $e(t - L_d)$ lies in lobe $i-1$, so lobe i




Figure 1: Lemma 1 and Proposition 2, evaluated on the lag-cancelled loop. (a) The three whitened counts against M_s ($\delta = 0.02$); N_0 stays within half a turn of half the number of crossings before settling (Corollary 1). (b) A record with $M_s = 2.00$ crosses twice before it settles within δ. (c) Its portrait Γ_0: between crossings (on the dashed line $e = 0$) the curve turns exactly half a turn around the end point ($+$). The radius is compressed for visibility; the angle is not.

is longer than L_d; and e moves toward zero on $(c_i + L_d, c_{i+1} + L_d)$, where $e(t - L_d)$ lies in lobe i. For $i = 0$ the extremum is the plateau $e = 1$ on $[0, L_d]$. (c) On lobe i, $|e| \le |E_i|$. After the extremum, $|\dot{e}| \le (k/L_d)|E_i|$, so e needs at least L_d/k to reach zero and $|e(t)| \le |E_i| \min\{1, k(c_{i+1} - t)/L_d\}$ on the last L_d of the lobe. Since $e(c_{i+1}) = 0$, $E_{i+1} = -\frac{k}{L_d} \int_{c_{i+1}-L_d}^{c_{i+1}} e\, dt$, and the bound integrates to $r(k)|E_i|$. (d) Integrating $\dot{e}$ from $c_i + L_d$ to $c_{i+1} + L_d$ gives the area $\frac{L_d}{k}(|E_i| + |E_{i+1}|)$ of lobe i, as the extrema alternate in sign. By (c), $|E_{i+2}| < |E_i|$ for $r(k) < 1$, that is $k < 3/2$, where $M_s = 26.2$. □

So on lag-cancelled loops N_0 reads the number of crossings, and crossings read M_s: none if and only if $M_s \le 1.394$, and by (c) the extrema decay at least geometrically. Fig. 1 illustrates both statements.

2.3 Counts do not certify in general

Outside lag-cancelled loops, crossings and M_s are not tied. A first-order plant with $T = 0.3L_d$ under PI with $T_i = 8T$ and gain margin 1.624 has $M_s = 2.62$, yet its error never crosses the setpoint by more than 2%; the oscillation rides on a slow decay (M_s of the continuous loop; 2.61 for the digital loop of Fig. 2). Conversely, overshoot from a controller zero can produce crossings at a low M_s. So counts can guide tuning but cannot certify it. The same step, however, contains M_s.

3 Result 2: The Same Step Certifies M_s

A digital controller runs at sampling period T_s. The loop it closes, seen at the samples, is linear and time invariant. From here on $L(z)$, $P(z)$, $S = 1/(1+L)$ and $M_s = \max_{\theta\in[0,\pi]} |S(e^{j\theta})|$, $\theta = \omega T_s$, denote this loop, the loop that actually runs.

Lemma 2 (Exact identity) *Let the loop be stable, with one degree of freedom and strictly proper L (the measurement precedes the control action), and let e_n be the error after a unit setpoint step at $n = 0$ from rest, without disturbances, so $e_{-1} = 0$ and $e_0 = 1$; let $a_n = \Delta e_n = e_n - e_{n-1}$. Then*

$$S(e^{j\theta}) = \sum_{n\ge 0} a_n e^{-jn\theta}. \tag{4}$$

Proof: $E(z) = S(z)R(z)$ with $R(z) = 1/(1 - z^{-1})$, so $S = (1 - z^{-1})E$. In a stable loop a_n decays exponentially, so the series converges on the unit circle. □

In continuous time the same argument gives $S(j\omega) = \int_0^\infty e^{-j\omega t} de(t)$. A record is finite. The only quantity that it cannot give is the variation of the error after it ends.

Assumption 1 (Settled record) *The loop is stable, and the record $e_0, \dots, e_N$ satisfies $\sum_{n>N} |a_n| \le \tau$ for a known τ.*

In a stable loop $|a_n| \le c\rho^n$ with $\rho < 1$, so the tail variation falls geometrically with the record length; τ states how settled the record is, in units of the step.

Theorem 1 (Certified bounds from one record) *Under Assumption 1, let $\hat{S}(\theta) = \sum_{n=0}^{N} a_n e^{-jn\theta}$, let G be a uniform grid on $[0, \bar{\theta}]$, $\bar{\theta} \le \pi$, with spacing h and both ends, and let*

$$J = \sum_{n=0}^{N} |n - n_c|\,|a_n|, \quad B = \sum_{n=1}^{N-1} |a_{n+1} - a_n| + |a_N| + 2\tau,$$

for any n_c. Then $\underline{M} \le M_s \le \overline{M}$, with

$$\underline{M} = \max_{\theta\in G} |\hat{S}(\theta)| - \tau,$$
$$\overline{M} = \max\left\{ \max_{\theta\in G} |\hat{S}(\theta)| + \tfrac{hJ}{2} + \tau,\ 1 + \tfrac{B}{\sin(\bar{\theta}/2)} \right\}, \tag{5}$$

where the second term is dropped if $\bar{\theta} = \pi$. With τ equal to the true tail, $N \to \infty$, $h \to 0$ and $\bar{\theta} = \pi$, both bounds converge to M_s.

Proof: By (4), $|S - \hat{S}| \le \sum_{n>N} |a_n| \le \tau$ at every θ, which gives $\underline{M}$. On $[0, \bar{\theta}]$, $|\hat{S}|$ equals $|e^{jn_c\theta}\hat{S}|$, whose derivative is bounded by J; every θ is within $h/2$ of a grid point, which gives the first term of $\overline{M}$. On $[\bar{\theta}, \pi]$, let $z = e^{-j\theta}$

Algorithm 2: certified SPIN: line 7 of Algorithm 1 becomes

7a: compute $\overline{M}$ by Theorem 1: $\bar\theta$ solves $1+B/\sin(\bar\theta/2) = M^*$ ($\bar\theta = \pi$ if none), $hJ/2 \le \eta$
7b: **if** $\overline{M} \le M^*$ **then** raise all gains by one step (accept)
7c: **else** predict, by Proposition 3, M_s after SPIN's move of each band (lower it, raise those below)
7d: apply the highest band predicted to lower M_s, at most $n_{\max}$ times between acceptances; otherwise lower all gains by one step; end the iteration

Defaults: $M^* = 1.7$, $\tau = 10^{-3}$, $\eta = 2\cdot 10^{-3}$, $n_{\max} = 10$.

and $Z_n = \sum_{m=1}^{n} z^m$, so $|Z_n| \le 2/|1-z| = 1/\sin(\theta/2)$. Summation by parts gives $\sum_{n\ge1} a_n z^n = \sum_{n\ge1}(a_n - a_{n+1})Z_n$, and $\sum_{n\ge N}|a_n - a_{n+1}| \le |a_N| + 2\tau$, so $|S - a_0| \le B/\sin(\theta/2)$ with $a_0 = 1$. Convergence: the true tail and hJ tend to zero. □

Every quantity in (5) except τ comes from the record; the grid values are one chirp z-transform. The second term needs no grid: for a smooth record B is small and certifies all high frequencies at once.

4 Certified SPIN

Algorithm 2 changes only line 7 of SPIN. The counts still shape the tuning; the bound decides whether it is accepted. On a rejection it uses SPIN's own two moves: lowering one band while raising those below it, or lowering all gains.

Theorem 2 (Certified SPIN) *Let the plant be stable, let $K_iP(1) > 0$, let Assumption 1 hold for every record, let $hJ/2 \le \eta$, and for (iii), (iv) let no gain be clipped by the box of Algorithm 1. (i) Every tuning accepted by Algorithm 2 has $M_s \le M^*$. (ii) For gains K, let $m = \min\{0, \inf_{0<\theta\le\pi} \mathrm{Re}\, L(e^{j\theta})\}$. For $0 < \lambda < 1/|m|$ the loop with gains λK is stable and*

$$M_s(\lambda K) \le \frac{1}{1-\lambda|m|}. \tag{6}$$

(iii) If $M^* > 1 + 2\tau + \eta$, every run of consecutive rejections by the test of line 7b ends, in an acceptance or in a rejection by the counts (lines 2–10 of Algorithm 1). It has at most $n_{\max}$ band moves, and each stretch of uniform back-offs has at most $\lceil \ln \frac{|m|M'}{M'-1} / \ln \frac{1}{1-\beta} \rceil$ of them, $M' = M^* - 2\tau - \eta$, with m of the gains where the stretch starts. (iv) Every move except an acceptance lowers $\Phi = \ln K_i + 2\ln K_p + 4\ln K_d$ by at least $\ln \frac{1}{1-\beta}$, so the gains never return to earlier values without an acceptance in between.

Proof: (i) Theorem 1. (ii) L is bounded on the unit circle except near $z = 1$, where the integral term has a bounded real part because P is analytic there and $\mathrm{Re}\, 1/(e^{j\theta} - 1) = -\frac{1}{2}$; so m is finite. Then $|1 + \lambda L| \ge 1 + \lambda\, \mathrm{Re}\, L \ge 1 - \lambda|m| > 0$, which gives (6). The Nyquist curve of λL lies in $\mathrm{Re} \ge -\lambda|m| > -1$, also on the indentation at $z = 1$, where $K_iP(1) > 0$ makes the real part large and positive; it cannot encircle -1, and L has no poles outside the unit disc, so the loop is stable. (iii) Line 7d allows at most $n_{\max}$ band moves. In a stretch of uniform back-offs from gains K, after j of them $\lambda = (1-\beta)^j$, and (6) gives $M_s \le M'$ for the stated j. In (5) the grid term is then at most $M_s + \tau + \eta + \tau \le M^*$, and the second term is at most M^* by the choice of $\bar\theta$, so the test passes unless the counts reject first. (iv) A band move changes Φ by $\ln \frac{1}{1-\beta}(\sum_{j<k} w_j - w_k)$ with $w = (1,2,4)$, which is at most $-\ln \frac{1}{1-\beta}$; lowering all gains changes it by $-7\ln \frac{1}{1-\beta}$, and line 3 by $-17\ln 2$. A repeated state needs $\sum \Delta\Phi = 0$, hence an acceptance, which raises Φ. □

So the test never traps SPIN: it either certifies a tuning or returns control to the original rules. Part (i) holds with or without the box. Part (iv) does not exclude a drift without acceptance, in which Φ falls forever; that is a property of the counts and is stopped by the gain box of SPIN, as Section 5 shows.

A uniform back-off is safe by (ii) but costs load rejection; lowering one band is often cheaper, and the same record tells what each move does.

Proposition 3 (Prediction from one step) *For any controller C' on the same plant, $S' = S/(S + (1-S)C'/C)$ exactly. If the record gives $\hat S = S + \varepsilon$, the prediction $\hat S'$ errs by $\hat S' - S' = \varepsilon\,(C'/C)\,S'\hat S'/(S\hat S)$.*

Proof: $L' = LC'/C$ with $L = (1-S)/S$; subtracting the two expressions gives the error. □

The prediction only selects the move; each move is checked by the next step, so safety never depends on it.

5 Confirmation in Simulation

Setup We compare SPIN as published with certified SPIN (Algorithm 2), with 200 iterations, derivative filter ratio 10 and the gain box $[0.001, 10]$ of [1]. Because the box ties the result to the start, every loop runs from two starts: SIMC on a half-rule model with τ_c three times its dead time (cautious), and twice as bold. The plants are those of [1],

$$P_1 = \frac{e^{-s}}{(10s+1)(s+1)^3}, \qquad P_2 = \frac{1.25\,e^{-8s}}{(5s+1)^4},$$
$$P_3 = \frac{e^{-10s}}{(2s+1)(s+1)^3}, \qquad P_4 = \frac{e^{-4s}}{(8s+1)^6},$$

with PI and PID; a delay-dominant $e^{-5s}/(s+1)$, two lag-dominant $e^{-s}/(10s+1)$ and $e^{-0.5s}/((10s+1)(s+1))$ with PI; a fast $e^{-0.1s}/((s+1)(0.5s+1))$ with PID; and $e^{-L_d s}/((s+1)(0.5s+1)(0.25s+1))$ with PID and $L_d \in \{0.25, \dots, 16\}$ (dead-time share 0.125 to 0.90). The controller runs at $T_s = \min(T_a/100, T_f/20)$ for PID, with T_f the derivative filter time constant and T_a the plant's dead time plus its lag time constants, and at $T_a/1000$ for PI; each lag is discretized exactly

for a piecewise-constant input and the delay is rounded to whole samples. The record covers $15T_a$. P and D act on the error. All M_s below are those of this digital loop, computed from its exact L. At the end, SPIN cycles between a few tunings; we report the most aggressive one accepted in the last 60 iterations.

Result 1 On the lag-cancelled loop with $1/e < k < 3/2$, the bound (c) of Proposition 2 held for every extremum (with equality for the first when $k \geq 1$), the lobe areas decreased, each interval between crossings turned by $\frac{1}{2}$ turn to 10^{-6}, also after a linear map, and the whitened count of SPIN satisfied Corollary 1 for all 126 values of k tested; (3) matched a direct search of M_s to six digits.

Lemma 2 and Theorem 1 For each of the 146 tunings accepted in all runs of this section (both rules; cautious, bold and boxless; distinct within each run), we simulated a record four times longer to measure the true tail $\sum_{n>N}|a_n|$. It was at most $2.8 \cdot 10^{-5}$, so Assumption 1 held with $\tau = 10^{-3}$; the identity (4) held up to this tail and round-off; and every true M_s lay within its bounds (here $\bar{\theta}$ makes the second term equal to the read peak), with $\overline{M} - M_s \leq \eta + \tau + 2.8 \cdot 10^{-5}$. On short records the tail is large and the bounds are wide, yet they contain M_s and close in as the error settles (Fig. 2(b)).

Theorem 2 and Proposition 3 Published SPIN ended above $M^* = 1.7$ on 9 of the 19 loops from the cautious start (up to 2.01) and on 8 from the bold start (up to 2.09); which loops failed depended on the start, because the gain box often set the result (Table 1). Certified SPIN ended at or below M^* on all loops from both starts, as Theorem 2(i) guarantees; the highest value was 1.69. Without the gain box, published SPIN went above the target on 12 of the 18 loops that converged (up to 2.05), and certified SPIN stayed at or below it on all 18 (up to 1.68). Along the uniform back-off from the most aggressive published tuning of each loop (cautious start), the loop stayed stable and (6) held, and the predicted M_s after every band move matched the true value to 10^{-7} (Fig. 3(b)). Runs of rejections by the test contained at most 4 band moves, below $n_{\max}$, and every loop accepted at least 7 times in its last 60 iterations. The exception is $L_d = 16$ without the box, which converges under neither rule: the counts reject in a repeating pattern that lowers K_d in every round, the drift that Theorem 2(iv) allows. The price of the target is load rejection: the integrated absolute error after a unit load step at the plant input rose by 7.8% on average over the 19 loops (6.4% from the bold start).

Table 1: M_s of the digital loop for the most aggressive tuning that published and certified SPIN accept, from the cautious and the bold start, and the change of load-step IAE (cautious start).

		published		certified		
		caut.	bold	caut.	bold	ΔIAE
P_1	PI	1.46	1.46	1.46	1.46	–
	PID	1.66	**1.84**	1.66	1.61	–
P_2	PI	1.64	1.67	1.64	1.67	–
	PID	1.59	**1.78**	1.59	1.66	–
P_3	PI	1.67	1.63	1.67	1.63	–
	PID	**1.81**	**1.74**	1.69	1.60	+23%
P_4	PI	1.55	1.60	1.55	1.60	–
	PID	1.61	1.55	1.61	1.55	–
delay-dom.	PI	1.68	1.63	1.68	1.63	–
lag-dom.	PI	**2.01**	1.69	1.67	1.69	+52%
2 lags	PI	1.44	1.47	1.44	1.47	–
fast	PID	**1.89**	**1.98**	1.66	1.69	0%

6 Conclusion

The count of Γ_0 is within half a turn of half the number of setpoint crossings when the lobes of the error shrink; on lag-cancelled loops the crossings read M_s exactly, so by eye an error that never crosses the setpoint means $M_s \leq 1.394$. On any stable digital loop the setpoint step that SPIN already records gives the sensitivity function exactly, and one finite record gives certified bounds on M_s; every setpoint change in a historian, made from rest, certifies M_s without a model. As the acceptance test of SPIN, the upper bound certifies every accepted tuning, and every run of rejections ends, so the test never traps the original rules. The theorems assume a linear loop and a settled record; noise and real loops are the subject of a follow-up. Scripts for every number and figure are in `https://github.com/ottapav/robopid-simulator`, folder `docs/ECC27_certified_SPIN`.

References

[1] D. Pachner, P. Otta, J. Dostál, and V. Havlena, "Model-free PID tuning by step-response inspection," submitted to *J. Process Control*, 2026.

[2] K. J. Åström and T. Hägglund, "Revisiting the Ziegler–Nichols step response method for PID control," *J. Process Control*, vol. 14, no. 6, pp. 635–650, 2004.

[3] S. Skogestad, "Simple analytic rules for model reduction and PID controller tuning," *J. Process Control*, vol. 13, no. 4, pp. 291–309, 2003.

[4] S. Skogestad and C. Grimholt, "The SIMC method for smooth PID controller tuning," in *PID Control in the Third Millennium*, R. Vilanova and A. Visioli, Eds. London: Springer, 2012, pp. 147–175.

[5] L. Desborough and R. Miller, "Increasing customer value of industrial control performance monitoring—Honeywell's experience," in *Chemical Process Control VI*, AIChE Symp. Ser. no. 326, vol. 98, 2002, pp. 169–188.

[6] M. Bauer, A. Horch, L. Xie, M. Jelali, and N. Thornhill, "The current state of control loop performance monitoring—a sur-




Figure 2: Lemma 2 and Theorem 1. (a) $|S|$ from one setpoint step (dashed) lies on the true one (thick), for P_4 with SIMC PI and for the slow-integral loop whose peak the counts miss. (b) The bounds (5) relative to the true M_s against the record length, with τ the true tail, for three published tunings; the floor of the upper bound is η/M_s.




Figure 3: Published against certified SPIN ($M^* = 1.7$). (a) The loops of Table 1. Filled orange: published, cautious start; open orange: published, bold start; blue: certified, cautious start. (b) P_3 with PID near the peak. Published tuning ($\overline{M} = 1.81 > M^*$, ○); one move lowering K_i ($M_s = 1.739$, as predicted from the same record by Proposition 3); the tuning certified SPIN accepts (1.689). (c) The family $e^{-L_d s}/((s+1)(0.5s+1)(0.25s+1))$ with PID against the dead-time share.

vey of application in industry," *J. Process Control*, vol. 38, pp. 1–10, 2016.

[7] Q.-G. Wang, C. C. Hang, and Q. Bi, "Process frequency response estimation from relay feedback," *Control Eng. Pract.*, vol. 5, no. 9, pp. 1293–1302, 1997.

[8] P. M. J. Van den Hof and R. J. P. Schrama, "An indirect method for transfer function estimation from closed loop data," *Automatica*, vol. 29, no. 6, pp. 1523–1527, 1993.

[9] K. Isoshima, M. Tanemura, and Y. Chida, "Data-driven estimation of the lower bounds of gain and phase margins," *Automatica*, vol. 153, art. 111008, 2023.

[10] F. M. Asl and A. G. Ulsoy, "Analysis of a system of linear delay differential equations," *J. Dyn. Syst. Meas. Control*, vol. 125, no. 2, pp. 215–223, 2003.

[11] I. Győri and G. Ladas, *Oscillation Theory of Delay Differential Equations with Applications*. Oxford: Clarendon Press, 1991.

[12] H. Hjalmarsson, M. Gevers, S. Gunnarsson, and O. Lequin, "Iterative feedback tuning: theory and applications," *IEEE Control Syst. Mag.*, vol. 18, no. 4, pp. 26–41, 1998.

[13] N. J. Killingsworth and M. Krstić, "PID tuning using extremum seeking: online, model-free performance optimization," *IEEE Control Syst. Mag.*, vol. 26, no. 1, pp. 70–79, 2006.

[14] M. Shamsuzzoha and S. Skogestad, "The setpoint overshoot method: a simple and fast closed-loop approach for PID tuning," *J. Process Control*, vol. 20, no. 10, pp. 1220–1234, 2010.

[15] M. C. Campi, A. Lecchini, and S. M. Savaresi, "Virtual reference feedback tuning: a direct method for the design of feedback controllers," *Automatica*, vol. 38, no. 8, pp. 1337–1346, 2002.