

Actuator Reality Shaping for Zero-Shot Sim-to-Real Robot Learning

Satoshi Yamamori^{1,2}, Koji Ishihara², Kentaro Minamikawa¹, Kiyoharu Ohomori¹,
Taiyo Yazaki¹, Norikazu Sugimoto², and Jun Morimoto^{1,2}

¹Graduate School of Informatics, Kyoto University, Kyoto, Japan

²Dept. of Brain Robot Interface, Computational Neuroscience Labs, ATR, Kyoto, Japan

Abstract: Sim-to-real transfer in robot learning is often limited by discrepancies between the ideal actuator dynamics assumed during policy training and the nonlinear, hardware-dependent behavior of physical motors. While conventional approaches attempt to bridge this gap by increasing simulator fidelity through system identification, domain randomization, or learned actuator models, we introduce an alternative paradigm: actuator reality shaping. Instead of modifying the simulator to match the real world, our method shapes the closed-loop behavior of physical actuators to match the idealized second-order reference dynamics used in simulation. By equipping each joint with a two-degree-of-freedom feedforward–feedback controller, we decouple reference-response shaping from robust stabilization, thereby providing a standardized actuator interface for reinforcement learning policies. As a result, policies trained only with the prescribed reference model can be deployed zero-shot on real hardware without task-level fine-tuning or learned actuator models. We validate the approach on a single-joint high-gear-ratio servo under external loads and a 7-DOF robotic arm reaching task, where actuator reality shaping substantially reduces sim-to-real tracking error and improves zero-shot task performance compared with standard servo-control and representative real-to-sim-to-real baselines. We further demonstrate zero-shot transfer on a wheeled-legged robot driving over a slope and a humanoid robot walking, suggesting that actuator reality shaping can serve as a reusable interface for robot learning across diverse hardware platforms.

Keywords: Reinforcement learning for physical robot control, Sim-to-real transfer, Actuator Reality Shaping

1 Introduction

Reinforcement learning (RL) has enabled impressive locomotion and manipulation controllers when trained in GPU-accelerated, large-scale physical simulation [1, 2, 3, 4, 5]. However, bridging the *sim-to-real gap*, the performance degradation that arises when policies trained in simulation are deployed on physical hardware, remains a central challenge in robot learning. A major source of this gap lies at the actuator level. While rigid-body simulators often model joints as ideal torque sources or simplified servo systems, real actuators exhibit friction, stiction, backlash, transmission compliance, inertia mismatch, saturation, and electromechanical delays. These unmodeled effects distort the relationship between commanded and realized joint motion, causing policies optimized in simulation to drive the physical robot along unintended trajectories. The resulting mismatch can degrade task performance, amplify tracking errors, and, in dynamic tasks, destabilize the robot.

The dominant strategy for reducing the sim-to-real gap has been to make the simulator more realistic [6]. Domain randomization (DR) trains policies over randomized physical parameters so that the real system is likely to lie within the training distribution [6, 7]. Although effective in many settings, this robustness often comes at the cost of task-specific performance, since policies must succeed




Figure 1: **Actuator reality shaping.** We make the real actuator behave like the simulator’s ideal model, rather than the reverse. (*Top*) simulation with the ideal second-order reference model; (*Bottom*) zero-shot hardware deployment, where a per-joint 2-DoF driver shapes the response so that $\theta \approx \theta_{\text{ref}}$.

across a broad range of dynamics rather than exploit a precise actuator model. A complementary line of work augments the simulator with physics-based or learned actuator models identified from input–output data [1, 8], or learns online adaptation modules that infer latent environment or actuator parameters during deployment [2]. Despite their success, these approaches share a common dependency: they adapt the simulation or policy to a particular hardware distribution. As a result, they typically require hardware-specific data collection or identification, which must be repeated when actuators are replaced, degrade over time, or are transferred to a different robot platform. This dependency limits the reusability of policies trained in simulation and motivates an alternative interface that standardizes the actuator behavior seen by the policy, rather than continually adapting the simulator to each hardware instance.

We propose an alternative perspective: *actuator reality shaping*. Instead of modifying the simulator to match each physical actuator, we modify the low-level actuator controller so that the hardware presents to the policy the same reference dynamics used during simulation. As illustrated in Figure 1, an RL policy is trained in simulation against an idealized second-order actuator model, and is then deployed zero-shot on hardware, where a per-joint 2-DoF driver shapes the physical actuator response to match the prescribed reference dynamics. Concretely, we introduce a *two-degree-of-freedom* (2-DoF) controller at each joint driver. Here, “two-degree-of-freedom” is a control-theoretic term [9]: it denotes a controller with two independent design freedoms, typically realized as a feedforward path and a feedback path. This structure allows the reference-response behavior and robust stabilization against disturbances and modeling errors to be designed separately. The feedforward path specifies the desired closed-loop dynamics seen in simulation, while the feedback path compensates for disturbances and residual actuator-model mismatch. We detail these two paths in Section 4 and Figure 2. The resulting driver layer encourages the real joint to follow the same second-order reference dynamics assumed during policy training, thereby providing a standardized actuator interface between the RL policy and the physical hardware. Consequently, a policy trained against this reference model in simulation can be deployed on the real system without task-level fine-tuning or learned actuator models, as long as the physical actuator can track the prescribed dynamics within its bandwidth and saturation limits.

The resulting 2-DoF layer plays a role analogous to a device driver: it hides hardware-specific actuator behavior behind a common interface exposed to the policy. In our case, this interface is dy-

namical rather than software-based: the policy interacts with the prescribed second-order reference model used in simulation, while the low-level driver compensates for the physical actuator dynamics. This separation provides three practical advantages. First, it enables *policy-level hardware abstraction*: the same policy can be reused across compatible actuator platforms by redesigning or retuning only the low-level driver, rather than retraining the policy. Second, it provides a *smooth learning interface*: because the policy is trained against a consistent, idealized actuator response, policy optimization is less exposed to hardware-specific nonlinearities such as friction, backlash, and delay. Third, it improves *modularity*: the driver can be designed from a compact actuator description, such as the torque constant, rotor inertia, and bandwidth limits, without requiring task-level real-world rollouts or learned actuator models.

Our main contributions are as follows:

1. We introduce the *actuator reality shaping* paradigm for sim-to-real transfer in robot learning, and derive a 2-DoF control architecture that shapes the closed-loop actuator response to match a prescribed simulator reference model.
2. We validate the proposed architecture through single-joint tracking experiments with controlled disturbance injection, and demonstrate zero-shot sim-to-real transfer on a 7-DOF robotic-arm reaching task. We compare against the factory cascaded servo controller, a tuned PID controller, and a learned Delta Action baseline (ASAP [10]).
3. We further evaluate the generality of the approach through additional zero-shot transfer demonstrations on a wheeled-legged robot with velocity-controlled wheels and a full humanoid robot performing stable forward walking.

2 Related Work

Sim-to-Real Transfer in Robot Learning Existing sim-to-real methods fall into three groups. *Domain randomization (DR)* [6, 11, 12, 13, 7] trains under randomized parameters so the real system lies within the training distribution, but yields conservative worst-case policies and large simulation budgets; adaptive variants such as SimOpt [14] update the distribution from real rollouts, Rapid Motor Adaptation [2] distills an online module that infers environment parameters from proprioceptive history, and ASAP [10] learns a Delta Action model from real rollouts to compensate the dynamics mismatch at the policy level. *Actuator modeling* instead augments the simulator with a model identified from hardware data—a black-box network [1, 15, 16] or a few interpretable parameters (rotor inertia, friction, damping)—and implicitly assumes a small residual gap: most demonstrations use *quasi-direct-drive* actuators with low gear ratios, whose torque response approximates an ideal current source. High-gear-ratio joints violate this assumption, as reflected friction, stiction, and backlash dominate the joint torque and cannot be captured as a simple parametric perturbation. *Data-driven system identification* estimates environment parameters online and conditions the controller on them, with roots in classical adaptive control [17, 18] and biped-locomotion work refining a bootstrap controller against a data-driven model [19, 20], or trains an *environment-aware* policy with an online-identified latent code [21, 22, 23]. All these share a structural cost: hardware-specific data and/or online identification that must be repeated when the hardware changes. We take the dual perspective—rather than identifying the hardware so the policy adapts to it, we shape the hardware’s closed-loop response at the driver level so the policy perceives a fixed, simulator-defined plant on every platform; even high-gear-ratio joints emulate the ideal reference plant, with residual error absorbed at runtime by the disturbance observer and integral feedback.

Two-Degree-of-Freedom and Model Reference Control The 2-DoF control architecture decouples reference tracking from disturbance rejection through independent feedforward and feedback designs [9, 24, 25], and is commonly combined with a disturbance observer to reject friction and load [26, 27, 28]. However, these approaches operate at the level of individual joint control and are therefore insufficient for generating whole-body motion. As a result, their use as a *sim-to-real interface layer* has not been sufficiently explored. Our design shares the reference-model layer idea with a fixed-gain 2-DoF controller derived from a minimal actuator model, avoiding convergence

monitoring, gain scheduling, and adaptation–saturation stability issues, and requiring no hardware adaptation data.

3 Problem Formulation

Markov Decision Process in Actuator We consider a Multi-DoF robot with n revolute joints actuated by DC motors. An RL policy $\pi : \mathcal{O} \rightarrow \mathcal{A}$ maps an observation $o_t \in \mathcal{O}$ to a goal joint angle $\bar{\theta}_t \in \mathcal{A}$. In simulation, joint j is governed by a PD controller acting on the goal joint angle:

$$I_{\text{sim}}\ddot{\theta}_j = K_p(\bar{\theta}_j - \theta_j) - D\dot{\theta}_j + f_j, \quad (1)$$

where I_{sim} , K_p , D are the simulated inertia, proportional gain, and damping coefficient, and f_j is the net external joint torque. The transition operator of the MDP is defined by the dynamics (1), and the policy π is optimized against this operator using RL algorithm, e.g. PPO [3].

Actuator Gap In simulation, (1) implicitly assumes that the commanded torque $\tau_{\text{cmd}} = K_p(\bar{\theta}_j - \theta_j) - D\dot{\theta}_j$ is produced instantaneously at the joint. On real hardware, joint j is driven by a motor with dynamics:

$$J_{\text{real}}\ddot{\theta}_j = K_{\tau i}(i_j - i_{d,j}) - d_{\text{real}}\dot{\theta}_j - \tau_{f,j}(\dot{\theta}_j) - \tau_{\text{ext},j}, \quad (2)$$

where J_{real} is the actual rotor inertia (including gear reflection), $K_{\tau i}$ the torque constant, i_j the current command, $i_{d,j}$ a disturbance current (e.g., cogging), d_{real} the viscous damping, $\tau_{f,j}(\dot{\theta})$ a velocity-dependent friction term (Coulomb friction and stiction), and $\tau_{\text{ext},j}$ an external load torque. Linearizing the mechanical dynamics around the operating point and taking the torque-to-angle relation, we describe each joint by a plant transfer function $P(s) = \theta_j(s)/\tau_j(s)$. From the inertia and damping terms of (1) and (2) we obtain $P_{\text{sim}}(s) = \frac{1}{I_{\text{sim}}s^2 + Ds}$, $P_{\text{real}}(s) = \frac{1}{J_{\text{real}}s^2 + d_{\text{real}}s}$, where the nonlinear and exogenous terms of (2)—the velocity-dependent friction $\tau_{f,j}(\dot{\theta}_j)$, the disturbance current $K_{\tau i}i_{d,j}$, and the external load $\tau_{\text{ext},j}$ —enter P_{real} additively as a lumped disturbance torque. The *actuator gap* is the multiplicative uncertainty of the real plant relative to the simulated one,

$$\Delta P_j(s) = \frac{P_{\text{real}}(s)}{P_{\text{sim}}(s)} - 1 = \frac{I_{\text{sim}}s + D}{J_{\text{real}}s + d_{\text{real}}} - 1, \quad (3)$$

so that $P_{\text{real}}(s) = (1 + \Delta P_j(s))P_{\text{sim}}(s)$. This dimensionless gap captures the inertia mismatch $J_{\text{real}} - I_{\text{sim}}$ and the damping mismatch $d_{\text{real}} - D$, while the friction, cogging, and external load act as additive disturbances on top of $\Delta P_j(s)$. It is the same model error ΔP that the controller in Sec. 4 attenuates. Our objective is to design a controller that suppresses the effect of the actuator gap, $\Delta P_j \rightarrow 0$ and the disturbance influence, so that the closed loop reduces to the simulated reference dynamics; consequently $\|\theta_j(t) - \theta_{\text{ref},j}(t)\| \rightarrow 0$ for all bounded disturbances $\tau_{\text{ext},j}$, where $\theta_{\text{ref},j}$ is the output of the simulator reference model (1) driven by the same policy goal joint angles $\bar{\theta}_j$. If this objective is achieved, the policy π perceives identical dynamics in simulation and on the real hardware, enabling zero-shot transfer.

4 Method

Figure 2 shows the proposed per-joint actuator reality shaping architecture: a cascaded two-degree-of-freedom (2-DoF) controller—a position outer loop wrapped around a velocity inner loop and augmented with a disturbance observer (DOB)—that drives the real motor to reproduce the simulator’s reference dynamics. We detail each component in the following subsections.

Two-Degree-of-Freedom Controller We adopt the standard 2-DoF control structure [9, 24] to independently specify the reference tracking and disturbance rejection characteristics. Let $P(s)$ denote the plant block. The control input is:

$$u = \frac{F(s)}{\hat{P}(s)}r + K(s)e, \quad e = F(s)r - y, \quad (4)$$




Figure 2: Proposed actuator reality shaping architecture (single joint): a cascaded 2-DoF controller (a position outer loop around a velocity inner loop) augmented with a disturbance observer (DOB) drives the real motor so that its closed-loop response tracks the simulator’s reference model.

where r is the reference (the policy goal joint angle $\bar{\theta}$), y is the measured output (θ), $F(s)$ is the desired system response block, and $K(s)$ is the feedback block. Let $P(s) = (1 + \Delta P(s))\hat{P}(s)$ be the true plant including model error ΔP for nominal plant $\hat{P}(s)$. The closed-loop transfer function from reference to output and from disturbance to output is:

$$y = \underbrace{\left(1 + \frac{\Delta P}{1 + PK}\right)}_{\approx 1} Fr + \underbrace{\frac{P}{1 + PK}}_{\text{sensitivity}} d, \quad (5)$$

where d is the input disturbance torque; the step-by-step derivation is given in Appendix B. When the feedback gain K is sufficiently large to compensate for the model error (ΔP), the output tracks $y \sim Fr$ regardless of the disturbance rejection loop, so F can be designed independently to match the simulator’s reference dynamics. We choose:

$$F_1(s) = \frac{K_p}{I_{\text{sim}}s^2 + Ds + K_p}, F_2(s) = \frac{\alpha}{s + \alpha}, \quad (6)$$

so that the outer-loop plant $P_1 \approx F_2/s$, since the inner velocity loop’s closed-loop response closely follows the reference model F_2 under the inner-loop 2-DoF velocity control.

The feedback block $K(s)$ must include an integrator to guarantee zero steady-state tracking error in the presence of constant disturbances, by the internal model principle. We use:

$$K(s) = k_p + \frac{k_i}{s} + k_d s, \quad (7)$$

a proportional-integral-derivative (PID) controller.

Disturbance Observer The 2-DoF controller is augmented with a disturbance observer (DOB) [26, 27] that estimates the disturbance torque $\hat{\tau}_d$ from the commanded torque and the measured velocity through a low-pass filter with cutoff frequency α_{dob} , and cancels it by subtracting a compensation torque $\hat{\tau}_d$ from the commanded current before it is sent to the driver, attenuating the residual model error ΔP below α_{dob} . The detailed derivation, including the filtered disturbance estimate and the resulting effective plant, is provided in Appendix C, and the reconstruction accuracy of the estimated disturbance is reported in Appendix D.

Cascaded Position-Velocity Control For position-controlled revolute joints (e.g., arm joints), we cascade two 2-DoF loops. The inner loop is a velocity control loop with plant $\hat{P}_2 = 1/(Js + d)$ and reference model matched to the velocity response F_2 , where J is the nominal inertia and d is the nominal viscous damping. The outer loop is a position control loop whose reference model F_1 is the full second-order response (1) and plant $P_1 \sim \hat{P}_1 = F_2/s$. The outer loop outputs a goal joint velocity $\bar{\theta}$ that serves as the reference for the inner loop. Implementation details (per-step procedure

and DOB low-pass filter) and the controller parameters used in all experiments are provided in Appendix E (Table 2).

5 Experimental Setup

We evaluate *actuator reality shaping* on platforms of increasing task complexity: a single-joint testbench (reference-model tracking under static and dynamic disturbances), a 7-DOF arm (end-effector reaching under inter-joint coupling), and a wheeled-legged robot and humanoid robot (zero-shot driving and bipedal walking across embodiments).

Hardware Platform. We evaluate on three custom-built, in-house platforms: a 7-DOF robotic arm; a wheeled-legged robot (31 DOF), a tripod of four 7-DOF arms rigidly coupled at a central body, three terminating in wheel actuators for combined manipulation and locomotion; and a humanoid robot (22 DOF) with two 6-DOF legs, a 2-DOF waist, and two 4-DOF arms. Their IsaacSim models are built from URDF files whose kinematic trees come directly from the original CAD data. Because these models lack the implicit parameter tuning of commercial robots and vendor-supplied simulation assets, the sim-to-real gap on our platforms is considerably more severe than on off-the-shelf hardware, making them a stringent testbed for zero-shot transfer.

All single-joint experiments are conducted on a testbench using the same joint actuator unit deployed on the robots: a high-gear-ratio servo with a cycloidal gear reducer (Dynamixel YM070, 99:1, ROBOTIS), so that the identified motor parameters and controller gains transfer directly to the multi-joint experiments without re-tuning. The YM070 is used for the single-joint tracking experiments, the robotic arm reaching task, and the wheeled-legged robot experiments, whereas the Dynamixel PH54 (501.9:1, ROBOTIS) is used for the humanoid walking experiment. The high gear ratio reflects link-side inertia back through N^2 ($N=99$ for the YM070, $N=501.9$ for the PH54), so motor-side inertia dominates the joint-level dynamics by orders of magnitude. Inter-joint inertial coupling is therefore small relative to the motor-side inertia and appears at the DOB as a low-frequency bounded perturbation within the rejection bandwidth, validating the per-joint decentralized DOB assumption.

Simulator and Policy Training. The simulator is Isaac Sim [29, 30] with joint dynamics implemented as (1), and policies are trained within the IsaacLab learning framework [31]. RL policies are trained using PPO [3]; the actor-critic architecture and per-task training settings are summarized in Appendix F (Table 3). For the humanoid walking task, we build on the public implementation of BeyondMimic [32], replacing only the actuator model and low-level controller with our 2-DoF+DOB design while keeping the policy architecture, reward terms, and training pipeline unchanged. The physical-parameter randomization ranges used for the humanoid walking and wheeled-robot reaching tasks are listed in Appendix G.

Comparison Methods. We compare against the following baselines, all running at the same 500 Hz driver-level control frequency. To isolate the DOB’s contribution, we report two configurations of our method: *2-DoF*, the feedforward–feedback controller (4) alone, and *2-DoF+DOB*, the same controller augmented with the disturbance observer (see Appendix C); elsewhere we refer to the method simply as 2-DoF, as the DOB is an optional enhancement rather than a separate architecture.

PID Cascade: the servo’s factory default controller—a multi-stage (cascaded) position–velocity–current PID loop running on the drive firmware. It is a feedback-only, 1-DoF controller with no feedforward path. This represents the standard servo-controller baseline a practitioner obtains out of the box without any actuator-aware redesign.

Simple PD: a single-loop PD controller (no feedforward, no DOB, no cascade) that outputs the motor current command directly from the joint state, $i = k_p(\theta_{\text{ref}} - \theta) - k_d\dot{\theta}$, with gains k_p, k_d manually tuned for stable tracking on the real hardware.

Additionally, for the reaching task we include a learned actuator-modeling baseline:

Table 1: Mean $\pm$ std of the deviation from the simulated reference trajectory, in joint space ($|\Delta\theta|$, $|\Delta\dot{\theta}|$) for single-axis tracking and in task space ($\|\Delta p\|$, $\|\Delta\dot{p}\|$) for the reaching task, for each method. Statistics are computed over 5 trials for both the single-axis tracking and the reaching task.

Method	single-axis tracking		reaching task	
	$ \Delta\theta $ [rad]	$ \Delta\dot{\theta} $ [rad/s]	$\ \Delta p\ $ [m]	$\ \Delta\dot{p}\ $ [m/s]
Cascade	$(4.9 \pm 2.7) \times 10^{-2}$	3.6 ± 1.5	$(3.7 \pm 3.5) \times 10^{-2}$	$(6.1 \pm 2.8) \times 10^{-1}$
PD	$(3.3 \pm 5.8) \times 10^{-2}$	$(1.7 \pm 7.5) \times 10^{-1}$	$(4.7 \pm 4.1) \times 10^{-3}$	$(6.5 \pm 5.8) \times 10^{-2}$
2DoF	$(2.6 \pm 1.5) \times 10^{-3}$	$(\mathbf{1.3} \pm \mathbf{1.4}) \times \mathbf{10^{-2}}$	$(2.6 \pm 2.0) \times 10^{-3}$	$(1.0 \pm 0.6) \times 10^{-1}$
2DoF + DoB	$(\mathbf{1.8} \pm \mathbf{1.3}) \times \mathbf{10^{-3}}$	$(3.2 \pm 3.1) \times 10^{-2}$	$(\mathbf{1.3} \pm \mathbf{0.9}) \times \mathbf{10^{-3}}$	$(\mathbf{1.8} \pm \mathbf{0.7}) \times \mathbf{10^{-2}}$

ASAP [10]: a Delta Action model trained on real-world rollouts of the arm to compensate the simulation-to-reality dynamics mismatch, deployed on top of the same policy. Concretely, a Delta Action policy π_Δ is learned so that the deployed action augments the base policy output,

$$a = \pi(s) + \pi_\Delta(s), \quad (8)$$

where π_Δ is fitted to minimize the mismatch between the simulated transition under a and the observed real-world transition, i.e. $\min_{\pi_\Delta} \mathbb{E}[\|f_{\text{sim}}(s, a) - s'_{\text{real}}\|^2]$. Unlike our method, ASAP requires hardware-specific data collection to fit the Delta Action model.

6 Results

Single-Axis Tracking. We compare the baselines (PID cascade, Simple PD, 2-DoF) with our 2-DoF+DOB on a YM070 servo, taking the simulator reference dynamics (1) as the target. The phase portraits of the position error $\Delta\theta = \theta - \theta_{\text{ref}}$ and velocity error $\Delta\dot{\theta} = \dot{\theta} - \dot{\theta}_{\text{ref}}$ (Appendix A, Fig. 5a) show that the PID Cascade and Simple PD controllers leave a large sim-to-real gap—their position loops track the commanded goal angle rather than the reference dynamics, producing a systematic bias along $\Delta\theta$ —whereas the 2-DoF and 2-DoF+DOB clouds stay near the origin owing to the feedforward filter F , which reduces phase lag without overshoot. 2-DoF alone leaves a slight position offset, indicating the DOB further suppresses disturbance torques such as friction.

Over a 20 s sinusoidal reference (20° amplitude, 2.5 s period; 5 runs), the 2-DoF+DOB controller reduces the mean position deviation by 96.3% and 94.5% relative to the PID Cascade and Simple PD baselines, and the mean velocity deviation—the cascade’s dominant error mode—by 99.1% relative to the cascade (Table 1). The 2-DoF and 2-DoF+DOB results are similar in single-axis tracking; the DOB’s advantage instead becomes pronounced in the reaching task.

Reaching Task. The end-effector error on the reaching task, where the 7-DOF arm tracks a lemniscate (figure-eight) trajectory, is reported in the phase portrait of Appendix A (Fig. 5b); the policy trained against the ideal reference model (1) in IsaacSim transfers zero-shot to real hardware via 2-DoF+DOB, and we compare the deployed real-robot trajectory against the simulated one. Controllers other than 2-DoF track the target poorly, and as before the DOB further improves tracking.

Figure 3 compares our method against ASAP [10], a real-to-sim-to-real framework that corrects the simulator from real-world data and retrain the policy. The ASAP residual (8) reduced the sim-to-real gap, but to do so it output larger actions than the base policy π , destabilizing training in simulation (loss curves in Appendix H); its real-robot performance was thus not substantially better than the untuned factory Default. Our method instead attains good zero-shot performance without any fine-tuning.

Over the steady-state window of the lemniscate (5 runs, Table 1), the 2-DoF+DOB controller attains the lowest end-effector deviation—a 96.5% reduction relative to the factory PID cascade; the DOB accounts for a further 50% over 2-DoF alone, and 2-DoF+DOB reduces the error by 72% over the tuned Simple PD baseline, since uncompensated friction in the PD and cascaded controllers introduces a systematic offset the policy cannot anticipate.




Figure 3: Comparison with ASAP [10] on the reaching task




Figure 4: **Zero-shot demonstrations on other embodiments.** The per-joint 2-DoF driver layer applied to (a) a wheeled legged robot climbing a slope and (b) a humanoid robot’s zero-shot walk.

Zero-Shot Demonstrations on Other Embodiments. We further deploy the 2-DoF driver layer on two other platforms; time-lapse sequences are shown in Fig. 4.

Wheeled legged robot. Applied to the velocity-controlled wheel actuators, a policy trained against the reference model transfers zero-shot, climbing a slope (Fig. 4a) whose height must be inferred from per-joint states and IMU posture alone, difficult for poorly backdrivable high-gear-ratio servos, yet the 2-DoF controller succeeds by reproducing the simulator’s compliant spring-damper behavior.

Humanoid robot. Using a different servo (PH54), we train a walking policy with the off-the-shelf BeyondMimic [32] framework, swapping only the actuator model for the ideal reference model. The policy transfers without hardware-specific tuning and the robot takes stable forward steps (Fig. 4b), showing the approach carries over to a high-DOF, dynamically balancing whole-body platform.

7 Limitations

The method treats the joint-axis inertia as a constant I_{sim} , whereas it depends on the whole-body configuration $I_{\text{sim}}(q)$; this is negligible at high gear ratios but not for quasi-direct-drive actuators, where accounting for it (e.g., via Model Reference Adaptive Control) is a promising direction. The nominal J and $K_{\tau i}$ still require a coarse estimate, and whether the approach extends to strongly nonlinear hardware remains open.

8 Conclusion

We have presented *actuator reality shaping*: a per-joint two-degree-of-freedom controller that, using only a minimal motor model, drives real actuators to replicate the simulator’s second-order reference dynamics. By relocating the sim-to-real adaptation burden to a transparent, hardware-agnostic driver layer, it enables zero-shot transfer without hardware-specific data.

Acknowledgments

We would like to express our sincere gratitude to Professor Kazuya Yoshida and Assistant Professor Kentaro Uno at Tohoku University and the development team for inspiring the modular robot, MoonBot-mini model. This work was supported by JST ACT-X (Grant No. JPMJAX25CR), JST-Moonshot R&D Program (Grant No. JPMJMS223B-03), JST-Mirai Program (Grant No. JPMJMI21B1), JST-ASPIRE Program (Grant No. JPMJAP2503), and JSPS KAKENHI (Grant No. 22H04998 and 23K24925) and subsidized by NEDO (Grant No. JPNP14004), Japan.

References

- [1] J. Hwangbo, J. Lee, A. Dosovitskiy, D. Bellicoso, V. Tsounis, V. Koltun, and M. Hutter. Learning agile and dynamic motor skills for legged robots. *Science Robotics*, 4(26):eaau5872, 2019. doi:10.1126/scirobotics.aau5872.
- [2] A. Kumar, Z. Fu, D. Pathak, and J. Malik. RMA: Rapid motor adaptation for legged robots. *Robotics: Science and Systems*, 2021. doi:10.15607/RSS.2021.XVII.011.
- [3] J. Schulman, F. Wolski, P. Dhariwal, A. Radford, and O. Klimov. Proximal policy optimization algorithms, 2017.
- [4] R. Grandia, E. Knoop, M. A. Hopkins, G. Wiedebach, J. Bishop, S. Pickles, D. Müller, and M. Bächer. Design and control of a bipedal robotic character. In *Robotics: Science and Systems (RSS)*, 2024.
- [5] Z. Fu, Q. Zhao, Q. Wu, G. Wetzstein, and C. Finn. HumanPlus: Humanoid shadowing and imitation from humans. In *Conference on Robot Learning (CoRL)*, 2024.
- [6] J. Tobin, R. Fong, A. Ray, J. Schneider, W. Zaremba, and P. Abbeel. Domain randomization for transferring deep neural networks from simulation to the real world. In *2017 IEEE/RSJ International Conference on Intelligent Robots and Systems (IROS)*, pages 23–30, 2017. doi:10.1109/IROS.2017.8202133.
- [7] OpenAI, I. Akkaya, M. Andrychowicz, M. Chociej, M. Litwin, B. McGrew, A. Petron, A. Paino, M. Plappert, G. Powell, R. Ribas, J. Schneider, N. Tezak, J. Tworek, P. Welinder, L. Weng, Q. Yuan, W. Zaremba, and L. Zhang. Solving Rubik’s Cube with a Robot Hand. *arXiv preprint arXiv:1910.07113*, 2019.
- [8] F. Bjelonic, F. Tischhauser, and M. Hutter. Towards bridging the gap: Systematic sim-to-real transfer for diverse legged robots. *arXiv preprint arXiv:2509.06342*, 2025.
- [9] T. Sugie and T. Yoshikawa. General solution of robust tracking problem in two-degree-of-freedom control systems. *IEEE Transactions on Automatic Control*, 31(6):552–554, 1986. doi:10.1109/TAC.1986.1104337.
- [10] T. He, J. Gao, W. Xiao, Y. Zhang, Z. Wang, J. Wang, Z. Luo, G. He, N. Sobanbabu, C. Pan, Z. Yi, G. Qu, K. Kitani, J. Hodgins, L. Fan, Y. Zhu, C. Liu, and G. Shi. ASAP: Aligning simulation and real-world physics for learning agile humanoid whole-body skills. In *Robotics: Science and Systems (RSS)*, 2025.

- [11] X. B. Peng, M. Andrychowicz, W. Zaremba, and P. Abbeel. Sim-to-real transfer of robotic control with dynamics randomization. In *2018 IEEE International Conference on Robotics and Automation (ICRA)*, pages 3803–3810, 2018. doi:[10.1109/ICRA.2018.8460528](https://doi.org/10.1109/ICRA.2018.8460528).
- [12] J. Tan, T. Zhang, E. Coumans, A. Iscen, Y. Bai, D. Hafner, S. Bohez, and V. Vanhoucke. Sim-to-Real: Learning agile locomotion for quadruped robots. In *Proceedings of Robotics: Science and Systems XIV*, 2018. doi:[10.15607/RSS.2018.XIV.010](https://doi.org/10.15607/RSS.2018.XIV.010).
- [13] M. Andrychowicz, B. Baker, M. Chociej, R. Józefowicz, B. McGrew, J. Pachocki, A. Petron, M. Plappert, G. Powell, A. Ray, J. Schneider, S. Sidor, J. Tobin, P. Welinder, L. Weng, and W. Zaremba. Learning dexterous in-hand manipulation. *The International Journal of Robotics Research*, 39(1):3–20, 2020. doi:[10.1177/0278364919887447](https://doi.org/10.1177/0278364919887447).
- [14] Y. Chebotar, A. Handa, V. Makoviychuk, M. Macklin, J. Issac, N. Ratliff, and D. Fox. Closing the Sim-to-Real loop: Adapting simulation randomization with real world experience. In *2019 International Conference on Robotics and Automation (ICRA)*, pages 8973–8979, 2019. doi:[10.1109/ICRA.2019.8793789](https://doi.org/10.1109/ICRA.2019.8793789).
- [15] J. Lee, J. Hwangbo, L. Wellhausen, V. Koltun, and M. Hutter. Learning quadrupedal locomotion over challenging terrain. *Science Robotics*, 5(47):eabc5986, 2020. doi:[10.1126/scirobotics.abc5986](https://doi.org/10.1126/scirobotics.abc5986).
- [16] T. Miki, J. Lee, J. Hwangbo, L. Wellhausen, V. Koltun, and M. Hutter. Learning robust perceptive locomotion for quadrupedal robots in the wild. *Science Robotics*, 7(62):eabk2822, 2022. doi:[10.1126/scirobotics.abk2822](https://doi.org/10.1126/scirobotics.abk2822).
- [17] J.-J. E. Slotine and W. Li. *Applied Nonlinear Control*. Prentice Hall, Englewood Cliffs, New Jersey, USA, 1991.
- [18] K. J. Åström and B. Wittenmark. *Adaptive Control*. Dover Publications, 2nd edition, 2008.
- [19] J. Morimoto and C. G. Atkeson. Minimax differential dynamic programming: An application to robust biped walking. In S. Becker, S. Thrun, and K. Obermayer, editors, *Advances in Neural Information Processing Systems*, volume 15, pages 1563–1570, Vancouver, British Columbia, Canada, 2002. MIT Press.
- [20] J. Morimoto and C. G. Atkeson. Nonparametric representation of an approximated Poincaré map for learning biped locomotion. *Autonomous Robots*, 27(2):131–144, 2009. doi:[10.1007/s10514-009-9133-z](https://doi.org/10.1007/s10514-009-9133-z).
- [21] W. Yu, J. Tan, C. K. Liu, and G. Turk. Preparing for the unknown: Learning a universal policy with online system identification. In N. M. Amato, S. S. Srinivasa, N. Ayanian, and S. Kuindersma, editors, *Proceedings of Robotics: Science and Systems XIII*, Cambridge, Massachusetts, USA, 2017. doi:[10.15607/RSS.2017.XIII.048](https://doi.org/10.15607/RSS.2017.XIII.048).
- [22] W. Yu, V. C. V. Kumar, G. Turk, and C. K. Liu. Sim-to-real transfer for biped locomotion. In *2019 IEEE/RSJ International Conference on Intelligent Robots and Systems (IROS)*, pages 3503–3510, Macau, China, 2019. IEEE. doi:[10.1109/IROS40897.2019.8968053](https://doi.org/10.1109/IROS40897.2019.8968053).
- [23] X. B. Peng, E. Coumans, T. Zhang, T.-W. E. Lee, J. Tan, and S. Levine. Learning agile robotic locomotion skills by imitating animals. In *Proceedings of Robotics: Science and Systems XVI*, Held Virtually, 2020. doi:[10.15607/RSS.2020.XVI.064](https://doi.org/10.15607/RSS.2020.XVI.064).
- [24] M. Araki and H. Taguchi. Two-degree-of-freedom PID controllers. *International Journal of Control, Automation, and Systems*, 1(4):401–411, 2003.
- [25] T. Umeno and Y. Hori. Robust speed control of DC servomotors using modern two degrees-of-freedom controller design. *IEEE Transactions on Industrial Electronics*, 38(5):363–368, 1991. doi:[10.1109/41.97556](https://doi.org/10.1109/41.97556).

- [26] K. Ohishi, M. Nakao, K. Ohnishi, and K. Miyachi. Microprocessor-controlled DC motor for load-insensitive position servo system. *IEEE Transactions on Industrial Electronics*, IE-34(1): 44–49, 1987. doi:10.1109/TIE.1987.350923.
- [27] E. Sariyildiz and K. Ohnishi. Stability and robustness of disturbance-observer-based motion control systems. *IEEE Transactions on Industrial Electronics*, 62(1):414–422, 2015. doi:10.1109/TIE.2014.2327009.
- [28] W.-H. Chen, J. Yang, L. Guo, and S. Li. Disturbance-observer-based control and related methods—An overview. *IEEE Transactions on Industrial Electronics*, 63(2):1083–1095, 2016. doi:10.1109/TIE.2015.2478397.
- [29] NVIDIA. Isaac Sim. URL <https://github.com/isaac-sim/IsaacSim>.
- [30] V. Makoviychuk, L. Wawrzyniak, Y. Guo, M. Lu, K. Storey, M. Macklin, D. Hoeller, N. Rudin, A. Allshire, A. Handa, and G. State. Isaac Gym: High Performance GPU-Based Physics Simulation for Robot Learning. In *Proceedings of the Neural Information Processing Systems Track on Datasets and Benchmarks*, 2021.
- [31] M. Mittal, C. Yu, Q. Yu, J. Liu, N. Rudin, D. Hoeller, J. L. Yuan, R. Singh, Y. Guo, H. Mazhar, A. Mandlekar, B. Babich, G. Birchfield, M. Hutter, and A. Garg. Orbit: A unified simulation framework for interactive robot learning environments. *IEEE Robotics and Automation Letters*, 8(6):3740–3747, 2023. doi:10.1109/LRA.2023.3270034.
- [32] Q. Liao, T. Truong, X. Huang, Y. Gao, G. Tevet, K. Sreenath, and C. K. Liu. Beyond-Mimic: From motion tracking to versatile humanoid control via guided diffusion. *arXiv preprint arXiv:2508.08241*, 2025. URL https://github.com/HybridRobotics/whole_body_tracking.

A Phase Portraits




Figure 5: Phase portraits comparing how closely each controller reproduces the simulator reference dynamics (1). **(a)** Single-axis sinusoidal tracking on the YM070 joint ($\Delta\theta$, $\Delta\dot{\theta}$), overlaid for all four controllers. **(b)** 7-DoF arm lemniscate reaching, with axes the norms of the end-effector position and velocity error vectors. The 2-DoF+DOB cloud concentrates near the origin; disabling the DOB or using the PD/cascade controllers increases the spread.

B Derivation of the 2-DoF Closed-Loop Response

This appendix derives equation (5) step by step. The three governing relations of the 2-DoF structure are

$$y = P(u + d), \quad (9)$$

$$u = \frac{F}{\hat{P}} r + K e, \quad (10)$$

$$e = F r - y, \quad (11)$$

where the true plant is related to the nominal model through the multiplicative uncertainty ΔP via

$$P = (1 + \Delta P) \hat{P}, \quad \text{equivalently} \quad \frac{P}{\hat{P}} = 1 + \Delta P. \quad (12)$$

Step 1: substitute the error into the control input. Inserting (11) into (10) gives

$$u = \frac{F}{\hat{P}} r + K(F r - y). \quad (13)$$

Step 2: substitute the control input into the plant equation. Substituting (13) into (9) yields

$$y = P \left(\frac{F}{\hat{P}} r + K(F r - y) + d \right) = \frac{P}{\hat{P}} F r + P K F r - P K y + P d. \quad (14)$$

Step 3: collect y on the left-hand side. Moving the $P K y$ term to the left and factoring,

$$(1 + P K) y = \frac{P}{\hat{P}} F r + P K F r + P d. \quad (15)$$

Step 4: apply the uncertainty decomposition. Using (12) to replace $P/\hat{P}$ with $1 + \Delta P$,

$$(1 + P K) y = (1 + \Delta P) F r + P K F r + P d = (1 + P K) F r + \Delta P F r + P d, \quad (16)$$

where the last equality groups the two terms that share the common factor $F r$.

Step 5: divide by the return-difference $1 + P K$. Dividing both sides of (16) by $1 + P K$ gives the closed-loop response,

$$y = \left(1 + \frac{\Delta P}{1 + P K} \right) F r + \frac{P}{1 + P K} d, \quad (17)$$

which is exactly (5).

Interpretation. The first term of (17) is the reference response: it reduces to $F r$ when the model is exact ($\Delta P = 0$), and any residual model mismatch is attenuated by the sensitivity function $1/(1 + P K)$. The second term is the input-disturbance response, shaped by the sensitivity function $P/(1 + P K)$. This decoupling is the design principle exploited in the main text: the feedforward block F is chosen to match the simulator's reference dynamics, while the feedback block K is tuned independently to reject disturbances and steady-state offsets. Setting $r = 0$ recovers the standard input-sensitivity expression $y = \frac{P}{1 + P K} d$. That is, for sufficiently large K , the disturbance response is suppressed.

C Disturbance Observer

The DOB estimates the lumped disturbance torque τ_d from the commanded torque $\tau = K_{\tau i} i$ and the measured velocity $\dot{\theta}$. From the motor equation $J\ddot{\theta} = \tau - d\dot{\theta} - \tau_d$, the disturbance can be extracted as $\tau_d = \tau - (sJ + d)\dot{\theta}$. Because this expression involves differentiating the velocity signal $\dot{\theta}$, which amplifies encoder noise, we low-pass filter the estimate:

$$\hat{\tau}_d = \frac{\alpha_{\text{dob}}}{s + \alpha_{\text{dob}}} \left(\tau - (sJ + d)\dot{\theta} \right), \quad (18)$$

where α_{dob} is the DOB low-pass cutoff frequency in rad/s. The estimated disturbance is cancelled by subtracting a compensation current $i_{\text{comp}} = \hat{\tau}_d / K_{\tau i}$ from the commanded current before it is sent to the driver.

Table 2: Controller parameters used in experiments. Hardware parameters ($K_{\tau i}$, J , d) are identified from a pendulum free-response fit; controller and simulator parameters are design choices.

Parameter	Symbol	PH54	YM070
Torque constant	$K_{\tau i}$ [N·m/A]	4.8	1.389
Nominal inertia	J [kg·m ²]	0.0763	0.0152
Nominal viscous damp.	d [N·m·s/rad]	0.02	1.0
Time const. for F_2	α [rad/s]	15	30
DOB cutoff	α_{dob} [rad/s]	10	200
PID gain for Pos.	k_p, k_i, k_d	[15, 0, 0.02]	[50, 10, 1]
PID gain for Vel.	k_p, k_i, k_d	[3, 3, 0.01]	[15, 8, 0.1]
Sim. spring gain	K_p [N·m/rad]	50	30
Sim. damping	D [N·m·s/rad]	3.16	3.46
Sim. inertia	I_{sim} [kg·m ²]	0.05	0.1

Table 3: PPO training hyperparameters per task.

Task	Network (MLP)	Iterations	Rollout/env	Parallel envs
Reaching	[512, 256]	4,000	128	4,096
Rover	[512, 256, 128]	10,000	64	4,096
Humanoid	[512, 256, 128]	30,000	24	4,096

D Disturbance Observer Accuracy

The nominal motor model ($K_{\tau i}$, J , d) is estimated from a coarse one-shot fit of the motor equation (2), so a residual model error ΔP remains by construction. Since this residual is cancelled at runtime by the DOB rather than removed offline, we characterize it through the DOB’s reconstruction accuracy below, not through offline identification accuracy.

To evaluate DOB accuracy, we command a sinusoidal target joint angle with amplitude 20 deg and period 2.5 s, and compare the torque measured by the calibrated torque gauge against the torque estimated from the motor current. The mean absolute error between the gauge-measured torque and the current-estimated torque is 0.37 N·m for YM070 and 0.66 N·m for PH54.

E Implementation Details

The 2-DoF controller runs on the motor driver at $f_{\text{ctrl}} = 500$ Hz. At each step, the following operations are executed in order: (1) read encoder angle θ and compute velocity $\dot{\theta}$; (2) compute feedforward torque $\tau_{\text{ff}} = \frac{F}{P}r$; (3) compute feedback torque $\tau_{\text{fb}} = K(Fr - \theta)$; (4) compute DOB estimate $\hat{\tau}_d$; (5) sum and saturate: $i = \text{clip}((\tau_{\text{ff}} + \tau_{\text{fb}} - \hat{\tau}_d)/K_{\tau i}, -i_{\text{max}}, i_{\text{max}})$; (6) send i to the motor driver. The velocity $\dot{\theta}$ used by the DOB is passed through an additional low-pass filter at $0.5\alpha_{\text{dob}}$ to reduce encoder noise before entering the DOB numerator, at the cost of a small additional phase lag that is negligible relative to the control bandwidth. The controller parameters used in all experiments are summarized in Table 2.

F PPO Training Hyperparameters

The actor and critic networks use a standard MLP architecture with ELU activations, where the number of hidden units per layer is chosen per task. Table 3 lists, for each task, the MLP architecture (hidden units per layer), the number of PPO iterations, the rollout length per environment, and the number of parallel environments used during training.

Table 4: Domain randomization ranges for physical parameters (humanoid walking).

Parameter	Target body	Range	Unit	Operation
Static friction	all bodies	[0.3, 1.6]	—	uniform
Dynamic friction	all bodies	[0.3, 1.2]	—	uniform
Restitution	all bodies	[0.0, 0.5]	—	uniform
P gain (stiffness)	all joints	[80, 500]	—	uniform
D gain (damping)	all joints	[0.8, 5.0]	—	uniform
CoM offset (x)	torso/base	[−0.025, 0.025]	m	additive
CoM offset (y)	torso/base	[−0.05, 0.05]	m	additive
CoM offset (z)	torso/base	[−0.05, 0.05]	m	additive

Table 5: Domain randomization ranges for physical parameters (wheeled-robot reaching).

Parameter	Target	Range	Unit	Operation	Distribution
Joint stiffness	all joints	[0.3, 3.0]	—	scale	log-uniform
Joint damping	all joints	[0.75, 1.5]	—	scale	log-uniform
Joint friction	all joints	[0.9, 1.1]	—	scale	uniform
Joint armature	all joints	[0.9, 1.1]	—	scale	uniform
End-effector mass	ee_link	[0.5, 3.0]	—	scale	uniform
External force	ee_link_3	[−5, 5]	N	additive	uniform
External torque	ee_link_3	[−5, 5]	N·m	additive	uniform
Disturbance interval	—	[0.5, 5.0]	s	—	uniform

G Domain Randomization

Tables 4 and 5 summarize the ranges of the physical parameters that are randomized at the start of each episode for the humanoid walking task and the wheeled-robot reaching task, respectively. Joint-position resets and observation noise are omitted from these tables.

For the wheeled-robot reaching task, actuator gains and joint parameters are scaled multiplicatively around their nominal values. The end-effector link mass is scaled to emulate payload variation, and an external force/torque disturbance is applied to the end-effector at random intervals to test robustness.

H ASAP Model Training Loss

To complement the end-effector error comparison in Fig. 3, we report the training loss for the delta-action [10] baseline. ASAP’s delta-action model is fit on real-robot rollouts, and the loss values below show the per-stage convergence behavior we observed when reproducing this phase on our hardware. The box plots illustrate that ASAP’s correction relies on hardware-specific data collection, in contrast to the zero-shot transfer used by our 2-DoF+DOB approach. The model uses a single-step horizon ($H = 1, 1/60$ s), predicting the one-step correction from the current state.




Figure 6: ASAP training-loss (paired runs). Curves correspond to the delta-action model fit on real-robot rollouts during ASAP’s Stage-A phase. Used as supporting evidence for the comparison in Fig. 3.