MIX Alphameric Codes

SYMBOL	CODE									
MIX and Printer	Computer and Magnetic Tape	Paper Tape Channel X	0	C	8	4	2	1	Punch Card	
(Space)	00			√					(Blank)	
A	01	X	0					1	12	1
B	02	X	0				2		12	2
C	03	X	0	√			2	1	12	3
D	04	X	0			4			12	4
E	05	X	0	√		4		1	12	5
F	06	X	0	√		4	2		12	6
G	07	X	0			4	2	1	12	7
H	10	X	0		8				12	8
I	11	X	0	√	8			1	12	9
Δ	12	X	0	√					12	
J	13	X		√				1	11	1
K	14	X		√			2		11	2
L	15	X					2	1	11	3
M	16	X		√		4			11	4
N	17	X				4		1	11	5
O	20	X				4	2		11	6
P	21	X		√		4	2	1	11	7
Q	22	X		√	8				11	8
R	23	X			8			1	11	9
Σ	24	X							11	
Π	25		0						0	1
S	26		0	√			2		0	2
T	27		0				2	1	0	3
U	30		0	√		4			0	4
V	31		0			4		1	0	5
W	32		0			4	2		0	6
X	33		0	√		4	2	1	0	7
Y	34		0	√	8				0	8
Z	35		0		8			1	0	9
0 (Zero)	36			√	8		2		0	
1	37							1		1
2	40						2			2
3	41			√			2	1		3
4	42					4				4
5	43			√		4		1		5
6	44			√		4	2			6
7	45					4	2	1		7
8	46				8					8
9	47			√	8			1		9
.	50	X	0	√	8		2		12	2-8
,	51	X	0		8		2	1	12	3-8
(	52	X	0	√	8	4			12	4-8
)	53	X	0		8	4		1	12	5-8
+	54	X	0		8	4	2		12	6-8
-	55	X	0		8		2	1	12	7-7
*	56	X			8		2		11	2-8
/	57	X		√	8		2	1	11	3-8
=	60	X			8	4			11	4-8
$	61	X		√	8	4		1	11	5-8
<	62	X		√	8	4	2		11	6-8
>	63	X			8	4	2	1	11	7-8
@	64		0		8		2		0	2-8
;	65		0	√	8		2	1	0	3-8
:	66		0		8	4			0	4-8
'	67		0	√	8	4		1	0	5-8

MIX

A Summary of Operations in Operation-Code Order

INSTR.FORMAT					OPERATION		
±	AA	I	F	C	ABR	DF	NAME
±	aaaa	i	L:R	00	NOP	0	NO OPERATION
±	aaaa	i	L:R	01	ADD	0:5	ADD
±	aaaa	i	06	01	FADD		FLOATING ADD
±	aaaa	i	07	01	OR		LOGICAL SUM
±	aaaa	i	L:R	02	SUB	0:5	SUBTRACT
±	aaaa	i	06	02	FSUB		FLOATING SUBTRACT
±	aaaa	i	07	02	XOR		LOGICAL DIFFERENCE
±	aaaa	i	L:R	03	MUL	0:5	MULTIPLY
±	aaaa	i	06	03	FMUL		FLOATING MULTIPLY
±	aaaa	i	07	03	AND		LOGICAL PRODUCT
±	aaaa	i	L:R	04	DIV	0:5	DIVIDE
±	aaaa	i	06	04	FDIV		FLOATING DIVIDE
±	aaaa	i	00	05	NUM		CONVERT TO NUMERIC
±	aaaa	i	01	05	CHAR		CONVERT TO CHARACTERS
±	aaaa	i	02	05	HLT		HALT
±	aaaa	i	07	05	INT		INTERRUPT
±	aaaa	i	10	05	NEG		LOGICAL NEGATION
±	aaaa	i	11	05	XCH		EXCHANGE A AND X
±	aaaa	i	12	05	XEQ		EXECUTE
±	aaaa	i	00	06	SLA		SHIFT LEFT A
±	aaaa	i	01	06	SRA		SHIFT RIGHT A
±	aaaa	i	02	06	SLAX		SHIFT LEFT AX
±	aaaa	i	03	06	SRAX		SHIFT RIGHT AX
±	aaaa	i	04	06	SLC		SHIFT LEFT AX CIRCULARLY
±	aaaa	i	05	06	SRC		SHIFT RIGHT AX CIRCULARLY
±	aaaa	i	06	06	SLB		SHIFT LEFT LOGICAL AX
±	aaaa	i	07	06	SRB		SHIFT RIGHT LOGICAL AX
±	aaaa	i	N	07	MOVE	1	MOVE WORDS
±	aaaa	i	L:R	10+[r]	LD[r]	0:5	LOAD
±	aaaa	i	L:R	20+[r]	LD[r]N	0:5	LOAD r NEGATIVE
±	aaaa	i	L:R	30+[r]	ST[r]	0:5	STORE
±	aaaa	i	L:R	40	STJ	0:2	STORE J
±	aaaa	i	L:R	41	STZ	0:5	STORE ZERO
±	aaaa	i	U	42	JBUS	0	JUMP BUSY
±	aaaa	i	U	43	IOC	0	I/O CONTROL
±	aaaa	i	U	44	IN	0	INPUT
±	aaaa	i	U	45	OUT	0	OUTPUT
±	aaaa	i	U	46	JRED	0	JUMP READY
±	aaaa	i	00	47	JMP		JUMP
±	aaaa	i	01	47	JSJ		JUMP SAVE J
±	aaaa	i	02	47	JOV		JUMP ON OVERFLOW
±	aaaa	i	03	47	JNOV		JUMP ON NO OVERFLOW
±	aaaa	i	04	47	JL		JUMP ON LESS
±	aaaa	i	05	47	JE		JUMP ON EQUAL
±	aaaa	i	06	47	JG		JUMP ON GREATER
±	aaaa	i	07	47	JGE		JUMP ON GREATER-OR-EQUAL
±	aaaa	i	10	47	JNE		JUMP ON UNEQUAL
±	aaaa	i	11	47	JLE		JUMP ON LESS-OR-EQUAL
±	aaaa	i	00	50+[r]	J[r]N		JUMP r NEGATIVE
±	aaaa	i	01	50+[r]	J[r]Z		JUMP r ZERO
±	aaaa	i	02	50+[r]	J[r]P		JUMP r POSITIVE
±	aaaa	i	03	50+[r]	J[r]NN		JUMP r NONNEGATIVE
±	aaaa	i	04	50+[r]	J[r]NZ		JUMP r NONZERO
±	aaaa	i	05	50+[r]	J[r]NP		JUMP r NONPOSITIVE
±	aaaa	i	06	50+[r]	J[r]E		JUMP r EVEN
±	aaaa	i	07	50+[r]	J[r]O		JUMP r ODD
±	aaaa	i	00	60+[r]	INC[r]		INCREASE r
±	aaaa	i	01	60+[r]	DEC[r]		DECREASE r
±	aaaa	i	02	60+[r]	ENT[r]		ENTER r
±	aaaa	i	03	60+[r]	ENN[r]		ENTER NEGATIVE r
±	aaaa	i	04	60+[r]	CP[r]M		COMPARE r WITH M
±	aaaa	i	L:R	70+[r]	CMP[r]	0:5	COMPARE r
±	aaaa	i	06	70	FCMP		FLOATING COMPARE

[r]: rA=0, rI1, rI2, rI3, rI4, rI5, rI6, rX=7, i: I1:I2, 7 is indirect addressing