

DW01_inc

Incrementer

Version, STAR, and myDesignWare Subscriptions: [IP Directory](#)

Features and Benefits

- Parameterized word length

Revision History

Description

Incrementer DW01_inc adds 1 to an input number A to produce the output SUM.




Table 1-1 Pin Description

Pin Name	Width	Direction	Function
A	<i>width</i> bits	Input	Input data
SUM	<i>width</i> bits	Output	Increment (A + 1)

Table 1-2 Parameter Description

Parameter	Values	Description
width	≥ 1	Word length of A and SUM

Table 1-3 Synthesis Implementations^a

Implementation Name	Function	License Feature Required
rpl	Ripple-carry synthesis model	none
cla	Carry-look-ahead synthesis model	none
pparch	Delay-optimized flexible parallel-prefix	DesignWare
apparch	Area-optimized flexible architecture that can be optimized for area, for speed, or for area, speed	DesignWare

a. During synthesis, Synopsys synthesis tools select the appropriate architecture for your constraints. Alternatively, you may use the set_implementation command to choose one specific implementation from those listed in this table. For details, see the documentation for your Synopsys synthesis tool.

Table 1-4 Simulation Models

Model	Function
DW01.DW01_INC_CFG_SIM	Design unit name for VHDL simulation
dw/dw01/src/DW01_inc_sim.vhd	VHDL simulation model source code
dw/sim_ver/DW01_inc.v	Verilog simulation model source code

Related Topics

- [Math – Arithmetic Overview](#)
- [DesignWare Building Block IP User Guide](#)

HDL Usage Through Operator Inferencing - VHDL

```
library IEEE;
use IEEE.std_logic_1164.all;
use IEEE.std_logic_arith.all;

entity DW01_inc_oper is
    generic(wordlength: integer := 8);
    port(in1 : in STD_LOGIC_VECTOR(wordlength-1 downto 0);
         sum : out STD_LOGIC_VECTOR(wordlength-1 downto 0));
end DW01_inc_oper;

architecture oper of DW01_inc_oper is
    signal in_signed,sum_signed: SIGNED(wordlength-1 downto 0);
begin
    in_signed <= SIGNED(in1);

    -- infer the "+" addition operator
    sum_signed <= in_signed + 1;
    sum <= STD_LOGIC_VECTOR(sum_signed);
end oper;
```

HDL Usage Through Operator Inferencing - Verilog

```
module DW01_inc_oper(in1,sum);  
    parameter wordlength = 8;  
  
    input [wordlength-1:0] in1;  
    output [wordlength-1:0] sum;  
  
    assign sum = in1 + 1;  
endmodule
```

HDL Usage Through Component Instantiation - VHDL

```

library IEEE,DWARE;
use IEEE.std_logic_1164.all;
use DWARE.DWpackages.all;
use DWARE.DW_foundation_comp.all;

entity DW01_inc_inst is
    generic ( inst_width : NATURAL := 8 );
    port ( inst_A      : in std_logic_vector(inst_width-1 downto 0);
          SUM_inst    : out std_logic_vector(inst_width-1 downto 0) );
end DW01_inc_inst;

architecture inst of DW01_inc_inst is
begin

    -- Instance of DW01_inc
    U1 : DW01_inc
        generic map ( width => inst_width )
        port map ( A => inst_A, SUM => SUM_inst );
end inst;

-- pragma translate_off
configuration DW01_inc_inst_cfg_inst of DW01_inc_inst is
    for inst
    end for; -- inst
end DW01_inc_inst_cfg_inst;
-- pragma translate_on

```

HDL Usage Through Component Instantiation - Verilog

```

module DW01_inc_inst( inst_A, SUM_inst );

    parameter width = 8;

    input [width-1 : 0] inst_A;
    output [width-1 : 0] SUM_inst;

    // Instance of DW01_inc
    DW01_inc #(width)
        U1 ( .A(inst_A), .SUM(SUM_inst) );

endmodule

```

Revision History

For notes about this release, see the [DesignWare Building Block IP Release Notes](#).

For lists of both known and fixed issues for this component, refer to the [STAR report](#).

For a version of this datasheet with visible change bars, click [here](#).

Date	Release	Updates
September 2024	DWBB_202409.0	■ Updated date and version; no technical changes
December 2023	DWBB_202312.0	■ Updated date and version; no technical changes
March 2019	DWBB_201903.0	■ Removed Table 1-4, “Obsolete Synthesis Implementations”
January 2019	DWBB_201806.5	■ Updated example in “ HDL Usage Through Component Instantiation - VHDL ” on page 5 ■ Added this Revision History table and the document links on this page

Copyright Notice and Proprietary Information

© 2024 Synopsys, Inc. All rights reserved. This Synopsys software and all associated documentation are proprietary to Synopsys, Inc. and may only be used pursuant to the terms and conditions of a written license agreement with Synopsys, Inc. All other use, reproduction, modification, or distribution of the Synopsys software or the associated documentation is strictly prohibited.

Destination Control Statement

All technical data contained in this publication is subject to the export control laws of the United States of America. Disclosure to nationals of other countries contrary to United States law is prohibited. It is the reader's responsibility to determine the applicable regulations and to comply with them.

Disclaimer

SYNOPSYS, INC., AND ITS LICENSORS MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

Trademarks

Synopsys and certain Synopsys product names are trademarks of Synopsys, as set forth at <https://www.synopsys.com/company/legal/trademarks-brands.html>.

All other product or company names may be trademarks of their respective owners.

Free and Open-Source Software Licensing Notices

If applicable, Free and Open-Source Software (FOSS) licensing notices are available in the product installation.

Third-Party Links

Any links to third-party websites included in this document are for your convenience only. Synopsys does not endorse and is not responsible for such websites and their practices, including privacy practices, availability, and content.

Synopsys, Inc.
www.synopsys.com

