Network Notes

January 8, 2022

Contents

Chapter 1

The Network Protocol

.

1.1   Overview

Loconet is a peer to peer distributed network system on which all devices can monitor
the network data flow. The network is event driven by different devices in time, and is
not polled by a centralised controller in normal operation. The normal network state is
idle, with no data traffic unless a device has information to send. With no traffic flow, the
network is quiet.

The network data is sent in asynchronous format using 1 start bit, 8 data bits and 1 stop bit.
The 8 bit data is transmitted least significant bit first. The bit times are 60.0 μS or 16,660
baud +/- 1.5%. A computer can connect to a Digitrax USB interface at higher baud rates
and the device will make the necessary conversion. Bytes may be transmitted back-to-back,
with a start bit immediately following the stop bit of the previous character.

Any message that has format or framing errors, data errors or is a fragment caused by
noise glitches and does not completely follow the message format will be ignored by all
receivers, and a new opcode will be scanned for re-synchronisation.

The **Busy** message is included to allow the command station to keep the network active
whilst it is performing a task that requires a response, and entails a significant processing
delay, i.e. it can ensure no new requests are started until it has responded to the last
message. The **Busy** message should be simply stripped and ignored.

If a device disconnects from the network and so does not access or reference a slot within the

system purge time, the command station will force the un-accessed slot to common status
so other system devices can use the slot. The typical purge time of a command station is
about 200 seconds. A good "ping" or slot update activity is about every 100 seconds, i.e.
if a user makes no change to a throttle/slot within 100 seconds, the throttle/device should
automatically send another speed update at the current speed to reset the purge timeout
for that slot.

1.2   Message Format

All the network communications are via multi-byte messages. The command station is
defined as the device that is maintaining the refresh stack for DCC packet generation
and is actively generating the DCC track data. Refresh of information is typically only
performed for mobile decoders. Stationary type decoders are not refreshed and individual
immediate commands are sent out to the track as requested.

The command station is only privileged in respect to performing the task of maintaining
the locomotive refresh stack and generating DCC packets. In this way other network
transactions may occur that the command station does not need to be involved with or
understand, as long as they follow the message protocol and timing requirements. i.e. other
devices may have a dialog on the network without disturbing or involving the command
station. Devices on the network monitor the messages, check for format and data integrity
and parse good messages to decode if action is required in the context. Devices such as
throttles, input sensors, computer interfaces and control panels may generate the network
messages without needing prompting or polling by a central controller.

Devices frequently will be added and removed from an operating the network. The devices
and protocol are tolerant of electrical and data transients. The format chosen gives a
good degree of data integrity, guaranteed quick network-state synchronisation, high data
throughput, good distribution of access to many competing devices and low event latency.
Also, the devices may be operated without need for unique ID or other requirements that
can make network administration awkward.

The data bytes on the network are defined as 8 bit data with the most significant bit as
an opcode flag bit. If the most significant bit, d7, is 1 then the 7 least significant bits are
interpreted as a network opcode . The opcode byte may only occur once in a valid message
and is the first byte of a message. The opcode does not necessarily uniquely identify a
message type. Sometimes the opcode must be used in combination of other bits or bytes
in the message. All the remaining bytes in the message must have a most significant bit
of 0, including the last checksum byte. The checksum is the 1's complement of the byte
wise exclusive or of all the bytes in the message, except the checksum itself. To validate

data accuracy, all the bytes in a correctly formatted message are exclusive or'ed. If this resulting byte value is 0xFF, then the message data is accepted as good.

The opcodes may be examined to determine message length and if subsequent response message is required. Data bits d6 and d5 encode the message length. The message length includes the opcode and the checksum bytes. The bit d3 = 1 implies that a follow-on message or reply is expected. For variable byte messages The byte following the opcode in the message is a 7 bit byte count.

d7	d6	d5	d4	d3	d2	d1	d0	
1	0	0	E	D	C	B	A	2 byte message
1	0	1	E	D	C	B	A	4 byte message
1	1	0	E	D	C	B	A	6 byte message
1	1	1	E	D	C	B	A	Variable length message.

The A,B,C,D,E are bits available to encode 32 opcodes per message length.

1.3   Refresh Slots

The command station's refresh stack is used to control the locomotives. The refresh stack is an array of read/write refresh slots. There are two protocols for manipulating the refresh slots. Protocol 1 allows up to 120 locomotive slots and each slot contains 10 bytes of data relating to the locomotive. Protocol 2 allows up to 960 locomotive slots and each slot contains 15 bytes of data relating to the locomotive. Not all command stations implement both protocols. A command station may also not implement the maximum number of locomotive slots for the protocols it supports. Where a command station implements both protocols messages from both protocols can be freely mixed. The user should check the TRK status bits to determine if protocol 1 and/or 2 are supported. In this document message mnemonics that are suffixed "P1" belong to protocol 1 and those suffixed "P2" belong to protocol 2. The slot number is a principal component of the protocol and is similar to a file handle. In addition to the locomotive slots there are slots reserved for system and command station control. These slots are numbered 120 to 127 (0x78 to 0x7F) and are encoded differently from the locomotive slots. Slot 123 (0x7B) is allocated to the fast clock. Slot 124 (0x7C) is allocated for read/write access to the programming track and slot 127 (0x7F) contains the command station configuration settings. Protocol 1 uses a single 7 bit number to identify a slot. Protocol 2 uses a 3 bit number to identify the page or bank of slots and a 7 bit number to identify the slot within the page or bank. Within the protocol 2 page slots numbered 0x00 to 0x77 are locomotive slots and slots numbered 0x78 to 0x7F are system slots.

1.4   Getting Started

To request a mobile or locomotive decoder task in the refresh stack, a throttle device requests a slot for the locomotive address by sending either the **getLocoSlotDataSAdr** or **getLocoSlotDataLAdr** commands. Which one depends on what type of decoder address you are using - short 2 digit or long 4 digit. The command station responds with **LocoSlotData** response that contains this locomotive address and all of its state information. If the address is currently not in any slot, the command station will load this new locomotive address into a new slot (speed=0, direction forwards, functions off and 128 step mode) and return this as a **LocoSlotData** response. If no inactive slots are free to load the new locomotive address, the response will be the **Ack** with a fail response code of 0x00.

The throttle/computer must then examine the slot data bytes to work out how to process the command station response. If the slot status 1 byte shows the slot to be "common" or "idle" the throttle may change the slot to "in use" by performing a null move instruction on this slot (see **MoveSlots**). This activation mechanism is used to guarantee proper slot usage interlocking in a multi-user asynchronous environment.

If the slot return information shows the locomotive requested is "in use" or up-consisted (i.e. the SL_CONUP, bit 6 of slot status $1 = 1$) the user should not use the slot. Any up-consisted locomotives must be unlinked before usage. Always process the result from the **LinkSlots** and **UnlinkSlots** commands, since the command station reserves the right to change the reply slot number and can reject the linking tasks under several circumstances. Verify the reply slot number and the link UP/DN bits in slot status 1 are as you expected.

The throttle will then be able to update speed, direction and function information. Whenever slot information is changed in an active slot , the slot is flagged to be updated as the next DCC packet sent to the track. If the slot is part of linked consist slots the whole consist chain is updated consecutively.

If a throttle is disconnected from the the Network, upon reconnection (if the throttle retains the slot state from before disconnection) it will request the full status of the slot it was previously using. If the reported status and speed, function data etc., from the command station exactly matches the remembered slot state the throttle will continue using the slot. If the slot data does not match, the throttle will assume the slot was purged free by the system and will go through the setup log on procedure again.

With this procedure the throttle does not need to have a unique ID number. Slot addresses do not imply they contain any particular locomotive address. The system can be mapped such that the slot address matches the locomotive address within, if the user directly reads and writes to slots without using the command station to allocate locomotive addresses.

1.5 Messages

The following information is provided for each of the messages:

Description:

Description of the message's function.

Protocol:

Which protocol the message belongs to. Only messages that relate to refresh slots belong to a protocol.

Group:

Which message size group the message belongs to.

Opcode:

The opcode mnemonic. This is the Digitrax assigned mnemonic when known.

Type:

The message type - broadcast, command, response, or message.

Encoding:

How the message is encoded byte by byte.

Response:

The response expected from a command message, if applicable.

Signature:

The bits and bytes that must be tested to determine the message's unique type.

Notes:

Any notes.

1.5.1   Ack

Description:

This message provides a response code from a command.

Group:

4-Byte Message

Opcode:

OPC_LONG_ACK

Type:

Response

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 1 | 0 | 0 |

0xB4   Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n |

<LOPC>   Opcode of the command that this message is a response to with the most significant bit set to 0.

Byte 2:

| 0 | n | n | n | n | n | n | n |

<ACK1>   Response code.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 1 | 0 | 0 |

0xB4

Notes:

None.

1.5.2   Busy

Description:

The **Busy** broadcast message allows the command station to keep the network active whilst it is performing a task that requires a response, and entails a significant processing delay, i.e. it can ensure no new requests are started until it has responded to the last message. The **Busy** message should be simply stripped and ignored.

Group:

2-Byte Message

Opcode:

OPC_BUSY

Type:

Broadcast

Encoding:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0x81 | Opcode. |

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 0 | 0x7E | Checksum. |

Response:

None

Signature:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0x81 |

Notes:

None.

1.5.3   CfgSlotDataP1

Description:

This response provides the current command station configuration slot data. It is sent by the command station in response to the **GetCfgSlotDataP1** command.

Protocol:

1

Group:

Variable-Byte Message

Opcode:

OPC_SL_RD_DATA

Type:

Response

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 1 | 0xE7   Opcode.

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 | 0x0E   Message length (14 bytes).

OST1 to OST6 encode the command station's option switch table. The narrative is based upon information in the the DCS210 and DCS240 user manuals. A bit value of 1 means that the switch is closed and a value of 0 means that a switch is thrown. OpSw 8, OpSw 16, OpSw 24, OpSw 32 and OpSw 40 cannot be read due to bit 7 being cleared in the message format. The manual shows these switches as defaulting to thrown, i.e. 0, and are flagged in all cases except OpSw 40 as "do not change".

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Configuration slot number.

Byte 3:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <OST1>   Option switch table byte 1.

Bit	Switch #	Default	Effect on system operation
d6	OpSw 07	t	do not change
d5	OpSw 06	t	t = check for decoder before programming
			c = program without checking for device
d4	OpSw 05	t	do not change
d3	OpSw 04	t	do not change
d2	OpSw 03	t	t = command station's booster normal
			c = command station's booster is auto reversing
d1	OpSw 02	t	t = command station mode
			c = booster only mode.
d0	OpSw 01	t	do not change.

Byte 4:

0	d6	d5	d4	d3	d2	d1	d0

<OST2>   Option switch table byte 2.

Bit	Switch #	Default	Effect on system operation
d6	OpSw 15	t	t = purging will not change loco speed
			c = purging will force a loco to 0 speed
d5	OpSw 14	t	t = loco address purging enabled
			c = loco address purging disabled
d4	OpSw 13	t	t = loco address purge time 200 seconds
			c = loco address purge time 600 seconds
d3	OpSw 12	t	do not change
d2	OpSw 11	t	do not change
d1	OpSw 10	c	do not change
d0	OpSw 09	c	do not change

Byte 5:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | \<OST3\>   Option switch table byte 3.

Bit	Switch #	Default	Effect on system operation
d6	OpSw 23	t	SW23
d5	OpSw 22	c	SW22
d4	OpSw 21	c	SW21
d3	OpSw 20	t	t = enable address 0x00 or analog stretching for conventional locos
			. c = disable address 0x00 or analog stretching for conventional locos
d2	OpSw 19	t	do not change
d1	OpSw 18	t	t = normal command station booster short circuit shutdown time
			c = extended command station booster short circuit shutdown time
d0	OpSw 17	t	t = automatic advanced decode (FX) consists are enabled
			c = automatic advanced decode (FX) consists are disabled

SW21	SW22	SW23	Global system default type for new locos
t	t	t	28 step mode
t	t	c	reserved
t	c	t	14 step mode
t	c	c	reserved
c	t	t	reserved
c	t	c	reserved
c	c	t	128 step mode
c	c	c	128 step FX mode

Byte 6:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <OST4> | Option switch table byte 4. |

<u>Bit</u>	<u>Switch #</u>	<u>Default</u>	<u>Effect on system operation</u>
d6	OpSw 31	t	t = normal route/switch output rate when not trinary
			c = fast route/switch output rate when not trinary
d5	OpSw 30	t	do not change
d4	OpSw 29	t	do not change
d3	OpSw 28	t	t = enable interrogate commands at power on
			c = disable interrogate commands at power on
d2	OpSw 27	t	t = enable normal switch commands, a.k.a. the "Bushby bit"
			c = disable normal switch commands, a.k.a. the "Bushby bit" (allows attached computer to handle switch control logic)
d1	OpSw 26	c	t = disable routes
			c = enable routes
d0	OpSw 25	t	t = enable route echo over the Network
			c = disbale route echo over the Network

Byte 7:

| 0 | d6 | 0 | 0 | d3 | d2 | d1 | d0 | <TRK> | Global system track status. |

d6	1 means this command station implements version 2 slot commands. This can be turned off on the DCS240 by setting the OpSw 44 to be closed.
d3	1 means the programming track is busy.
d2	1 means this master implements the Network version 1.1 capability, 0 means the master is a DT200.
d1	0 means the track is paused, broadcast an emergency stop.
d0	1 means the DCC packets are on in the master, global power up.

Byte 8:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | \<OST5\>   Option switch table byte 5.

Bit	Switch #	Default	Effect on system operation
d6	OpSw 39	t	c = clear all internal memory states, including OpSw 36 and 37
d5	OpSw 38	t	t = loco reset button activates OpSw 39 c = loco reset activates slot zero
d4	OpSw 37	t	c = clears all routes
d3	OpSw 36	t	c = clears all mobile decoder info and consists
d2	OpSw 35	t	t = enables loco reset buttone c = disable loco reset button
d1	OpSw 34	t	t = disallow track to power up to run state, if set to run prior to power up c = allow track to power up to run state, if set to run prior to power up
d0	OpSw 33	c	t = track power off at power on c = allow track power to restore to prior state at power on

Byte 9:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<OST6>   Option switch table byte 6.

Bit	Switch #	Default	Effect on system operation
d6	OpSw 47	t	t = normal program track setting
			c = program track is brake generator when not programming. Braking is DCC set to speed 0 (not emergency stop) for address 0, light on, broadcast to all addresses.
d5	OpSw 46	t	do not change
d4	OpSw 45	t	t = enable reply for switch state request
			c = disable reply for switch state request
d3	OpSw 44	t	do not change (DCS210)
	OpSw 44	t	maximum slots to 400 (DCS240) and enable protocol 2 support
	OpSw 44	c	maximum slots to 120 (DCS240) and disable protocol 2 support
d2	OpSw 43	t	t = enable the Network update of command station's track status
			c = disable the Network update of command station's track status
d1	OpSw 42	t	t = enable 2 short beeps when loco address purged
			c = disable 2 short beeps when loco address purged
d0	OpSw 41	t	t = diagnostic click disabled
			c = diagnostic click when valid the Network commands incoming and routes being output

Byte 10:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Unknown.

d6
d5
d4
d3
d2
d1
d0

Byte 11:

| 0 | n | n | n | n | n | n | n |

   \<CSM\>   Product code.

Product Code	Model
0x1B	DCS210
0x1C	DCS240

Byte 12:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

                                       Unknown.

d6
d5
d4
d3
d2
d1
d0

Byte 13:

| 0 | n | n | n | n | n | n | n |

   \<CHK\>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 1 |

0xE7

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 |

0x0E

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F

Byte 7:

| 0 | × | 0 | 0 | × | × | × | × |

Notes:

None.

1.5.4 ConsistDirF0F4

Description:

This command sets the consist element's direction and function F0 to F4 states.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_CONSIST_FUNC

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 1 | 1 | 0 | 0xB6 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 2:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 | <DIRF> | Consist element's direction and function F0 to F4 states. |

d5	Direction: 1 means forward and 0 means backwards.
d4	F0 state: 1 means on and 0 means off.
d3	F4 state: 1 means on and 0 means off.
d2	F3 state: 1 means on and 0 means off.
d1	F2 state: 1 means on and 0 means off.
d0	F1 state: 1 means on and 0 means off.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 1 | 1 | 0 | 0xB6

Byte 1:

| 0 | n | n | n | n | n | n | n | less than 0x78

Byte 2:

| 0 | 0 | × | × | × | × | × | × |

Notes:

None.

1.5.5   GetBrdOpSw

Description:

Get board option switch setting.

Group:

6-Byte Message

Opcode:

OPC_BRD_OPSW (unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 |

0xD0   Opcode.

Byte 1:

| 0 | 1 | 1 | 0 | 0 | 0 | 1 | d0 |

The bit d0 is the most significant bit of the board id.

Byte 2:

| 0 | n | n | n | n | n | n | n |

<BIDL>   Least significant 7 bits of the board id.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<BTYPE>   Board type code.

Board	Type Code
PM4	0x70.
BDL16	0x71.
SE8C	0x72.
DS64	0x73.

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Byte and bit number.

The high nibble encodes the byte number, and the low nibble the bit number. The byte number is calculated as (OpSw# - 1) >> 3 and the bit number is (OpSw# - 1) - byte number × 8.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

Ack ¡- *** SHOULD NOT BE A RESPONSE ***

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 |

0xD0

Byte 1:

| 0 | 1 | 1 | 0 | 0 | 0 | 1 | × |

Notes:

*** THIS HAS NOT BEEN TESTED ***

1.5.6 GetCfgSlotDataP1

Description:

This command requests the configuration slot data. The command station responds with a **CfgSlotDataP1** message.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_RQ_SL_DATA

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 1 | 0xBB | Opcode. |

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F |

Byte 2:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 3:

| 0 | n | n | n | n | n | n | n | \<CHK> | Checksum. |

Response:

CfgSlotDataP1

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 1 | 0xBB |

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 2:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Notes:

None.

1.5.7 GetInterfaceData

Description:

This command is sent by a computer to request an **InterfaceData** response from the attached network interface device.

Group:

2-Byte Message

Opcode:

OPC_BUSY

Type:

Command

Applicable Hardware:

Digitrax PR4 and DCS240.

Encoding:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | | 0x81 | | Opcode. |

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 0 | | 0x7E | | Checksum. |

Response:

Interface device returns an **InterfaceData** response.

Signature:

None - the command is intercepted by the interface and is not passed on to the network.

Notes:

None.

1.5.8   GetLocoSlotDataLAdrP1

Description:

This command requests the slot number for the selected locomotive address. If the loco-
motive is found in the slot table then the command station returns an **LocoSlotDataP1**
response with the slot information. If it is not found then the command station will put
the locomotive into a free slot and then return an **LocoSlotDataP1** response with the slot
information. If there are no free slots then the command station returns an **Ack** containing
a response code of 0x00.

The command station will generate NMRA 14 bit or long address packets for the locomo-
tive. The address must be in the range 128 to 9983.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_LOCO_ADR

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 1 | 1 | 0xBF   Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n | \<ADR2\>   Address high 7 bits.

Byte 2:

| 0 | n | n | n | n | n | n | n | \<ADR\>   Address low 7 bits.

Byte 3:

| 0 | n | n | n | n | n | n | n | \<CHK\>   Checksum.

Response:

LocoSlotDataP1 if success, otherwise

Ack

<LOPC>	<ACK1>	Meaning
0x3F	0x00	No free slot, command failed.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 1 | 1 | 0xBF

Byte 1:

| 0 | n | n | n | n | n | n | n | not equal to 0

Notes:

This command is not supported by the Digitrax DT200 command station.

1.5.9   GetLocoSlotDataLAdrP2

Description:

This command requests the slot number for the selected locomotive address. If the locomotive is found in the slot table then the command station returns an **LocoSlotDataP2** response with the slot information. If it is not found then the command station will put the locomotive into a free slot and then return an **LocoSlotDataV2** response with the slot information. If there are no free slots then the command station returns an **Ack** containing a response code of 0x00.

The command station will generate NMRA 14 bit or long address packets for the locomotive. The address must be in the range 128 to 9983.

Protocol:

2

Group:

4-Byte Message

Opcode:

OPC_LOCO_ADR_P2 (unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0xBE   Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n | <ADR2>   Address high 7 bits.

Byte 2:

| 0 | n | n | n | n | n | n | n | <ADR>   Address low 7 bits.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

LocoSlotDataP2 if success, otherwise

Ack.

<LOPC>	<ACK1>	Meaning
0x3E	0x00	No free slot, command failed.

Signature:

Byte 0:

1	0	1	1	1	1	1	0	0xBE

Byte 1:

0	n	n	n	n	n	n	n	not equal to 0

Notes:

None.

1.5.10   GetLocoSlotDataP1

Description:

This command requests the locomotive slot data for the specified slot number. The command station responds with a **LocoSlotDataP1** response.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_RQ_SL_DATA

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 1 | 0xBB | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 2:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | d0 | 0x00 |

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

LocoSlotDataP1

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 1 | 0xBB |

Byte 1:

0	n	n	n	n	n	n	n	less than 0x78

Byte 2:

0	0	0	0	0	0	0	d0	0x00

<u>Notes:</u>

None.

1.5.11   GetLocoSlotDataP2

<u>Description:</u>

This command requests the locomotive slot data for the specified slot number. The command station responds with a **LocoSlotDataP2** response.

<u>Protocol:</u>

2

<u>Group:</u>

4-Byte Message

<u>Direction:</u>   → Switch

<u>Opcode:</u>

OPC_RQ_SL_DATA

<u>Type:</u>

Command

<u>Encoding:</u>

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 1 | 0xBB   Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n | <SLOT#>   Slot number in the range 0x00 to
                                                  0x77.

Byte 2:

| 0 | 1 | 0 | 0 | d3 | d2 | d1 | d0 | <SLOTP>   Bits d2 to d0 contain the slot page
                                                  number in the range 0x0 to 0x7.
                                                  The bit d3 does something but its
                                                  function is not yet known.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

<u>Response:</u>

LocoSlotDataP2

Signature:

Byte 0:

1	0	1	1	1	0	1	1	0xBB

Byte 1:

0	n	n	n	n	n	n	n	less than 0x78

Byte 2:

0	1	0	0	×	×	×	×

Notes:

None.

1.5.12   GetLocoSlotDataSAdrP1

Description:

This command requests the slot number for the selected locomotive address. If the loco-
motive is found in the slot table then the command station returns an **LocoSlotDataP1**
response with the slot information. If it is not found then the command station will put
the locomotive into a free slot and then return an **LocoSlotDataP1** response with the slot
information. If there are no free slots then the command station returns an **Ack** containing
a response code of 0x00.

The command station will generate NMRA 7 bit or short address packets for the locomo-
tive. The address has the range 0 to 127. The analog locomotive is selected with address
0.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_LOCO_ADR

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 1 | 1 | 0xBF   Opcode.

Byte 1:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 2:

| 0 | n | n | n | n | n | n | n | \<ADR\>   Short address in the range 0 to
                                                  127.

Byte 3:

0	n	n	n	n	n	n	n

<CHK>   Checksum.

Response:

LocoSlotDataP1 if success, otherwise

Ack

<LOPC>	<ACK1>	Meaning
0x3F	0x00	No free slot, command failed.

Signature:

Byte 0:

1	0	1	1	1	1	1	1

0xBF

Byte 1:

0	0	0	0	0	0	0	0

0x00

Notes:

None.

1.5.13   GetLocoSlotDataSAdrP2

Description:

This command requests the slot number for the selected locomotive address. If the loco-
motive is found in the slot table then the command station returns an **LocoSlotDataP2**
response with the slot information. If it is not found then the command station will put
the locomotive into a free slot and then return an **LocoSlotDataP2** response with the slot
information. If there are no free slots then the command station returns an **Ack** containing
a response code of 0x00.

The command station will generate NMRA 7 bit or short address packets for the locomo-
tive. The address has the range 0 to 127. The analog locomotive is selected with address
0.

Protocol:

2

Group:

4-Byte Message

Opcode:

OPC_LOCO_ADR_P2 (unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0xBE   Opcode.

Byte 1:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 2:

| 0 | n | n | n | n | n | n | n | <ADR>   Short address in the range 0 to
                                                 127.

Byte 3:

0	n	n	n	n	n	n	n	<CHK> Checksum.

Response:

LocoSlotDataP2 if success, otherwise

Ack

<LOPC>	<ACK1>	Meaning
0x3E	0x00	No free slot, command failed.

Signature:

Byte 0:

1	0	1	1	1	1	1	0	0xBE

Byte 1:

0	0	0	0	0	0	0	0	0x00

Notes:

None.

1.5.14   IMMPacket

Description:

Send n-byte DCC immediate packet.

Group:

Variable-Byte Message

Opcode:

OPC_IMM_PACKET

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 1 | 1 | 0 | 1 | 0xED   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x0B   Message length (11 bytes).

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 3:

| 0 | d6 | d5 | d4 | 0 | d2 | d1 | d0 | <REPS>   Number of immediate bytes and
                                                                repeat count.

d6	N2. Number of immediate bytes.
d5	N1. Number of immediate bytes.
d4	N0. Number of immediate bytes.
d2	R2. Repeat count.
d1	R1. Repeat count.
d0	R0. Repeat count.

Byte 4:

| 0 | 0 | 1 | d4 | d3 | d2 | d1 | d0 | <DHII>   High bits of IM1 to IM5.

d4	IM5.7. High bit.
d3	IM4.7. High bit.
d2	IM3.7. High bit.
d1	IM2.7. High bit.
d0	IM1.7. High bit.

Byte 5:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<IM1> Data item 1 low 7 bits.

Byte 6:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<IM2> Data item 2 low 7 bits.

Byte 7:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<IM3> Data item 3 low 7 bits.

Byte 8:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<IM4> Data item 4 low 7 bits.

Byte 9:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<IM5> Data item 5 low 7 bits.

Byte 10:

| 0 | n | n | n | n | n | n | n |

<CHK> Checksum.

Response:

Ack.

<LOPC>	<ACK1>	Meaning
0x7D	0x7F	Command OK, if command station.
0x7E	<lim address>	Command OK, if limited master.
0x7D	0x00	Internal buffer busy or full.

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 1 | 1 | 0 | 1 |

0xED

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 |

0x0B

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 3:

| 0 | × | × | × | 0 | × | × | × |

Byte 4:

| 0 | 0 | 1 | × | × | × | × | × |

Notes:

None.

1.5.15   InterfaceData

Description:

This is sent by an interface device in response to a **getInterfaceData** command.

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Response

Applicable Hardware:

Digitrax PR4 and DCS240.

Encoding:

Byte 0:

1	1	1	0	0	1	0	1

0xE5   Opcode.

Byte 1:

0	0	0	1	0	0	0	0

0x10   Message length (16 bytes).

Byte 2:

0	0	1	0	0	0	1	0

0x22

Byte 3:

0	0	1	0	0	0	1	0

0x22

Byte 4:

0	0	0	0	0	0	0	1

0x01

Byte 5:

0	0	0	0	0	0	0	0

0x00

Byte 6:

0	n	n	n	n	n	n	n

<D1>   Serial Number low byte low 7 bits.

Byte 7:

| 0 | n | n | n | n | n | n | n | <D2> | Serial Number high byte low 7 bits. |

Byte 8:

| 0 | n | n | n | n | n | n | n | <D3> | It contains a value but the meaning is unknown. |

Byte 9:

| 0 | n | n | n | n | n | n | n | <D4> | Unknown - set to zero for PR4 and DCS240. |

Byte 10:

| 0 | n | n | n | n | n | n | n | <PXCT2> | Unknown - set to zero for PR4 and DCS240. |

Byte 11:

| 0 | n | n | n | n | n | n | n | <D5> | Maybe hardware version. |

Byte 12:

| 0 | n | n | n | n | n | n | n | <D6> | Software version. |

Byte 13:

| 0 | n | n | n | n | n | n | n | <D7> | Maybe hardware version. |

Byte 14:

| 0 | n | n | n | n | n | n | n | <D8> | Product code. |

Byte 15:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5 |

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10 |

Byte 2:

| 0 | 0 | 1 | 0 | 0 | 0 | 1 | 0 | 0x22

Byte 3:

| 0 | 0 | 1 | 0 | 0 | 0 | 1 | 0 | 0x22

Byte 4:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0x01

Byte 5:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 10:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Notes:

```
PR4 #1

<D0> 0xe5 OPCODE
<D1> 0x10 LENGTH
<D2> 0x22 SRC
<D3> 0x22 DSTL
<D4> 0x01 DSTH
<D5> 0x00 PXCT1 <- I would have expected b4 = 1
<D6> 0x08 Serial Number Low Byte
<D7> 0x07 Serial Number High Byte - Actual serial number 0x0788
<D8> 0x16
<D9> 0x00
<D10> 0x00 PXCT2
<D11> 0x00
<D12> 0x00
<D13> 0x00
<D14> 0x24 Product Code for PR4
<D15> 0x36  CHSUM


PR4 #2

<D0> 0xe5 OPCODE OPC_PEER_XFER
<D1> 0x10 LENGTH
<D2> 0x22 SRC
```

```
<D3> 0x22 DSTL
<D4> 0x01 DSTH
<D5> 0x00 PXCT1
<D6> 0x57 Serial Number Low Byte
<D7> 0x13 Serial Number High Byte - Actual serial number 0x1357
<D8> 0x16
<D9> 0x00
<D10> 0x00 PXCT2
<D11> 0x00
<D12> 0x00
<D13> 0x00
<D14> 0x24 Product Code for PR4
<D15> 0x7d CHKSUM


DCS240

<D0> 0xe5 OPCODE
<D1> 0x10 Length
<D2> 0x22 SRC
<D3> 0x22 DSTL
<D4> 0x01 DSTH
<D5> 0x00 PXCT1 <- I would have expected b4 to be 1
<D6> 0x2b Serial Number Low Byte
<D7> 0x0a  Serial Number High Byte - Actual serial number 0x0aab
<D8> 0x14
<D9> 0x00
<D10> 0x00 PXCT2
<D11> 0x01 Hardware Version?
<D12> 0x03 Software Version
<D13> 0x01 Hardware Version?
<D14> 0x1c Product Code for DCS240
<D15> 0x21
```

1.5.16   IPLDataLoad

Description:

This command loads firmware data into a device that supports IPL. D1 is the lowest addressed byte and D8 is the highest addressed byte.

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10   Message length (16 bytes).

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Broadcast id.

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Broadcast id.

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Broadcast id.

Byte 5:

| 0 | 1 | 0 | 0 | d3 | d2 | d1 | d0 | <PXCT1>   Download code 0x40 and high bits of D1 to D4.

d3   D4.7. High bit
d2   D3.7. High bit
d1   D2.7. High bit
d0   D1.7. High bit

Byte 6:

| 0 | n | n | n | n | n | n | n |

<D1>   Data Byte 1. Low 7 bits.

Byte 7:

| 0 | n | n | n | n | n | n | n |

<D2>   Data Byte 2. Low 7 bits.

Byte 8:

| 0 | n | n | n | n | n | n | n |

<D3>   Data Byte 3. Low 7 bits.

Byte 9:

| 0 | n | n | n | n | n | n | n |

<D4>   Data Byte 4. Low 7 bits.

Byte 10:

| 0 | 0 | 1 | 0 | n | n | n | n |

<PXCT2>   Data type code 0x20 and high bits
              for D5 to D8.

d3   D8.7. High bit
d2   D7.7. High bit
d1   D6.7. High bit
d0   D5.7. High bit

Byte 11:

| 0 | n | n | n | n | n | n | n |

<D5>   Data Byte 5. Low 7 bits.

Byte 12:

| 0 | n | n | n | n | n | n | n |

<D6>   Data Byte 6. Low 7 bits.

Byte 13:

| 0 | n | n | n | n | n | n | n |

<D7>   Data Byte 7. Low 7 bits.

Byte 14:

| 0 | n | n | n | n | n | n | n |

<D8>   Data Byte 8. Low 7 bits.

Byte 15:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 5:

| 0 | 1 | 0 | 0 | × | × | × | × |

Byte 10:

| 0 | 0 | 1 | 0 | × | × | × | × |

Notes:

None.

1.5.17   IPLDevData

Description:

An IPL capable device sends this response in response to an **IPLDiscover** broadcast message.

*** THIS NEEDS CHECKING ***

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Response

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 0x14   Message length (20 bytes).

Byte 2:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 1 | 0x0F

Byte 3:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10

Byte 4:

| 0 | 0 | 0 | 0 | d3 | d2 | d1 | d0 | <PXCT1>

d3	D4.7. High bit
d2	D3.7. High bit
d1	D2.7. High bit
d0	D1.7. High bit

Byte 5:

| 0 | n | n | n | n | n | n | n | <D1>   Product code low 7 bits.

Product Code	Device
0x01	LNRP
0x04	UT4
0x0C	WTL12
0x14	DB210 Opto
0x15	DB210
0x16	DB220
0x1A	DCS210+
0x1B	DCS210
0x1C	DCS240
0x23	PR3
0x24	PR4
0x2A	DT402
0x32	DT500
0x33	DCS51
0x34	DCS52
0x3E	DT602
0x51	BXPA1
0x58	BXP88
0x5C	UR92
0x63	LNWI

Byte 6:

0	n	n	n	n	n	n	n

<D2>   Hardware version 2 low 7 bits.

D2	Meaning
0x00	Slave all
0x18	Slave RF24

Byte 7:

0	n	n	n	n	n	n	n

<D3>   Data item 3. Low 7 bits.

Byte 8:

0	d6	d5	d4	d3	d2	d1	d0

<D4>   Software Version Number low 7 bits.

d6	version number bit 3
d5	version number bit 2.
d4	version number bit 1
d3	version number bit 0
d2	subversion number bit 2
d1	subversion number bit 1
d0	subversion number bit 0

e.g. 0x09 decodes as version 1.1.

Byte 9:

| 0 | 0 | 0 | 0 | d3 | d2 | d1 | d0 | <PXCT2>   High bits of D5 to D8.

d3	D8.7. High bit
d2	D7.7. High bit
d1	D6.7. High bit
d0	D5.7. High bit

Byte 10:

| 0 | n | n | n | n | n | n | n | <D5>   Data item 5. Low 7 bits.

Byte 11:

| 0 | n | n | n | n | n | n | n | <D6>   Serial number low byte low 7 bits.

Byte 12:

| 0 | n | n | n | n | n | n | n | <D7>   Serial number high byte low 7 bits.

Byte 13:

| 0 | n | n | n | n | n | n | n | <D8>   Data item 8. Low 7 bits.

Byte 14:

| 0 | 0 | 0 | 0 | n | n | n | n | <PXCT3>   High bits for D9 to D12.

d3	D12.7. High bit
d2	D11.7. High bit
d1	D10.7. High bit
d0	D9.7. High bit

Byte 15:

| 0 | n | n | n | n | n | n | n | <D9>   Data item 9. Low 7 bits.

Byte 16:

| 0 | n | n | n | n | n | n | n | <D10> | Data item 10. Low 7 bits. |

Byte 17:

| 0 | n | n | n | n | n | n | n | <D11> | Data item 11. Low 7 bits. |

Byte 18:

| 0 | n | n | n | n | n | n | n | <D12> | Data item 8. Low 12 bits. |

Byte 19:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Notes:

These came from DigiPLII:

e5 14 0f 08 00 00 00 00 00 00 00 01 00 00 00 00 00 00 00 08

e5 14 0f 10 00 24 00 00 00 02 00 08 07 00 00 00 00 00 00 38

e5 14 0f 10 00 24 00 00 00 00 00 57 13 00 00 00 00 00 00 71

e5 14 0f 10 00 1b 00 00 03 02 00 54 10 00 00 00 00 00 00 4f

PR4 with serial number 0x0788 ver 0

PR4 with serial 0x1357 ver 0

DCS210 with SN 0x10D4 ver 0.3

DCS240 with SN 0x0AAB ver 0.3

1.5.18 IPLDiscover

Description:

This broadcast message requests IPL capable devices to report their IPL information. The devices each respond with a **IPLDevData** response.

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Broadcast

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5 | Opcode. |

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 0x14 | Message length (20 bytes). |

Byte 2:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 1 | 0x0F |

Byte 3:

| 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0x08 |

Byte 4:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 5:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 6:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 7:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 8:

0	0	0	0	0	0	0	0

0x00

Byte 9:

0	0	0	0	0	0	0	0

0x00

Byte 10:

0	0	0	0	0	0	0	0

0x00

Byte 11:

0	0	0	0	0	0	0	1

0x01

Byte 12:

0	0	0	0	0	0	0	0

0x00

Byte 13:

0	0	0	0	0	0	0	0

0x00

Byte 14:

0	0	0	0	0	0	0	0

0x00

Byte 15:

0	0	0	0	0	0	0	0

0x00

Byte 16:

0	0	0	0	0	0	0	0

0x00

Byte 17:

0	0	0	0	0	0	0	0

0x00

Byte 18:

0	0	0	0	0	0	0	0

0x00

Byte 19:

0	n	n	n	n	n	n	n

<CHK>   Checksum.

Response:

IPLDevData

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 0x14

Byte 2:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 1 | 0x0F

Byte 3:

| 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0x08

Byte 4:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 5:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 6:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 7:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 8:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 9:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 10:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 11:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0x01

Byte 12:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 13:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 14:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 15:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 16:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 17:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 18:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

<u>Notes:</u>

None.

1.5.19   IPLEndLoad

Description:

This command ends a device firmware update.

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 |

0xE5   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 |

0x10   Message length (16 bytes).

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F   Broadcast id.

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F   Broadcast id.

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F   Broadcast id.

Byte 5:

| 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0 |

0x40   Download code.

Byte 6:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |

0x00

Byte 7:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |

0x00

Byte 8:

0	0	0	0	0	0	0	0	0x00

Byte 9:

0	0	0	0	0	0	0	0	0x00

Byte 10:

0	1	0	0	n	n	n	n	0x40	End load type code.

Byte 11:

0	0	0	0	0	0	0	0	0x00

Byte 12:

0	0	0	0	0	0	0	0	0x00

Byte 13:

0	0	0	0	0	0	0	0	0x00

Byte 14:

0	0	0	0	0	0	0	0	0x00

Byte 15:

0	n	n	n	n	n	n	n	<CHK>	Checksum.

Response:

None

Signature:

Byte 0:

1	1	1	0	0	1	0	1	0xE5

Byte 1:

0	0	0	1	0	0	0	0	0x10

Byte 2:

0	1	1	1	1	1	1	1	0x7F

Byte 3:

0	1	1	1	1	1	1	1	0x7F

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 5:

| 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | 0x40

Byte 6:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 7:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 8:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 9:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 10:

| 0 | 1 | 0 | 0 | n | n | n | n | 0x40

Byte 11:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 12:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 13:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 14:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Notes:

None.

1.5.20   IPLSetAddr

Description:

This command sets the address of where to load the next block of firmware data.

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 |

0xE5   OPC_PEER_XFER opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 |

0x10   Message length (16 bytes).

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F   Broadcast id.

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F   Broadcast id.

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 |

0x7F   Broadcast id.

Byte 5:

| 0 | 1 | 0 | 0 | d3 | d2 | d1 | d0 |

<PXCT1>   Download code 0x40 and high bits
               of D1 to D4.

d3	D4.7. High bit
d2	D3.7. High bit
d1	D2.7. High bit
d0	D1.7. High bit

Byte 6:

| 0 | n | n | n | n | n | n | n | <D1> | Address High Byte. Low 7 bits. |

Byte 7:

| 0 | n | n | n | n | n | n | n | <D2> | Address Mid Byte. Low 7 bits. |

Byte 8:

| 0 | n | n | n | n | n | n | n | <D3> | Address Low Byte. Low 7 bits. |

Byte 9:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | <D4> | Reserved always 0x00. Low 7 bits. |

Byte 10:

| 0 | 0 | 0 | 1 | n | n | n | n | <PXCT2> | Address type code 0x10 and high bits for D5 to D8. |

d3   D8.7. High bit
d2   D7.7. High bit
d1   D6.7. High bit
d0   D5.7. High bit

Byte 11:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | <D5> | Reserved always 0x00. Low 7 bits. |

Byte 12:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | <D6> | Reserved always 0x00. Low 7 bits. |

Byte 13:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | <D7> | Reserved always 0x00. Low 7 bits. |

Byte 14:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | <D8> | Reserved always 0x00. Low 7 bits. |

Byte 15:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5 |

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10 |

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F |

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F |

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F |

Byte 5:

| 0 | 1 | 0 | 0 | $\times$ | $\times$ | $\times$ | $\times$ |

Byte 9:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 10:

| 0 | 0 | 0 | 1 | $\times$ | $\times$ | $\times$ | $\times$ |

Byte 11:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 12:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 13:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

Byte 14:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00 |

<u>Notes:</u>

None.

1.5.21   IPLSetupBL2

Description:

This command initiates a firmware update for a device that supports IPL Bootloader 2
protocol.

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10   Message length (16 bytes).

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Broadcast id.

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Broadcast id.

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F   Broadcast id.

Byte 5:

| 0 | 1 | 0 | 0 | d3 | d2 | d1 | d0 | <PXCT1>   Download code 0x40 and high bits
                                                      of D1 to D4.

d3	D4.7. High bit
d2	D3.7. High bit
d1	D2.7. High bit
d0	D1.7. High bit

Byte 6:

| 0 | n | n | n | n | n | n | n | `<D1>` | Manufacturer code. Low 7 bits. |

<u>Code</u>   <u>Manufacturer</u>
0x00   Digitrax

Byte 7:

| 0 | n | n | n | n | n | n | n | `<D2>` | Product code. Low 7 bits. |

Byte 8:

| 0 | n | n | n | n | n | n | n | `<D3>` | Hardware version. Low 7 bits. |

Byte 9:

| 0 | n | n | n | n | n | n | n | `<D4>` | Software version. Low 7 bits. |

Byte 10:

| 0 | 0 | 0 | 0 | n | n | n | n | `<PXCT2>` | Setup download type code 0x00 and high bits for D5 to D8. |

d3   D8.7. High bit
d2   D7.7. High bit
d1   D6.7. High bit
d0   D5.7. High bit

Byte 11:

| 0 | n | n | n | n | n | n | n | `<D5>` | Options. Low 7 bits. |

Byte 12:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | `<D6>` | Reserved always 0x00. Low 7 bits. |

Byte 13:

| 0 | n | n | n | n | n | n | n | `<D7>` | Number of blocks to erase 7. Low 7 bits. |

This is calculated as INT(0.5 + (Last Address - First Address) / Erase Blk Size).

Byte 14:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | `<D8>` | Reserved always 0x00. Low 7 bits. |

Byte 15:

| 0 | n | n | n | n | n | n | n | `<CHK>` | Checksum. |

Response:

None

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 3:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 4:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 0x7F

Byte 5:

| 0 | 1 | 0 | 0 | d3 | × | × | × |

Byte 10:

| 0 | 0 | 0 | 0 | × | × | × | × |

Byte 12:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Byte 14:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0x00

Notes:

None.

1.5.22   LinkSlotsP1

Description:

This command links slot SL1 to slot SL2. The command station sets SL_CONUP/DN flags appropriately. If the command was successful then a **LocoSlotDataP1** response will be returned. An invalid link will return a **Ack** with a response code of 0x00.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_LINK_SLOTS

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 0 | 1 | 0xB9 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SL1> | Slot number in the range 0x01 to 0x77. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SL2> | Slot number in the range 0x01 to 0x77. |

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

LocoSlotDataP1

or

Ack

<LOPC>	<ACK1>	Meaning
0x39	0x00	Invalid link, link failed.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 0 | 1 | 0xB9

Byte 1:

| 0 | n | n | n | n | n | n | n | in the range 0x01 to 0x77.

Byte 2:

| 0 | n | n | n | n | n | n | n | in the range 0x01 to 0x77.

Notes:

None.

1.5.23 LinkSlotsP2

Description:

This command links slot SL1 to slot SL2. The command station sets SL_CONUP/DN flags appropriately. If the command was successful then a **LocoSlotDataP2** response will be returned. An invalid link will return a **Ack** with a response code of 0x00.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial Mnemonic)

Type:

Command

Encoding:

Byte 0:

1	1	0	1	0	1	0	0	0xD4	Opcode.

Byte 1:

0	0	1	1	1	d2	d1	d0	<SL1P>	Bits d2 to d0 contain the SL1 slot page number in the range 0x0 to 0x7.

Byte 2:

0	n	n	n	n	n	n	n	<SL1#>	Slot number SL1 in the range 0x00 to 0x77.

Byte 3:

0	1	0	0	0	d2	d1	d0	<SL2P>	Bits d2 to d0 contain the SL2 slot page number in the range 0x0 to 0x7.

Byte 4:

0	n	n	n	n	n	n	n	<SL2#>	Slot number SL2 in the range 0x00 to 0x77.

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

LocoSlotDataP2 or **Ack**.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 1 | 1 | × | × | × |

Byte 2:

| 0 | n | n | n | n | n | n | n | less than 0x78

Byte 3:

| 0 | 1 | 0 | 0 | 0 | × | × | × |

Byte 4:

| 0 | n | n | n | n | n | n | n | less than 0x78

Notes:

None.

1.5.24 LocoBinStateP2

Description:

This command sets the locomotive's binary states with addresses in the range 1 to 32767. The address of 0 is a broadcast command and will set or reset all binary states.

Protocol:

2?

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4 | Opcode. |

Byte 1:

| 0 | 0 | 0 | d4 | d3 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. The bit d4 contains the function state where 1 means on and 0 means off. The bit d3 contains the high bit of the binary state address (bit 14). |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number. |

Byte 3:

| 0 | n | n | n | n | n | n | n | <BSA0> | Binary state address bits 0 to 6. |

Byte 4:

| 0 | n | n | n | n | n | n | n | <BSA1> | Binary state address bits 7 to 13. |

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 |

0xD4

Byte 1:

| 0 | 0 | 0 | × | × | × | × | × |

Notes:

*** THIS HAS NOT BEEN TESTED ***

1.5.25 LocoDirF0F4P1

Description:

This function sets the locomotive's direction and function F0 to F4 states.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_LOCO_DIRF

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 0 | 0 | 0 | 0 | 1 | 0xA1 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 2:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 | <DIRF> | Locomotive's direction and state of functions F0 to F4. |

d5	Direction: 1 means forward and 0 means backwards.
d4	F0 state: 1 means on and 0 means off.
d3	F4 state: 1 means on and 0 means off.
d2	F3 state: 1 means on and 0 means off.
d1	F2 state: 1 means on and 0 means off.
d0	F1 state: 1 means on and 0 means off.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 0 | 0 | 0 | 0 | 1 | 0xA1

Byte 1:

| 0 | n | n | n | n | n | n | n | less than 0x78

Byte 2:

| 0 | 0 | × | × | × | × | × | × |

Notes:

None.

1.5.26 LocoDirF0F4P2

Description:

This command sets the locomotive's direction and function F0 to F4 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4 | Opcode. |

Byte 1:

| 0 | 0 | 1 | 0 | 0 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number. |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 1 | 0 | 0x06 | Subcode. |

Byte 4:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 | | Direction and function states. |

d5   Direction: 1 means forward and 0 means backwards.
d4   F0 state: 1 means on and 0 means off.
d3   F4 state: 1 means on and 0 means off.
d2   F3 state: 1 means on and 0 means off.
d1   F2 state: 1 means on and 0 means off.
d0   F1 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 0 | 0 | × | × | × |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 1 | 0 | 0x06

Byte 4:

| 0 | 0 | × | × | × | × | × | × |

Notes:

None.

1.5.27 LocoF0F6P2

Description:

This command sets the locomotive's function F0 to F6 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D5_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | 0xD5 | Opcode. |

Byte 1:

| 0 | 0 | 0 | 1 | 0 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 | 0x6D | Subcode. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | | Function states. |

d6   F6 state: 1 means on and 0 means off.

d5   F5 state: 1 means on and 0 means off.

d4   F0 state: 1 means on and 0 means off.

d3   F4 state: 1 means on and 0 means off.

d2   F3 state: 1 means on and 0 means off.

d1   F2 state: 1 means on and 0 means off.

d0   F1 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | 0xD5

Byte 1:

| 0 | 0 | 0 | 1 | 0 | × | × | × |

Byte 2:

| 0 | n | n | n | n | n | n | n | less than 0x78

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 | 0x6D

Notes:

None.

1.5.28 LocoF5F8P1

Description:

This command sets the locomotive's function F5 to F8 states.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_LOCO_SND

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 0 | 0 | 0 | 1 | 0 | 0xA2 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 2:

| 0 | 0 | 0 | 0 | d3 | d2 | d1 | d0 | <SND> | Locomotive's function F5 to F8 states. |

d3	F8 state: 1 means on and 0 means off.
d2	F7 state: 1 means on and 0 means off.
d1	F6 state: 1 means on and 0 means off.
d0	F5 state: 1 means on and 0 means off.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Signature:

Byte 0:

1	0	1	0	0	0	1	0

0xA2

Byte 1:

0	n	n	n	n	n	n	n

less than 0x78

Byte 2:

0	0	0	0	×	×	×	×

Notes:

None.

1.5.29   LocoF7F13P2

<u>Description:</u>

This command sets the locomotive's function F7 to F13 states.

<u>Protocol:</u>

2

<u>Group:</u>

6-Byte Message

<u>Opcode:</u>

OPC_D5_GROUP (Unofficial mnemonic)

<u>Type:</u>

Command

<u>Encoding:</u>

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | 0xD5 | Opcode. |

Byte 1:

| 0 | 0 | 0 | 1 | 1 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 | 0x6D | Subcode. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | | Function states. |

d6   F13 state: 1 means on and 0 means off.
d5   F12 state: 1 means on and 0 means off.
d4   F11 state: 1 means on and 0 means off.
d3   F10 state: 1 means on and 0 means off.
d2   F9 state: 1 means on and 0 means off.
d1   F8 state: 1 means on and 0 means off.
d0   F7 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 |

0xD5

Byte 1:

| 0 | 0 | 0 | 1 | 1 | × | × | × |

Byte 2:

| 0 | n | n | n | n | n | n | n |

less than 0x78

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 |

0x6D

Notes:

None.

1.5.30 LocoF5F11P2

Description:

This command sets the locomotive's function F5 to F11 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4 | Opcode. |

Byte 1:

| 0 | 0 | 1 | 0 | 0 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number. |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0x07 | Subcode. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | | Function states. |

d6   F11 state: 1 means on and 0 means off.
d5   F10 state: 1 means on and 0 means off.
d4   F9 state: 1 means on and 0 means off.
d3   F8 state: 1 means on and 0 means off.
d2   F7 state: 1 means on and 0 means off.
d1   F6 state: 1 means on and 0 means off.
d0   F5 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 0 | 0 | × | × | × |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0x07

Notes:

None.

1.5.31   LocoF12F20F28P2

Description:

This command sets the locomotive's function F12, F20, and F28 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 |

0xD4   Opcode.

Byte 1:

| 0 | 0 | 1 | 0 | 0 | d2 | d1 | d0 |

<SLOTP>   Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7.

Byte 2:

| 0 | n | n | n | n | n | n | n |

<SLOT#>   Slot number.

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 0 | 1 |

0x05   Subcode.

Byte 4:

| 0 | 0 | 0 | 0 | 0 | d2 | d1 | d0 |

Function states.

d2   F28 state: 1 means on and 0 means off.
d1   F20 state: 1 means on and 0 means off.
d0   F12 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 0 | 0 | × | × | × |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 0 | 1 | 0x05

Byte 4:

| 0 | 0 | 0 | 0 | 0 | × | × | × |

Notes:

None.

1.5.32   LocoF13F19P2

Description:

This command sets the locomotive's function F13 to F19 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4 | Opcode. |

Byte 1:

| 0 | 0 | 1 | 0 | 0 | d2 | d1 | d0 | \<SLOTP\> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | \<SLOT#\> | Slot number. |

Byte 3:

| 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0x08 | Subcode. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | | Function states. |

d6   F19 state: 1 means on and 0 means off.
d5   F18 state: 1 means on and 0 means off.
d4   F17 state: 1 means on and 0 means off.
d3   F16 state: 1 means on and 0 means off.
d2   F15 state: 1 means on and 0 means off.
d1   F14 state: 1 means on and 0 means off.
d0   F13 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 |

0xD4

Byte 1:

| 0 | 0 | 1 | 0 | 0 | × | × | × |

Byte 3:

| 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0 |

0x08

Notes:

None.

1.5.33 LocoF14F20P2

Description:

This command sets the locomotive's function F14 to F20 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D5_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | 0xD5 | Opcode. |

Byte 1:

| 0 | 0 | 1 | 0 | 0 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 | 0x6D | Subcode. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | | Function states. |

d6	F20 state: 1 means on and 0 means off.
d5	F19 state: 1 means on and 0 means off.
d4	F18 state: 1 means on and 0 means off.
d3	F17 state: 1 means on and 0 means off.
d2	F16 state: 1 means on and 0 means off.
d1	F15 state: 1 means on and 0 means off.
d0	F14 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 |

0xD5

Byte 1:

| 0 | 0 | 1 | 0 | 0 | × | × | × |

Byte 2:

| 0 | n | n | n | n | n | n | n |

less than 0x78

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 |

0x6D

Notes:

None.

1.5.34 LocoF21F27P2

Description:

This command sets the locomotive's function F21 to F27 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

1	1	0	1	0	1	0	0	0xD4	Opcode.

Byte 1:

0	0	1	0	0	d2	d1	d0	<SLOTP>	Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7.

Byte 2:

0	n	n	n	n	n	n	n	<SLOT#>	Slot number.

Byte 3:

0	0	0	0	0	1	0	1	0x09	Subcode.

Byte 4:

0	d6	d5	d4	d3	d2	d1	d0		Function states.

d6   F27 state: 1 means on and 0 means off.
d5   F26 state: 1 means on and 0 means off.
d4   F25 state: 1 means on and 0 means off.
d3   F24 state: 1 means on and 0 means off.
d2   F23 state: 1 means on and 0 means off.
d1   F22 state: 1 means on and 0 means off.
d0   F21 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n | \<CHK\>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 0 | 0 | $\times$ | $\times$ | $\times$ |

Byte 3:

| 0 | 0 | 0 | 0 | 1 | 0 | 0 | 1 | 0x09

Notes:

None.

1.5.35 LocoF21F28P2

Description:

This command sets the locomotive's function F21 to F28 states.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D5_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 | 0xD5 | Opcode. |

Byte 1:

| 0 | 0 | 1 | d4 | d3 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. d4 and d3 encode the F28 state where 0b10 means on and 0b01 means off. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 | 0x6D | Subcode. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | | Function states. |

d6   F27 state: 1 means on and 0 means off.
d5   F26 state: 1 means on and 0 means off.
d4   F25 state: 1 means on and 0 means off.
d3   F24 state: 1 means on and 0 means off.
d2   F23 state: 1 means on and 0 means off.
d1   F22 state: 1 means on and 0 means off.
d0   F21 state: 1 means on and 0 means off.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 |

0xD5

Byte 1:

| 0 | 0 | 1 | d4 | d3 | × | × | × |

d4 and d3 can be 0b10 or 0b01

Byte 2:

| 0 | n | n | n | n | n | n | n |

less than 0x78

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 |

0x6D

Notes:

None.

1.5.36   LocoSlotDataP1

Description:

This response provides the data for a specific locomotive slot.

Protocol:

1

Group:

Variable-Byte Message

Opcode:

OPC_SL_RD_DATA

Type:

Response

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 1 | 0xE7   Opcode.

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 | 0x0E   Message length (14 bytes).

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#>   Slot number in the range 0x00 to 0x77. Slot 0x00 is the dispatch special slot.

Byte 3:

| d7 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <STAT1>   Slot status 1.

d7	d6	
0	0	Free, no consist linking.
0	1	Consist sub-member.
1	0	Consist top-member.
1	1	Consist Mid-Consist member.

Note: d7 is set to 0 in the message by the command station and so may not correctly reflect the actual setting in the slot table.

d5	d4	
0	0	Free slot, no valid data. Not refreshed.
0	1	Common. Locomotive address in this slot. Refreshed.
1	0	Idle. Locomotive address in this slot. Not refreshed.
1	1	In Use. Locomotive address in this slot. Refreshed.

d3	
0	No slot consist linked into this slot.
1	Slot consist linked into this slot.

d2	d1	d0	
0	0	0	28 step decoder. 3-byte packet regular mode
0	0	1	28 step decoder. Generate trinary packets for this mobile address
0	1	0	14 step decoder.
0	1	1	128 step decoder.
1	0	0	28 step decoder. Allow advanced consisting
1	0	1	reserved
1	1	0	reserved
1	1	1	128 step decoder. Allow advanced consisting

Byte 4:

| 0 | n | n | n | n | n | n | n |

<ADR>   If <ADR2> is 0 then this contains the NMRA short address. If <ADR2> is greater than 0 then this contains the low 7 bits of the NMRA long address.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<SPD>   Speed in the range 0x00 to 0x7F. 0x00 means inertial stop and 0x01 means emergency stop. Other values mean increasing speed.

Byte 6:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 |

<DIRF>   Locomotive direction and state of functions F0 to F4.

d5   Direction: 1 means forward and 0 means backwards.
d4   F0 state: 1 means on and 0 means off.
d3   F4 state: 1 means on and 0 means off.
d2   F3 state: 1 means on and 0 means off.
d1   F2 state: 1 means on and 0 means off.
d0   F1 state: 1 means on and 0 means off.

Byte 7:

| 0 | d6 | 0 | 0 | d3 | d2 | d1 | d0 |

<TRK>   Global system track status.

d6   1 means this command station implements protocol 2 messages. This can be turned off on the DCS240 by setting the OpSw 44 to be closed.
d3   1 means the programming track is busy.
d2   1 means this command station implements protocol 1 messages and 0 means the command station is a DT200.
d1   0 means the track is paused, broadcast an emergency stop.
d0   1 means the DCC packets are on in the command station and the track power is on.

Byte 8:

| 0 | 0 | 0 | 0 | d3 | d2 | 0 | d0 |

<SS2>   Slot status 2.

d3   1 means expansion in ID1/2, 0 means encoded alias.
d2   1 means expansion ID1/2 is not ID usage.
d0   1 means this slot has suppressed advanced consist.

Byte 9:

| 0 | n | n | n | n | n | n | n |

<ADR2>   If <ADR2> is greater than 0 then this contains the high 7 bits of the NMRA long address.

Byte 10:

| 0 | 0 | 0 | 0 | d3 | d2 | d1 | d0 |

<SND>   Function F5 to F8 states.

d3   F8 state: 1 means on and 0 means off.
d2   F7 state: 1 means on and 0 means off.
d1   F6 state: 1 means on and 0 means off.
d0   F5 state: 1 means on and 0 means off.

Byte 11:

| 0 | n | n | n | n | n | n | n |

<ID1>   7-bit ls ID code written by throttle when STAT2.4 = 1.

Byte 12:

| 0 | n | n | n | n | n | n | n |

       <ID2>   7-bit ms ID code written by throttle when STAT2.4 = 1.

Byte 13:

| 0 | n | n | n | n | n | n | n |

       <CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 1 |

       0xE7

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 |

       0x0E

Byte 2:

| 0 | n | n | n | n | n | n | n |

       less than 0x78.

Byte 6:

| 0 | 0 | × | × | × | × | × | × |

Byte 7:

| 0 | × | 0 | 0 | × | × | × | × |

Byte 8:

| 0 | 0 | 0 | 0 | × | × | 0 | × |

Byte 10:

| 0 | 0 | 0 | 0 | × | × | × | × |

Notes:

None.

1.5.37   LocoSlotDataP2

Description:

This response provides data for a specific locomotive slot.

Protocol:

2

Group:

Variable-Byte Message

Opcode:

OPC_SL_RD_DATA_P2 (Unofficial mnemonic)

Type:

Response

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 0 | 0xE6 | Opcode. |

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 1 | 0x15 | Message length (21 bytes). |

Byte 2:

| 0 | 0 | 0 | 0 | 0 | d2 | d1 | d0 | <SLOTP#> | Slot page number in the range 0x0 to 0x7. |

Byte 3:

| 0 | n | n | n | n | n | n | n | <SLOTL#> | Slot number in the range 0x00 to 0x77. |

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <STAT1> | Slot status 1. |

d7	d6	
0	0	Free, no consist linking.
0	1	Consist sub-member.
1	0	Consist top-member.
1	1	Consist Mid-Consist member.

Note: d7 is set to 0 in the message by the command station and so may not correctly reflect the actual setting in the slot table.

d5	d4	
0	0	Free slot, no valid data. Not refreshed.
0	1	Common. Locomotive address in this slot. Refreshed.
1	0	Idle. Locomotive address in this slot. Not refreshed.
1	1	In Use. Locomotive address in this slot. Refreshed.

d3	
0	No slot consist linked into this slot.
1	Slot consist linked into this slot.

d2	d1	d0	
0	0	0	28 step decoder. 3-byte packet regular mode
0	0	1	28 step decoder. Generate trinary packets for this mobile address
0	1	0	14 step decoder.
0	1	1	128 step decoder.
1	0	0	28 step decoder. Allow advanced consisting
1	0	1	reserved
1	1	0	reserved
1	1	1	128 step decoder. Allow advanced consisting

Byte 5:

0	n	n	n	n	n	n	n

<ADR>   Low address.

Byte 6:

0	n	n	n	n	n	n	n

<ADR2>   High address.

Byte 7:

0	d6	d5	d4	d3	d2	d1	d0

<TRK>   Global system track status.

d6 1 means this command station implements protocol 2 messages. This can be turned off on the DCS240 by setting the OpSw 44 to be closed.

d5 Reserved. Set to 0.

d4 Reserved. Set to 0.

d3 1 means the programming track is busy.

d2 1 means this command station implements protocol 1 messages. 0 means the command station is a DT200.

d1 0 means the track is paused, broadcast an emergency stop.

d0 1 means the DCC packets are on in the command station and track power is on.

Byte 8:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <SPD>   Speed in the range 0x00 to 0x7F. 0x00 means inertial stop and 0x01 means emergency stop. Other values mean increasing speed.

Byte 9:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Functions.

d6 F8 state: 1 means on and 0 means off

d5 F0 state: 1 means on and 0 means off

d4 F12 state: 1 means on and 0 means off

d3

d2

d1 F20 state: 1 means on and 0 means off

d0

Byte 10:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Direction.

d6

d5 Direction: 1 means forwards and 0 means backwards

d4

d3

d2

d1

d0

Byte 11:

0	d6	d5	d4	d3	d2	d1	d0

Functions.

d6   F11 state: 1 means on and 0 means off
d5   F10 state: 1 means on and 0 means off
d4   F9 state: 1 means on and 0 means off
d3
d2
d1
d0

Byte 12:

0	d6	d5	d4	d3	d2	d1	d0

Functions.

d6   F19 state: 1 means on and 0 means off
d5   F18 state: 1 means on and 0 means off
d4   F17 state: 1 means on and 0 means off
d3   F16 state: 1 means on and 0 means off
d2   F15 state: 1 means on and 0 means off
d1   F14 state: 1 means on and 0 means off
d0   F13 state: 1 means on and 0 means off

Byte 13:

0	d6	d5	d4	d3	d2	d1	d0

Functions.

d6   F7 state: 1 means on and 0 means off
d5   F6 state: 1 means on and 0 means off
d4   F5 state: 1 means on and 0 means off
d3   F4 state: 1 means on and 0 means off
d2   F3 state: 1 means on and 0 means off
d1   F2 state: 1 means on and 0 means off
d0   F1 state: 1 means on and 0 means off

Byte 14:

0	d6	d5	d4	d3	d2	d1	d0

Unknown.

d6
d5
d4
d3
d2
d1
d0

Byte 15:

0	d6	d5	d4	d3	d2	d1	d0

Unknown.

d6
d5
d4
d3
d2
d1
d0

Byte 16:

0	d6	d5	d4	d3	d2	d1	d0

Consist slot page number.

d6
d5
d4
d3
d2   Consist slot page b2
d1   Consist slot page b1
d0   Consist slot page b0

Byte 17:

0	n	n	n	n	n	n	n

Consist slot number in the range 0x00 to 0x77.

Byte 18:

0	d6	d5	d4	d3	d2	d1	d0

Throttle id low bits.

Byte 19:

0	d6	d5	d4	d3	d2	d1	d0

Throttle id high bits.

Byte 20:

0	n	n	n	n	n	n	n

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 0 | 0xE6

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 1 | 0x15

Byte 2:

| 0 | 0 | 0 | 0 | 0 | × | × | × |

Byte 7:

| 0 | × | 0 | 0 | × | × | × | × |

Notes:

None.

1.5.38 LocoSpdP1

Description:

This command sets the locomotive's speed in the range 0 to 127. 0 means inertial stop and 1 means emergency stop. Other values mean increasing speed.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_LOCO_SPD

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0xA0 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SPD> | Locomotive speed in the range 0 to 127. |

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0xA0 |

Byte 1:

| 0 | n | n | n | n | n | n | n | less than 0x78

<u>Notes:</u>

None.

1.5.39 LocoSpdP2

*** THIS WAS SENT BY iTrain NEEDS TESTING ***

Description:

This function sets the locomotive's speed in the range 0 to 127. 0 means inertial stop and 1 means emergency stop. Other values mean increasing speed.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4 | Opcode. |

Byte 1:

| 0 | 0 | 1 | 0 | 0 | d2 | d1 | d0 | <SLOTP> | Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#> | Slot number in the range 0x00 to 0x77. |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0x04 | Subcode. |

Byte 4:

| 0 | n | n | n | n | n | n | n | <SPD> | Locomotive speed in the range 0x00 to 0x7F. |

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 0 | 0 | × | × | × |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | 0x04

Notes:

None.

1.5.40   LocoSpdDirP2

Description:

This function sets the locomotive's speed in the range 0 to 127 and direction. 0 means inertial stop and 1 means emergency stop. Other values mean increasing speed.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D5_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

1	1	0	1	0	1	0	1

0xD5   Opcode.

Byte 1:

0	0	0	0	d3	d2	d1	d0

<SLOTP>   Bits d2 to d0 contain the slot page number in the range 0x0 to 0x7. Bit d3 contains the direction where 1 means forwards and 0 means backwards.

Byte 2:

0	n	n	n	n	n	n	n

<SLOT#>   Slot number in the range 0x00 to 0x77.

Byte 3:

0	1	1	0	1	1	0	1

0x6D   Subcode.

Byte 4:

0	n	n	n	n	n	n	n

<SPD>   Locomotive speed in the range 0x00 to 0x7F.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 1 |

0xD5

Byte 1:

| 0 | 0 | 0 | 0 | × | × | × | × |

Byte 2:

| 0 | n | n | n | n | n | n | n |

less than 0x78

Byte 3:

| 0 | 1 | 1 | 0 | 1 | 1 | 0 | 1 |

0x6D

Notes:

None.

1.5.41 MoveSlotsP1

<u>Description:</u>

Move slots.

SRC	DEST	Action
0	×	Dispatch get. Return **LocoSlotDataP1** of dispatch slot.
SRC	0	Dispatch put. Mark slot as dispatch.
SRC	SRC	Null move. SRC is set to in use.
SRC	DEST	Move slot data from SRC to DEST if not in use. Clear SRC.

<u>Protocol:</u>

1

<u>Group:</u>

4-Byte Message

<u>Opcode:</u>

OPC_MOVE_SLOTS

<u>Type:</u>

Command

<u>Encoding:</u>

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 0 | 0xBA Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n | <SRC> Source slot number in the range 0x00 to 0x77.

Byte 2:

| 0 | n | n | n | n | n | n | n | <DEST> Destination slot number in the range 0x00 to 0x77.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> Checksum.

<u>Response:</u>

LocoSlotDataP1

or

Ack.

<LOPC>	<ACK1>	Meaning
0x3A	0x00	Illegal move.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 1 | 0 | 0xBA

Byte 1:

| 0 | n | n | n | n | n | n | n | less than 0x78

Byte 2:

| 0 | n | n | n | n | n | n | n | less than 0x78

Notes:

None.

1.5.42   MoveSlotsP2

Description:

Move slots.

SRC	DEST	Action
0	×	Dispatch get. Return **LocoSlotDataP2** of dispatch slot.
SRC	0	Dispatch put. Mark slot as dispatch.
SRC	SRC	Null move. SRC is set to in use.
SRC	DEST	Move slot data from SRC to DEST if not in use. Clear SRC.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial Mnemonic)

Type:

Command

Encoding:

Byte 0:

1	1	0	1	0	1	0	0	0xD4	Opcode.

Byte 1:

0	0	1	1	1	d2	d1	d0	<SRCP>	Bits d2 to d0 contain the source slot page number in the range 0x0 to 0x7.

Byte 2:

0	n	n	n	n	n	n	n	<SRC>	Source slot number.

Byte 3:

0	0	0	0	0	d2	d1	d0	<DESTP>	Bits d2 to d0 contain the destination slot page number in the range 0x0 to 0x7.

Byte 4:

| 0 | n | n | n | n | n | n | n | <DEST>   Destination slot number.

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

LocoSlotDataP2 or **Ack**.

*** NEED TO CONFIRM ERROR CODE ***

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4

Byte 1:

| 0 | 0 | 1 | 1 | 1 | × | × | × |

Byte 3:

| 0 | 0 | 0 | 0 | 0 | × | × | × |

Notes:

None.

1.5.43   PeerXfer16

Description:

This command sends the 8 bytes of data from one device to another peer to peer. This message takes many forms and so what is presented here is a generic description. The specific forms are included elsewhere as detailed messages in their own right.

SRC	DSTL	DSTH	Comments
0x00			Source is command station.
Don't Care	0x00	0x00	Broadcast Message.
0x70 to 0x7E			Reserved.
0x7F	0x00	0x00	Broadcast throttle message transfer.
0x7F	ID1	ID2	Throttle message transfer. ID1 and ID2 encode ID.

Protocol:

1

Group:

Variable-Byte Message

Opcode:

OPC_PEER_XFER

Type:

Message

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 | 0x10   Message length (16 bytes).

Byte 2:

| 0 | n | n | n | n | n | n | n | <SRC>   Source id in the range 0x00 to 0x7F.

Byte 3:

| 0 | n | n | n | n | n | n | n |

     \<DSTL>   Destination id low in the range 0x00 to 0x7F.

Byte 4:

| 0 | n | n | n | n | n | n | n |

     \<DSTH>   Destination id high in the range 0x00 to 0x7F.

Byte 5:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

     \<PXCT1>   Address type code and high bits of D1 to D4.

d6	XC2. Address type code.
d5	XC1. Address type code.
d4	XC0. Address type code.
d3	D4.7. High bit
d2	D3.7. High bit
d1	D2.7. High bit
d0	D1.7. High bit

XC2	XC1	XC0	Meaning
0	0	0	7 bit peer to peer addresses.
0	0	1	reserved.
0	1	0	reserved.
0	1	1	reserved.
1	0	0	IPL download.
1	0	1	reserved.
1	1	0	reserved.
1	1	1	reserved.

Byte 6:

| 0 | n | n | n | n | n | n | n |

     \<D1>   Data item 1. Low 7 bits.

Byte 7:

| 0 | n | n | n | n | n | n | n |

     \<D2>   Data item 2. Low 7 bits.

Byte 8:

| 0 | n | n | n | n | n | n | n |

     \<D3>   Data item 3. Low 7 bits.

Byte 9:

| 0 | n | n | n | n | n | n | n |

     \<D4>   Data item 4. Low 7 bits.

Byte 10:

0	n	n	n	n	n	n	n

<PXCT2>   Data type code and high bits for D5 to D8.

d6   XC5. Data type code.
d5   XC4. Data type code.
d4   XC3. Data type code.
d3   D8.7. High bit
d2   D7.7. High bit
d1   D6.7. High bit
d0   D5.7. High bit

XC5	XC4	XC3	Meaning
0	0	0	ANSI text string. IPL download setup subcode.
0	0	1	IPL download address subcode.
0	1	0	IPL download send data subcode.
0	1	1	IPL download verify data subcode.
1	0	0	IPL download end of operation subcode.
1	0	1	reserved.
1	1	0	reserved.
1	1	1	reserved.

Options flags

```
private static final int DO_NOT_CHECK_SOFTWARE_VERSION = 0x00;
    private static final int CHECK_SOFTWARE_VERSION_LESS = 0x04;

    private static final int DO_NOT_CHECK_HARDWARE_VERSION = 0x00;
    private static final int REQUIRE_HARDWARE_VERSION_EXACT_MATCH = 0x01;
    private static final int ACCEPT_LATER_HARDWARE_VERSIONS = 0x03;
```

Byte 11:

0	n	n	n	n	n	n	n

<D5>   Data item 5. Low 7 bits.

Byte 12:

0	n	n	n	n	n	n	n

<D6>   Data item 6. Low 7 bits.

Byte 13:

0	n	n	n	n	n	n	n

<D7>   Data item 7. Low 7 bits.

Byte 14:

0	n	n	n	n	n	n	n

<D8>   Data item 8. Low 7 bits.

Byte 15:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 |

0xE5

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 0 | 0 | 0 |

0x10

Notes:

None.

1.5.44   ProgCV

Description:

The **ProgCV** command is used to read and write a locomotive's mobile decoder configuration variables.

Group:

Variable-Byte Message

Opcode:

OPC_WR_SL_DATA

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 1 | 1 | 1 | 1 | 0xEF   Opcode.

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 | 0x0E   Message length.

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0 | 0x7C   Programming slot number.

Byte 3:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <PCMD>   Programming command.

d6   0 means read and 1 means write
d5   1 means byte mode and 0 means bit mode
d4   TY1
d3   TY0
d2   0 means service mode on programming track, 1 means operations mode on mainline.
d1   1 - unknown
d0   1 - unknown

d5	d4	d3	d2	d1	d0	Programming Mode
1	0	0	0	×	×	Paged mode byte read/write on service track
1	0	1	0	×	×	Direct mode byte read/write on service track
0	0	1	0	×	×	Direct mode bit read/write on service track
×	1	0	0	×	×	Physical register byte read/write on service track
×	1	1	0	×	×	Service track reserved function
1	0	0	1	×	×	Ops mode byte program on mainline no feedback
1	0	1	1	×	×	Ops mode byte program on mainline with feedback
0	0	0	1	×	×	Ops mode bit program on mainline no feedback
0	0	1	1	×	×	Ops mode bit program on mainline with feedback

Byte 4:

0	0	0	0	0	0	0	0	0x00

Byte 5:

0	n	n	n	n	n	n	n	\<HOPSA\>	In operations mode programming this contains the 7 high address bits of the locomotive to program. 0x00 if service mode.

Byte 6:

0	n	n	n	n	n	n	n	\<LOPSA\>	In operations mode programming this contains the 7 low address bits of the locomotive to program. 0x00 if service mode.

Byte 7:

0	0	0	0	0	0	0	0	0x00

Byte 8:

0	0	d5	d4	0	0	d1	d0	\<CVH\>	Configuration Variable number high 3 bits and most significant bit of data byte.

d5   CV9
d4   CV8
d1   DATA7
d0   CV7

Byte 9:

| 0 | n | n | n | n | n | n | n |

<CVH>   Configuration Variable number low 7 bits. CV1 is 0x0000, CV2 is 0x0001 etc.

Byte 10:

| 0 | n | n | n | n | n | n | n |

<DATA>   Data value low 7 bits.

Byte 11:

| 0 | n | n | n | n | n | n | n |

<SNH>   Throttle ID low 7 bits of low byte.

Byte 12:

| 0 | n | n | n | n | n | n | n |

<SNL>   Throttle ID low 7 bits of high byte.

Byte 13:

| 0 | 1 | 1 | 1 | 1 | 1 | 1 | 0 |

0x7E   Checksum.

Response:

Ack and if command is accepted a **ProgSlotData** message

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 1 | 1 | 1 | 1 |

0xEF

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 |

0x0E

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0 |

0x7C

Byte 4:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |

0x00

Byte 7:

| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |

0x00

Byte 8:

0	0	×	×	0	0	×	×

Notes:

None.

1.5.45 ProgSlotDataP1

Description:

This response provides data for the programming slot.

Group:

Variable-Byte Message

Opcode:

OPC_SL_RD_DATA

Type:

Response

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 1 | 0xE7 | Opcode. |

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 | 0x0E | Message length. |

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0 | 0x7C | Programming slot number. |

Byte 3:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <PCMD> | Last programming command. |

d6 0 means read and 1 means write
d5 1 means byte mode and 0 means bit mode
d4 TY1
d3 TY0
d2 0 means service mode on programming track, 1 means operations mode on mainline.
d1 1 - unknown
d0 1 - unknown

d5	d4	d3	d2	d1	d0	Programming Mode
1	0	0	0	×	×	Paged mode byte read/write on service track
1	0	0	1	×	×	Direct mode byte read/write on service track
0	0	0	1	×	×	Direct mode bit read/write on service track
×	0	1	0	×	×	Physical register byte read/write on service track
×	0	1	1	×	×	Service track reserved function
1	0	0	1	×	×	Ops mode byte program no feedback
1	0	1	1	×	×	Ops mode byte program with feedback
0	0	0	1	×	×	Ops mode bit program no feedback
0	0	1	1	×	×	Ops mode bit program with feedback

Byte 4:

0	0	0	0	d3	d2	d1	d0

<PSTAT>

d3   1 means user aborted the previous command
d2   1 means failed to detect read compare acknowledge from decoder
d1   1 means no write acknowledge response from decoder
d0   1 means service mode programming track is empty - no decoder detected

Byte 5:

0	n	n	n	n	n	n	n

<HOPSA>   In operations mode programming this contains the 7 high address bits of the locomotive to program. 0x00 if service mode.

Byte 6:

0	n	n	n	n	n	n	n

<LOPSA>   In operations mode programming this contains the 7 low address bits of the locomotive to program. 0x00 if service mode.

Byte 7:

0	d6	0	0	d3	d2	d1	d0

<TRK>   Global system track status.

d6   1 means this command station implements version 2 slot commands. This can be turned off on the DCS240 by setting the OpSw 44 to be closed.

d3   1 means the programming track is busy.

d2   1 means this master implements the Network version 1.1 capability, 0 means the master is a DT200.

d1   0 means the track is paused, broadcast an emergency stop.

d0   1 means the DCC packets are on in the master, global power up.

Byte 8:

0	0	d5	d4	0	0	d1	d0		<CVH>	Configuration Variable number high 3 bits and most significant bit of data byte.

d5   CV9
d4   CV8
d1   DATA7
d0   CV7

Byte 9:

0	n	n	n	n	n	n	n		<CVH>	Configuration Variable number low 7 bits. CV1 is 0x0000, CV2 is 0x0001 etc.

Byte 10:

0	n	n	n	n	n	n	n		<DATA>	Data value low 7 bits.

Byte 11:

0	n	n	n	n	n	n	n		<SNH>	Throttle ID low 7 bits of low byte.

Byte 12:

0	n	n	n	n	n	n	n		<SNL>	Throttle ID low 7 bits of high byte.

Byte 13:

0	1	1	1	1	1	1	0		0x7E	Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 1 | 1 |

0xE7

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 |

0x0E

Byte 2:

| 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0 |

0x7C

Byte 4:

| 0 | 0 | 0 | 0 | × | × | × | × |

Byte 7:

| 0 | × | 0 | 0 | × | × | × | × |

Byte 8:

| 0 | 0 | × | × | 0 | 0 | × | × |

Notes:

None.

_____

1.5.46   PwrOff

Description:

This command turns the track power off.

Group:

2-Byte Message

Opcode:

OPC_GPOFF

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0x82   Opcode.

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 1 | 0 | 1 | 0x7D   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0x82

Notes:

None.

1.5.47   PwrOn

Description:

This command turns the track power on.

Group:

2-Byte Message

Opcode:

OPC_GPON

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 1 | 1 | 0x83   Opcode.

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0 | 0x7C   Checksum.

Response:

After power on the command station sends an **getCfgSlotDataP1** message. It also sends a sequence of OPC_SW_REQ messages with the following values of SW1 and SW2:

SW1	SW2	Purpose
0x78	0x27	
0x79	0x27	
0x7A	0x27	
0x7B	0x27	
0x78	0x07	Interrogate all PM4 inputs?
0x79	0x07	Interrogate all BDL16 input reports?
0x7A	0x07	Interrogate all SE8 input reports?
0x7B	0x07	Interrogate all DS64 input reports.

Signature:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 0 | 1 | 1 | 0x83

<u>Notes:</u>

None.

1.5.48   Reset

Description:

This broadcast message is sent by a command station when its "Loco Reset" button has been pressed. Software should reload any locally cached slot data from the command station.

Group:

2-Byte Message

Opcode:

OPC_LOCO_RESET

Type:

Broadcast

Encoding:

Byte 0:

| 1 | 0 | 0 | 0 | 1 | 0 | 1 | 0 | 0x8A   Opcode.

Byte 1:

| 0 | 1 | 1 | 1 | 0 | 1 | 0 | 1 | 0x75   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 0 | 0 | 1 | 0 | 1 | 0 | 0x8A

Notes:

None.

1.5.49 SensRepGenIn

Description:

General sensor input report.

Group:

4-Byte Message

Opcode:

OPC_INPUT_REP

Type:

Message

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 1 | 0 |

0xB2   Opcode.

Byte 1:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<IN1>   Sensor address A7 to A1.

d6	A7.
d5	A6.
d4	A5.
d3	A4.
d2	A3.
d1	A2.
d0	A1.

Byte 2:

| 0 | 1 | d5 | d4 | d3 | d2 | d1 | d0 |

<IN2>   Sensor address A11 to A8, A0 and sensor input state.

d5	A0.
d4	Input state: 1 means sensor input >= 6V, and 0 means sensor input = 0V.
d3	A11.
d2	A10.
d1	A9.
d0	A8.

Byte 3:

| 0 | n | n | n | n | n | n | n |

     `<CHK>`   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 1 | 0 |

     0xB2

Byte 2:

| 0 | 1 | × | × | × | × | × | × |

Notes:

None.

1.5.50   SensRepTurnIn

Description:

Turnout sensor input report.

Group:

4-Byte Message

Opcode:

OPC_SW_REP

Type:

Message

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 0 | 1 | 0xB1 | Opcode. |

Byte 1:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <SN1> | Sensor address A7 to A1. |

d6   A7.
d5   A6.
d4   A5.
d3   A4.
d2   A3.
d1   A2.
d0   A1.

Byte 2:

| 0 | 1 | d5 | d4 | d3 | d2 | d1 | d0 | <SN2> | Sensor address A11 to A8, A0 and sensor state. |

d5   A0.
d4   Input sensor state, 1 means sensor $>= 6V$, 0 means
      sensor $= 0V$.
d3   A11.
d2   A10.
d1   A9.
d0   A8.

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 0 | 1 | 0xB1 |

Byte 2:

| 0 | 1 | × | × | × | × | × | × |

Notes:

None.

1.5.51   SensRepTurnOut

Description:

Turnout sensor output report.

Group:

4-Byte Message

Opcode:

OPC_SW_REP

Type:

Message

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 0 | 1 | 0xB1 | Opcode. |

Byte 1:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <SN1> | Sensor address A6 to A0. |

d6   A6.
d5   A5.
d4   A4.
d3   A3.
d2   A2.
d1   A1.
d0   A0.

Byte 2:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 | <SN2> | Sensor address A10 to A7 and sensor state. |

d5   0 means closed output line is off and 1 means the closed
      output line is on.
d4   0 means thrown output line is off and 1 means the
      thrown output line is on.
d3   A10.
d2   A9.
d1   A8.
d0   A7.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 0 | 1 |

0xB1

Byte 2:

| 0 | 0 | × | × | × | × | × | × |

Notes:

None.

1.5.52   SetBrdOpSw

Description:

Set board OpSw.

Group:

6-Byte Message

Opcode:

OPC_BRD_OPSW (Unofficial mnemonic)

Type:

Broadcast

Encoding:

Byte 0:

1	1	0	1	0	0	0	0

0xD0   Opcode.

Byte 1:

0	1	1	1	0	0	1	d0

The bit d0 is the most significant bit of the board id.

Byte 2:

0	n	n	n	n	n	n	n

<BIDL>   Least significant 7 bits of the board id.

Byte 3:

0	n	n	n	n	n	n	n

<BTYPE>   Board type code.

Board	Type Code
PM4	0x70.
BDL16	0x71.
SE8C	0x72.
DS64	0x73.

Byte 4:

0	d6	d5	d4	d3	d2	d1	d0

Byte and bit number.

The high nibble encodes the byte number, and the low nibble the bit number. The byte number is calculated as (OpSw# - 1) >> 3 and the bit number is (OpSw# - 1) - byte number $\times$ 8.

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

Response:

Ack

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | 0xD0

Byte 1:

| 0 | 1 | 1 | 1 | 0 | 0 | 1 | × |

Notes:

None.

1.5.53 SetIdleState

Description:

This command sets the network to "idle" state. The command station broadcasts an emergency stop.

Group:

2-Byte Message

Opcode:

OPC_IDLE

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 1 | 0 | 1 | 0x85 | Opcode. |

Byte 1:

| 0 | 1 | 1 | 1 | 1 | 0 | 1 | 0 | 0x7A | Checksum. |

Response:

None

Signature:

Byte 0:

| 1 | 0 | 0 | 0 | 0 | 1 | 0 | 1 | 0x85 |

Notes:

None.

1.5.54   SetLocoSlotDataP1

Description:

This command sets the locomotive slot data for the specified slot.

Protocol:

1

Group:

Variable-Byte Message

Opcode:

OPC_WR_SL_DATA

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 1 | 1 | 1 | 1 | 0xEF   Opcode.

Byte 1:

| 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 | 0x0E   Message length (14 bytes).

Byte 2:

| 0 | n | n | n | n | n | n | n | <SLOT#>   Slot number in the range 0x00 to
                                                    0x77. Slot 0x00 is the dispatch
                                                    special slot.

Byte 3:

| d7 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <STAT1>   Slot status 1.

d7	d6	
0	0	Free, no consist linking.
0	1	Consist sub-member.
1	0	Consist top-member.
1	1	Consist Mid-Consist member.

Note: d7 is set to 0 in the message by the command station and so may not correctly reflect the actual setting in the slot table.

d5	d4	
0	0	Free slot, no valid data. Not refreshed.
0	1	Common. Locomotive address in this slot. Refreshed.
1	0	Idle. Locomotive address in this slot. Not refreshed.
1	1	In Use. Locomotive address in this slot. Refreshed.

d3	
0	No slot consist linked into this slot.
1	Slot consist linked into this slot.

d2	d1	d0	
0	0	0	28 step decoder. 3-byte packet regular mode
0	0	1	28 step decoder. Generate trinary packets for this mobile address
0	1	0	14 step decoder.
0	1	1	128 step decoder.
1	0	0	28 step decoder. Allow advanced consisting
1	0	1	reserved
1	1	0	reserved
1	1	1	128 step decoder. Allow advanced consisting

Byte 4:

0	n	n	n	n	n	n	n

<ADR>   If <ADR2> is 0 then this contains the NMRA short address. If <ADR2> is greater than 0 then this contains the low 7 bits of the NMRA long address.

Byte 5:

0	n	n	n	n	n	n	n

<SPD>   Speed in the range 0x00 to 0x7F. 0x00 means inertial stop and 0x01 means emergency stop. Other values mean increasing speed.

Byte 6:

0	0	d5	d4	d3	d2	d1	d0

<DIRF>   Locomotive direction and state of functions F0 to F4.

d5   Direction: 1 means forward and 0 means backwards.

d4   F0 state: 1 means on and 0 means off.

d3   F4 state: 1 means on and 0 means off.

d2   F3 state: 1 means on and 0 means off.

d1   F2 state: 1 means on and 0 means off.

d0   F1 state: 1 means on and 0 means off.

Byte 7:

| 0 | d6 | 0 | 0 | d3 | d2 | d1 | d0 | \<TRK>   Global system track status.

d6   1 means this command station implements protocol 2 messages. This can be turned off on the DCS240 by setting the OpSw 44 to be closed.

d3   1 means the programming track is busy.

d2   1 means this command station implements protocol 1 messages and 0 means the command station is a DT200.

d1   0 means the track is paused, broadcast an emergency stop.

d0   1 means the DCC packets are on in the command station and the track power is on.

Byte 8:

| 0 | 0 | 0 | 0 | d3 | d2 | 0 | d0 | \<SS2>   Slot status 2.

d3   1 means expansion in ID1/2, 0 means encoded alias.

d2   1 means expansion ID1/2 is not ID usage.

d0   1 means this slot has suppressed advanced consist.

Byte 9:

| 0 | n | n | n | n | n | n | n | \<ADR2>   If \<ADR2> is greater than 0 then this contains the high 7 bits of the NMRA long address.

Byte 10:

| 0 | 0 | 0 | 0 | d3 | d2 | d1 | d0 | \<SND>   Function F5 to F8 states.

d3   F8 state: 1 means on and 0 means off.

d2   F7 state: 1 means on and 0 means off.

d1   F6 state: 1 means on and 0 means off.

d0   F5 state: 1 means on and 0 means off.

Byte 11:

| 0 | n | n | n | n | n | n | n | \<ID1>   7-bit ls ID code written by throttle when STAT2.4 = 1.

Byte 12:

0	n	n	n	n	n	n	n

<ID2>   7-bit ms ID code written by throttle when STAT2.4 = 1.

Byte 13:

0	n	n	n	n	n	n	n

<CHK>   Checksum.

Response:

Ack

Signature:

Byte 0:

1	1	1	0	1	1	1	1

0xEF

Byte 1:

0	0	0	0	1	1	1	0

0x0E

Byte 2:

0	n	n	n	n	n	n	n

less than 0x78

Byte 6:

0	0	×	×	×	×	×	×

Byte 7:

0	×	0	0	×	×	×	×

Byte 8:

0	0	0	0	×	×	0	×

Byte 10:

0	0	0	0	×	×	×	×

Notes:

None.

1.5.55   SetLocoSlotDataP2

Description:

This command sets the locomotive slot data for the specified slot number.

Protocol:

2

Group:

Variable-Byte Message

Opcode:

OPC_WR_SL_DATA_P2 (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 1 | 1 | 1 | 0 |

0xEE   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 1 |

0x15   Message length (21 bytes).

Byte 2:

| 0 | 0 | 0 | 0 | 0 | d2 | d1 | d0 |

<SLOTP#>   Slot page number in the range 0x0 to 0x7.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<SLOTL#>   Slot number in the range 0x00 to 0x77.

Byte 4:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<STAT1>   Slot status 1.

d7	d6	
0	0	Free, no consist linking.
0	1	Consist sub-member.
1	0	Consist top-member.
1	1	Consist Mid-Consist member.

Note: d7 is set to 0 in the message by the command station and so may not correctly reflect the actual setting in the slot table.

d5	d4	
0	0	Free slot, no valid data. Not refreshed.
0	1	Common. Locomotive address in this slot. Refreshed.
1	0	Idle. Locomotive address in this slot. Not refreshed.
1	1	In Use. Locomotive address in this slot. Refreshed.

d3	
0	No slot consist linked into this slot.
1	Slot consist linked into this slot.

d2	d1	d0	
0	0	0	28 step decoder. 3-byte packet regular mode
0	0	1	28 step decoder. Generate trinary packets for this mobile address
0	1	0	14 step decoder.
0	1	1	128 step decoder.
1	0	0	28 step decoder. Allow advanced consisting
1	0	1	reserved
1	1	0	reserved
1	1	1	128 step decoder. Allow advanced consisting

Byte 5:

0	n	n	n	n	n	n	n

<ADR>   Low address.

Byte 6:

0	n	n	n	n	n	n	n

<ADR2>   High address.

Byte 7:

0	d6	d5	d4	d3	d2	d1	d0

<TRK>   Global system track status.

d6   1 means this command station implements protocol 2
        messages. This can be turned off on the DCS240 by
        setting the OpSw 44 to be closed.

d5   Reserved. Set to 0.

d4   Reserved. Set to 0.

d3   1 means the programming track is busy.

d2   1 means this command station implements protocol 1
        messages. 0 means the command station is a DT200.

d1   0 means the track is paused, broadcast an emergency
        stop.

d0   1 means the DCC packets are on in the command sta-
        tion and track power is on.

Byte 8:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | \<SPD\>   Speed in the range 0x00 to 0x7F.
                                                         0x00 means inertial stop and 0x01
                                                         means emergency stop. Other val-
                                                         ues mean increasing speed.

Byte 9:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Functions.

d6   F8 state: 1 means on and 0 means off

d5   F0 state: 1 means on and 0 means off

d4   F12 state: 1 means on and 0 means off

d3

d2

d1   F20 state: 1 means on and 0 means off

d0

Byte 10:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | Direction.

d6

d5   Direction: 1 means forwards and 0 means backwards

d4

d3

d2

d1

d0

Byte 11:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Functions.

d6   F11 state: 1 means on and 0 means off
d5   F10 state: 1 means on and 0 means off
d4   F9 state: 1 means on and 0 means off
d3
d2
d1
d0

Byte 12:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Functions.

d6   F19 state: 1 means on and 0 means off
d5   F18 state: 1 means on and 0 means off
d4   F17 state: 1 means on and 0 means off
d3   F16 state: 1 means on and 0 means off
d2   F15 state: 1 means on and 0 means off
d1   F14 state: 1 means on and 0 means off
d0   F13 state: 1 means on and 0 means off

Byte 13:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Functions.

d6   F7 state: 1 means on and 0 means off
d5   F6 state: 1 means on and 0 means off
d4   F5 state: 1 means on and 0 means off
d3   F4 state: 1 means on and 0 means off
d2   F3 state: 1 means on and 0 means off
d1   F2 state: 1 means on and 0 means off
d0   F1 state: 1 means on and 0 means off

Byte 14:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Unknown.

d6
d5
d4
d3
d2
d1
d0

Byte 15:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Unknown.

d6
d5
d4
d3
d2
d1
d0

Byte 16:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Consist slot page number.

d6
d5
d4
d3
d2   Consist slot page b2
d1   Consist slot page b1
d0   Consist slot page b0

Byte 17:

| 0 | n | n | n | n | n | n | n |

Consist slot number in the range 0x00 to 0x77.

Byte 18:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Throttle id low bits.

Byte 19:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

Throttle id high bits.

Byte 20:

| 0 | n | n | n | n | n | n | n | <CHK>   Checksum.

<u>Response:</u>

Ack

<LOPC>	<ACK1>	Meaning
0x6E	0x7F	Command OK.

Signature:

Byte 0:

1	1	1	0	1	1	1	0

0xEE

Byte 1:

0	0	0	1	0	1	0	1

0x15

*** THERE SHOULD BE MORE ONCE ALL THE BYTES ARE DETERMINED ***

Notes:

None.

1.5.56   SetLocoSlotStat1

Description:

This command sets the locomotive slot status 1 values for the specified slot number.

Protocol:

1

Group:

4-Byte Message

Opcode:

OPC_SLOT_STAT1

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 1 | 0 | 1 |

0xB5   Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n |

<SLOT#>   Slot number in the range 0x00 to
                0x77.

Byte 2:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 |

<STAT1>   Slot status 1.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

None.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 1 | 0 | 1 |

0xB5

Byte 1:

| 0 | n | n | n | n | n | n | n | less than 0x78 |

<u>Notes:</u>

None.

1.5.57   SetSwWithAck

Description:

This command sets a specified switch to a specified state. The switch responds with an
Ack.

Group:

4-Byte Message

Opcode:

OPC_SW_ACK

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 0 | 1 | 0xBD   Opcode.

Byte 1:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | \<SW1\>   Switch address A6 to A0.

d6   A6.
d5   A5.
d4   A4.
d3   A3.
d2   A2.
d1   A1.
d0   A0.

Byte 2:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 | \<SW2\>   Switch address A10 to A7 and
                                                            switch control bits.

d5   Direction.   1 means closed/green, and 0 means
       thrown/red.
d4   Output. 1 means on, and 0 means off.
d3   A10.
d2   A9.
d1   A8.
d0   A7.

Byte 3:

0	n	n	n	n	n	n	n

<CHK>   Checksum.

Response:

Ack

<LOPC>	<ACK1>	Meaning
0x3D	0x00	FIFO is full, command rejected.
0x3D	0x7F	Command accepted.

Signature:

Byte 0:

1	0	1	1	1	1	0	1

0xBD

Byte 2:

0	0	×	×	×	×	×	×

Notes:

None.

1.5.58   OPC_SV_PROG

Operation: Program system variables.

Group: Variable-Byte Message

Direction: device → device

Encoding:

Byte 0:

| 1 | 1 | 1 | 0 | 0 | 1 | 0 | 1 | 0xE5   Opcode.

Byte 1:

| 0 | 0 | 0 | 1 | 0 | 1 | 0 | 0 | 0x14   Message length (20 bytes).

Byte 2:

| 0 | n | n | n | n | n | n | n | <SRC>   Source id in the range 0x00 to 0x7F.

Byte 3:

| 0 | n | n | n | n | n | n | n | <SV_CMD>   Specifies the SV access type.

Byte 4:

| 0 | n | n | n | n | n | n | n | <DSTH>   Destination id high in the range 0x00 to 0x7F.

Byte 5:

| 0 | n | n | n | n | n | n | n | <HOST>   Device host identifier.

This should be 0x00 for discover devices broadcast.

Host Id	Device
0x01	LNRP
0x04	UT4
0x0C	WTL12
0x14	DB210 Opto
0x15	DB210
0x16	DB220
0x1A	DCS210+
0x1B	DCS210
0x1C	DCS240
0x23	PR3
0x24	PR4
0x2A	DT402
0x32	DT500
0x33	DCS51
0x34	DCS52
0x3E	DT602
0x51	BXPA1
0x58	BXP88
0x5C	UR92
0x63	LNWI

Byte 6:

0	n	n	n	n	n	n	n

Hardware version.

Host Id	Device
0x00	Slave all
0x18	Slave RF24

Byte 7:

0	n	n	n	n	n	n	n

Reserved.

Byte 8:

0	d6	d5	d4	d3	d2	d1	d0

Software Version Number.

d6	version number bit 3
d5	version number bit 2.
d4	version number bit 1
d3	version number bit 0
d2	subversion number bit 2
d1	subversion number bit 1
d0	subversion number bit 0

e.g. 0x09 decodes as version 1.1.

This is set to 0x00 for discover devices broadcast message.

Byte 9:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <PXCT1>   Address type code and high bits of D1 to D4.

d6   XC2. Address type code.
d5   XC1. Address type code.
d4   XC0. Address type code.
d3   D4.7. High bit
d2   D3.7. High bit
d1   D2.7. High bit
d0   D1.7. High bit

XC2	XC1	XC0	Meaning
0	0	0	7 bit peer to peer addresses.
0	0	1	reserved.
0	1	0	reserved.
0	1	1	reserved.
1	0	0	reserved.
1	0	1	reserved.
1	1	0	reserved.
1	1	1	reserved.

Byte 10:

| 0 | n | n | n | n | n | n | n | <D1>   Data item 1. Low 7 bits.

Byte 11:

| 0 | n | n | n | n | n | n | n | <D2>   Data item 2. Low 7 bits.

This should be 0x01 for a discover devices broadcast message.

Byte 12:

| 0 | n | n | n | n | n | n | n | <D3>   Data item 3. Low 7 bits.

Byte 13:

| 0 | n | n | n | n | n | n | n | <D4>   Data item 4. Low 7 bits.

Byte 14:

| 0 | n | n | n | n | n | n | n | <PXCT2>   Data type code and high bits for D5 to D8.

d6   XC5. Data type code.
d5   XC4. Data type code.
d4   XC3. Data type code.
d3   D8.7. High bit
d2   D7.7. High bit
d1   D6.7. High bit
d0   D5.7. High bit

XC5	XC4	XC3	Meaning
0	0	0	ANSI text string.
0	0	1	reserved.
0	1	0	reserved.
0	1	1	reserved.
1	0	0	reserved.
1	0	1	reserved.
1	1	0	reserved.
1	1	1	reserved.

Byte 15:

0	n	n	n	n	n	n	n

<D5>   Data item 5. Low 7 bits.

Byte 16:

0	n	n	n	n	n	n	n

<D6>   Data item 6. Low 7 bits.

Byte 17:

0	n	n	n	n	n	n	n

<D7>   Data item 7. Low 7 bits.

Byte 18:

0	n	n	n	n	n	n	n

<D8>   Data item 8. Low 7 bits.

Byte 19:

0	n	n	n	n	n	n	n

<CHK>   Checksum.

Description:

This command sends the data from one device to another peer to peer.

SRC	DSTL	DSTH	Comments
0x0F	0x08	0x00	Discover devices broadcast message.
0x0F	0x10	0x00	Discover device response.

Response:

OPC_PEER_XFER_20 for discover devices.

<u>Notes:</u>

The discover response decoded peer transfer message encodes as follows:

D1   IPL Version Number
D2   Serial Number - low byte
D3   Serial Number - high byte
D4
D5   Serial Number 2 - low byte
D6   Serial Number 2 - high byte
D7
D8

The IPL version number is encoded as follows:

d6   version number bit 3
d5   version number bit 2.
d4   version number bit 1
d3   version number bit 0
d2   subversion number bit 2
d1   subversion number bit 1
d0   subversion number bit 0

e.g. 0x09 decodes as version 1.1.

These came from DigiPLII:

message Length = 20 e5 14 0f 10 00 24 00 00 00 02 00 08 07 00 00 00 00 00 00 38

message Length = 20 e5 14 0f 08 00 00 00 00 00 00 00 01 00 00 00 00 00 00 00 08

message Length = 20 e5 14 0f 10 00 24 00 00 00 00 00 57 13 00 00 00 00 00 00 71

message Length = 20 e5 14 0f 10 00 1b 00 00 03 02 00 54 10 00 00 00 00 00 00 4f

It reports PR4 with serial number 0x0788 ver 0 PR4 with serial 0x1357 ver 0 DCS240 with SN 0x0AAB ver 0.3 DCS210 with SN 0x10D4 ver 0.3

1.5.59 SwReq

Description:

Command a turnout controller to a specified state. *** CHECK THIS ***

Group:

4-Byte Message

Opcode:

OPC_SW_REQ

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 0 | 0 | 0xB0 | Opcode. |

Byte 1:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <SW1> | Switch address A6 to A0. |

d6	A6.
d5	A5.
d4	A4.
d3	A3.
d2	A2.
d1	A1.
d0	A0.

Byte 2:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 | <SW2> | Switch address A10 to A7 and switch control bits. |

d5	Direction. 1 means closed/green, and 0 means thrown/red.
d4	Output. 1 means on, and 0 means off.
d3	A10.
d2	A9.
d1	A8.
d0	A7.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

Ack if command failed, otherwise no response.

<LOPC>	<ACK1>	Meaning
0x30	0x00	Command failed.

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 0 | 0 | 0 | 0 |

0xB0

Byte 2:

| 0 | 0 | × | × | × | × | × | × |

Notes:

The on power on the command station sends a sequence of OPC_SW_REQ messages with the following values of SW1 and SW2:

SW1	SW2	Purpose
0x78	0x27	
0x79	0x27	
0x7A	0x27	
0x7B	0x27	
0x78	0x07	Interrogate all PM4 inputs?
0x79	0x07	Interrogate all BDL16 input reports?
0x7A	0x07	Interrogate all SE8 input reports?
0x7B	0x07	Interrogate all DS64 input reports.

1.5.60   SwState

Description:

Request state of switch. *** NEED TO CHECK ***

Group:

4-Byte Message

Opcode:

OPC_SW_STATE

Type:

Message?

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 1 | 0 | 0 |

0xBC   Opcode.

Byte 1:

| 0 | n | n | n | n | n | n | n |

<SW1>   Switch address A6 to A0.

Byte 2:

| 0 | 0 | d5 | d4 | d3 | d2 | d1 | d0 |

<SW2>   Switch address A10 to A7 and switch control bits.

    d5   Direction. 1 means closed/green, and 0 means thrown/red.
    d4   Output. 1 means on, and 0 means off.
    d3   A10.
    d2   A9.
    d1   A8.
    d0   A7.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

Ack

Signature:

Byte 0:

1	0	1	1	1	1	0	0

0xBC

Byte 2:

0	0	×	×	×	×	×	×

Notes:

This needs to be tested to see what the real purpose is.

1.5.61   TransRep

Description:

Transponder input report.

Group:

6-Byte Message

Opcode:

OPC_TRANS_REP

Type:

Broadcast

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | 0xD0 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | | A value of 0x20 means the positive detection of a transponder, 0x00 means no longer detected. |

Byte 2:

| 0 | 0 | 0 | 0 | n | n | n | n | <ZONE#> | Zone indicator (0x0 = A, 0x2 = B, 0x4 = C, 0x6 = D). |

Byte 3:

| 0 | n | n | n | n | n | n | n | <ADR> | Locomotive address low bits. |

Byte 4:

| 0 | n | n | n | n | n | n | n | <ADR2> | Locomotive address high bits. |

Byte 5:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

None.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 0 | 0 | 0 | 0xD0.

*** THERE SHOULD BE MORE ***

Notes:

None.

1.5.62 UnlinkSlotsP1

Description:

This command unlinks slot SL1 from slot SL2.

Protocol:

1

Group:

Variable-Byte Message

Opcode:

OPC_UNLINK_SLOTS

Type:

Command

Encoding:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 0 | 0 | 0xB8 | Opcode. |

Byte 1:

| 0 | n | n | n | n | n | n | n | <SL1> | Slot number in the range 0x00 to 0x77. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SL2> | Slot number in the range 0x00 to 0x77. |

Byte 3:

| 0 | n | n | n | n | n | n | n | <CHK> | Checksum. |

Response:

Returns **LocoSlotDataP1** or **Ack**

Signature:

Byte 0:

| 1 | 0 | 1 | 1 | 1 | 0 | 0 | 0 | 0xB8 |

Byte 1:

| 0 | n | n | n | n | n | n | n | less than 0x78

Byte 2:

| 0 | n | n | n | n | n | n | n | less than 0x78

<u>Notes:</u>

None.

1.5.63 UnlinkSlotsP2

Description:

This command unlinks slot SL1 from a consist. The command station sets SL_CONUP/DN flags appropriately. If the command was successful then a **LocoSlotDataP2** response will be returned. An invalid link will return a **Ack** with a response code of 0x00.

Protocol:

2

Group:

6-Byte Message

Opcode:

OPC_D4_GROUP (Unofficial mnemonic)

Type:

Command

Encoding:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 0xD4 | Opcode. |

Byte 1:

| 0 | 0 | 1 | 1 | 1 | d2 | d1 | d0 | <SL1P> | Bits d2 to d0 contain the SL1 slot page number in the range 0x0 to 0x7. |

Byte 2:

| 0 | n | n | n | n | n | n | n | <SL1#> | Slot number SL1 in the range 0x00 to 0x77. |

Byte 3:

| 0 | 1 | 0 | 1 | 0 | d2 | d1 | d0 | <SL1P> | Bits d2 to d0 contain the SL1 slot page number in the range 0x0 to 0x7. This is the same value as byte 1. |

Byte 4:

| 0 | n | n | n | n | n | n | n |

<SL1#>   Slot number SL1 in the range 0x00 to 0x77. This is the same value as byte 2.

Byte 5:

| 0 | n | n | n | n | n | n | n |

<CHK>   Checksum.

Response:

LocoSlotDataP2 or **Ack**.

Signature:

Byte 0:

| 1 | 1 | 0 | 1 | 0 | 1 | 0 | 0 |

0xD4

Byte 1:

| 0 | 0 | 1 | 1 | 1 | × | × | × |

Byte 2:

| 0 | n | n | n | n | n | n | n |

less than 0x78

Byte 3:

| 0 | 1 | 0 | 1 | 0 | × | × | × |

Byte 4:

| 0 | n | n | n | n | n | n | n |

less than 0x78

Notes:

None.

Chapter 2

Fast Clock

2.1 Summary

The command station provides a system fast clock and parameters are stored in slot #123 (0x7B). Use OPC_WR_SL_DATA to write new clock information, The current slot information can be read using OPC_RQ_SL_DATA. This will return an OPC_SL_RD_DATA message containing the fast clock information. This message is called the "sync". Other throttles will update to this sync. Note that all attached display devices keep a current clock calculation based on this sync read value, i.e. devices must not continuously poll the clock slot to generate time, but use this merely to restore sync and follow current rate etc. The clock slot is typically "pinged" or read every 70 to 100 seconds, by a single user, so all attached devices can synchronise any phase drifts. Upon seeing a sync read, all devices should reset their local sub-minute phase counter and invalidate the sync update ping generator.

2.2 Slot #123 Encoding

Byte 0:

| 0 | 1 | 1 | 1 | 1 | 0 | 1 | 1 | 0x7B   Slot number.

Byte 1:

| 0 | n | n | n | n | n | n | n |

<RATE>   Clock rate.   0x00 means freeze
                clock, 0x01 means 1:1 rate, 0x0A
                means 10:1, etc.   The maximum
                value 0x7F means 128:1.

Byte 2:

| 0 | n | n | n | n | n | n | n |

<FRACL>   Sub-minute counter low bits.

Byte 3:

| 0 | n | n | n | n | n | n | n |

<FRACH>   Sub-minute counter high bits.

The implementation and meaning of FRACL and FRACH depend upon the specific clock generator. These values should not be used externally. These values are reset when a valid sync message is seen.

That said, the following timing was derived for the DCS240.

Get:

maxTick = 0xBFF

ticks = maxTick - (0x3FFF - ((<FRACL> & 0x7F) — ((<FRACH> & 0x7F) << 7)))

seconds = 60.0 * ticks / (maxTick + 1)

Set:

temp = ticks - maxTick + 0x3FFF

<FRACL> = temp & 0x7F

<FRACH> = (temp >> 7) & 0x7F

Byte 4:

| 0 | n | n | n | n | n | n | n |

<MINS>   Fast clock minutes.   This is en-
                coded.

Get:

temp = ((255 - <MINS>) & 0x7F) mod 60

minutes = (60 - temp) mod 60

Set:

<MINS> = (255 - (60 - minutes)) & 0x7F

Byte 5:

| 0 | d6 | d5 | d4 | d3 | d2 | d1 | d0 | <TRK> | Global system track status. |

d6	Reserved. Set to 0.
d5	Reserved. Set to 0.
d4	Reserved. Set to 0.
d3	1 means the programming track is busy.
d2	1 means this master implements the Network version 1.1 capability, 0 means the master is a DT200.
d1	0 means the track is paused, broadcast an emergency stop.
d0	1 means the DCC packets are on in the master, global power up.

Byte 6:

| 0 | n | n | n | n | n | n | n | <HRS> | Fast clock hours. This is encoded. |

Get:

temp = ((256 - <HRS>) & 0x7F) mod 24

hours = (24 - temp) mod 24

Set:

<HRS> = (256 - (24 - hours)) & 0x7F

Byte 7:

| 0 | n | n | n | n | n | n | n | <DAYS> | Fast clock days. Number of 24 hour clock rolls. |

Byte 8:

| 0 | d6 | 0 | 0 | 0 | 0 | 0 | 0 | <CNTRL> | The bit d6 indicates valid clock information. 1 means good and 0 means ignore. |

Byte 9:

| 0 | n | n | n | n | n | n | n | <ID1> | Device ID low bits. |

Byte 10:

| 0 | n | n | n | n | n | n | n | <ID2> | Device ID high bits. |

ID1 and ID2 indicate the device that last set the clock. 0x00, 0x00 means that not set has happened. 0x7F, 0x7X are reserved for computer use.

Chapter 3

Updating Firmware

3.1 Bootloader Protocol 1

3.2 Bootloader Protocol 2

1. The IPL Setup message is sent twice to initiate the download.

2. Each block is sent,

3. The IPL End Operation message is sent.

A block consists of an IPL Address message following by 1 or more IPL Data messages.

3.3   Firmware Parameters

PC	Device	DT	BV	HV	SV	CK	DL	OP	PB	EB	ED	DC
0x01	LNRP	09OCT15	1	0	3	64	8	1	64	64	8	0x50
0x04	UT4											
0x06	UT6	05APR21	2	0	1	64	11	2	512	4096	40	0x2E
0x0C	WTL12											
0x14	DB210O	06MAR20	2	1	2	64	7	2	512	4096	25	0x08
0x15	DB210	06MAR20	2	1	2	64	7	2	512	4096	25	0x08
0x16	DB220	06MAR20	2	1	2	64	7	2	512	4096	25	0x08
0x1A	DCS210+											
0x1B	DCS210	06MAR20	2	1	3	64	5	2	256	2048	40	0x2C
0x1C	DCS240	06MAR20	2	1	3	64	5	2	256	2048	40	0x2C
0x23	PR3	12FEB14	1	0	8	64	5	1	-	1024	-	0x14
0x24	PR4	05JAN18	0	0	0	64	5	2	256	2048	60	0x1C
0x2A	DT402	10OCT16	1	0	17	64	15	1	64	64	15	0x73
0x2A	DT402	05AUG16	1	0	17	64	15	1	64	64	15	0x4B
0x32	DT500	10OCT16	1	0	1	64	15	1	64	64	15	0x0E
0x33	DCS51	06OCT14	1	0	5	64	12	1	-	-	-	0x0E
0x34	DCS52	17JUN21	2	0	1	64	11	2	512	4096	40	0x2C
0x3E	DT602	15JUL21	2	0	1	64	11	2	512	4096	40	0x30
0x51	BXPA1	18JUN21	2	0	1	64	6	2	512	4096	41	0x0A
0x58	BXP88	21OCT17	2	0	2	64	50	2	256	2048	100	0x18
0x5C	UR92	07DEC15	0	1	8	64	16	1	64	64	16	0x24
0x5D	UR93	30AUG21	2	0	0	64	5	2	512	4096	25	0x0A
0x63	LNWI	11MAR21	2	1	2	64	5	2	512	4096	25	0x12

EBS	LNRP	DT402	DT500	DCS51	DCS52
32	0x20	0x65	0x1B	-	0x00
64	0x50	0x73	0x0E	0x0E	0x00
128	0x28	0x3A	0x47	-	0x00
192	0x1B	0x7C	0x05	-	0x2B
256	0x14	0x5D	0x64	-	0x40
1024	0x05	0x18	0x19	-	0x30
2048	0x03	0x0C	0x0D	-	0x58
4096	0x02	0x06	0x07	-	0x2C
8192	0x01	0x03	0x04	-	0x16
16384	-	0x02	0x02	-	0x0B
32768	-	0x01	0x01	-	0x06
65536	-	-	-	-	0x03

3.4 DMF File Format

The manufacturer's DMF file format is a modified form of the Intel Hexadecimal Object File Format. Character encoding is ASCII. The file consists of multiple "records" each terminated by an ASCII linefeed character (0x0A). There are four types of record and they appear in the file in the following order:

1. Sync records

2. Parameter records

3. Data records

4. End of File record

3.4.1 Sync Records

Sync records are used to identify the file as a DMF file. There are six sync records each consisting of a single ASCII # character (0x23).

Example:

```
#
#
#
#
#
#
```

3.4.2 Parameter Records

PARAM MARK	PARAMETER NAME	NAME TERMINATOR	VALUE
! (0x21) <SPC> (0x20)	ASCII text	: (0x3A) <SPC> (0x20)	decimal value
2 bytes	variable bytes	2 byte	variable bytes

PARAMETER RECORD FORMAT

Parameter records start with a two byte PARAM MARK. This consists of the ASCII code for the exclamation mark (0x21) followed by the ASCII code for the space character (0x20). The PARAMETER NAME is next. The PARAMETER NAME is ASCII encoded text identifying the parameter. The PARAMETER NAME may include spaces. It is terminated by the NAME TERMINATOR which consists of the ASCII code for a colon

(0x3A) followed by the ASCII code for a space character (0x20). The last field is the VALUE field. This is a decimal numeric value encoded as ASCII text.

The following parameters have been identified and they are presented in the following order (it is not known if the order is significant):

1. Bootloader Version

2. Manufacturer Code

3. Product Code

4. Hardware Version

5. Software Version

6. Chunk Size

7. Delay

8. Options

9. First Address

10. Last Address

11. Prog Blk Size

12. Erase Blk Size

13. Erase Dly

Example:

```
! Bootloader Version: 2
! Manufacturer Code: 0
! Product Code: 88
! Hardware Version: 0
! Software Version: 2
! Chunk Size: 64
! Delay: 50
! Options: 2
! First Address: 24576
! Last Address: 73728
! Prog Blk Size: 256
! Erase Blk Size: 2048
! Erase Dly: 100
```

3.4.3 Data Records

RECORD MARK (:)	RECLEN	LOAD OFFSET	RECTYP	DATA	CHKSUM
1 byte	2 bytes	6 bytes	2 bytes	n bytes	2 bytes

DATA RECORD FORMAT

The data record provides a set of hexadecimal digits that represent the ASCII code for data bytes that make up a portion of a memory image.

Each data record begins with a RECORD MARK field containing the ASCII code for the colon (:) character (0x3A).

Each record has a RECLEN field which specifies the number of bytes of data which follows the RECTYP field of the record. Note that one data byte is represented by two ASCII characters. The maximum value of the RECLEN field is hexadecimal "FF" or 255. Although the maximum is 255, the manufacturer seems to prefer 64.

Each record has a LOAD OFFSET field which specifies the 24-bit starting load offset of the data bytes.

The RECTYP field for data records is "00".

Each record has a variable length DATA field, it consists of zero or more bytes encoded as pairs of hexadecimal digits.

Each record ends with a CHKSUM field that contains the ASCII hexadecimal representation of the two's complement of the 8-bit bytes that result from converting each pair of ASCII hexadecimal digits to one byte of binary, from and including the RECLEN field to and including the last byte of the DATA field. Therefore, the sum of all the ASCII pairs in a record after converting to binary, form the RECLEN field up to and including the CHKSUM field, is zero.

The contents of the individual fields within the record are:

RECORD MARK   This field contains 0x3A, the encoding of the ASCII colon
                   (:) character.

RECLEN   The field contains two ASCII hexadecimal digits that specify
                   the number of data bytes in the record. The maximum value
                   is "FF" or 0x4646 (255 decimal).

LOAD OFFSET   This field contains six ASCII hexadecimal digits representing
                   the address at which the first byte of the data is to be placed.
                   Most significant digit is presented first.

RECTYP   This field contains 0x3030, the hexadecimal encoding of the
                   ASCII characters "00", which specifies the record type to be
                   a data record.

DATA   This field contains pairs of ASCII hexadecimal digits, one
                   pair for each data byte.

CHKSUM   This field contains the check sum on the RECLEN, LOAD
                   OFFSET, RECTYP, and DATA fields.

Example:

```
:400060000057AAC3880FAAC388559AC38855AAC388553AC38855AAC38855AAC3884A0
0C38855AAC38855AAC3882DFCC38861B8C3882DFCC38861B8C3882DFCC38861B8C3886D
```

3.4.4   End of File Record

RECORD MARK	RECLEN	LOAD OFFSET	RECTYP	CHKSUM
(:)	"00"	"000000"	"01"	"FF"
1 byte	2 bytes	6 bytes	2 bytes	2 bytes

END OF FILE RECORD FORMAT

The End of File Record specifies the end of the file.

The contents of the individual fields within the record are:

RECORD MARK | This field contains 0x3A, the encoding of the ASCII colon (:) character.

RECLEN | The field contains 0x3030, the hexadecimal encoding of the ASCII characters "00". Since this record does not contain any DATA bytes, the length is zero.

LOAD OFFSET | This field contains 303030303030H, the hexadecimal encoding of the ASCII characters "000000", since this field is not used for this record.

RECTYP | This field contains 0x3031, the hexadecimal encoding of the ASCII characters "01", which specifies the record type to be an End of File Record.

CHKSUM | This field contains the check sum on the RECLEN, LOAD OFFSET, and RECTYP fields. Since all the fields are static, the check sum can also be calculated statically, and the value is 4646H, the hexadecimal encoding of the ASCII characters "FF".

Example:

```
:0000000001FF
```

Chapter 4

Programming Configuration Variables (CVs)

4.1 Introduction

The decoders installed in your locomotives provide you with the ability to create a more realistic operating experience through the configuration variables (CVs for short). The network protocol supports configuration of up to 1024 CVs.

It is a good idea to run your decoders with the default CV values that come pre-programmed in your decoders until you get used to the performance characteristic and how they work on your layout. Once you are comfortable with running the trains, then you can begin customizing locomotive characteristics.

Each CV (configuration variable) controls a specific characteristic of the decoder, which in turn controls how the locomotive performs. See your decoder manual for a list of the most commonly used CVs and their meanings. Each decoder comes pre-programmed from the factory with the default settings outlined in your decoder manual. You can change your decoder's performance characteristics by changing the CV values entered in the CVs you want to change. Each of these CVs can be set up when your command station is in the programming mode. The CVs are remembered in the decoder until it is reprogrammed to with a different CV value. Please refer to your mobile decoder manual for a complete listing of the CVs supported by each decoder.

Programming decoder CVs is usually done on an isolated programming track.

There are four programming modes:

- Paged mode

- Physical register mode

- Direct mode

- Operations mode

4.1.1 Paged Mode Programming

4.1.2 Physical Register Programming

Physical Register Mode can only read CV01-CV08. You should not rely on values in the display for CVs above 08 when reading back in physical register mode.

4.1.3 Direct Mode Programming

This is the preferred programming mode.

4.1.4 Operations Mode Programming

Operations mode programming lets you program CVs in locomotives equipped with Extended Packet Format decoders while they are on the mainline. A typical use for Ops mode programming would be to change the acceleration rate (CV03) or the deceleration rate (CV04) of your locomotives to simulate the weight and braking capability of the train to compensate for changing the number of cars or power units on a train.

Operations Mode read back can only be used with decoders that are capable of operations mode read back when there is a device attached to the network that supports operations mode read back. Digitrax transponding decoders and the DCS210 or DCS240 command stations would allow operations mode read back.

4.2   Programming Mobile Decoder Addresses

Be sure that only the loco you want to program is on the programming track. If you are using operations mode programming, the loco you want to program can be anywhere on the layout but it must have a decoder that is capable of operations mode programming installed.

There are two addressing methods - short and long. The short addresses can take a value between 0 and 127, and long addresses a value between 128 and 9983. The bit 5 of mobile decoder's configuration register (CV29) determines what addressing method is used. If bit 5 is set to 1 then long addresses are used, and when bit 5 is 0 then short addresses are used. Short addresses are stored in CV1, and long addresses in CV17 and CV18. The address values stored in CV17 and CV18 are not the high and low bytes of the address value. The CV17 and CV18 values must be calculated from the address value as follows:

TEMP = address + 49152

CV18 = TEMP & 0xFF

CV17 = TEMP >> 8

Example:

address = 4007

TEMP = 49152 + 4007 = 53159 = 0xCFA7

CV18 = 0xA7 = 167

CV17 = 0xCF = 207

read cv


```
Read CV
unknown
    65830.9ms
<D0> 0xef 0b11101111 <- OPC_PROG
<D1> 0x0e 0b00001110 <- Message Length
<D2> 0x7c 0b01111100 <- Special programming slot number
<D3> 0x2b 0b00101011 <- PCMD

d7 0
d6 0 - read
d5 1 - byte mode
d4 0 - TV1
d3 1 - TV0
d2 0 - service mode on programming track
d1 1 - unknown
d0 1  - unknown

Direct mode byte read on service track
```

```
<D4> 0x00 0b00000000 - 0x00
<D5> 0x00 0b00000000 - HOPSA - Ops mode programming - 7 high address bits of Loco to pro
<D6> 0x0e 0b00001110 - LOPSA - Ops Mode programming - 7 low address bits of loco to prog
<D7> 0x00 0b00000000 - TRK - normal track status for command station - this doesn't look
<D8> 0x00 0b00000000 - CVH
<D9> 0x00 0b00000000 - CVL
<D10> 0x0f 0b00001111 - DATA
<D11> 0x6d 0b01101101 - Throttle serial number
<D12> 0x52 0b01010010 - Throttle serial number
<D13> 0x77 0b01110111

response
     1722.5ms
<D0> 0xe7 0b11100111 <- Opcode
<D1> 0x0e 0b00001110 <- length
<D2> 0x7c 0b01111100 <- Programming slot
<D3> 0x2b 0b00101011 <- PCMD
<D4> 0x00 0b00000000 <- PSTAT - success
<D5> 0x00 0b00000000 <- HOPSA
<D6> 0x02 0b00000010 <- LOPSA should be 0
<D7> 0x47 0b01000111 <- TRK
<D8> 0x02 0b00000010 <- CVH : 0, 0, CV9, CV8, 0, 0, D7, CV7
<D9> 0x04 0b00000100 <- CVL - CV5
<D10> 0x16 0b00010110  <- low 7 bits of value
<D11> 0x6d 0b01101101 <- SN
<D12> 0x52 0b01010010  <- SN
<D13> 0x2b 0b00101011 <- CHK
```

value displayed is 150 10010110

PCMD

d7   0
d6   1 = write, 0 = read
d5   1 = byte operation, 0 = bit operation (if possible)
d4   TV1
d3   TV0
d2   1 = Ops mode on mainlines, 0 = service mode on programming track
d1   0 - reserved
d0   0 - reserved

Byte Mode	Ops Mode	TV1	TV0	Meaning
1	0	0	0	Paged mode byte read/write on service track
1	0	0	1	Direct mode byte read/write on service track
0	0	0	1	Direct mode bit read/write on service track
×	0	1	0	Physical register byte read/write on service track
×	0	1	1	Service track reserved function
1	1	0	0	Ops mode byte program no feedback
1	1	0	1	Ops mode byte program with feedback
0	1	0	0	Ops mode bit program no feedback
0	1	0	1	Ops mode bit program with feedback

```
ack
<D0> 0xb4 0b10110100
<D1> 0x6f 0b01101111
<D2> 0x01 0b00000001
<D3> 0x25 0b00100101

unknown
    1731.6ms <D0> 0xe7 0b11100111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x2b 0b00101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x02 0b00000010
<D7> 0x47 0b01000111
<D8> 0x00 0b00000000
<D9> 0x00 0b00000000
<D10> 0x0f 0b00001111
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x34 0b00110100

ack
      10.6ms <D0> 0xb4 0b10110100
<D1> 0x3b 0b00111011
<D2> 0x00 0b00000000
<D3> 0x70 0b01110000

Read CV 2
unknown
```

```
    6772.5ms <D0> 0xef 0b11101111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x2b 0b00101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x0e 0b00001110
<D7> 0x00 0b00000000
<D8> 0x00 0b00000000
<D9> 0x01 0b00000001
<D10> 0x0f 0b00001111
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x76 0b01110110


ack
      15.5ms <D0> 0xb4 0b10110100
<D1> 0x6f 0b01101111
<D2> 0x01 0b00000001
<D3> 0x25 0b00100101


unknown
    1720.8ms <D0> 0xe7 0b11100111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x2b 0b00101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x02 0b00000010
<D7> 0x47 0b01000111
<D8> 0x00 0b00000000
<D9> 0x01 0b00000001
<D10> 0x07 0b00000111
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x3d 0b00111101


------------------- CV2
unknown
   11836.0ms <D0> 0xef 0b11101111
<D1> 0x0e 0b00001110
```

```
<D2> 0x7c 0b01111100
<D3> 0x2b 0b00101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x0e 0b00001110
<D7> 0x00 0b00000000
<D8> 0x00 0b00000000
<D9> 0x01 0b00000001
<D10> 0x07 0b00000111
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x7e 0b01111110


ack
        6.1ms <D0> 0xb4 0b10110100
<D1> 0x6f 0b01101111
<D2> 0x01 0b00000001
<D3> 0x25 0b00100101


unknown
    1730.2ms <D0> 0xe7 0b11100111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x2b 0b00101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x02 0b00000010
<D7> 0x47 0b01000111
<D8> 0x00 0b00000000
<D9> 0x01 0b00000001
<D10> 0x07 0b00000111
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x3d 0b00111101


<- failure nothing on prog track

<D0> 0xe7 0b11100111 <- opcode
<D1> 0x0e 0b00001110 <- length
<D2> 0x7c 0b01111100  <- prog slot
<D3> 0x2b 0b00101011 <- PCMD
```

```
<D4> 0x01 0b00000001 <- PSTAT
<D5> 0x00 0b00000000
<D6> 0x01 0b00000001
<D7> 0x47 0b01000111
<D8> 0x02 0b00000010
<D9> 0x04 0b00000100
<D10> 0x16 0b00010110
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x29 0b00101001

PSTAT

d7 0 - reserved
d6 0 - reserved
d5 0 - reserved
d4 0 - reserved
d3 1 = user aborted command
d2 1 = failed to detect read compare ack from decoder
d1 1 = no write ack from decoder
d0 - 1 = service mode programming track empty - no decoder detected


-----> write 150 to CV5

unknown
    7846.9ms

<D0> 0xef 0b11101111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x6b 0b01101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x0e 0b00001110
<D7> 0x00 0b00000000
<D8> 0x02 0b00000010
<D9> 0x04 0b00000100
<D10> 0x16 0b00010110
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
```

```
<D13> 0x28 0b00101000

ack
       4.6ms
<D0> 0xb4 0b10110100
<D1> 0x6f 0b01101111
<D2> 0x01 0b00000001
<D3> 0x25 0b00100101

unknown
     894.9ms
<D0> 0xe7 0b11100111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x6b 0b01101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x02 0b00000010
<D7> 0x47 0b01000111
<D8> 0x02 0b00000010
<D9> 0x04 0b00000100
<D10> 0x16 0b00010110
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x6b 0b01101011

---> write 150 to CV5 nothing on prog track

unknown
   11349.0ms <D0> 0xef 0b11101111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x6b 0b01101011
<D4> 0x00 0b00000000
<D5> 0x00 0b00000000
<D6> 0x0e 0b00001110
<D7> 0x00 0b00000000
<D8> 0x02 0b00000010
<D9> 0x04 0b00000100
<D10> 0x16 0b00010110
<D11> 0x6d 0b01101101
```

```
<D12> 0x52 0b01010010
<D13> 0x28 0b00101000

ack
        6.0ms <D0> 0xb4 0b10110100
<D1> 0x6f 0b01101111
<D2> 0x01 0b00000001
<D3> 0x25 0b00100101

unknown
     723.9ms <D0> 0xe7 0b11100111
<D1> 0x0e 0b00001110
<D2> 0x7c 0b01111100
<D3> 0x6b 0b01101011
<D4> 0x01 0b00000001
<D5> 0x00 0b00000000
<D6> 0x02 0b00000010
<D7> 0x47 0b01000111
<D8> 0x02 0b00000010
<D9> 0x04 0b00000100
<D10> 0x16 0b00010110
<D11> 0x6d 0b01101101
<D12> 0x52 0b01010010
<D13> 0x6a 0b01101010
```

4.3   List of all supported CVs

CV	Name	Description	Range	Value
1	Loco address	Address of engine (For Multiprotocol decoders: Range 1-255 for Motorola)	1 - 127	3
2	Start voltage	Sets the minimum speed of the engine	1 - 255	3
3	Acceleration	This value multiplied by 0.25 is the time from stop to maximum speed. For LokSound 5 DCC: The unit is 0.896 seconds	0 - 255	28
4	Deceleration	This value multiplied by 0.25 is the time from maximum speed to stop. For LokSound 5 DCC: The unit is 0.896 seconds	0 - 255	21
5	Maximum speed	Maximum speed of the engine	0 - 255	255
6	Medium speed	Medium speed of the engine. Use only if 3-point speed table is enabled. For LokSound 5 DCC only.		
7	Version number	Internal software version of decoder	-	-
8	Manufacturer's ID	Manufacturers's ID ESU - Writing value 8 in this CV triggers a reset to factory default values	151	-
9	Motor PWM Frequenz	Motor PWM frequency as a multiple of 1000 Hz.	10 - 50	40
13	Analog Modus F1-F8	Status of functions F1 to F8 in analogue mode (see chapter 12.7)	0-255	1
14	Analog Modus FL, F9-F15	Status of function F0, F9 to F12 in analogue mode (see chapter 12.7)	0-63	1
15 & 16	Decoder Lock	Decoder-Lock Function according to NMRA. For details please see: http://www.nmra.org/standards/DCC/WGpublic/0305051/0305051.html	0 - 255	0
17 & 18	Long address of the loco	Long address of engine (see chapter 9.2)	128 - 9999	192
19	Consist Address	Additional address for consist operation. Value 0 or 128 means: consist address is disabled. 1 – 127 consist address active, normal direction. 129 – 255 consist address active reverse direction.	0-255	0
21	Consist Mode F1-F8	Status of functions F1 to F8 in Consist mode. Meaning of the bits as in CV 13	0-255	0
22	Consist Mode FL, F9-F12	Status of functions FL, F9 to F12 in Consist mode. Meaning of the bits as in CV 14.	0-63	0
23	Adjust Acceleration	Factor for adjusting Acceleration CV 3. Values from 0 to 127 are added to CV 3. If the values are to be subtracted, additionally set bit 7 (value 128). The unit is 0.896 seconds.	0 - 127	0

CV	Name	Description	Range	Value
24	Adjust Deceleration	Factor for adjusting the deceleration CV 4. Values from 0 to 127 are added to CV 3. If the values are to be subtracted, additionally set bit 7 (value 128). The unit is 0.896 seconds.	0 - 127	0
27	Brake mode	Allowed (enabled) Brake modes 28		

Bit	Function	Value
0	ABC braking, voltage higher on the right hand side	1
1	ABC braking, voltage higher on the left hand side	2
2	ZIMO® HLU brakes active	4
3	Brake on DC, if polarity against driving direction	8
4	Brake on DC, if polarity like driving direction	16
5	Selectrix brake diode, brakes if polarity is against driving direction	32
6	Selectrix brake diode, rakes if polarity is like driving direction	64
7	Loco brakes with constant brake distance if Speed=0	128
-	28	

CV	Name	Description	Range	Value
28	RailCom® Configuration	Settings for RailCom®	131	

Bit	Function	Value
0	Channel 1 Address broadcast enabled	1
1	Data transmission allowed on Channel	2
7	RailCom® Plus automatic loco recognition active	128

CV	Name	Description		
29	Configuration register	This register contains important information, some of which are only relevant for DCC operation.		

Bit	Function	Value
0	Normal direction of travel	0
	Reversed direction of travel	1
1	14 speed steps DCC	0
	28 or 128 speed steps DCC	2
2	Disable analog operation	0
	Enable analog operation	4
3	Disable RailCom®	0
	Enable RailCom®	8
4	Speed curve through CV 2, 5, 6 (LokSound 5 DCC ONLY).	0
	Speed curve through CV 67 - 94 (Multiprotocol)	16
5	Short addresses (CV 1) in DCC mode	0
	Long addresses (CV 17 + 18) in DCC mode	32

CV	Name	Description	Range	Value
31	Index Register H	Selection page for CV257-512. For LokSound 5 usually set to 16	16	16
32	Index Register L	Selection page for CV257-512	0 - 16	0
47	Protocol selection	Which protocols are active. Please see chapter 9.5.	0 - 255	13

Bit	Function	Value
0	DCC protocol active	1
1	M4 protocol active (Not for LokSound 5 DCC)	2
2	Motorola® protocol active (Not for LokSound 5 DCC)	4
3	Selectrix® protocol active (Not for LokSound 5 DCC)	8

CV	Name	Description	Range	Value
49	Extended Configuration #1		0-255	19

Bit	Function
0	Disable Load control (Back-EMF)
	Enable Load control (Back-EMF)
1	Reserved
2	Reserved
3	Märklin® Consecutive addresses, "low"-Bit
4	Automatic DCC speed step detection
	Disable DCC speed step detection
	Enable DCC speed step detection
5	LGB® function button mode
	Disable LGB® function button mode
	Enable LGB® function button mode
6	Reserved
7	Märklin® Consecutive addresses, "High"-Bit. Please consider chapte

CV	Name	Description	Range	Value
50	Analogue mode Selection of allowed analogue modes		0 - 3	3

Bit	Function	Value
0	AC Analogue Mode	
	Disable AC Analog Mode	0
	Enable AC Analog Mode	1
1	DC Analogue mode	
	Disable DC Analogue mode	0
	Enable DC Analogue Mode	2
2	QSI Quantum Engineer DC Support	
	Disable QSI Quantum Engineer Support	0
	Enable QSI Quantum Engineer Support	4

CV	Name	Description	Range	Value
51	K Slow Cut-off	Inernal Speedstep, until K Slow is active	0 - 255	10
52	BEMF Param. K Slow "K" -	Portion of the PI-Controller valid for lower speed steps	0 - 255	10
53	Control Reference voltage	Defines the Back EMF voltage, which the motor should generate at maximum speed. The higher the efficiency of the motor, the higher this value may be set. If the engine does not reach maximum speed, reduce this parameter	0 - 255	130
54	Load control Parameter K	K–component of the internal PI-controller. Defines the effect of load control. The higher the value, the stronger the effect of Back EMF control.	0 - 255	50
55	Load control Parameter I	I–component of the internal PI-controller. Defines the momentum (inertia) of the motor. The higher the momentum of the motor (large flywheel or bigger motor), the lower this value has to be set.	0 - 255	100
56	BEMF Influence at VMin	0-100%. Defines the "Strengh" of the BEMF at minimum speed step	1 - 255	255
57	Steam chuff synchronisation #1	Defines the steam chuff synchronisation. See chapter 13.3.	1 - 255	30
58	Steam chuff synchronisation #2	Defines the steam chuff synchronisation. See chapter 13.3.	1 - 255	20
63	Sound volume "Master"	Master volume for all sounds.	0 - 192	128
64	Brake sound threshold "Brake On"	If the actual loco speed step is smaller than or equals the value indicated here, the brake sound is triggered. Compare chapter 13.4.	0 - 255	60

CV	Name	Description	Range	Value
65	Brake sound threshold "Brake Off"	If the actual loco speed step is smaller than the one indicated here (up to 255), the brake sound will be switched off again. Compare chapter 13.4.	0 - 255	7
66	Forward Trimm	Divided by 128 is the factor used to multiply the motor voltage when driving forward. The value 0 deactivates the trim.	0 - 255	128
67-94	Speed table	Defines motor voltage for speed steps. The values "in between" will be interpolated.	0 - 255	-
95	Reverse Trimm	Divided by 128 is the factor used to multiply the motor voltage when driving backwards. Value 0 deactivates the trim.	0 - 255	128
101	Shunting Mode Trimm	Divided by 128, this gives the factor by which the motor voltage is multiplied when the shunting gear is active. See section 10.1.2.	0 - 128	64
102	Brake Mode Exit Delay	Time as a multiple of 16 milliseconds that must pass before a detected braking distance is left again. See section 10.4.6.	0 - 255	12
103	Load adjustment "Optional Load"	Divided by 128, this gives the factor that changes CV3, CV4 and the sound when "Optional Load" is active. See section 10.7.	0 - 255	0
104	Load adjustment "Primary Load"	Divided by 128, this gives the factor that changes CV3, CV4 and the sound when "Primary Load" is active. See section 10.7.	0 - 255	255
105	User CV #1	Free CV. Here you are able to save what ever you want.	0 - 255	0
106	User CV #2	Free CV. Here you are able to save what ever you want.	0 - 255	0
111	Gearbox backlash	Time as a multiple of 16 mS, for which the motor runs at minimum speed after reversing the direction to prevent gear box jerking.	0 - 255	0
112	Frequency for Flashing light effects	Flashing frequency for Strobe lighting effects. Multiple of 0.065536 seconds. See section 12.5.4.	0 - 255	20
113	Power Fail Bypass	The time that the decoder bridges via the PowerPack after an interruption of voltage. Unit: A multiple of 0.032768 sec. See section 6.12.2.	0 - 255	32
116	Slow speed BEMF Sampling period	Frequency of BEMF measurement in 0.1 milliseconds at speed step 1	50 - 200	50
117	Full speed BEMF Sampling period	Frequency of BEMF measurement in 0.1 milliseconds at speed step 255	50 - 200	150

CV	Name	Description	Range	Value
118	Slow speed BEMF	Measurement gap length VMin Length of the BEMF measuring gap in 0.1 milliseconds at speed step 1	10 - 20	150
119	Full speed BEMF	Measurement gap length Vmax Length of the BEMF measuring gap in 0.1 milliseconds at speed step 255	10 - 20	15
123	ABC Mode "Slow drive"	Speed which is valid in the slow driving section during ABC braking.	0	-
124	Extended Configuration #2	Additional important settings for decoders		21

Bit	Description	Value
0	Bi-directional bit: Keep driving direction when changing direction.	1
	Do not keep driving direction.	0
1	Disable decoder lock with CV 15 / 16	0
	Enable decoder lock with CV 15 / 16	2
2	Disable prime mover startup delay	0
	Enable prime mover startup delay	4
3	Disable SUSI protocol	0
	Enable SUSI protocol	8
4	Enable Output AUX9 (LokSound 5 H0 only)	0
	Enable Wheel Sensor input (LokSound 5 H0 only)	16
5	Motor Overload Protection	
	Motor is not switched off when blocked.	0
	Motor is switched off for a few seconds when blocked to avoid burnout	32
6	Disable Automatic parking Brake	0
	Enable Automatic parking Brake (EMK Braking)	64
7	Reserved	128

CV	Name	Description	Range	Value
125	Start voltage	Analog DC See section 10.8.	0 - 255	90
126	Maximum speed	Analog DC See section 10.8.	0 - 255	130
127	Start voltage	Analog AC See section 10.8.	0 - 255	90
128	Maximum speed	Analog AC See section 10.8.	0 - 255	130
129	Analog Functions	"Hysterese" Offset voltage for functions in analogue mode. Chapter 10.8.	0 - 255	15
130	Analog Motor	"Hysterese" Offset voltage for motor functions in analogue mode. Chapter 10.8.	0 - 255	5
132	Grade Crossing Hold Time	Grade Crossing holding time. See chapter 12.5.3.	0 - 255	80
133	Sound Fader	Volume when sound fader is active. See chapter 13.5.	0 - 255	128
134	ABC-Mode "Sensibility"	Threshold, from which asymmentry on ABC shall be recognised.	4 - 32	10

CV	Name	Description	Range	Value
138	Smoke Unit Trim Fan	Divided by 128, this gives the factor by which the fan speed of synchronized smoke units can be adjusted.	0 - 255	128
139	Smoke Unit Trim Temperature	Divided by 128, this gives the factor by which the temperature of synchronized smoke units can be adjusted.	0 - 255	128
140	Smoke Time-Out	Time until automatic shutdown of the smoke unit.	0 - 255	255
141	Smoke Chuff Min	Minimum duration of a steam chuff of an external smoke unit in 0.041 seconds resolution.	0 - 255	10
142	Smoke Chuff max	Maximum duration of a steam chuff of an external smoke unit in 0.041 seconds resolution.	0 - 255	125
143	Smoke Chuff Length	Divided by 128, this gives the factor by which the duration of the steam chuffs can be adjusted relative to the trigger pulses.	0 - 255	100
144	Smoke Pre Heat Temperature	Preheating temperature in degrees Celsius for secondary smoke generators (cylinder smoke unit)	0 - 255	150
149	ABC Shuttle Train Holdtimet	Time in seconds, which has to be passed for ABC shuttle train operation, before the direction of travel is changed. See section 10.4.4.3.	0 - 255	255
150	HLU Speedlimit 1	HLU Speed limit 1. Internal speedstep.	0 - 255	42
151	HLU Speedlimit 2	(U) HLU Speed limit 2 (U). Internal speedstep.	0 - 255	85
152	HLU Speedlimit 3	HLU Speed limit 3. Internal speedstep.	0 - 255	127
153	HLU Speedlimit 4	(L) HLU Speed limit 4 (L). Internal speedstep.	0 - 255	170
154	HLU Speedlimit 5	HLU Speed limit 5. Internal speedstep.	0 - 255	212
155 -170	Sound CV 1 - Sound CV 16	16 CVs for selecting sounds that can be assigned within sound projects. Please note the documentation for the sound project.	0 - 255	0
179	Brake Function 1	Deceleration Value of which 33% of CV 4 will be deducted if the Brake Function 1 is active. See section 10.6.	0 - 255	80
180	Brake Function 2	Deceleration Value of which 33% of CV 4 will be deducted if the Brake Function 2 is active. See section 10.6.	0 - 255	40
181	Brake Function 3	Deceleration Value of which 33% of CV 4 will be deducted if the Brake Function 3 is active. See section 10.6.	0 - 255	40
182	Brake Function 1 max.	Speed Highest speed step that can be reached when Brake function 1 is active.	0 - 126	0

CV	Name	Description	Range	Value
183	Brake Function 2 max.	Speed Highest speed step that can be reached when Brake function 1 is active.	0 - 126	126
184	Brake Function 3 max.	Speed Highest speed step that can be reached when Brake function 1 is active.	0 - 126	126
246	Automatic decoupling Driving speed	Speed of the loco while decoupling; the higher the value, the faster the loco. Value 0 switches the automatic coupler off. Automatic decoupling is only active if the function output is adjusted to "pulse" or "coupler".	0 - 255	0
247	Decoupling - Removing time	This value multiplied with 0.016 defines the time the loco needs for moving away from the train (automatic decoupling).	0 – 255	0
248	Decoupling - Pushing time	This value multiplied with 0.016 defines the time the loco needs for pushing against the train (automatic decoupling).	0 – 255	0
249	Minimum steam chuff distance	Minimum distance of two steam chuffs, independant from sensor data. Compage chapter 13.3.	0 – 255	0
250	Secondary steam chuff trigger	Defines the distance between two consecutive steam chuffs for the secondary steam chuff generator. The value indicates the promilles the steam chuff distances of the secondary steam chuff generator ought to be shorter then those of the primary steam chuff generator. It is needed.for steam locos with two independent boogies, such as "Big Boy" or "Mallet".	0 – 255	0
253	Constant brake mode	Determines the constant brake mode. Only active, if CV254 > 0 Function CV 253 = 0: Decoder stops linearly CV 253 > 0: Decoder stops constantly linear	0 – 255	0
254	Constant braking distance forward	A value > 0 determines the way of brake distance it adheres to, independent from speed.	0 – 255	0
255	Constant braking distance backward	Constant braking distances during reverse driving. Only active, if value > 0, otherwise the value of CV 254 is used. Useful for reversible trains.	0 – 255	0

Appendix A

Reference Tables

LSD	MSD	0 000	1 001	2 010	3 011	4 100	5 101	6 110	7 111
0	0000	NUL	DLE	SPC	0	@	P	'	p
1	0000	SOH	DC1	!	1	A	Q	a	q
2	0010	STX	DC2	"	2	B	R	b	r
3	0011	ETX	DC3	#	3	C	S	c	s
4	0100	EOT	DC4	$	4	D	T	d	t
5	0101	ENG	NAK	%	5	E	U	e	u
6	0110	ACK	SYN	&	6	F	V	f	v
7	0111	BEL	ETB	'	7	G	W	g	w
8	1000	BS	CAN	(	8	H	X	h	x
9	1001	HT	EM	)	9	I	Y	i	y
A	1010	LF	SUB	*	:	J	Z	j	z
B	1011	VT	ESC	+	;	K	[	k	{
C	1100	FF	FS	,	<	L	\	l	|
D	1101	CR	GS	-	=	M	]	m	}
E	1110	SO	RS	.	>	N	^	n	~
F	1111	SI	US	/	?	O	_	o	DEL

TABLE A-1. ASCII Character Set (7-Bit Code)