One ROM

One ROM Chip Compatibility

This document shows which chips each One ROM Fire hardware variant emulates.

One ROM firmware v0.8.1

8 November 2026

Built from one-rom 1b189260 · source `docs/COMPATIBILITY.md`

Copyright © 2026 Piers Finlayson <piers@piers.rocks> · MIT licence

https://onerom.org

Contents

24-pin boards 3
28-pin boards 4
32-pin boards 6
40-pin boards 8
Per-board details 10
One ROM Fire 24 (rev A/A2) — fire-24-a 10
One ROM Fire 24 (rev B) — fire-24-usb-b 11
One ROM Fire 24 (rev C) — fire-24-c 12
One ROM Fire 24 (rev D) — fire-24-d 13
One ROM Fire 24 (rev E) — fire-24-e 14
One ROM Fire 24 (rev F) — fire-24-f 15
One ROM Fire 24 (rev G) — fire-24-g 16
One ROM Fire 28 (rev A/A2/A3/A4) 17
One ROM Fire 28 (rev B) — fire-28-b 19
One ROM Fire 28 (rev C) — fire-28-c 20
One ROM Fire 28 (rev D) — fire-28-d 22
One ROM Fire 32 (rev A) — fire-32-a 24
One ROM Fire 32 (rev B) — fire-32-b 26
One ROM Fire 32 (rev C) — fire-32-c 28
One ROM Fire 40 (rev A) — fire-40-a 30
One ROM Fire 40 (rev B) — fire-40-b 30
One ROM Fire 40 (rev C) — fire-40-c 31

© 2026 Piers Finlayson · onerom.org · MIT licence

This document shows which chips each One ROM Fire hardware variant emulates.

ROM size is the chip's actual storage capacity.

Image size is the space used on One ROM device's internal flash to emulate that chip. This can be larger than the original ROM itself, due to the way One ROM works.

One ROM typically has a 2MB flash, with 64KB reserved for the firmware and metadata. The remainder is available for ROM images. The total number of images that can be supported is based on the image size of each ROM.

Some lower pin count ROMs can be emulated by larger One ROMs, by inserting the larger One ROM in the smaller socket, with the top pins (1, 2, ...) hanging out (and it is not necessary to solder these pins to One ROM if using like this). If doing this, it is *extremely* important that power is rerouted to One ROM's VCC pin, or to the 5V header pin, or One ROM may be damaged.

Some greater pin count ROMs can be emulated by a smaller One ROM, provided the ROM's extra address pins fall on socket positions that One ROM does not use. In this case, the smaller One ROM gets installed to the bottom of the larger socket, with the top pins of the socket unpopulated. A short fly-lead must be run from each additional address pin of those socket pins to the X1 (and, if two are needed, X2) header pin on One ROM.

Every image size below assumes One ROM monitors all of the chip's control lines — every chip select, or /CE and /OE — which is what the tools produce unless told otherwise. A chip that One ROM can only serve with one of those lines left unmonitored is shown as unsupported here, because doing that requires the `allow_cs_ignore` config option and cannot be expressed on the `onerom` command line at all.

Cell	Meaning
64KB	Image size of a chip this board supports
64KB*	Supported with One ROM overhanging the socket (top pins exposed — power reroute required)
64KB†	Supported with fly-lead wire(s) from the chip socket's address pin(s) to One ROM's X1 (and X2) header pin
–	Not supported on this board

24-pin boards

24-pin chips (native)

Chip	ROM size	24A	24B	24C	24D	24E	24F	24G
2704	512B	2KB	2KB	512B	512B	512B	512B	512B
HM7641	512B	2KB	2KB	512B	512B	512B	512B	512B
2708	1KB	4KB	4KB	1KB	1KB	1KB	1KB	1KB
2316	2KB	32KB	32KB	2KB	2KB	2KB	2KB	2KB
2716	2KB	32KB	32KB	2KB	2KB	2KB	2KB	2KB
28C16	2KB	32KB	32KB	2KB	2KB	2KB	2KB	2KB
9316	2KB	32KB	32KB	2KB	2KB	2KB	2KB	2KB

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	24A	24B	24C	24D	24E	24F	24G
9316A	2KB	32KB	32KB	2KB	2KB	2KB	2KB	2KB
2332	4KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
2732	4KB	32KB	32KB	4KB	4KB	4KB	4KB	4KB
27C32	4KB	32KB	32KB	4KB	4KB	4KB	4KB	4KB
4732	4KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
9332	4KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
2364	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
4764	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
MCM68364	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
MCM68764	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
MCM68A364	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
MCM68A764	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
MK36000	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB
MM52164	8KB	64KB	64KB	8KB	8KB	8KB	8KB	8KB

28-pin chips (with fly-leads)

Chip	ROM size	24A	24B	24C	24D	24E	24F	24G
2764	8KB	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†
27C64	8KB	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†
27LC64	8KB	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†
28C64	8KB	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†	32KB†

28-pin boards

28-pin chips (native)

Chip	ROM size	28A	28B	28C	28D
2764	8KB	32KB	32KB	32KB	32KB
27C64	8KB	32KB	32KB	32KB	32KB
27LC64	8KB	32KB	32KB	32KB	32KB
28C64	8KB	32KB	32KB	32KB	32KB
23128	16KB	32KB	32KB	32KB	32KB
27128	16KB	32KB	32KB	32KB	32KB
27C128	16KB	32KB	32KB	32KB	32KB

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	28A	28B	28C	28D
27LC128	16KB	32KB	32KB	32KB	32KB
HN613128P	16KB	32KB	32KB	32KB	32KB
23256	32KB	64KB	64KB	64KB	64KB
27256	32KB	64KB	64KB	64KB	64KB
27C256	32KB	64KB	64KB	64KB	64KB
27LC256	32KB	64KB	64KB	64KB	64KB
27SF256	32KB	64KB	64KB	64KB	64KB
28C256	32KB	32KB	32KB	32KB	32KB
23QL384	48KB	128KB	128KB	256KB	256KB
23512	64KB	64KB	64KB	64KB	64KB
23QL512	64KB	128KB	128KB	256KB	256KB
27512	64KB	64KB	64KB	64KB	64KB
27C512	64KB	64KB	64KB	64KB	64KB
27LC512	64KB	64KB	64KB	64KB	64KB
27SF512	64KB	64KB	64KB	64KB	64KB
231024	128KB	256KB	256KB	128KB	128KB
23C1000	128KB	256KB	256KB	128KB	128KB
23C1000A	128KB	256KB	256KB	128KB	128KB
MX23C1000	128KB	256KB	256KB	128KB	128KB
TC531000	128KB	256KB	256KB	128KB	128KB

24-pin chips (with overhang)

Chip	ROM size	28A	28B	28C	28D
2704	512B	4KB*	4KB*	4KB*	4KB*
HM7641	512B	-	-	4KB*	4KB*
2708	1KB	16KB*	16KB*	8KB*	8KB*
2716	2KB	32KB*	32KB*	32KB*	32KB*
28C16	2KB	32KB*	32KB*	32KB*	32KB*
2732	4KB	32KB*	32KB*	32KB*	32KB*
27C32	4KB	32KB*	32KB*	32KB*	32KB*
2364	8KB	128KB*	128KB*	256KB*	256KB*
4764	8KB	128KB*	128KB*	256KB*	256KB*
MCM68364	8KB	128KB*	128KB*	256KB*	256KB*

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	28A	28B	28C	28D
MCM68764	8KB	128KB*	128KB*	256KB*	256KB*
MCM68A364	8KB	128KB*	128KB*	256KB*	256KB*
MCM68A764	8KB	128KB*	128KB*	256KB*	256KB*
MK36000	8KB	128KB*	128KB*	256KB*	256KB*
MM52164	8KB	128KB*	128KB*	256KB*	256KB*

32-pin chips (with fly-leads)

Chip	ROM size	28A	28B	28C	28D
28C512	64KB	64KB†	64KB†	64KB†	64KB†
23C1010	128KB	-	-	128KB†	128KB†
27C010	128KB	-	-	128KB†	128KB†
27C1000A	128KB	-	-	128KB†	128KB†
27C1001	128KB	-	-	128KB†	128KB†
29F010	128KB	-	-	128KB†	128KB†
39SF010	128KB	-	-	128KB†	128KB†
SST39SF010	128KB	-	-	128KB†	128KB†

32-pin boards

32-pin chips (native)

Chip	ROM size	32A	32B	32C
28C512	64KB	256KB	64KB	64KB
23C1001	128KB	-	128KB	128KB
23C1010	128KB	512KB	128KB	128KB
27C010	128KB	512KB	128KB	128KB
27C100	128KB	512KB	256KB	256KB
27C1000	128KB	512KB	256KB	256KB
27C1000A	128KB	512KB	128KB	128KB
27C1001	128KB	512KB	128KB	128KB
27C301	128KB	512KB	256KB	256KB
29F010	128KB	512KB	128KB	128KB
39SF010	128KB	512KB	128KB	128KB
D23C1001	128KB	-	128KB	128KB

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	32A	32B	32C
SST39SF010	128KB	512KB	128KB	128KB
27C020	256KB	512KB	256KB	256KB
27C2001	256KB	512KB	256KB	256KB
29F020	256KB	512KB	256KB	256KB
39SF020	256KB	512KB	256KB	256KB
SST39SF020	256KB	512KB	256KB	256KB
27C040	512KB	512KB	512KB	512KB
27C4001	512KB	512KB	512KB	512KB
29F040	512KB	-	512KB	512KB
39SF040	512KB	-	512KB	512KB
SST39SF040	512KB	-	512KB	512KB
27C080	1MB	512KB	512KB	512KB
27C801	1MB	512KB	512KB	512KB

28-pin chips (with overhang)

Chip	ROM size	32A	32B	32C
2764	8KB	256KB*	32KB*	32KB*
27C64	8KB	256KB*	32KB*	32KB*
27LC64	8KB	256KB*	32KB*	32KB*
28C64	8KB	256KB*	32KB*	32KB*
27128	16KB	256KB*	32KB*	32KB*
27C128	16KB	256KB*	32KB*	32KB*
27LC128	16KB	256KB*	32KB*	32KB*
23256	32KB	256KB*	32KB*	32KB*
27256	32KB	256KB*	32KB*	32KB*
27C256	32KB	256KB*	32KB*	32KB*
27LC256	32KB	256KB*	32KB*	32KB*
27SF256	32KB	256KB*	32KB*	32KB*
28C256	32KB	256KB*	64KB*	64KB*
23512	64KB	256KB*	64KB*	64KB*
27512	64KB	256KB*	64KB*	64KB*
27C512	64KB	256KB*	64KB*	64KB*
27LC512	64KB	256KB*	64KB*	64KB*

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	32A	32B	32C
27SF512	64KB	256KB*	64KB*	64KB*
231024	128KB	512KB*	256KB*	256KB*
23C1000	128KB	512KB*	256KB*	256KB*
23C1000A	128KB	512KB*	256KB*	256KB*
MX23C1000	128KB	512KB*	256KB*	256KB*
TC531000	128KB	512KB*	256KB*	256KB*

24-pin chips (with overhang)

Chip	ROM size	32A	32B	32C
2704	512B	32KB*	4KB*	4KB*
HM7641	512B	32KB*	-	-
2708	1KB	64KB*	8KB*	8KB*
2716	2KB	256KB*	32KB*	32KB*
28C16	2KB	256KB*	32KB*	32KB*
2732	4KB	256KB*	32KB*	32KB*
27C32	4KB	256KB*	32KB*	32KB*

40-pin boards

Chip	ROM size	40A	40B	40C
27C200	256KB	512KB	256KB	256KB
27C200Pin31NC	256KB	512KB	256KB	256KB
HN62402	256KB	512KB	256KB	256KB
23C4100	512KB	512KB	512KB	512KB
27C400	512KB	512KB	512KB	512KB
27C400Pin31A17	512KB	-	512KB	512KB
27C4100	512KB	512KB	512KB	512KB
AT27C400	512KB	512KB	512KB	512KB
HN62404	512KB	512KB	512KB	512KB
HN62424	512KB	512KB	512KB	512KB
M27C400	512KB	512KB	512KB	512KB
MB834200	512KB	512KB	512KB	512KB
MX23C4100	512KB	512KB	512KB	512KB

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	40A	40B	40C
MX27C4100	512KB	512KB	512KB	512KB
TCS534200	512KB	512KB	512KB	512KB

© 2026 Piers Finlayson · onerom.org · MIT licence

Per-board details

Full chip list for each board. Where a particular ROM type goes by multiple identifiers (for example 27512, 27C512, 27SF512), each type appears as a separate row.

The **Fit** column says how the chip sits in the board's socket:

Fit	Meaning
`native`	Chip and board have the same pin count — it goes straight in
`overhang`	Chip has *fewer* pins than the board, so One ROM's top pins hang out of the socket
`larger socket (no fly-leads)`	Chip has *more* pins than the board, but no address line among the extra ones: One ROM sits in the bottom of the socket with nothing to wire
`fly-lead to X1` (and `X2`)	Chip has more pins than the board, and the overhanging address line(s) must be wired to One ROM's X1 (and X2) header pin

Every fit other than `native` is a cross-size fit, and in all of them One ROM's power pins may not line up with the socket's — power must be rerouted to One ROM's own VCC or 5V header pin. `larger socket (no fly-leads)` means no *signal* wiring is needed. It doesn't mean the chip simply drops in.

One ROM Fire 24 (rev A/A2) — fire-24-a

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	2KB	native
HM7641	512B	2KB	native
2708	1KB	4KB	native
2316	2KB	32KB	native
2716	2KB	32KB	native
28C16	2KB	32KB	native
9316	2KB	32KB	native
9316A	2KB	32KB	native
2332	4KB	64KB	native
2732	4KB	32KB	native
27C32	4KB	32KB	native
4732	4KB	64KB	native
9332	4KB	64KB	native
2364	8KB	64KB	native
4764	8KB	64KB	native
MCM68364	8KB	64KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	64KB	native
MCM68A364	8KB	64KB	native
MCM68A764	8KB	64KB	native
MK36000	8KB	64KB	native
MM52164	8KB	64KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 24 (rev B) — fire-24-usb-b

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	2KB	native
HM7641	512B	2KB	native
2708	1KB	4KB	native
2316	2KB	32KB	native
2716	2KB	32KB	native
28C16	2KB	32KB	native
9316	2KB	32KB	native
9316A	2KB	32KB	native
2332	4KB	64KB	native
2732	4KB	32KB	native
27C32	4KB	32KB	native
4732	4KB	64KB	native
9332	4KB	64KB	native
2364	8KB	64KB	native
4764	8KB	64KB	native
MCM68364	8KB	64KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	64KB	native
MCM68A364	8KB	64KB	native
MCM68A764	8KB	64KB	native
MK36000	8KB	64KB	native
MM52164	8KB	64KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 24 (rev C) — fire-24-c

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	512B	native
HM7641	512B	512B	native
2708	1KB	1KB	native
2316	2KB	2KB	native
2716	2KB	2KB	native
28C16	2KB	2KB	native
9316	2KB	2KB	native
9316A	2KB	2KB	native
2332	4KB	8KB	native
2732	4KB	4KB	native
27C32	4KB	4KB	native
4732	4KB	8KB	native
9332	4KB	8KB	native
2364	8KB	8KB	native
4764	8KB	8KB	native
MCM68364	8KB	8KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	8KB	native
MCM68A364	8KB	8KB	native
MCM68A764	8KB	8KB	native
MK36000	8KB	8KB	native
MM52164	8KB	8KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 24 (rev D) — fire-24-d

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	512B	native
HM7641	512B	512B	native
2708	1KB	1KB	native
2316	2KB	2KB	native
2716	2KB	2KB	native
28C16	2KB	2KB	native
9316	2KB	2KB	native
9316A	2KB	2KB	native
2332	4KB	8KB	native
2732	4KB	4KB	native
27C32	4KB	4KB	native
4732	4KB	8KB	native
9332	4KB	8KB	native
2364	8KB	8KB	native
4764	8KB	8KB	native
MCM68364	8KB	8KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	8KB	native
MCM68A364	8KB	8KB	native
MCM68A764	8KB	8KB	native
MK36000	8KB	8KB	native
MM52164	8KB	8KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 24 (rev E) — fire-24-e

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	512B	native
HM7641	512B	512B	native
2708	1KB	1KB	native
2316	2KB	2KB	native
2716	2KB	2KB	native
28C16	2KB	2KB	native
9316	2KB	2KB	native
9316A	2KB	2KB	native
2332	4KB	8KB	native
2732	4KB	4KB	native
27C32	4KB	4KB	native
4732	4KB	8KB	native
9332	4KB	8KB	native
2364	8KB	8KB	native
4764	8KB	8KB	native
MCM68364	8KB	8KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	8KB	native
MCM68A364	8KB	8KB	native
MCM68A764	8KB	8KB	native
MK36000	8KB	8KB	native
MM52164	8KB	8KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 24 (rev F) — fire-24-f

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	512B	native
HM7641	512B	512B	native
2708	1KB	1KB	native
2316	2KB	2KB	native
2716	2KB	2KB	native
28C16	2KB	2KB	native
9316	2KB	2KB	native
9316A	2KB	2KB	native
2332	4KB	8KB	native
2732	4KB	4KB	native
27C32	4KB	4KB	native
4732	4KB	8KB	native
9332	4KB	8KB	native
2364	8KB	8KB	native
4764	8KB	8KB	native
MCM68364	8KB	8KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	8KB	native
MCM68A364	8KB	8KB	native
MCM68A764	8KB	8KB	native
MK36000	8KB	8KB	native
MM52164	8KB	8KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 24 (rev G) — fire-24-g

24-pin chips (native)

Chip	ROM size	Image size	Fit
2704	512B	512B	native
HM7641	512B	512B	native
2708	1KB	1KB	native
2316	2KB	2KB	native
2716	2KB	2KB	native
28C16	2KB	2KB	native
9316	2KB	2KB	native
9316A	2KB	2KB	native
2332	4KB	8KB	native
2732	4KB	4KB	native
27C32	4KB	4KB	native
4732	4KB	8KB	native
9332	4KB	8KB	native
2364	8KB	8KB	native
4764	8KB	8KB	native
MCM68364	8KB	8KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MCM68764	8KB	8KB	native
MCM68A364	8KB	8KB	native
MCM68A764	8KB	8KB	native
MK36000	8KB	8KB	native
MM52164	8KB	8KB	native

28-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	fly-lead to X1
27C64	8KB	32KB	fly-lead to X1
27LC64	8KB	32KB	fly-lead to X1
28C64	8KB	32KB	fly-lead to X1

One ROM Fire 28 (rev A/A2/A3/A4) — fire-28-a

28-pin chips (native)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	native
27C64	8KB	32KB	native
27LC64	8KB	32KB	native
28C64	8KB	32KB	native
23128	16KB	32KB	native
27128	16KB	32KB	native
27C128	16KB	32KB	native
27LC128	16KB	32KB	native
HN613128P	16KB	32KB	native
23256	32KB	64KB	native
27256	32KB	64KB	native
27C256	32KB	64KB	native
27LC256	32KB	64KB	native
27SF256	32KB	64KB	native
28C256	32KB	32KB	native
23QL384	48KB	128KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
23512	64KB	64KB	native
23QL512	64KB	128KB	native
27512	64KB	64KB	native
27C512	64KB	64KB	native
27LC512	64KB	64KB	native
27SF512	64KB	64KB	native
231024	128KB	256KB	native
23C1000	128KB	256KB	native
23C1000A	128KB	256KB	native
MX23C1000	128KB	256KB	native
TC531000	128KB	256KB	native

24-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2704	512B	4KB	overhang
2708	1KB	16KB	overhang
2716	2KB	32KB	overhang
28C16	2KB	32KB	overhang
2732	4KB	32KB	overhang
27C32	4KB	32KB	overhang
2364	8KB	128KB	overhang
4764	8KB	128KB	overhang
MCM68364	8KB	128KB	overhang
MCM68764	8KB	128KB	overhang
MCM68A364	8KB	128KB	overhang
MCM68A764	8KB	128KB	overhang
MK36000	8KB	128KB	overhang
MM52164	8KB	128KB	overhang

32-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
28C512	64KB	64KB	larger socket (no fly-leads)

© 2026 Piers Finlayson · onerom.org · MIT licence

One ROM Fire 28 (rev B) — fire-28-b

28-pin chips (native)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	native
27C64	8KB	32KB	native
27LC64	8KB	32KB	native
28C64	8KB	32KB	native
23128	16KB	32KB	native
27128	16KB	32KB	native
27C128	16KB	32KB	native
27LC128	16KB	32KB	native
HN613128P	16KB	32KB	native
23256	32KB	64KB	native
27256	32KB	64KB	native
27C256	32KB	64KB	native
27LC256	32KB	64KB	native
27SF256	32KB	64KB	native
28C256	32KB	32KB	native
23QL384	48KB	128KB	native
23512	64KB	64KB	native
23QL512	64KB	128KB	native
27512	64KB	64KB	native
27C512	64KB	64KB	native
27LC512	64KB	64KB	native
27SF512	64KB	64KB	native
231024	128KB	256KB	native
23C1000	128KB	256KB	native
23C1000A	128KB	256KB	native
MX23C1000	128KB	256KB	native
TC531000	128KB	256KB	native

24-pin chips (with overhang)

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
2704	512B	4KB	overhang
2708	1KB	16KB	overhang
2716	2KB	32KB	overhang
28C16	2KB	32KB	overhang
2732	4KB	32KB	overhang
27C32	4KB	32KB	overhang
2364	8KB	128KB	overhang
4764	8KB	128KB	overhang
MCM68364	8KB	128KB	overhang
MCM68764	8KB	128KB	overhang
MCM68A364	8KB	128KB	overhang
MCM68A764	8KB	128KB	overhang
MK36000	8KB	128KB	overhang
MM52164	8KB	128KB	overhang

32-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
28C512	64KB	64KB	larger socket (no fly-leads)

One ROM Fire 28 (rev C) — fire-28-c

28-pin chips (native)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	native
27C64	8KB	32KB	native
27LC64	8KB	32KB	native
28C64	8KB	32KB	native
23128	16KB	32KB	native
27128	16KB	32KB	native
27C128	16KB	32KB	native
27LC128	16KB	32KB	native
HN613128P	16KB	32KB	native
23256	32KB	64KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
27256	32KB	64KB	native
27C256	32KB	64KB	native
27LC256	32KB	64KB	native
27SF256	32KB	64KB	native
28C256	32KB	32KB	native
23QL384	48KB	256KB	native
23512	64KB	64KB	native
23QL512	64KB	256KB	native
27512	64KB	64KB	native
27C512	64KB	64KB	native
27LC512	64KB	64KB	native
27SF512	64KB	64KB	native
231024	128KB	128KB	native
23C1000	128KB	128KB	native
23C1000A	128KB	128KB	native
MX23C1000	128KB	128KB	native
TC531000	128KB	128KB	native

24-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2704	512B	4KB	overhang
HM7641	512B	4KB	overhang
2708	1KB	8KB	overhang
2716	2KB	32KB	overhang
28C16	2KB	32KB	overhang
2732	4KB	32KB	overhang
27C32	4KB	32KB	overhang
2364	8KB	256KB	overhang
4764	8KB	256KB	overhang
MCM68364	8KB	256KB	overhang
MCM68764	8KB	256KB	overhang
MCM68A364	8KB	256KB	overhang
MCM68A764	8KB	256KB	overhang

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MK36000	8KB	256KB	overhang
MM52164	8KB	256KB	overhang

32-pin chips (with fly-leads)

Chip	ROM size	Image size	Fit
28C512	64KB	64KB	larger socket (no fly-leads)
23C1010	128KB	128KB	fly-lead to X1
27C010	128KB	128KB	fly-lead to X1
27C1000A	128KB	128KB	fly-lead to X1
27C1001	128KB	128KB	fly-lead to X1
29F010	128KB	128KB	fly-lead to X1
39SF010	128KB	128KB	fly-lead to X1
SST39SF010	128KB	128KB	fly-lead to X1

One ROM Fire 28 (rev D) — fire-28-d

28-pin chips (native)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	native
27C64	8KB	32KB	native
27LC64	8KB	32KB	native
28C64	8KB	32KB	native
23128	16KB	32KB	native
27128	16KB	32KB	native
27C128	16KB	32KB	native
27LC128	16KB	32KB	native
HN613128P	16KB	32KB	native
23256	32KB	64KB	native
27256	32KB	64KB	native
27C256	32KB	64KB	native
27LC256	32KB	64KB	native
27SF256	32KB	64KB	native
28C256	32KB	32KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
23QL384	48KB	256KB	native
23512	64KB	64KB	native
23QL512	64KB	256KB	native
27512	64KB	64KB	native
27C512	64KB	64KB	native
27LC512	64KB	64KB	native
27SF512	64KB	64KB	native
231024	128KB	128KB	native
23C1000	128KB	128KB	native
23C1000A	128KB	128KB	native
MX23C1000	128KB	128KB	native
TC531000	128KB	128KB	native

24-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2704	512B	4KB	overhang
HM7641	512B	4KB	overhang
2708	1KB	8KB	overhang
2716	2KB	32KB	overhang
28C16	2KB	32KB	overhang
2732	4KB	32KB	overhang
27C32	4KB	32KB	overhang
2364	8KB	256KB	overhang
4764	8KB	256KB	overhang
MCM68364	8KB	256KB	overhang
MCM68764	8KB	256KB	overhang
MCM68A364	8KB	256KB	overhang
MCM68A764	8KB	256KB	overhang
MK36000	8KB	256KB	overhang
MM52164	8KB	256KB	overhang

32-pin chips (with fly-leads)

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
28C512	64KB	64KB	larger socket (no fly-leads)
23C1010	128KB	128KB	fly-lead to X1
27C010	128KB	128KB	fly-lead to X1
27C1000A	128KB	128KB	fly-lead to X1
27C1001	128KB	128KB	fly-lead to X1
29F010	128KB	128KB	fly-lead to X1
39SF010	128KB	128KB	fly-lead to X1
SST39SF010	128KB	128KB	fly-lead to X1

One ROM Fire 32 (rev A) — fire-32-a

32-pin chips (native)

Chip	ROM size	Image size	Fit
28C512	64KB	256KB	native
23C1010	128KB	512KB	native
27C010	128KB	512KB	native
27C100	128KB	512KB	native
27C1000	128KB	512KB	native
27C1000A	128KB	512KB	native
27C1001	128KB	512KB	native
27C301	128KB	512KB	native
29F010	128KB	512KB	native
39SF010	128KB	512KB	native
SST39SF010	128KB	512KB	native
27C020	256KB	512KB	native
27C2001	256KB	512KB	native
29F020	256KB	512KB	native
39SF020	256KB	512KB	native
SST39SF020	256KB	512KB	native
27C040	512KB	512KB	native
27C4001	512KB	512KB	native
27C080	1MB	512KB	native
27C801	1MB	512KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

28-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2764	8KB	256KB	overhang
27C64	8KB	256KB	overhang
27LC64	8KB	256KB	overhang
28C64	8KB	256KB	overhang
27128	16KB	256KB	overhang
27C128	16KB	256KB	overhang
27LC128	16KB	256KB	overhang
23256	32KB	256KB	overhang
27256	32KB	256KB	overhang
27C256	32KB	256KB	overhang
27LC256	32KB	256KB	overhang
27SF256	32KB	256KB	overhang
28C256	32KB	256KB	overhang
23512	64KB	256KB	overhang
27512	64KB	256KB	overhang
27C512	64KB	256KB	overhang
27LC512	64KB	256KB	overhang
27SF512	64KB	256KB	overhang
231024	128KB	512KB	overhang
23C1000	128KB	512KB	overhang
23C1000A	128KB	512KB	overhang
MX23C1000	128KB	512KB	overhang
TC531000	128KB	512KB	overhang

24-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2704	512B	32KB	overhang
HM7641	512B	32KB	overhang
2708	1KB	64KB	overhang
2716	2KB	256KB	overhang
28C16	2KB	256KB	overhang
2732	4KB	256KB	overhang

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
27C32	4KB	256KB	overhang

One ROM Fire 32 (rev B) — fire-32-b

32-pin chips (native)

Chip	ROM size	Image size	Fit
28C512	64KB	64KB	native
23C1001	128KB	128KB	native
23C1010	128KB	128KB	native
27C010	128KB	128KB	native
27C100	128KB	256KB	native
27C1000	128KB	256KB	native
27C1000A	128KB	128KB	native
27C1001	128KB	128KB	native
27C301	128KB	256KB	native
29F010	128KB	128KB	native
39SF010	128KB	128KB	native
D23C1001	128KB	128KB	native
SST39SF010	128KB	128KB	native
27C020	256KB	256KB	native
27C2001	256KB	256KB	native
29F020	256KB	256KB	native
39SF020	256KB	256KB	native
SST39SF020	256KB	256KB	native
27C040	512KB	512KB	native
27C4001	512KB	512KB	native
29F040	512KB	512KB	native
39SF040	512KB	512KB	native
SST39SF040	512KB	512KB	native
27C080	1MB	512KB	native
27C801	1MB	512KB	native

28-pin chips (with overhang)

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
2764	8KB	32KB	overhang
27C64	8KB	32KB	overhang
27LC64	8KB	32KB	overhang
28C64	8KB	32KB	overhang
27128	16KB	32KB	overhang
27C128	16KB	32KB	overhang
27LC128	16KB	32KB	overhang
23256	32KB	32KB	overhang
27256	32KB	32KB	overhang
27C256	32KB	32KB	overhang
27LC256	32KB	32KB	overhang
27SF256	32KB	32KB	overhang
28C256	32KB	64KB	overhang
23512	64KB	64KB	overhang
27512	64KB	64KB	overhang
27C512	64KB	64KB	overhang
27LC512	64KB	64KB	overhang
27SF512	64KB	64KB	overhang
231024	128KB	256KB	overhang
23C1000	128KB	256KB	overhang
23C1000A	128KB	256KB	overhang
MX23C1000	128KB	256KB	overhang
TC531000	128KB	256KB	overhang

24-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2704	512B	4KB	overhang
2708	1KB	8KB	overhang
2716	2KB	32KB	overhang
28C16	2KB	32KB	overhang
2732	4KB	32KB	overhang
27C32	4KB	32KB	overhang

© 2026 Piers Finlayson · onerom.org · MIT licence

One ROM Fire 32 (rev C) — fire-32-c

32-pin chips (native)

Chip	ROM size	Image size	Fit
28C512	64KB	64KB	native
23C1001	128KB	128KB	native
23C1010	128KB	128KB	native
27C010	128KB	128KB	native
27C100	128KB	256KB	native
27C1000	128KB	256KB	native
27C1000A	128KB	128KB	native
27C1001	128KB	128KB	native
27C301	128KB	256KB	native
29F010	128KB	128KB	native
39SF010	128KB	128KB	native
D23C1001	128KB	128KB	native
SST39SF010	128KB	128KB	native
27C020	256KB	256KB	native
27C2001	256KB	256KB	native
29F020	256KB	256KB	native
39SF020	256KB	256KB	native
SST39SF020	256KB	256KB	native
27C040	512KB	512KB	native
27C4001	512KB	512KB	native
29F040	512KB	512KB	native
39SF040	512KB	512KB	native
SST39SF040	512KB	512KB	native
27C080	1MB	512KB	native
27C801	1MB	512KB	native

28-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2764	8KB	32KB	overhang
27C64	8KB	32KB	overhang

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
27LC64	8KB	32KB	overhang
28C64	8KB	32KB	overhang
27128	16KB	32KB	overhang
27C128	16KB	32KB	overhang
27LC128	16KB	32KB	overhang
23256	32KB	32KB	overhang
27256	32KB	32KB	overhang
27C256	32KB	32KB	overhang
27LC256	32KB	32KB	overhang
27SF256	32KB	32KB	overhang
28C256	32KB	64KB	overhang
23512	64KB	64KB	overhang
27512	64KB	64KB	overhang
27C512	64KB	64KB	overhang
27LC512	64KB	64KB	overhang
27SF512	64KB	64KB	overhang
231024	128KB	256KB	overhang
23C1000	128KB	256KB	overhang
23C1000A	128KB	256KB	overhang
MX23C1000	128KB	256KB	overhang
TC531000	128KB	256KB	overhang

24-pin chips (with overhang)

Chip	ROM size	Image size	Fit
2704	512B	4KB	overhang
2708	1KB	8KB	overhang
2716	2KB	32KB	overhang
28C16	2KB	32KB	overhang
2732	4KB	32KB	overhang
27C32	4KB	32KB	overhang

© 2026 Piers Finlayson · onerom.org · MIT licence

One ROM Fire 40 (rev A) — fire-40-a

Chip	ROM size	Image size	Fit
27C200	256KB	512KB	native
27C200Pin31NC	256KB	512KB	native
HN62402	256KB	512KB	native
23C4100	512KB	512KB	native
27C400	512KB	512KB	native
27C4100	512KB	512KB	native
AT27C400	512KB	512KB	native
HN62404	512KB	512KB	native
HN62424	512KB	512KB	native
M27C400	512KB	512KB	native
MB834200	512KB	512KB	native
MX23C4100	512KB	512KB	native
MX27C4100	512KB	512KB	native
TCS534200	512KB	512KB	native

One ROM Fire 40 (rev B) — fire-40-b

Chip	ROM size	Image size	Fit
27C200	256KB	256KB	native
27C200Pin31NC	256KB	256KB	native
HN62402	256KB	256KB	native
23C4100	512KB	512KB	native
27C400	512KB	512KB	native
27C400Pin31A17	512KB	512KB	native
27C4100	512KB	512KB	native
AT27C400	512KB	512KB	native
HN62404	512KB	512KB	native
HN62424	512KB	512KB	native
M27C400	512KB	512KB	native
MB834200	512KB	512KB	native
MX23C4100	512KB	512KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence

Chip	ROM size	Image size	Fit
MX27C4100	512KB	512KB	native
TCS534200	512KB	512KB	native

One ROM Fire 40 (rev C) — fire-40-c

Chip	ROM size	Image size	Fit
27C200	256KB	256KB	native
27C200Pin31NC	256KB	256KB	native
HN62402	256KB	256KB	native
23C4100	512KB	512KB	native
27C400	512KB	512KB	native
27C400Pin31A17	512KB	512KB	native
27C4100	512KB	512KB	native
AT27C400	512KB	512KB	native
HN62404	512KB	512KB	native
HN62424	512KB	512KB	native
M27C400	512KB	512KB	native
MB834200	512KB	512KB	native
MX23C4100	512KB	512KB	native
MX27C4100	512KB	512KB	native
TCS534200	512KB	512KB	native

© 2026 Piers Finlayson · onerom.org · MIT licence