Faust Standard Libraries

Contents

11

Faust Libraries

NOTE: this documentation was automatically generated.

This page provides information on how to use the Faust libraries.

The `/libraries` folder contains the different Faust libraries. If you wish to add your own functions to this library collection, you can refer to the "Contributing" section providing a set of coding conventions.

WARNING: These libraries replace the "old" Faust libraries. They are still being beta tested so you might encounter bugs while using them. If your codes still use the "old" Faust libraries, you might want to try to use Bart Brouns' script that automatically makes an old Faust code compatible with the new libraries: https://github.com/magnetophon/faustCompressors/blob/master/newlib.sh. If you find a bug, please report it at rmichon_at_ccrma_dot_stanford_dot_edu. Thanks ;)!

Using the Faust Libraries

The easiest and most standard way to use the Faust libraries is to import `stdfaust.lib` in your Faust code:

```
import("stdfaust.lib");
```

This will give you access to all the Faust libraries through a series of environments:

- sf: all.lib
- an: analyzers.lib
- ba: basics.lib
- co: compressors.lib
- de: delays.lib
- dm: demos.lib
- dx: dx7.lib
- en: envelopes.lib
- fi: filters.lib
- ho: hoa.lib
- ma: maths.lib
- ef: misceffects.lib
- os: oscillators.lib
- no: noises.lib
- pf: phaflangers.lib
- pm: physmodels.lib
- re: reverbs.lib
- ro: routes.lib
- si: signals.lib
- sp: spats.lib
- sy: synths.lib
- ve: vaeffects.lib

Environments can then be used as follows in your Faust code:

```
import("stdfaust.lib");
process = os.osc(440);
```

In this case, we're calling the `osc` function from `oscillators.lib`.

You can also access all the functions of all the libraries directly using the `sf` environment:

```
import("stdfaust.lib");
process = sf.osc(440);
```

Alternatively, environments can be created by hand:

```
os = library("oscillators.lib");
process = os.osc(440);
```

Finally, libraries can be simply imported in the Faust code (not recommended):

```
import("oscillators.lib");
process = osc(440);
```

Contributing

If you wish to add a function to any of these libraries or if you plan to add a new library, make sure that you follow the following conventions:

New Functions

- All functions must be preceded by a markdown documentation header respecting the following format (open the source code of any of the libraries for an example):

```
//-----------------functionName-------------------
// Description
//
// #### Usage
//
// ```
// Usage Example
// ```
//
// Where:
//
// * argument1: argument 1 description
//---------------------------------------------
```

- Every time a new function is added, the documentation should be updated simply by running `make doclib`.
- The environment system (e.g. `os.osc`) should be used when calling a function declared in another library (see the section on *Using the Faust Libraries*).

- Try to reuse exisiting functions as much as possible.
- If you have any question, send an e-mail to rmichon_at_ccrma_dot_stanford_dot_edu.

New Libraries

- Any new "standard" library should be declared in `stdfaust.lib` with its own environment (2 letters - see `stdfaust.lib`).
- Any new "standard" library must be added to `generateDoc`.
- Functions must be organized by sections.
- Any new library should at least `declare` a `name` and a `version`.
- The comment based markdown documentation of each library must respect the following format (open the source code of any of the libraries for an example):

```
//############### libraryName #################
// Description
//
// * Section Name 1
// * Section Name 2
// * ...
//
// It should be used using the `[...]` environment:
//
// ```
// [...] = library("libraryName");
// process = [...].functionCall;
// ```
//
// Another option is to import `stdfaust.lib` which already contains the `[...]`
// environment:
//
// ```
// import("stdfaust.lib");
// process = [...].functionCall;
// ```
//#############################################

//================= Section Name ==============
// Description
//============================================
```

- If you have any question, send an e-mail to rmichon_at_ccrma_dot_stanford_dot_edu.

General Organization

Only the libraries that are considered to be "standard" are documented:

- `analyzers.lib`
- `basics.lib`
- `compressors.lib`
- `delays.lib`
- `demos.lib`
- `dx7.lib`
- `envelopes.lib`
- `filters.lib`
- `hoa.lib`
- `maths.lib`
- `misceffects.lib`
- `oscillators.lib`
- `noises.lib`
- `phaflangers.lib`
- `physmodels.lib`
- `reverbs.lib`
- `routes.lib`
- `signals.lib`
- `spats.lib`
- `synths.lib`
- `tonestacks.lib` (not documented but example in `/examples/misc`)
- `tubes.lib` (not documented but example in `/examples/misc`)
- `vaeffects.lib`

Other deprecated libraries such as `music.lib`, etc. are present but are not documented to not confuse new users.

The doumentation of each library can be found in `/documentation/library.html` or in `/documentation/library.pdf`.

The `/examples` directory contains all the examples from the `/examples` folder of the Faust distribution as well as new ones. Most of them were updated to reflect the coding conventions described in the next section. Examples are organized by types in different folders. The `/old` folder contains examples that are fully deprecated, probably because they were integrated to the libraries and fully rewritten (see `freeverb.dsp` for example). Examples using deprecated libraries were integrated to the general tree but a warning comment was added at their beginning to point readers to the right library and function.

Coding Conventions

In order to have a uniformized library system, we established the following conventions (that hopefully will be followed by others when making modifications

to them :-)).

Documentation

- All the functions that we want to be "public" are documented.
- We used the `faust2md` "standards" for each library: `//###` for main title (library name - equivalent to `#` in markdown), `//===` for section declarations (equivalent to `##` in markdown) and `//---` for function declarations (equivalent to `####` in markdown - see `basics.lib` for an example).
- Sections in function documentation should be declared as `####` markdown title.
- Each function documentation provides a "Usage" section (see `basics.lib`).

Library Import

To prevent cross-references between libraries we generalized the use of the `library("")` system for function calls in all the libraries. This means that everytime a function declared in another library is called, the environment corresponding to this library needs to be called too. To make things easier, a `stdfaust.lib` library was created and is imported by all the libraries:

```
an = library("analyzers.lib");
ba = library("basics.lib");
co = library("compressors.lib");
de = library("delays.lib");
dm = library("demos.lib");
dx = library("dx7.lib");
en = library("envelopes.lib");
fi = library("filters.lib");
ho = library("hoa.lib");
ma = library("maths.lib");
ef = library("misceffects.lib");
os = library("oscillators.lib");
no = library("noises.lib");
pf = library("phaflangers.lib");
pm = library("physmodels.lib");
re = library("reverbs.lib");
ro = library("routes.lib");
sp = library("spats.lib");
si = library("signals.lib");
sy = library("synths.lib");
ve = library("vaeffects.lib");
```

For example, if we wanted to use the `smooth` function which is now declared in `signals.lib`, we would do the following:

```
import("stdfaust.lib");

process = si.smooth(0.999);
```

This standard is only used within the libraries: nothing prevents coders to still import `signals.lib` directly and call `smooth` without `ro.`, etc.

"Demo" Functions

"Demo" functions are placed in `demos.lib` and have a built-in user interface (UI). Their name ends with the `_demo` suffix. Each of these function have a `.dsp` file associated to them in the `/examples` folder.

Any function containing UI elements should be placed in this library and respect these standards.

"Standard" Functions

"Standard" functions are here to simplify the life of new (or not so new) Faust coders. They are declared in `/libraries/doc/standardFunctions.md` and allow to point programmers to preferred functions to carry out a specific task. For example, there are many different types of lowpass filters declared in `filters.lib` and only one of them is considered to be standard, etc.

Copyright / License

Now that Faust libraries are less author specific, each function will normally have its own copyright-and-license line in the library source (the `.lib` file, such as `analyzers.lib`). If not, see if the function is defined within a section of the `.lib` file stating the license in source-code comments. If not, then the copyright and license given at the beginning of the `.lib` file may be assumed, when present. If not, run `git blame` on the `.lib` file and ask the person who last edited the function!

Note that it is presently possible for a library function released under one license to utilize another library function having some different license. There is presently no indication of this situation in the Faust compiler output, but such notice is planned. For now, library contributors should strive to use only library functions having compatible licenses, and concerned end-users must manually determine the union of licenses applicable to the library functions they are using.

Standard Functions

Dozens of functions are implemented in the Faust libraries and many of them are very specialized and not useful to beginners or to people who only need to use Faust for basic applications. This section offers an index organized by categories of the "standard Faust functions" (basic filters, effects, synthesizers, etc.). This index only contains functions without a user interface (UI). Faust functions with a built-in UI can be found in `demos.lib`.

Analysis Tools

Function Type	Function Name	Description
Amplitude Follower	`an.amp_follower`	Classic analog audio envelope follower
Octave Analyzers	`an.mth_octave_analyzer[N]`	Octave analyzers

Basic Elements

Function Type	Function Name	Description
Beats	`ba.beat`	Pulses at a specific tempo
Block	`si.block`	Terminate n signals
Break Point Function	`ba.bpf`	Beak Point Function (BPF)
Bus	`si.bus`	Bus of n signals
Bypass (Mono)	`ba.bypass1`	Mono bypass
Bypass (Stereo)	`ba.bypass2`	Stereo bypass
Count Elements	`ba.count`	Count elements in a list
Count Down	`ba.countdown`	Samples count down
Count Up	`ba.countup`	Samples count up
Delay (Integer)	`de.delay`	Integer delay
Delay (Float)	`de.fdelay`	Fractional delay
Down Sample	`ba.downSample`	Down sample a signal
Impulsify	`ba.impulsify`	Turns a signal into an impulse
Sample and Hold	`ba.sAndH`	Sample and hold
Signal Crossing	`ro.cross`	Cross n signals
Smoother (Default)	`si.smoo`	Exponential smoothing
Smoother	`si.smooth`	Exponential smoothing with controllable pole
Take Element	`ba.take`	Take en element from a list
Time	`ba.time`	A simple timer

Conversion

Function Type	Function Name	Description
dB to Linear	`ba.db2linear`	Converts dB to linear values
Linear to dB	`ba.linear2db`	Converts linear values to dB
MIDI Key to Hz	`ba.midikey2hz`	Converts a MIDI key number into a frequency
Hz to MIDI Key	`ba.hz2midikey`	Converts a frequency into MIDI key number
Pole to T60	`ba.pole2tau`	Converts a pole into a time constant (t60)
Samples to Seconds	`ba.samp2sec`	Converts samples to seconds
Seconds to Samples	`ba.sec2samp`	Converts seconds to samples
T60 to Pole	`ba.tau2pole`	Converts a time constant (t60) into a pole

Effects

Function Type	Function Name	Description
Auto Wah	`ve.autowah`	Auto-Wah effect
Compressor	`co.compressor_mono`	Dynamic range compressor
Distortion	`ef.cubicnl`	Cubic nonlinearity distortion
Crybaby	`ve.crybaby`	Crybaby wah pedal
Echo	`ef.echo`	Simple echo
Flanger	`pf.flanger_stereo`	Flanging effect
Gate	`ef.gate_mono`	Mono signal gate
Limiter	`co.limiter_1176_R4_mono`	Limiter
Phaser	`pf.phaser2_stereo`	Phaser effect
Reverb (FDN)	`re.fdnrev0`	Feedback delay network reverberator
Reverb (Freeverb)	`re.mono_freeverb`	Most "famous" Schroeder reverberator
Reverb (Simple)	`re.jcrev`	Simple Schroeder reverberator
Reverb (Zita)	`re.zita_rev1_stereo`	High quality FDN reverberator
Panner	`sp.panner`	Linear stereo panner
Pitch Shift	`ef.transpose`	Simple pitch shifter
Panner	`sp.spat`	N outputs spatializer
Speaker Simulator	`ef.speakerbp`	Simple speaker simulator
Stereo Width	`ef.stereo_width`	Stereo width effect
Vocoder	`ve.vocoder`	Simple vocoder
Wah	`ve.wah4`	Wah effect

Envelope Generators

Function Type	Function Name	Description
ADSR	`en.adsr`	Attack/Decay/Sustain/Release envelope generator
AR	`en.ar`	Attack/Release envelope generator
ASR	`en.asr`	Attack/Sustain/Release envelope generator
Exponential	`en.smoothEnvelope`	Exponential envelope generator

Filters

Function Type	Function Name	Description
Bandpass (Butterworth)	`fi.bandpass`	Generic butterworth bandpass
Bandpass (Resonant)	`fi.resonbp`	Virtual analog resonant bandpass
Bandstop (Butterworth)	`fi.bandstop`	Generic butterworth bandstop
Biquad	`fi.tf2`	"Standard" biquad filter
Comb (Allpass)	`fi.allpass_fcomb`	Schroeder allpass comb filter
Comb (Feedback)	`fi.fb_fcomb`	Feedback comb filter
Comb (Feedforward)	`fi.ff_fcomb`	Feed-forward comb filter.
DC Blocker	`fi.dcblocker`	Default dc blocker
Filterbank	`fi.filterbank`	Generic filter bank
FIR (Arbitrary Order)	`fi.fir`	Nth-order FIR filter
High Shelf	`fi.high_shelf`	High shelf
Highpass (Butterworth)	`fi.highpass`	Nth-order Butterworth highpass
Highpass (Resonant)	`fi.resonhp`	Virtual analog resonant highpass
IIR (Arbitrary Order)	`fi.iir`	Nth-order IIR filter
Level Filter	`fi.levelfilter`	Dynamic level lowpass
Low Shelf	`fi.low_shelf`	Low shelf
Lowpass (Butterworth)	`fi.lowpass`	Nth-order Butterworth lowpass
Lowpass (Resonant)	`fi.resonlp`	Virtual analog resonant lowpass
Notch Filter	`fi.notchw`	Simple notch filter
Peak Equalizer	`fi.peak_eq`	Peaking equalizer section

Oscillators/Sound Generators

Function Type	Function Name	Description
Impulse	`os.impulse`	Generate an impulse on start-up
Impulse Train	`os.imptrain`	Band-limited impulse train
Phasor	`os.phasor`	Simple phasor
Pink Noise	`no.pink_noise`	Pink noise generator
Pulse Train	`os.pulsetrain`	Band-limited pulse train
Pulse Train (Low Frequency)	`os.lf_imptrain`	Low-frequency pulse train
Sawtooth	`os.sawtooth`	Band-limited sawtooth wave
Sawtooth (Low Frequency)	`os.lf_saw`	Low-frequency sawtooth wave
Sine (Filter-Based)	`os.osc`	Sine oscillator (filter-based)
Sine (Table-Based)	`os.oscsin`	Sine oscillator (table-based)
Square	`os.square`	Band-limited square wave
Square (Low Frequency)	`os.lf_squarewave`	Low-frequency square wave
Triangle	`os.triangle`	Band-limited triangle wave
Triangle (Low Frequency)	`os.lf_triangle`	Low-frequency triangle wave
White Noise	`no.noise`	White noise generator

Synths

Function Type	Function Name	Description
Additive Drum	`sy.additiveDrum`	Additive synthesis drum
Bandpassed Sawtooth	`sy.dubDub`	Sawtooth through resonant bandpass
Comb String	`sy.combString`	String model based on a comb filter
FM	`sy.fm`	Frequency modulation synthesizer
Lowpassed Sawtooth	`sy.sawTrombone`	"Trombone" based on a filtered sawtooth
Popping Filter	`sy.popFilterPerc`	Popping filter percussion instrument

analyzers.lib

Faust Analyzers library. Its official prefix is `an`.

Amplitude Tracking

amp_follower

Classic analog audio envelope follower with infinitely fast rise and exponential decay. The amplitude envelope instantaneously follows the absolute value going up, but then floats down exponentially. `amp_follower` is a standard Faust function.

Usage

```
_ : amp_follower(rel) : _
```

Where:

- `rel`: release time = amplitude-envelope time-constant (sec) going down

Reference

- Musical Engineer's Handbook, Bernie Hutchins, Ithaca NY, 1975 Electronotes Newsletter, Bernie Hutchins

---

amp_follower_ud

Envelope follower with different up and down time-constants (also called a "peak detector").

Usage

```
_ : amp_follower_ud(att,rel) : _
```

Where:

- `att`: attack time = amplitude-envelope time constant (sec) going up
- `rel`: release time = amplitude-envelope time constant (sec) going down

Note

We assume rel >> att. Otherwise, consider rel ~ max(rel,att). For audio, att is normally faster (smaller) than rel (e.g., 0.001 and 0.01). Use `amp_follower_ar` below to remove this restriction.

Reference

- "Digital Dynamic Range Compressor Design — A Tutorial and Analysis", by Dimitrios Giannoulis, Michael Massberg, and Joshua D. Reiss http://www.eecs.qmul.ac.uk/~josh/documents/GiannoulisMassbergReiss-dynamicrangecompression-JAES2012.pdf

---

Spectrum-Analyzers

Spectrum-analyzers split the input signal into a bank of parallel signals, one for each spectral band. They are related to the Mth-Octave Filter-Banks in `filters.lib`. The documentation of this library contains more details about the implementation. The parameters are:

- `M`: number of band-slices per octave (>1)
- `N`: total number of bands (>2)
- `ftop` = upper bandlimit of the Mth-octave bands ($<SR/2$)

In addition to the Mth-octave output signals, there is a highpass signal containing frequencies from ftop to SR/2, and a "dc band" lowpass signal containing frequencies from 0 (dc) up to the start of the Mth-octave bands. Thus, the N output signals are

```
highpass(ftop), MthOctaveBands(M,N-2,ftop), dcBand(ftop*2^(-M*(N-1)))
```

A Spectrum-Analyzer is defined here as any band-split whose bands span the relevant spectrum, but whose band-signals do not necessarily sum to the original signal, either exactly or to within an allpass filtering. Spectrum analyzer outputs are normally at least nearly "power complementary", i.e., the power spectra of the individual bands sum to the original power spectrum (to within some negligible tolerance).

Increasing Channel Isolation

Go to higher filter orders - see Regalia et al. or Vaidyanathan (cited below) regarding the construction of more aggressive recursive filter-banks using elliptic or Chebyshev prototype filters.

References

- "Tree-structured complementary filter banks using all-pass sections", Regalia et al., IEEE Trans. Circuits & Systems, CAS-34:1470-1484, Dec. 1987
- "Multirate Systems and Filter Banks", P. Vaidyanathan, Prentice-Hall, 1993
- Elementary filter theory: https://ccrma.stanford.edu/~jos/filters/

`mth_octave_analyzer`

Octave analyzer. `mth_octave_analyzer[N]` are standard Faust functions.

Usage

```
_ : mth_octave_analyzer(O,M,ftop,N) : par(i,N,_); // Oth-order Butterworth
_ : mth_octave_analyzer6e(M,ftop,N) : par(i,N,_); // 6th-order elliptic
```

Also for convenience:

```
_ : mth_octave_analyzer3(M,ftop,N) : par(i,N,_); // 3d-order Butterworth
_ : mth_octave_analyzer5(M,ftop,N) : par(i,N,_); // 5th-roder Butterworth
mth_octave_analyzer_default = mth_octave_analyzer6e;
```

Where:

- `O`: order of filter used to split each frequency band into two
- `M`: number of band-slices per octave
- `ftop`: highest band-split crossover frequency (e.g., 20 kHz)
- `N`: total number of bands (including dc and Nyquist)

Mth-Octave Spectral Level

Spectral Level: Display (in bar graphs) the average signal level in each spectral band.

`mth_octave_spectral_level6e`

Spectral level display.

Usage:

```
_ : mth_octave_spectral_level6e(M,ftop,NBands,tau,dB_offset) : _;
```

Where:

- `M`: bands per octave
- `ftop`: lower edge frequency of top band
- `NBands`: number of passbands (including highpass and dc bands),
- `tau`: spectral display averaging-time (time constant) in seconds,
- `dB_offset`: constant dB offset in all band level meters.

Also for convenience:

```
mth_octave_spectral_level_default = mth_octave_spectral_level6e;
spectral_level = mth_octave_spectral_level(2,10000,20);
```

`[third|half]_octave_[analyzer|filterbank]`

A bunch of special cases based on the different analyzer functions described above:

```
third_octave_analyzer(N) = mth_octave_analyzer_default(3,10000,N);
third_octave_filterbank(N) = mth_octave_filterbank_default(3,10000,N);
half_octave_analyzer(N) = mth_octave_analyzer_default(2,10000,N);
half_octave_filterbank(N) = mth_octave_filterbank_default(2,10000,N);
octave_filterbank(N) = mth_octave_filterbank_default(1,10000,N);
octave_analyzer(N) = mth_octave_analyzer_default(1,10000,N);
```

Usage

See `mth_octave_spectral_level_demo` in `demos.lib`.

Arbritary-Crossover Filter-Banks and Spectrum Analyzers

These are similar to the Mth-octave analyzers above, except that the band-split frequencies are passed explicitly as arguments.

`analyzer`

Analyzer.

Usage

```
_ : analyzer(O,freqs) : par(i,N,_); // No delay equalizer
```

Where:

- `O`: band-split filter order (ODD integer required for filterbank[i])
- `freqs`: (fc1,fc2,...,fcNs) [in numerically ascending order], where Ns=N-1 is the number of octave band-splits (total number of bands N=Ns+1).

If frequencies are listed explicitly as arguments, enclose them in parens:

```
_ : analyzer(3,(fc1,fc2)) : _,_,_
```

Fast Fourier Transform (fft) and its Inverse (ifft)

Sliding FFTs that compute a rectangularly windowed FFT each sample

`fft`

Fast Fourier Transform (FFT)

Usage

```
si.cbus(N) : fft(N) : si.cbus(N);
```

Where:

- `si.cbus(N)` is a bus of N complex signals, each specified by real and imaginary parts: (r0,i0), (r1,i1), (r2,i2), ...
- `N` is the FFT size (must be a power of 2: 2,4,8,16,...)
- `fft(N)` performs a length N FFT for complex signals (radix 2)
- The output is a bank of N complex signals containing the complex spectrum over time: (R0, I0), (R1,I1), ...
- The dc component is (R0,I0), where I0=0 for real input signals.

FFTs of Real Signals:

- To perform a sliding FFT over a real input signal, you can say

  ```
  process = signal : an.rtocv(N) : an.fft(N);
  ```

where `an.rtocv` converts a real (scalar) signal to a complex vector signal having a zero imaginary part.

- See `an.rfft_analyzer_c` (in `analyzers.lib`) and related functions for more detailed usage examples.

- Use `an.rfft_spectral_level(N,tau,dB_offset)` to display the power spectrum of a real signal.

- See `dm.fft_spectral_level_demo(N)` in `demos.lib` for an example GUI driving `an.rfft_spectral_level()`.

---

ifft

Inverse Fast Fourier Transform (IFFT)

Usage

`si.cbus(N) : ifft(N) : si.cbus(N);`

Where:

- N is the IFFT size (power of 2)
- Input is a complex spectrum represented as interleaved real and imaginary parts: (R0, I0), (R1,I1), (R2,I2), . . .
- Output is a bank of N complex signals giving the complex signal in the time domain: (r0, i0), (r1,i1), (r2,i2), . . .

---

amp_follower_ar

Envelope follower with independent attack and release times. The release can be shorter than the attack (unlike in `amp_follower_ud` above).

Usage

`_ : amp_follower_ar(att,rel) : _;`

- Author Jonatan Liljedahl, revised by RM

---

basics.lib

A library of basic elements for Faust organized in 5 sections:

- Conversion Tools
- Counters and Time/Tempo Tools
- Array Processing/Pattern Matching
- Selectors (Conditions)
- Other Tools (Misc)

The official prefix of this library is `ba`.

Conversion Tools

`samp2sec`

Converts a number of samples to a duration in seconds. `samp2sec` is a standard Faust function.

Usage

`samp2sec(n) : _`

Where:

- `n`: number of samples

`sec2samp`

Converts a duration in seconds to a number of samples. `samp2sec` is a standard Faust function.

Usage

`sec2samp(d) : _`

Where:

- `d`: duration in seconds

------

db2linear

Converts a loudness in dB to a linear gain (0-1). `db2linear` is a standard Faust function.

Usage

`db2linear(l) : _`

Where:

- `l`: loudness in dB

---

linear2db

Converts a linear gain (0-1) to a loudness in dB. `linear2db` is a standard Faust function.

Usage

`linear2db(g) : _`

Where:

- `g`: a linear gain

---

lin2LogGain

Converts a linear gain (0-1) to a log gain (0-1).

Usage

`_ : lin2LogGain : _`

---

log2LinGain

Converts a log gain (0-1) to a linear gain (0-1).

```
_ : log2LinGain : _
```

---

tau2pole

Returns a real pole giving exponential decay. Note that t60 (time to decay 60 dB) is ~6.91 time constants. `tau2pole` is a standard Faust function.

Usage

```
_ : smooth(tau2pole(tau)) : _
```

Where:

- `tau`: time-constant in seconds

---

pole2tau

Returns the time-constant, in seconds, corresponding to the given real, positive pole in (0,1). `pole2tau` is a standard Faust function.

Usage

```
pole2tau(pole) : _
```

Where:

- `pole`: the pole

---

midikey2hz

Converts a MIDI key number to a frequency in Hz (MIDI key 69 = A440). `midikey2hz` is a standard Faust function.

Usage

```
midikey2hz(mk) : _
```

Where:

- `mk`: the MIDI key number

---

hz2midikey

Converts a frequency in Hz to a MIDI key number (MIDI key 69 = A440).
`hz2midikey` is a standard Faust function.

Usage

`hz2midikey(f) : _`

Where:

- `f`: frequency in Hz

---

pianokey2hz

Converts a piano key number to a frequency in Hz (piano key 49 = A440).

Usage

`pianokey2hz(pk) : _`

Where:

- `pk`: the piano key number

---

hz2pianokey

Converts a frequency in Hz to a piano key number (piano key 49 = A440).

Usage

`hz2pianokey(f) : _`

Where:

- `f`: frequency in Hz

Counters and Time/Tempo Tools

`countdown`

Starts counting down from n included to 0. While trig is 1 the output is n. The countdown starts with the transition of trig from 1 to 0. At the end of the countdown the output value will remain at 0 until the next trig. `countdown` is a standard Faust function.

Usage

`countdown(n,trig) : _`

Where:

- `count`: the starting point of the countdown
- `trig`: the trigger signal (1: start at `n`; 0: decrease until 0)

`countup`

Starts counting up from 0 to n included. While trig is 1 the output is 0. The countup starts with the transition of trig from 1 to 0. At the end of the countup the output value will remain at n until the next trig. `countup` is a standard Faust function.

Usage

`countup(n,trig) : _`

Where:

- `count`: the maximum count value
- `trig`: the trigger signal (1: start at 0; 0: increase until `n`)

`sweep`

Counts from 0 to `period` samples repeatedly, while `run` is 1. Outsputs zero while `run` is 0.

Usage

```
sweep(period,run) : _
```

---

time

A simple timer that counts every samples from the beginning of the process.
`time` is a standard Faust function.

Usage

```
time : _
```

---

tempo

Converts a tempo in BPM into a number of samples.

Usage

```
tempo(t) : _
```

Where:

- `t`: tempo in BPM

---

period

Basic sawtooth wave of period `p`.

Usage

```
period(p) : _
```

Where:

- `p`: period as a number of samples

---

pulse

Pulses (10000) generated at period `p`.

Usage

```
pulse(p) : _
```

Where:

- `p`: period as a number of samples

---

pulsen

Pulses (11110000) of length `n` generated at period `p`.

Usage

```
pulsen(n,p) : _
```

Where:

- `n`: the length of the pulse as a number of samples
- `p`: period as a number of samples

---

cycle

Split nonzero input values into `n` cycles.

Usage

```
_ : cycle(n) <:
```

Where:

- `n`: the number of cycles/output signals

---

beat

Pulses at tempo `t`. `beat` is a standard Faust function.

Usage

```
beat(t) : _
```

Where:

- `t`: tempo in BPM

---

pulse_countup

Starts counting up pulses. While trig is 1 the output is counting up, while trig is 0 the counter is reset to 0.

Usage

```
_ : pulse_countup(trig) : _
```

Where:

- `trig`: the trigger signal (1: start at next pulse; 0: reset to 0)

---

pulse_countdown

Starts counting down pulses. While trig is 1 the output is counting down, while trig is 0 the counter is reset to 0.

Usage

```
_ : pulse_countdown(trig) : _
```

Where:

- `trig`: the trigger signal (1: start at next pulse; 0: reset to 0)

---

pulse_countup_loop

Starts counting up pulses from 0 to n included. While trig is 1 the output is counting up, while trig is 0 the counter is reset to 0. At the end of the countup (n) the output value will be reset to 0.

Usage

`_ : pulse_countup_loop(n,trig) : _`

Where:

- **n**: the highest number of the countup (included) before reset to 0.
- **trig**: the trigger signal (1: start at next pulse; 0: reset to 0)

---

resetCtr

Function that lets through the mth impulse out of each consecutive group of **n** impulses.

Usage

`_ : resetCtr(n,m) : _`

Where:

- **n**: the total number of impulses being split
- **m**: index of impulse to allow to be output

---

pulse_countdown_loop

Starts counting down pulses from 0 to n included. While trig is 1 the output is counting down, while trig is 0 the counter is reset to 0. At the end of the countdown (n) the output value will be reset to 0.

Usage

`_ : pulse_coundown_loop(n,trig) : _`

Where:

- **n**: the highest number of the countup (included) before reset to 0.
- **trig**: the trigger signal (1: start at next pulse; 0: reset to 0)

Array Processing/Pattern Matching

count

Count the number of elements of list l. `count` is a standard Faust function.

Usage

```
count(l)
count ((10,20,30,40)) -> 4
```

Where:

- `l`: list of elements

---

take

Take an element from a list. `take` is a standard Faust function.

Usage

```
take(e,l)
take(3,(10,20,30,40)) -> 30
```

Where:

- `p`: position (starting at 1)
- `l`: list of elements

---

subseq

Extract a part of a list.

Usage

```
subseq(l, p, n)
subseq((10,20,30,40,50,60), 1, 3) -> (20,30,40)
subseq((10,20,30,40,50,60), 4, 1) -> 50
```

Where:

- `l`: list
- `p`: start point (0: begin of list)
- `n`: number of elements

Note:

Faust doesn't have proper lists. Lists are simulated with parallel compositions and there is no empty list

---

Selectors (Conditions)

if

if-then-else implemented with a select2.

Usage

- `if(c, t, e) : _`

Where:

- `c`: condition
- `t`: signal selected while c is true
- `e`: signal selected while c is false

---

selector

Selects the ith input among n at compile time.

Usage

```
selector(i,n)
_,_,_,_ : selector(2,4) : _   // selects the 3rd input among 4
```

Where:

- `i`: input to select (`int`, numbered from 0, known at compile time)
- `n`: number of inputs (`int`, known at compile time, `n > i`)

There is also cselector for selecting among complex input signals of the form (real,imag).

---

selectn

Selects the ith input among N at run time.

Usage

```
selectn(N,i)
_,_,_,_ : selectn(4,2) : _   // selects the 3rd input among 4
```

Where:

- `N`: number of inputs (int, known at compile time, N > 0)
- `i`: input to select (int, numbered from 0)

Example test program

```
N=64;
process = par(n,N, (par(i,N,i) : selectn(N,n)));
```

---

select2stereo

Select between 2 stereo signals.

Usage

```
_,_,_,_ : select2stereo(bpc) : _,_,_,_
```

Where:

- `bpc`: the selector switch (0/1)

Other

latch

Latch input on positive-going transition of "clock" ("sample-and-hold").

Usage

```
_ : latch(clocksig) : _
```

Where:

- `clocksig`: hold trigger (0 for hold, 1 for bypass)

---

sAndH

Sample And Hold. `sAndH` is a standard Faust function.

Usage

`_ : sAndH(t) : _`

Where:

- `t`: hold trigger (0 for hold, 1 for bypass)

---

downSample

Down sample a signal. WARNING: this function doesn't change the rate of a signal, it just holds samples... `downSample` is a standard Faust function.

Usage

`_ : downSample(freq) : _`

Where:

- `freq`: new rate in Hz

---

peakhold

Outputs current max value above zero.

Usage

`_ : peakhold(mode) : _;`

Where:

`mode` means: 0 - Pass through. A single sample 0 trigger will work as a reset. 1 - Track and hold max value.

---

peakholder

Tracks abs peak and holds peak for 'holdtime' samples.

```
_ : peakholder(holdtime) : _;
```

---

impulsify

Turns the signal from a button into an impulse (1,0,0,... when button turns on). `impulsify` is a standard Faust function.

Usage

```
button("gate") : impulsify ;
```

---

automat

Record and replay to the values the input signal in a loop.

Usage

```
hslider(...) : automat(bps, size, init) : _
```

---

bpf

bpf is an environment (a group of related definitions) that can be used to create break-point functions. It contains three functions :

- `start(x,y)` to start a break-point function
- `end(x,y)` to end a break-point function
- `point(x,y)` to add intermediate points to a break-point function

A minimal break-point function must contain at least a start and an end point :

```
f = bpf.start(x0,y0) : bpf.end(x1,y1);
```

A more involved break-point function can contains any number of intermediate points:

```
f = bpf.start(x0,y0) : bpf.point(x1,y1) : bpf.point(x2,y2) : bpf.end(x3,y3);
```

In any case the `x_{i}` must be in increasing order (for all i, `x_{i} < x_{i+1}`). For example the following definition :

```
f = bpf.start(x0,y0) : ... : bpf.point(xi,yi) : ... : bpf.end(xn,yn);
```

implements a break-point function f such that :

- `f(x) = y_{0}` when `x < x_{0}`
- `f(x) = y_{n}` when `x > x_{n}`
- `f(x) = y_{i} + (y_{i+1}-y_{i})*(x-x_{i})/(x_{i+1}-x_{i})` when
  `x_{i} <= x` and `x < x_{i+1}`

`bpf` is a standard Faust function.

`listInterp`

Linearly interpolates between the elements of a list.

Usage

```
foo = listInterp((800,400,350,450,325),index);
i = 1.69; // range is 0-4
process = foo(i);
```

Where:

- `index`: the index (float) to interpolate between the different values. The
  range of `index` depends on the size of the list.

`bypass1`

Takes a mono input signal, route it to `e` and bypass it if `bpc = 1`. `bypass1` is a
standard Faust function.

Usage

```
_ : bypass1(bpc,e) : _
```

Where:

- `bpc`: bypass switch (0/1)
- `e`: a mono effect

`bypass2`

Takes a stereo input signal, route it to `e` and bypass it if `bpc = 1`. `bypass2` is a
standard Faust function.

Usage

```
_,_ : bypass2(bpc,e) : _,_
```

Where:

- **bpc**: bypass switch (0/1)
- **e**: a stereo effect

---

bypass1to2

Bypass switch for effect **e** having mono input signal and stereo output. Effect **e** is bypassed if **bpc = 1**. **bypass1to2** is a standard Faust function.

Usage

```
_ : bypass1(bpc,e) : _,_
```

Where:

- **bpc**: bypass switch (0/1)
- **e**: a mono-to-stereo effect

---

toggle

Triggered by the change of 0 to 1, it toggles the output value between 0 and 1.

Usage

```
_ : toggle : _
```

Examples

```
button("toggle") : toggle : vbargraph("output", 0, 1)
(an.amp_follower(0.1) > 0.01) : toggle : vbargraph("output", 0, 1) // takes audio input
```

---

on_and_off

The first channel set the output to 1, the second channel to 0.

Usage

```
_ , _ : on_and_off : _
```

Example

```
button("on"), button("off") : on_and_off : vbargraph("output", 0, 1)
```

`selectoutn`

Route input to the output among N at run time.

Usage

```
_ : selectoutn(n, s) : _,_,...n
```

Where:

- **n**: number of outputs (int, known at compile time, N > 0)
- **s**: output number to route to (int, numbered from 0) (i.e. slider)

Example

```
process = 1 : selectoutn(3, sel) : par(i,3,bar) ;
sel = hslider("volume",0,0,2,1) : int;
bar = vbargraph("v.bargraph", 0, 1);
```

---

compressors.lib

A library of compressor effects. Its official prefix is `co`.

Functions Reference

`compressor_mono`

Mono dynamic range compressors. `compressor_mono` is a standard Faust function

Usage

```
_ : compressor_mono(ratio,thresh,att,rel) : _
```

Where:

- `ratio`: compression ratio (1 = no compression, >1 means compression)
- `thresh`: dB level threshold above which compression kicks in (0 dB = max level)
- `att`: attack time = time constant (sec) when level & compression going up
- `rel`: release time = time constant (sec) coming out of compression

References

- http://en.wikipedia.org/wiki/Dynamic_range_compression
- https://ccrma.stanford.edu/~jos/filters/Nonlinear_Filter_Example_ Dynamic.html
- Albert Graef's "faust2pd"/examples/synth/compressor_.dsp
- More features: https://github.com/magnetophon/faustCompressors

———————————————————————

`compressor_stereo`

Stereo dynamic range compressors.

Usage

```
_,_ : compressor_stereo(ratio,thresh,att,rel) : _,_
```

Where:

- `ratio`: compression ratio (1 = no compression, >1 means compression)
- `thresh`: dB level threshold above which compression kicks in (0 dB = max level)
- `att`: attack time = time constant (sec) when level & compression going up
- `rel`: release time = time constant (sec) coming out of compression

References

- http://en.wikipedia.org/wiki/Dynamic_range_compression
- https://ccrma.stanford.edu/~jos/filters/Nonlinear_Filter_Example_ Dynamic.html
- Albert Graef's "faust2pd"/examples/synth/compressor_.dsp
- More features: https://github.com/magnetophon/faustCompressors

———————————————————————

`limiter_1176_R4_mono`

A limiter guards against hard-clipping. It can be can be implemented as a compressor having a high threshold (near the clipping level), fast attack and release, and high ratio. Since the ratio is so high, some knee smoothing is desirable ("soft limiting"). This example is intended to get you started using compressor_* as a limiter, so all parameters are hardwired to nominal values here. Ratios: 4 (moderate compression), 8 (severe compression), 12 (mild limiting), or 20 to 1 (hard limiting) Att: 20-800 MICROseconds (Note: scaled by ratio in the 1176) Rel: 50-1100 ms (Note: scaled by ratio in the 1176) Mike Shipley likes 4:1 (Grammy-winning mixer for Queen, Tom Petty, etc.) Faster attack gives "more bite" (e.g. on vocals) He hears a bright, clear eq effect as well (not implemented here) `limiter_1176_R4_mono` is a standard Faust function.

Usage

```
_ : limiter_1176_R4_mono : _;
```

Reference:

http://en.wikipedia.org/wiki/1176_Peak_Limiter

`limiter_1176_R4_stereo`

A limiter guards against hard-clipping. It can be can be implemented as a compressor having a high threshold (near the clipping level), fast attack and release, and high ratio. Since the ratio is so high, some knee smoothing is desirable ("soft limiting"). This example is intended to get you started using compressor_* as a limiter, so all parameters are hardwired to nominal values here. Ratios: 4 (moderate compression), 8 (severe compression), 12 (mild limiting), or 20 to 1 (hard limiting) Att: 20-800 MICROseconds (Note: scaled by ratio in the 1176) Rel: 50-1100 ms (Note: scaled by ratio in the 1176) Mike Shipley likes 4:1 (Grammy-winning mixer for Queen, Tom Petty, etc.) Faster attack gives "more bite" (e.g. on vocals) He hears a bright, clear eq effect as well (not implemented here)

Usage

```
_,_ : limiter_1176_R4_stereo : _,_;
```

Reference:

http://en.wikipedia.org/wiki/1176_Peak_Limiter

---

delays.lib

This library contains a collection of delay functions. Its official prefix is `de`.

Basic Delay Functions

delay

Simple `d` samples delay where `n` is the maximum delay length as a number of samples. Unlike the `@` delay operator, here the delay signal `d` is explicitely bounded to the interval [0..n]. The consequence is that delay will compile even if the interval of d can't be computed by the compiler. `delay` is a standard Faust function.

Usage

`_ : delay(n,d) : _`

Where:

- `n`: the max delay length (in samples)
- `d`: the delay length as a number of samples (integer)

---

fdelay

Simple `d` samples fractional delay based on 2 interpolated delay lines where `n` is the maximum delay length as a number of samples.

sdelay

s(mooth)delay: a mono delay that doesn't click and doesn't transpose when the delay time is changed.

Usage

```
_ : sdelay(N,it,dt) : _
```

Where :

- `N`: maximal delay in samples
- `it`: interpolation time (in samples) for example 1024
- `dt`: delay time (in samples)

Lagrange Interpolation

fdelaylti and fdelayltv

Fractional delay line using Lagrange interpolation.

Usage

```
_ : fdelaylt[i|v](order, maxdelay, delay, inputsignal) : _
```

Where `order=1,2,3,...` is the order of the Lagrange interpolation polynomial.

`fdelaylti` is most efficient, but designed for constant/slowly-varying delay. `fdelayltv` is more expensive and more robust when the delay varies rapidly.

NOTE: The requested delay should not be less than `(N-1)/2`.

References

- https://ccrma.stanford.edu/~jos/pasp/Lagrange_Interpolation.html
- Timo I. Laakso et al., "Splitting the Unit Delay - Tools for Fractional Delay Filter Design", IEEE Signal Processing Magazine, vol. 13, no. 1, pp. 30-60, Jan 1996.
- Philippe Depalle and Stephan Tassart, "Fractional Delay Lines using Lagrange Interpolators", ICMC Proceedings, pp. 341-343, 1996.

---

fdelay[n]

For convenience, `fdelay1`, `fdelay2`, `fdelay3`, `fdelay4`, `fdelay5` are also available where n is the order of the interpolation.

Thiran Allpass Interpolation

Thiran Allpass Interpolation

Reference

https://ccrma.stanford.edu/~jos/pasp/Thiran_Allpass_Interpolators.html

`fdelay[n]a`

Delay lines interpolated using Thiran allpass interpolation.

Usage

`_ : fdelay[N]a(maxdelay, delay, inputsignal) : _`

(exactly like `fdelay`)

Where:

- `N`=1,2,3, or 4 is the order of the Thiran interpolation filter, and the delay argument is at least N - 1/2.

Note

The interpolated delay should not be less than `N - 1/2`. (The allpass delay ranges from `N - 1/2` to `N + 1/2`.) This constraint can be alleviated by altering the code, but be aware that allpass filters approach zero delay by means of pole-zero cancellations. The delay range `[N-1/2,N+1/2]` is not optimal. What is?

Delay arguments too small will produce an UNSTABLE allpass!

Because allpass interpolation is recursive, it is not as robust as Lagrange interpolation under time-varying conditions. (You may hear clicks when changing the delay rapidly.)

First-order allpass interpolation, delay d in [0.5,1.5]

----

demos.lib

This library contains a set of demo functions based on examples located in the `/examples` folder. Its official prefix is `dm`.

Analyzers

`mth_octave_spectral_level_demo`

Demonstrate mth_octave_spectral_level in a standalone GUI.

Usage

```
_ : mth_octave_spectral_level_demo(BandsPerOctave);
_ : spectral_level_demo : _; // 2/3 octave
```

Filters

`parametric_eq_demo`

A parametric equalizer application.

Usage:

```
_ : parametric_eq_demo : _ ;
```

`spectral_tilt_demo`

A spectral tilt application.

Usage

```
_ : spectral_tilt_demo(N) : _ ;
```
Where:

- `N`: filter order (integer)

All other parameters interactive

`mth_octave_filterbank_demo` and `filterbank_demo`

Graphic Equalizer: Each filter-bank output signal routes through a fader.

Usage

```
_ : mth_octave_filterbank_demo(M) : _
_ : filterbank_demo : _
```

Where:

- `N`: number of bands per octave

Effects

cubicnl_demo

Distortion demo application.

Usage:

```
_ : cubicnl_demo : _;
```

---

gate_demo

Gate demo application.

Usage

```
_,_ : gate_demo : _,_;
```

---

compressor_demo

Compressor demo application.

Usage

```
_,_ : compressor_demo : _,_;
```

---

moog_vcf_demo

Illustrate and compare all three Moog VCF implementations above.

Usage

```
_ : moog_vcf_demo : _;
```

---

wah4_demo

Wah pedal application.

Usage

```
_ : wah4_demo : _;
```

---

crybaby_demo

Crybaby effect application.

Usage

```
_ : crybaby_demo : _ ;
```

---

flanger_demo

Flanger effect application.

Usage

```
_,_ : flanger_demo : _,_;
```

---

phaser2_demo

Phaser effect demo application.

Usage

```
_,_ : phaser2_demo : _,_;
```

---

stereo_reverb_tester

Handy test inputs for reverberator demos below.

Usage

```
_ : stereo_reverb_tester : _
```

---

fdnrev0_demo

A reverb application using `fdnrev0`.

Usage

```
_,_ : fdnrev0_demo(N,NB,BBSO) : _,_
```

Where:

- `n`: Feedback Delay Network (FDN) order / number of delay lines used = order of feedback matrix / 2, 4, 8, or 16 [extend primes array below for 32, 64, ...]
- `nb`: Number of frequency bands / Number of (nearly) independent T60 controls / Integer 3 or greater
- `bbso` = Butterworth band-split order / order of lowpass/highpass bandsplit used at each crossover freq / odd positive integer

---

zita_rev_fdn_demo

Reverb demo application based on `zita_rev_fdn`.

Usage

```
si.bus(8) : zita_rev_fdn_demo : si.bus(8)
```

---

zita_rev1

Example GUI for `zita_rev1_stereo` (mostly following the Linux `zita-rev1` GUI).

Only the dry/wet and output level parameters are "dezippered" here. If parameters are to be varied in real time, use `smooth(0.999)` or the like in the same way.

Usage

```
_,_ : zita_rev1 : _,_
```

Reference

http://www.kokkinizita.net/linuxaudio/zita-rev1-doc/quickguide.html

---

Generators

sawtooth_demo

An application demonstrating the different sawtooth oscillators of Faust.

Usage

```
sawtooth_demo : _
```

---

virtual_analog_oscillator_demo

Virtual analog oscillator demo application.

Usage

```
virtual_analog_oscillator_demo : _
```

---

oscrs_demo

Simple application demoing filter based oscillators.

Usage

```
oscrs_demo : _
```

---

velvet_noise_demo

Listen to velvet_noise!

Usage

```
velvet_noise_demo : _
```

---

latch_demo

Illustrate latch operation

Usage

```
echo 'import("stdfaust.lib");' > latch_demo.dsp
echo 'process = dm.latch_demo;' >> latch_demo.dsp
faust2octave latch_demo.dsp
Octave:1> plot(faustout);
```

---

envelopes_demo

Illustrate various envelopes overlaid, including their gate * 1.1

Usage

```
echo 'import("stdfaust.lib");' > envelopes_demo.dsp
echo 'process = dm.envelopes_demo;' >> envelopes_demo.dsp
faust2octave envelopes_demo.dsp
Octave:1> plot(faustout);
```

---

exciter

Psychoacoustic harmonic exciter, with GUI.

Usage

```
_ : exciter : _
```

References

- https://secure.aes.org/forum/pubs/ebriefs/?elib=16939
- https://www.researchgate.net/publication/258333577_Modeling_the_Harmonic_Exciter

---

vocoder_demo

Use example of the vocoder function where an impulse train is used as excitation.

Usage

```
_ : vocoder_demo : _;
```

---

freeverb_demo

Freeverb demo application.

Usage

```
_,_ : freeverb_demo : _,_;
```

---

dx7.lib

Yamaha DX7 emulation library. The various functions available in this library are used by the libraries generated from `.syx` DX7 preset files. This toolkit was greatly inspired by the CSOUND DX7 emulation package: http://www.parnasse.com/dx72csnd.shtml.

This library and its related tools are under development. Use it at your own risk!

dx7_ampf

DX7 amplitude conversion function. 3 versions of this function are available:

- `dx7_amp_bpf`: BPF version (same as in the CSOUND toolkit)
- `dx7_amp_func`: estimated mathematical equivalent of `dx7_amp_bpf`
- `dx7_ampf`: default (sugar for `dx7_amp_func`)

Usage:

```
dx7AmpPreset : dx7_ampf_bpf : _
```

Where:

- **dx7AmpPreset**: DX7 amplitude value (0-99)

———————————————————

dx7_egraterisef

DX7 envelope generator rise conversion function. 3 versions of this function are available:

- **dx7_egraterise_bpf**: BPF version (same as in the CSOUND toolkit)
- **dx7_egraterise_func**: estimated mathematical equivalent of **dx7_egraterise_bpf**
- **dx7_egraterisef**: default (sugar for **dx7_egraterise_func**)

Usage:

```
dx7envelopeRise : dx7_egraterisef : _
```

Where:

- **dx7envelopeRise**: DX7 envelope rise value (0-99)

———————————————————

dx7_egraterisepercf

DX7 envelope generator percussive rise conversion function. 3 versions of this function are available:

- **dx7_egrateriseperc_bpf**: BPF version (same as in the CSOUND toolkit)
- **dx7_egrateriseperc_func**: estimated mathematical equivalent of **dx7_egrateriseperc_bpf**
- **dx7_egraterisepercf**: default (sugar for **dx7_egrateriseperc_func**)

Usage:

```
dx7envelopePercRise : dx7_egraterisepercf : _
```

Where:

- **dx7envelopePercRise**: DX7 envelope percussive rise value (0-99)

———————————————————

`dx7_egratedecayf`

DX7 envelope generator decay conversion function. 3 versions of this function are available:

- `dx7_egratedecay_bpf`: BPF version (same as in the CSOUND toolkit)
- `dx7_egratedecay_func`: estimated mathematical equivalent of `dx7_egratedecay_bpf`
- `dx7_egratedecayf`: default (sugar for `dx7_egratedecay_func`)

Usage:

```
dx7envelopeDecay : dx7_egratedecayf : _
```

Where:

- `dx7envelopeDecay`: DX7 envelope decay value (0-99)

`dx7_egratedecaypercf`

DX7 envelope generator percussive decay conversion function. 3 versions of this function are available:

- `dx7_egratedecayperc_bpf`: BPF version (same as in the CSOUND toolkit)
- `dx7_egratedecayperc_func`: estimated mathematical equivalent of `dx7_egratedecayperc_bpf`
- `dx7_egratedecaypercf`: default (sugar for `dx7_egratedecayperc_func`)

Usage:

```
dx7envelopePercDecay : dx7_egratedecaypercf : _
```

Where:

- `dx7envelopePercDecay`: DX7 envelope decay value (0-99)

`dx7_eglv2peakf`

DX7 envelope level to peak conversion function. 3 versions of this function are available:

- `dx7_eglv2peak_bpf`: BPF version (same as in the CSOUND toolkit)
- `dx7_eglv2peak_func`: estimated mathematical equivalent of `dx7_eglv2peak_bpf`

- **dx7_eglv2peakf**: default (sugar for `dx7_eglv2peak_func`)

Usage:

```
dx7Level : dx7_eglv2peakf : _
```

Where:

- **dx7Level**: DX7 level value (0-99)

---

dx7_velsensf

DX7 velocity sensitivity conversion function.

Usage:

```
dx7Velocity  : dx7_velsensf : _
```

Where:

- **dx7Velocity**: DX7 level value (0-8)

---

dx7_fdbkscalef

DX7 feedback scaling conversion function.

Usage:

```
dx7Feedback  : dx7_fdbkscalef : _
```

Where:

- **dx7Feedback**: DX7 feedback value

---

dx7_op

DX7 Operator. Implements a phase-modulable sine wave oscillator connected to a DX7 envelope generator.

Usage:

`dx7_op(freq,phaseMod,outLev,R1,R2,R3,R4,L1,L2,L3,L4,keyVel,rateScale,type,gain,gate) : _`

Where:

- `freq`: frequency of the oscillator
- `phaseMod`: phase deviation (-1 - 1)
- `outLev`: preset output level (0-99)
- `R1`: preset envelope rate 1 (0-99)
- `R2`: preset envelope rate 2 (0-99)
- `R3`: preset envelope rate 3 (0-99)
- `R4`: preset envelope rate 4 (0-99)
- `L1`: preset envelope level 1 (0-99)
- `L2`: preset envelope level 2 (0-99)
- `L3`: preset envelope level 3 (0-99)
- `L4`: preset envelope level 4 (0-99)
- `keyVel`: preset key velocity sensitivity (0-99)
- `rateScale`: preset envelope rate scale
- `type`: preset operator type
- `gain`: general gain
- `gate`: trigger signal

---

dx7_algo

DX7 algorithms. Implements the 32 DX7 algorithms (a quick Google search should give your more details on this). Each algorithm uses 6 operators

Usage:

`dx7_algo(algN,egR1,egR2,egR3,egR4,egL1,egL2,egL3,egL4,outLevel,keyVelSens,ampModSens,opMode,`

Where:

- `algN`: algorithm number (0-31, should be an int. . .)
- `egR1`: preset envelope rates 1 (a list of 6 values between 0-99)
- `egR2`: preset envelope rates 2 (a list of 6 values between 0-99)
- `egR3`: preset envelope rates 3 (a list of 6 values between 0-99)
- `egR4`: preset envelope rates 4 (a list of 6 values between 0-99)
- `egL1`: preset envelope levels 1 (a list of 6 values between 0-99)
- `egL2`: preset envelope levels 2 (a list of 6 values between 0-99)
- `egL3`: preset envelope levels 3 (a list of 6 values between 0-99)
- `egL4`: preset envelope levels 4 (a list of 6 values between 0-99)
- `outLev`: preset output levels (a list of 6 values between 0-99)
- `keyVel`: preset key velocity sensitivities (a list of 6 values between 0-99)
- `ampModSens`: preset amplitude sensitivities (a list of 6 values between 0-99)

- `opMode`: preset operator mode (a list of 6 values between 0-1)
- `opFreq`: preset operator frequencies (a list of 6 values between 0-99)
- `opDetune`: preset operator detuning (a list of 6 values between 0-99)
- `opRateScale`: preset operator rate scale (a list of 6 values between 0-99)
- `feedback`: preset operator feedback (a list of 6 values between 0-99)
- `lfoDelay`: preset LFO delay (a list of 6 values between 0-99)
- `lfoDepth`: preset LFO depth (a list of 6 values between 0-99)
- `lfoSpeed`: preset LFO speed (a list of 6 values between 0-99)
- `freq`: fundamental frequency
- `gain`: general gain
- `gate`: trigger signal

`dx7_ui`

Generic DX7 function where all parameters are controllable using UI elements. The `master-with-mute` branch must be used for this function to work... This function is MIDI-compatible.

Usage

```
dx7_ui : _
```

---

envelopes.lib

This library contains a collection of envelope generators. Its official prefix is `en`.

Functions Reference

`smoothEnvelope`

An envelope with an exponential attack and release. `smoothEnvelope` is a standard Faust function.

Usage

```
smoothEnvelope(ar,t) : _
```

- `ar`: attack and release duration (s)
- `t`: trigger signal (0-1)

`ar`

AR (Attack, Release) envelope generator (useful to create percussion envelopes).
`ar` is a standard Faust function.

Usage

`ar(a,r,t) : _`

Where:

- `a`: attack (sec)
- `r`: release (sec)
- `t`: trigger signal (0 or 1)

`are`

ARE (Attack, Release) envelope generator with Exponential segments. Approximately equal to smoothEnvelope(Attack/6.91) when Attack == Release. `are` is
a standard Faust function.

Usage

`are(a,r,g) : _`

Where:

- `a`, `r`: attack (sec), release (sec)
- `g`: gate signal (>0 for attack, release begins when g returns to 0)

`asr`

ASR (Attack, Sustain, Release) envelope generator. `asr` is a standard Faust
function.

Usage

`asr(a,s,r,g) : _`

Where:

- `a`, `s`, `r`: attack (sec), sustain (percentage of g), release (sec)
- `g`: trigger signal (>0 for attack, then release is when g back to 0)

---

adsr

ADSR (Attack, Decay, Sustain, Release) envelope generator. `adsr` is a standard Faust function.

Usage

```
adsr(a,d,s,r,g) : _
```

Where:

- `a`, `d`, `s`, `r`: attack (sec), decay (sec), sustain level (percentage of max), release (sec)
- `g`: gate signal (>0 for attack, then release is when g back to 0)

---

dx7envelope

DX7 operator envelope generator with 4 independent rates and levels. It is essentially a 4 points BPF.

Usage

```
dx7_envelope(R1,R2,R3,R4,L1,L2,L3,L4,t) : _
```

Where:

- `RN`: rates in seconds
- `LN`: levels (0-1)
- `t`: trigger signa

---

adsre

ADSRE (Attack, Decay, Sustain, Release) envelope generator with Exponential segments. `adsre` is a standard Faust function.

Usage

```
adsre(a,d,s,r,g) : _
```

Where:

- **a**, **d**, **s**, **r**: attack (sec), decay (sec), sustain level (percentage of max), release (sec)
- **g**: gate signal (>0 for attack, then release is when g back to 0)

---

filters.lib

Faust Filters library; Its official prefix is `fi`.

The Filters library is organized into 18 sections:

- Basic Filters
- Comb Filters
- Direct-Form Digital Filter Sections
- Direct-Form Second-Order Biquad Sections
- Ladder/Lattice Digital Filters
- Useful Special Cases
- Ladder/Lattice Allpass Filters
- Digital Filter Sections Specified as Analog Filter Sections
- Simple Resonator Filters
- Butterworth Lowpass/Highpass Filters
- Special Filter-Bank Delay-Equalizing Allpass Filters
- Elliptic (Cauer) Lowpass Filters
- Elliptic Highpass Filters
- Butterworth Bandpass/Bandstop Filters
- Elliptic Bandpass Filters
- Parametric Equalizers (Shelf, Peaking)
- Mth-Octave Filter-Banks
- Arbritary-Crossover Filter-Banks and Spectrum Analyzers

For more information, see ../documentation/library.pdf

Basic Filters

zero

One zero filter. Difference equation: y(n) = x(n) - z * x(n-1).

Usage

```
_ : zero(z) : _
```

Where:

- **z**: location of zero along real axis in z-plane

Reference

https://ccrma.stanford.edu/~jos/filters/One_Zero.html

---

pole

One pole filter. Could also be called a "leaky integrator". Difference equation: y(n) = x(n) + p * y(n-1).

Usage

```
_ : pole(z) : _
```

Where:

- **p**: pole location = feedback coefficient

Reference

https://ccrma.stanford.edu/~jos/filters/One_Pole.html

---

integrator

Same as `pole(1)` [implemented separately for block-diagram clarity].

---

dcblockerat

DC blocker with configurable break frequency. The amplitude response is substantially flat above fb, and sloped at about +6 dB/octave below fb. Derived from the analog transfer function H(s) = s / (s + 2PIfb) by the low-frequency-matching bilinear transform method (i.e., the standard frequency-scaling constant 2*SR).

Usage

```
_ : dcblockerat(fb) : _
```

Where:

- `fb`: "break frequency" in Hz, i.e., -3 dB gain frequency.

Reference

https://ccrma.stanford.edu/~jos/pasp/Bilinear_Transformation.html

---

dcblocker

DC blocker. Default dc blocker has -3dB point near 35 Hz (at 44.1 kHz) and high-frequency gain near 1.0025 (due to no scaling). `dcblocker` is as standard Faust function.

Usage

```
_ : dcblocker : _
```

Comb Filters

ff_comb

Feed-Forward Comb Filter. Note that `ff_comb` requires integer delays (uses `delay` internally). `ff_comb` is a standard Faust function.

Usage

```
_ : ff_comb(maxdel,intdel,b0,bM) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (integer) comb-filter delay between 0 and maxdel
- `del`: current (float) comb-filter delay between 0 and maxdel
- `b0`: gain applied to delay-line input
- `bM`: gain applied to delay-line output and then summed with input

Reference

https://ccrma.stanford.edu/~jos/pasp/Feedforward__Comb__Filters.html

---

ff_fcomb

Feed-Forward Comb Filter. Note that `ff_fcomb` takes floating-point delays (uses `fdelay` internally). `ff_fcomb` is a standard Faust function.

Usage

```
_ : ff_fcomb(maxdel,del,b0,bM) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (integer) comb-filter delay between 0 and maxdel
- `del`: current (float) comb-filter delay between 0 and maxdel
- `b0`: gain applied to delay-line input
- `bM`: gain applied to delay-line output and then summed with input

Reference

https://ccrma.stanford.edu/~jos/pasp/Feedforward__Comb__Filters.html

---

ffcombfilter

Typical special case of `ff_comb()` where: `b0 = 1`.

---

fb_comb

Feed-Back Comb Filter (integer delay).

Usage

```
_ : fb_comb(maxdel,intdel,b0,aN) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (integer) comb-filter delay between 0 and maxdel

- `del`: current (float) comb-filter delay between 0 and maxdel
- `b0`: gain applied to delay-line input and forwarded to output
- `aN`: minus the gain applied to delay-line output before summing with the input and feeding to the delay line

Reference

https://ccrma.stanford.edu/~jos/pasp/Feedback_Comb_Filters.html

---

`fb_fcomb`

Feed-Back Comb Filter (floating point delay).

Usage

```
_ : fb_fcomb(maxdel,del,b0,aN) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (integer) comb-filter delay between 0 and maxdel
- `del`: current (float) comb-filter delay between 0 and maxdel
- `b0`: gain applied to delay-line input and forwarded to output
- `aN`: minus the gain applied to delay-line output before summing with the input and feeding to the delay line

Reference

https://ccrma.stanford.edu/~jos/pasp/Feedback_Comb_Filters.html

---

`rev1`

Special case of `fb_comb` (`rev1(maxdel,N,g)`). The "rev1 section" dates back to the 1960s in computer-music reverberation. See the `jcrev` and `brassrev` in `reverbs.lib` for usage examples.

`fbcombfilter` and `ffbcombfilter`

Other special cases of Feed-Back Comb Filter.

Usage

```
_ : fbcombfilter(maxdel,intdel,g) : _
_ : ffbcombfilter(maxdel,del,g) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (integer) comb-filter delay between 0 and maxdel
- `del`: current (float) comb-filter delay between 0 and maxdel
- `g`: feedback gain

Reference

https://ccrma.stanford.edu/~jos/pasp/Feedback__Comb__Filters.html

---

`allpass_comb`

Schroeder Allpass Comb Filter. Note that

```
allpass_comb(maxlen,len,aN) = ff_comb(maxlen,len,aN,1) : fb_comb(maxlen,len-1,1,aN);
```

which is a direct-form-1 implementation, requiring two delay lines. The implementation here is direct-form-2 requiring only one delay line.

Usage

```
_ : allpass_comb (maxdel,intdel,aN) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (integer) comb-filter delay between 0 and maxdel
- `del`: current (float) comb-filter delay between 0 and maxdel
- `aN`: minus the feedback gain

References

- https://ccrma.stanford.edu/~jos/pasp/Allpass_Two_Combs.html
- https://ccrma.stanford.edu/~jos/pasp/Schroeder_Allpass_Sections.html
- https://ccrma.stanford.edu/~jos/filters/Four_Direct_Forms.html

---

allpass_fcomb

Schroeder Allpass Comb Filter. Note that

`allpass_comb(maxlen,len,aN) = ff_comb(maxlen,len,aN,1) : fb_comb(maxlen,len-1,1,aN);`

which is a direct-form-1 implementation, requiring two delay lines. The implementation here is direct-form-2 requiring only one delay line.

`allpass_fcomb` is a standard Faust library.

Usage

```
_ : allpass_comb (maxdel,intdel,aN) : _
_ : allpass_fcomb(maxdel,del,aN) : _
```

Where:

- `maxdel`: maximum delay (a power of 2)
- `intdel`: current (float) comb-filter delay between 0 and maxdel
- `del`: current (float) comb-filter delay between 0 and maxdel
- `aN`: minus the feedback gain

References

- https://ccrma.stanford.edu/~jos/pasp/Allpass_Two_Combs.html
- https://ccrma.stanford.edu/~jos/pasp/Schroeder_Allpass_Sections.html
- https://ccrma.stanford.edu/~jos/filters/Four_Direct_Forms.html

---

rev2

Special case of `allpass_comb` (`rev2(maxlen,len,g)`). The "rev2 section" dates back to the 1960s in computer-music reverberation. See the `jcrev` and `brassrev` in `reverbs.lib` for usage examples.

---

allpass_fcomb5 and allpass_fcomb1a

Same as `allpass_fcomb` but use `fdelay5` and `fdelay1a` internally (Interpolation helps - look at an fft of faust2octave on

`` `1-1' <: allpass_fcomb(1024,10.5,0.95), allpass_fcomb5(1024,10.5,0.95);`). ``

Direct-Form Digital Filter Sections

iir

Nth-order Infinite-Impulse-Response (IIR) digital filter, implemented in terms of the Transfer-Function (TF) coefficients. Such filter structures are termed "direct form".

`iir` is a standard Faust function.

Usage

```
_ : iir(bcoeffs,acoeffs) : _
```

Where:

- `order`: filter order (int) = max(#poles,#zeros)
- `bcoeffs`: (b0,b1,...,b_order) = TF numerator coefficients
- `acoeffs`: (a1,...,a_order) = TF denominator coeffs (a0=1)

Reference

https://ccrma.stanford.edu/~jos/filters/Four_Direct_Forms.html

---

fir

FIR filter (convolution of FIR filter coefficients with a signal)

Usage

```
_ : fir(bv) : _
```

`fir` is standard Faust function.

Where:

- `bv` = b0,b1,...,bn is a parallel bank of coefficient signals.

Note

`bv` is processed using pattern-matching at compile time, so it must have this normal form (parallel signals).

Example

Smoothing white noise with a five-point moving average:

```
bv = .2,.2,.2,.2,.2;
process = noise : fir(bv);
```

Equivalent (note double parens):

```
process = noise : fir((.2,.2,.2,.2,.2));
```

`conv and convN`

Convolution of input signal with given coefficients.

Usage

```
_ : conv((k1,k2,k3,...,kN)) : _; // Argument = one signal bank
_ : convN(N,(k1,k2,k3,...)) : _; // Useful when N < count((k1,...))
```

`tf1, tf2 and tf3`

tfN = N'th-order direct-form digital filter.

Usage

```
_ : tf1(b0,b1,a1) : _
_ : tf2(b0,b1,b2,a1,a2) : _
_ : tf3(b0,b1,b2,b3,a1,a2,a3) : _
```

Where:

- `a`: the poles
- `b`: the zeros

Reference

https://ccrma.stanford.edu/~jos/fp/Direct_Form_I.html

`notchw`

Simple notch filter based on a biquad (`tf2`). `notchw` is a standard Faust function.

Usage:

```
_ : notchw(width,freq) : _
```

Where:

- `width`: "notch width" in Hz (approximate)
- `freq`: "notch frequency" in Hz

Reference

https://ccrma.stanford.edu/~jos/pasp/Phasing__2nd__Order__Allpass__Filters.
html

Direct-Form Second-Order Biquad Sections

Direct-Form Second-Order Biquad Sections

Reference

https://ccrma.stanford.edu/~jos/filters/Four__Direct__Forms.html

`tf21, tf22, tf22t and tf21t`

tfN = N'th-order direct-form digital filter where:

- `tf21` is tf2, direct-form 1
- `tf22` is tf2, direct-form 2
- `tf22t` is tf2, direct-form 2 transposed
- `tf21t` is tf2, direct-form 1 transposed

Usage

```
_ : tf21(b0,b1,b2,a1,a2) : _
_ : tf22(b0,b1,b2,a1,a2) : _
_ : tf22t(b0,b1,b2,a1,a2) : _
_ : tf21t(b0,b1,b2,a1,a2) : _
```

Where:

- `a`: the poles
- `b`: the zeros

Reference

https://ccrma.stanford.edu/~jos/fp/Direct_Form_I.html

Ladder/Lattice Digital Filters

Ladder and lattice digital filters generally have superior numerical properties relative to direct-form digital filters. They can be derived from digital waveguide filters, which gives them a physical interpretation.

`av2sv`

Compute reflection coefficients sv from transfer-function denominator av.

Usage

`sv = av2sv(av)`

Where:

- `av`: parallel signal bank `a1,...,aN`
- `sv`: parallel signal bank `s1,...,sN`

where `ro = ith` reflection coefficient, and `ai` = coefficient of `z^(-i)` in the filter transfer-function denominator `A(z)`.

Reference

https://ccrma.stanford.edu/~jos/filters/Step_Down_Procedure.html (where reflection coefficients are denoted by k rather than s).

`bvav2nuv`

Compute lattice tap coefficients from transfer-function coefficients.

Usage

`nuv = bvav2nuv(bv,av)`

Where:

- `av`: parallel signal bank `a1,...,aN`
- `bv`: parallel signal bank `b0,b1,...,aN`

- `nuv`: parallel signal bank `nu1,...,nuN`

where `nui` is the i'th tap coefficient, `bi` is the coefficient of `z^(-i)` in the filter numerator, `ai` is the coefficient of `z^(-i)` in the filter denominator

---

iir_lat2

Two-multiply latice IIR filter or arbitrary order.

Usage

`_ : iir_lat2(bv,av) : _`

Where:

- bv: zeros as a bank of parallel signals
- av: poles as a bank of parallel signals

---

allpassnt

Two-multiply lattice allpass (nested order-1 direct-form-ii allpasses).

Usage

`_ : allpassnt(n,sv) : _`

Where:

- `n`: the order of the filter
- `sv`: the reflexion coefficients (-1 1)

---

iir_kl

Kelly-Lochbaum ladder IIR filter or arbitrary order.

Usage

`_ : iir_kl(bv,av) : _`

Where:

- bv: zeros as a bank of parallel signals

- av: poles as a bank of parallel signals

---

allpassnklt

Kelly-Lochbaum ladder allpass.

Usage:

`_ : allpassklt(n,sv) : _`

Where:

- **n**: the order of the filter
- **sv**: the reflexion coefficients (-1 1)

---

iir_lat1

One-multiply latice IIR filter or arbitrary order.

Usage

`_ : iir_lat1(bv,av) : _`

Where:

- **bv**: zeros as a bank of parallel signals
- **av**: poles as a bank of parallel signals

---

allpassn1mt

One-multiply lattice allpass with tap lines.

Usage

`_ : allpassn1mt(n,sv) : _`

Where:

- **n**: the order of the filter
- **sv**: the reflexion coefficients (-1 1)

`iir_nl`

Normalized ladder filter of arbitrary order.

Usage

```
_ : iir_nl(bv,av) : _
```

Where:

- bv: zeros as a bank of parallel signals
- av: poles as a bank of parallel signals

References

- J. D. Markel and A. H. Gray, Linear Prediction of Speech, New York: Springer Verlag, 1976.
- https://ccrma.stanford.edu/~jos/pasp/Normalized_Scattering_ Junctions.html

---

`allpassnnlt`

Normalized ladder allpass filter of arbitrary order.

Usage:

```
_ : allpassnnlt(n,sv) : _
```

Where:

- `n`: the order of the filter
- `sv`: the reflexion coefficients (-1,1)

References

- J. D. Markel and A. H. Gray, Linear Prediction of Speech, New York: Springer Verlag, 1976.
- https://ccrma.stanford.edu/~jos/pasp/Normalized_Scattering_ Junctions.html

---

Useful Special Cases

`tf2np`

Biquad based on a stable second-order Normalized Ladder Filter (more robust to modulation than `tf2` and protected against instability).

Usage

`_ : tf2np(b0,b1,b2,a1,a2) : _`

Where:

- `a`: the poles
- `b`: the zeros

`wgr`

Second-order transformer-normalized digital waveguide resonator.

Usage

`_ : wgr(f,r) : _`

Where:

- `f`: resonance frequency (Hz)
- `r`: loss factor for exponential decay (set to 1 to make a numerically stable oscillator)

References

- https://ccrma.stanford.edu/~jos/pasp/Power_Normalized_Waveguide_Filters.html
- https://ccrma.stanford.edu/~jos/pasp/Digital_Waveguide_Oscillator.html

---

`nlf2`

Second order normalized digital waveguide resonator.

Usage

```
_ : nlf2(f,r) : _
```

Where:

- `f`: resonance frequency (Hz)
- `r`: loss factor for exponential decay (set to 1 to make a sinusoidal oscillator)

Reference

https://ccrma.stanford.edu/~jos/pasp/Power_Normalized_Waveguide_
Filters.html

`apnl`

Passive Nonlinear Allpass based on Pierce switching springs idea. Switch between allpass coefficient `a1` and `a2` at signal zero crossings.

Usage

```
_ : apnl(a1,a2) : _
```

Where:

- `a1` and `a2`: allpass coefficients

Reference

- "A Passive Nonlinear Digital Filter Design . . . " by John R. Pierce and Scott A. Van Duyne, JASA, vol. 101, no. 2, pp. 1120-1126, 1997

Ladder/Lattice Allpass Filters

An allpass filter has gain 1 at every frequency, but variable phase. Ladder/lattice allpass filters are specified by reflection coefficients. They are defined here as nested allpass filters, hence the names allpassn*.

References

- https://ccrma.stanford.edu/~jos/pasp/Conventional_Ladder_Filters.html
- https://ccrma.stanford.edu/~jos/pasp/Nested_Allpass_Filters.html
- Linear Prediction of Speech, Markel and Gray, Springer Verlag, 1976

`allpassn`

Two-multiply lattice - each section is two multiply-adds.

Usage:

```
_ : allpassn(n,sv) : _
```

Where:

- `n`: the order of the filter
- `sv`: the reflexion coefficients (-1 1)

References

- J. O. Smith and R. Michon, "Nonlinear Allpass Ladder Filters in FAUST", in Proceedings of the 14th International Conference on Digital Audio Effects (DAFx-11), Paris, France, September 19-23, 2011.

`allpassnn`

Normalized form - four multiplies and two adds per section, but coefficients can be time varying and nonlinear without "parametric amplification" (modulation of signal energy).

Usage:

```
_ : allpassnn(n,tv) : _
```

Where:

- `n`: the order of the filter
- `tv`: the reflexion coefficients (-PI PI)

`allpasskl`

Kelly-Lochbaum form - four multiplies and two adds per section, but all signals
have an immediate physical interpretation as traveling pressure waves, etc.

Usage:

`_ : allpassnkl(n,sv) : _`

Where:

- **n**: the order of the filter
- **sv**: the reflexion coefficients (-1 1)

`allpass1m`

One-multiply form - one multiply and three adds per section. Normally the most
efficient in special-purpose hardware.

Usage:

`_ : allpassn1m(n,sv) : _`

Where:

- **n**: the order of the filter
- **sv**: the reflexion coefficients (-1 1)

Digital Filter Sections Specified as Analog Filter Sections

`tf2s` and `tf2snp`

Second-order direct-form digital filter, specified by ANALOG transfer-function
polynomials B(s)/A(s), and a frequency-scaling parameter. Digitization via the
bilinear transform is built in.

Usage

`_ : tf2s(b2,b1,b0,a1,a0,w1) : _`

Where:

```
         b2 s^2 + b1 s + b0
H(s) = --------------------
            s^2 + a1 s + a0
```

and `w1` is the desired digital frequency (in radians/second) corresponding to analog frequency 1 rad/sec (i.e., `s = j`).

Example

A second-order ANALOG Butterworth lowpass filter, normalized to have cutoff frequency at 1 rad/sec, has transfer function

```
             1
H(s) = -----------------
         s^2 + a1 s + 1
```

where `a1 = sqrt(2)`. Therefore, a DIGITAL Butterworth lowpass cutting off at `SR/4` is specified as `tf2s(0,0,1,sqrt(2),1,PI*SR/2);`

Method

Bilinear transform scaled for exact mapping of w1.

Reference

https://ccrma.stanford.edu/~jos/pasp/Bilinear_Transformation.html

---

`tf3slf`

Analogous to tf2s above, but third order, and using the typical low-frequency-matching bilinear-transform constant 2/T ("lf" series) instead of the specific-frequency-matching value used in tf2s and tf1s. Note the lack of a "w1" argument.

Usage

`_ : tf3slf(b3,b2,b1,b0,a3,a2,a1,a0) : _`

`tf1s`

First-order direct-form digital filter, specified by ANALOG transfer-function polynomials B(s)/A(s), and a frequency-scaling parameter.

Usage

`tf1s(b1,b0,a0,w1)`

Where:

```
     b1 s + b0
```

H(s) = —————- s + a0

and `w1` is the desired digital frequency (in radians/second) corresponding to analog frequency 1 rad/sec (i.e., `s = j`).

Example

A first-order ANALOG Butterworth lowpass filter, normalized to have cutoff frequency at 1 rad/sec, has transfer function

```
        1
```

H(s) = ——— s + 1

so `b0 = a0 = 1` and `b1 = 0`. Therefore, a DIGITAL first-order Butterworth lowpass with gain -3dB at `SR/4` is specified as

`tf1s(0,1,1,PI*SR/2); // digital half-band order 1 Butterworth`

Method

Bilinear transform scaled for exact mapping of w1.

Reference

https://ccrma.stanford.edu/~jos/pasp/Bilinear__Transformation.html

———————————————————

`tf2sb`

Bandpass mapping of `tf2s`: In addition to a frequency-scaling parameter `w1` (set to HALF the desired passband width in rad/sec), there is a desired center-frequency parameter wc (also in rad/s). Thus, `tf2sb` implements a fourth-order digital bandpass filter section specified by the coefficients of a second-order analog lowpass prototpe section. Such sections can be combined in series for higher orders. The order of mappings is (1) frequency scaling (to set lowpass cutoff w1), (2) bandpass mapping to wc, then (3) the bilinear transform, with the usual scale parameter `2*SR`. Algebra carried out in maxima and pasted here.

Usage

```
_ : tf2sb(b2,b1,b0,a1,a0,w1,wc) : _
```

---

tf1sb

First-to-second-order lowpass-to-bandpass section mapping, analogous to tf2sb above.

Usage

```
_ : tf1sb(b1,b0,a0,w1,wc) : _
```

Simple Resonator Filters

resonlp

Simple resonant lowpass filter based on `tf2s` (virtual analog). `resonlp` is a standard Faust function.

Usage

```
_ : resonlp(fc,Q,gain) : _
_ : resonhp(fc,Q,gain) : _
_ : resonbp(fc,Q,gain) : _
```

Where:

- `fc`: center frequency (Hz)
- `Q`: q
- `gain`: gain (0-1)

---

resonhp

Simple resonant highpass filters based on `tf2s` (virtual analog). `resonhp` is a standard Faust function.

```
_ : resonlp(fc,Q,gain) : _
_ : resonhp(fc,Q,gain) : _
_ : resonbp(fc,Q,gain) : _
```

Where:

- `fc`: center frequency (Hz)
- `Q`: q
- `gain`: gain (0-1)

---

resonbp

Simple resonant bandpass filters based on `tf2s` (virtual analog). `resonbp` is a standard Faust function.

Usage

```
_ : resonlp(fc,Q,gain) : _
_ : resonhp(fc,Q,gain) : _
_ : resonbp(fc,Q,gain) : _
```

Where:

- `fc`: center frequency (Hz)
- `Q`: q
- `gain`: gain (0-1)

Butterworth Lowpass/Highpass Filters

lowpass

Nth-order Butterworth lowpass filter. `lowpass` is a standard Faust function.

Usage

```
_ : lowpass(N,fc) : _
```

Where:

- `N`: filter order (number of poles) [nonnegative constant integer]
- `fc`: desired cut-off frequency (-3dB frequency) in Hz

References

- https://ccrma.stanford.edu/~jos/filters/Butterworth_Lowpass_Design.
  html
- `butter` function in Octave (`"[z,p,g] = butter(N,1,'s');"`)

`highpass`

Nth-order Butterworth highpass filters. `highpass` is a standard Faust function.

Usage

`_ : highpass(N,fc) : _`

Where:

- `N`: filter order (number of poles) [nonnegative constant integer]
- `fc`: desired cut-off frequency (-3dB frequency) in Hz

References

- https://ccrma.stanford.edu/~jos/filters/Butterworth_Lowpass_Design.
  html
- `butter` function in Octave (`"[z,p,g] = butter(N,1,'s');"`)

`lowpass0_highpass1`

Special Filter-Bank Delay-Equalizing Allpass Filters

These special allpass filters are needed by filterbank et al. below. They are equivalent to (`lowpass(N,fc)` `+|-` `highpass(N,fc))/2`, but with canceling pole-zero pairs removed (which occurs for odd N).

`lowpass_plus|minus_highpass`

Elliptic (Cauer) Lowpass Filters

Elliptic (Cauer) Lowpass Filters

88

References

- <http://en.wikipedia.org/wiki/Elliptic_filter
- functions `ncauer` and `ellip` in Octave

`lowpass3e`

Third-order Elliptic (Cauer) lowpass filter.

Usage

```
_ : lowpass3e(fc) : _
```

Where:

- `fc`: -3dB frequency in Hz

Design

For spectral band-slice level display (see `octave_analyzer3e`):

```
[z,p,g] = ncauer(Rp,Rs,3);  % analog zeros, poles, and gain, where
Rp = 60  % dB ripple in stopband
Rs = 0.2 % dB ripple in passband
```

`lowpass6e`

Sixth-order Elliptic/Cauer lowpass filter.

Usage

```
_ : lowpass6e(fc) : _
```

Where:

- `fc`: -3dB frequency in Hz

Design

For spectral band-slice level display (see octave_analyzer6e):

```
[z,p,g] = ncauer(Rp,Rs,6);  % analog zeros, poles, and gain, where
 Rp = 80  % dB ripple in stopband
 Rs = 0.2 % dB ripple in passband
```

Elliptic Highpass Filters

highpass3e

Third-order Elliptic (Cauer) highpass filter. Inversion of `lowpass3e` wrt unit circle in s plane (s <- 1/s)

Usage

`_ : highpass3e(fc) : _`

Where:

- `fc`: -3dB frequency in Hz

---

highpass6e

Sixth-order Elliptic/Cauer highpass filter. Inversion of lowpass3e wrt unit circle in s plane (s <- 1/s)

Usage

`_ : highpass6e(fc) : _`

Where:

- `fc`: -3dB frequency in Hz

Butterworth Bandpass/Bandstop Filters

bandpass

Order 2*Nh Butterworth bandpass filter made using the transformation `s <- s + wc^2/s` on `lowpass(Nh)`, where `wc` is the desired bandpass center frequency. The `lowpass(Nh)` cutoff `w1` is half the desired bandpass width. `bandpass` is a standard Faust function.

Usage

`_ : bandpass(Nh,fl,fu) : _`

Where:

- `Nh`: HALF the desired bandpass order (which is therefore even)
- `fl`: lower -3dB frequency in Hz
- `fu`: upper -3dB frequency in Hz Thus, the passband width is `fu-fl`, and its center frequency is `(fl+fu)/2`.

Reference

http://cnx.org/content/m16913/latest/

---

bandstop

Order 2*Nh Butterworth bandstop filter made using the transformation `s <- s + wc^2/s` on `highpass(Nh)`, where `wc` is the desired bandpass center frequency. The `highpass(Nh)` cutoff `w1` is half the desired bandpass width. `bandstop` is a standard Faust function.

Usage

`_ : bandstop(Nh,fl,fu) : _`

Where:

- `Nh`: HALF the desired bandstop order (which is therefore even)
- `fl`: lower -3dB frequency in Hz
- `fu`: upper -3dB frequency in Hz Thus, the passband (stopband) width is `fu-fl`, and its center frequency is `(fl+fu)/2`.

Reference

http://cnx.org/content/m16913/latest/

Elliptic Bandpass Filters

bandpass6e

Order 12 elliptic bandpass filter analogous to `bandpass(6)`.

```
bandpass12e
```

Order 24 elliptic bandpass filter analogous to `bandpass(6).`

Parametric Equalizers (Shelf, Peaking)

Parametric Equalizers (Shelf, Peaking)

References

- http://en.wikipedia.org/wiki/Equalization
- http://www.musicdsp.org/files/Audio-EQ-Cookbook.txt
- Digital Audio Signal Processing, Udo Zolzer, Wiley, 1999, p. 124
- https://ccrma.stanford.edu/~jos/filters/Low_High_Shelving_Filters.html>
- https://ccrma.stanford.edu/~jos/filters/Peaking_Equalizers.html>
- maxmsp.lib in the Faust distribution
- bandfilter.dsp in the faust2pd distribution

low_shelf

First-order "low shelf" filter (gain boost|cut between dc and some frequency)
`low_shelf` is a standard Faust function.

Usage

```
_ : lowshelf(N,L0,fx) : _
_ : low_shelf(L0,fx) : _ // default case (order 3)
_ : lowshelf_other_freq(N,L0,fx) : _
```

Where: * `N`: filter order 1, 3, 5, . . . (odd only). (default should be 3) * `L0`: desired level (dB) between dc and fx (boost `L0>0` or cut `L0<0`) * `fx`: -3dB frequency of lowpass band (`L0>0`) or upper band (`L0<0`) (see "SHELF SHAPE" below).

The gain at SR/2 is constrained to be 1. The generalization to arbitrary odd orders is based on the well known fact that odd-order Butterworth band-splits are allpass-complementary (see filterbank documentation below for references).

Shelf Shape

The magnitude frequency response is approximately piecewise-linear on a log-log plot ("BODE PLOT"). The Bode "stick diagram" approximation L(lf) is easy to state in dB versus dB-frequency lf = dB(f):

- L0 > 0:

- L(lf) = L0, f between 0 and fx = 1st corner frequency;
- L(lf) = L0 - N * (lf - lfx), f between fx and f2 = 2nd corner frequency;
- L(lf) = 0, lf > lf2.
- lf2 = lfx + L0/N = dB-frequency at which level gets back to 0 dB.
- L0 < 0:
- L(lf) = L0, f between 0 and f1 = 1st corner frequency;
- L(lf) = - N * (lfx - lf), f between f1 and lfx = 2nd corner frequency;
- L(lf) = 0, lf > lfx.
- lf1 = lfx + L0/N = dB-frequency at which level goes up from L0.

See `lowshelf_other_freq`.

---

high_shelf

First-order "high shelf" filter (gain boost|cut above some frequency). `high_shelf` is a standard Faust function.

Usage

```
_ : highshelf(N,Lpi,fx) : _
_ : high_shelf(L0,fx) : _ // default case (order 3)
_ : highshelf_other_freq(N,Lpi,fx) : _
```

Where:

- `N`: filter order 1, 3, 5, ... (odd only).
- `Lpi`: desired level (dB) between fx and SR/2 (boost Lpi>0 or cut Lpi<0)
- `fx`: -3dB frequency of highpass band (L0>0) or lower band (L0<0) (Use highshelf_other_freq() below to find the other one.)

The gain at dc is constrained to be 1. See `lowshelf` documentation above for more details on shelf shape.

---

peak_eq

Second order "peaking equalizer" section (gain boost or cut near some frequency) Also called a "parametric equalizer" section. `peak_eq` is a standard Faust function.

Usage

```
_ : peak_eq(Lfx,fx,B) : _;
```

Where:

- **Lfx**: level (dB) at fx (boost Lfx>0 or cut Lfx<0)
- **fx**: peak frequency (Hz)
- **B**: bandwidth (B) of peak in Hz

———————————————

peak_eq_cq

Constant-Q second order peaking equalizer section.

Usage

`_ : peak_eq_cq(Lfx,fx,Q) : _;`

Where:

- **Lfx**: level (dB) at fx
- **fx**: boost or cut frequency (Hz)
- **Q**: "Quality factor" = fx/B where B = bandwidth of peak in Hz

———————————————

peak_eq_rm

Regalia-Mitra second order peaking equalizer section

Usage

`_ : peak_eq_rm(Lfx,fx,tanPiBT) : _;`

Where:

- **Lfx**: level (dB) at fx
- **fx**: boost or cut frequency (Hz)
- **tanPiBT**: `tan(PI*B/SR)`, where B = -3dB bandwidth (Hz) when $10^{(Lfx/20)} = 0 \sim PI*B/SR$ for narrow bandwidths B

Reference

P.A. Regalia, S.K. Mitra, and P.P. Vaidyanathan, "The Digital All-Pass Filter: A Versatile Signal Processing Building Block" Proceedings of the IEEE, 76(1):19-37, Jan. 1988. (See pp. 29-30.)

———————————————

`spectral_tilt`

Spectral tilt filter, providing an arbitrary spectral rolloff factor alpha in (-1,1), where -1 corresponds to one pole (-6 dB per octave), and +1 corresponds to one zero (+6 dB per octave). In other words, alpha is the slope of the ln magnitude versus ln frequency. For a "pinking filter" (e.g., to generate 1/f noise from white noise), set alpha to -1/2.

Usage

```
_ : spectral_tilt(N,f0,bw,alpha) : _
```

Where:

- `N`: desired integer filter order (fixed at compile time)
- `f0`: lower frequency limit for desired roll-off band
- `bw`: bandwidth of desired roll-off band
- `alpha`: slope of roll-off desired in nepers per neper (ln mag / ln radian freq)

Examples

See `spectral_tilt_demo`.

Reference

J.O. Smith and H.F. Smith, "Closed Form Fractional Integration and Differentiation via Real Exponentially Spaced Pole-Zero Pairs", arXiv.org publication arXiv:1606.06154 [cs.CE], June 7, 2016, http://arxiv.org/abs/1606.06154

`levelfilter`

Dynamic level lowpass filter. `levelfilter` is a standard Faust function.

Usage

```
_ : levelfilter(L,freq) : _
```

Where:

- `L`: desired level (in dB) at Nyquist limit (SR/2), e.g., -60
- `freq`: corner frequency (-3dB point) usually set to fundamental freq
- `N`: Number of filters in series where L = L/N

https://ccrma.stanford.edu/realsimple/faust_strings/Dynamic_Level_
Lowpass_Filter.html

---

levelfilterN

Dynamic level lowpass filter.

Usage

```
_ : levelfilterN(N,freq,L) : _
```

Where:

- `L`: desired level (in dB) at Nyquist limit (SR/2), e.g., -60
- `freq`: corner frequency (-3dB point) usually set to fundamental freq
- `N`: Number of filters in series where L = L/N

Reference

https://ccrma.stanford.edu/realsimple/faust_strings/Dynamic_Level_
Lowpass_Filter.html

Mth-Octave Filter-Banks

Mth-octave filter-banks split the input signal into a bank of parallel signals, one for each spectral band. They are related to the Mth-Octave Spectrum-Analyzers in `analysis.lib`. The documentation of this library contains more details about the implementation. The parameters are:

- `M`: number of band-slices per octave (>1)
- `N`: total number of bands (>2)
- `ftop`: upper bandlimit of the Mth-octave bands ($<SR/2$)

In addition to the Mth-octave output signals, there is a highpass signal containing frequencies from ftop to SR/2, and a "dc band" lowpass signal containing frequencies from 0 (dc) up to the start of the Mth-octave bands. Thus, the N output signals are

```
highpass(ftop), MthOctaveBands(M,N-2,ftop), dcBand(ftop*2^(-M*(N-1)))
```

A Filter-Bank is defined here as a signal bandsplitter having the property that summing its output signals gives an allpass-filtered version of the filter-bank input signal. A more conventional term for this is an "allpass-complementary filter bank". If the allpass filter is a pure delay (and possible scaling), the filter bank is said to be a "perfect-reconstruction filter bank" (see Vaidyanathan-1993 cited below for details). A "graphic equalizer", in which band signals are scaled by gains and summed, should be based on a filter bank.

The filter-banks below are implemented as Butterworth or Elliptic spectrum-analyzers followed by delay equalizers that make them allpass-complementary.

Increasing Channel Isolation

Go to higher filter orders - see Regalia et al. or Vaidyanathan (cited below) regarding the construction of more aggressive recursive filter-banks using elliptic or Chebyshev prototype filters.

References

- "Tree-structured complementary filter banks using all-pass sections", Regalia et al., IEEE Trans. Circuits & Systems, CAS-34:1470-1484, Dec. 1987
- "Multirate Systems and Filter Banks", P. Vaidyanathan, Prentice-Hall, 1993
- Elementary filter theory: https://ccrma.stanford.edu/~jos/filters/

`mth_octave_filterbank[n]`

Allpass-complementary filter banks based on Butterworth band-splitting. For Butterworth band-splits, the needed delay equalizer is easily found.

Usage

```
_ : mth_octave_filterbank(O,M,ftop,N) : par(i,N,_); // Oth-order
_ : mth_octave_filterbank_alt(O,M,ftop,N) : par(i,N,_); // dc-inverted version
```

Also for convenience:

```
_ : mth_octave_filterbank3(M,ftop,N) : par(i,N,_); // 3rd-order Butterworth
_ : mth_octave_filterbank5(M,ftop,N) : par(i,N,_); // 5th-order Butterworth
mth_octave_filterbank_default = mth_octave_filterbank5;
```

Where:

- `O`: order of filter used to split each frequency band into two
- `M`: number of band-slices per octave
- `ftop`: highest band-split crossover frequency (e.g., 20 kHz)

- `N`: total number of bands (including dc and Nyquist)

Arbritary-Crossover Filter-Banks and Spectrum Analyzers

These are similar to the Mth-octave analyzers above, except that the band-split frequencies are passed explicitly as arguments.

filterbank

Filter bank. `filterbank` is a standard Faust function.

Usage

```
_ : filterbank (O,freqs) : par(i,N,_); // Butterworth band-splits
```

Where:

- `O`: band-split filter order (ODD integer required for filterbank[i])
- `freqs`: (fc1,fc2,...,fcNs) [in numerically ascending order], where Ns=N-1 is the number of octave band-splits (total number of bands N=Ns+1).

If frequencies are listed explicitly as arguments, enclose them in parens:

```
_ : filterbank(3,(fc1,fc2)) : _,_,_
```

---

filterbanki

Inverted-dc filter bank.

Usage

```
_ : filterbanki(O,freqs) : par(i,N,_); // Inverted-dc version
```

Where:

- `O`: band-split filter order (ODD integer required for `filterbank[i]`)
- `freqs`: (fc1,fc2,...,fcNs) [in numerically ascending order], where Ns=N-1 is the number of octave band-splits (total number of bands N=Ns+1).

If frequencies are listed explicitly as arguments, enclose them in parens:

```
_ : filterbanki(3,(fc1,fc2)) : _,_,_
```

---

hoa.lib

Faust library for high order ambisonic. Its official prefix is `ho`.

encoder

Ambisonic encoder. Encodes a signal in the circular harmonics domain depending on an order of decomposition and an angle.

Usage

```
encoder(n, x, a) : _
```

Where:

- `n`: the order
- `x`: the signal
- `a`: the angle

---

decoder

Decodes an ambisonics sound field for a circular array of loudspeakers.

Usage

```
_ : decoder(n, p) : _
```

Where:

- `n`: the order
- `p`: the number of speakers

Note

Number of loudspeakers must be greater or equal to 2n+1. It's preferable to use 2n+2 loudspeakers.

```
decoderStereo
```

Decodes an ambisonic sound field for stereophonic configuration. An "home made" ambisonic decoder for stereophonic restitution (30° - 330°) : Sound field lose energy around 180°. You should use `inPhase` optimization with ponctual sources. #### Usage

`_ : decoderStereo(n) : _`

Where:

- **n**: the order

Optimization Functions

Functions to weight the circular harmonics signals depending to the ambisonics optimization. It can be `basic` for no optimization, `maxRe` or `inPhase`.

```
optimBasic
```

The basic optimization has no effect and should be used for a perfect circle of loudspeakers with one listener at the perfect center loudspeakers array.

Usage

`_ : optimBasic(n) : _`

Where:

- **n**: the order

```
optimMaxRe
```

The maxRe optimization optimize energy vector. It should be used for an auditory confined in the center of the loudspeakers array.

Usage

`_ : optimMaxRe(n) : _`

Where:

- **n**: the order

---

optimInPhase

The inPhase Optimization optimize energy vector and put all loudspeakers signals n phase. It should be used for an auditory.

Usage

" optimInPhase(n) : _ "

here:

n: the order

---

wider

Can be used to wide the diffusion of a localized sound. The order depending signals are weighted and appear in a logarithmic way to have linear changes.

Usage

`_ : wider(n,w) : _`

Where:

- **n**: the order
- **w**: the width value between 0 - 1

---

map

It simulate the distance of the source by applying a gain on the signal and a wider processing on the soundfield.

Usage

`map(n, x, r, a)`

Where:

- **n**: the order
- **x**: the signal

- `r`: the radius
- `a`: the angle in radian

---

rotate

Rotates the sound field.

Usage

```
_ : rotate(n, a) : _
```

Where:

- `n`: the order
- `a`: the angle in radian

---

maths.lib

Mathematic library for Faust. Some functions are implemenented as Faust foreign functions of `math.h` functions that are not part of Faust's primitives. Defines also various constants and several utilities.

The official prefix of this library is `ma`.

Functions Reference

SR

Current sampling rate (between 1000Hz and 192000Hz). Constant during program execution.

Usage

```
SR : _
```

BS

Current block-size. Can change during the execution.

Usage

```
BS : _
```

`PI`

Constant PI in double precisio.n

Usage

```
PI : _
```

`FTZ`

Flush to zero: force samples under the "maximum subnormal number" to be zero. Usually not needed in C++ because the architecture file take care of this, but can be useful in javascript for instance.

Usage

```
_ : ftz : _
```

See : http://docs.oracle.com/cd/E19957-01/806-3568/ncg_math.html

---

neg

Invert the sign (-x) of a signal.

Usage

```
_ : neg : _
```

---

sub(x,y)

Subtract `x` and `y`.

---

inv

Compute the inverse (1/x) of the input signal.

Usage

`_ : inv : _`

---

cbrt

Computes the cube root of of the input signal.

Usage

`_ : cbrt : _`

---

hypot

Computes the euclidian distance of the two input signals sqrt(xx+yy) without undue overflow or underflow.

Usage

`_,_ : hypot : _`

---

ldexp

Takes two input signals: x and n, and multiplies x by 2 to the power n.

Usage

`_,_ : ldexp : _`

---

scalb

Takes two input signals: x and n, and multiplies x by 2 to the power n.

Usage

`_,_ : scalb : _`

`log1p`

Computes $\log(1 + x)$ without undue loss of accuracy when x is nearly zero.

Usage

`_ : log1p : _`

`logb`

Return exponent of the input signal as a floating-point number.

Usage

`_ : logb : _`

`ilogb`

Return exponent of the input signal as an integer number.

Usage

`_ : ilogb : _`

`log2`

Returns the base 2 logarithm of x.

Usage

`_ : log2 : _`

---

expm1

Return exponent of the input signal minus 1 with better precision.

Usage

`_ : expm1 : _`

---

acosh

Computes the principle value of the inverse hyperbolic cosine of the input signal.

Usage

`_ : acosh : _`

---

asinh

Computes the inverse hyperbolic sine of the input signal.

Usage

`_ : asinh : _`

---

atanh

Computes the inverse hyperbolic tangent of the input signal.

Usage

`_ : atanh : _`

---

sinh

Computes the hyperbolic sine of the input signal.

`_ : sinh : _`

---

cosh

Computes the hyperbolic cosine of the input signal.

Usage

`_ : cosh : _`

---

tanh

Computes the hyperbolic tangent of the input signal.

Usage

`_ : tanh : _`

---

erf

Computes the error function of the input signal.

Usage

`_ : erf : _`

---

erfc

Computes the complementary error function of the input signal.

Usage

`_ : erfc : _`

`gamma`

Computes the gamma function of the input signal.

Usage

`_ : gamma : _`

`lgamma`

Calculates the natural logorithm of the absolute value of the gamma function of the input signal.

Usage

`_ : lgamma : _`

`J0`

Computes the Bessel function of the first kind of order 0 of the input signal.

Usage

`_ : J0 : _`

`J1`

Computes the Bessel function of the first kind of order 1 of the input signal.

Usage

`_ : J1 : _`

Jn

Computes the Bessel function of the first kind of order n (first input signal) of the second input signal.

Usage

`_,_ : Jn : _`

Y0

Computes the linearly independent Bessel function of the second kind of order 0 of the input signal.

Usage

`_ : Y0 : _`

Y1

Computes the linearly independent Bessel function of the second kind of order 1 of the input signal.

Usage

`_ : Y0 : _`

Yn

Computes the linearly independent Bessel function of the second kind of order n (first input signal) of the second input signal.

Usage

`_,_ : Yn : _`

---

fabs, fmax, fmin

Just for compatibility...

```
fabs = abs
fmax = max
fmin = min
```

---

np2

Gives the next power of 2 of x.

Usage

```
np2(n) : _
```

Where:

- **n**: an integer

---

frac

Gives the fractional part of n.

Usage

```
frac(n) : _
```

Where:

- **n**: a decimal number

---

modulo

Modulus operation.

Usage

```
modulo(x,N) : _
```

Where:

- `x`: the numerator
- `N`: the denominator

`isnan`

Return non-zero if and only if x is a NaN.

Usage

```
isnan(x)
_ : isnan : _
```

Where:

- `x`: signal to analyse

`chebychev`

Chebychev transformation of order n.

Usage

```
_ : chebychev(n) : _
```

Where:

- `n`: the order of the polynomial

Semantics

```
T[0](x) = 1,
T[1](x) = x,
T[n](x) = 2x*T[n-1](x) - T[n-2](x)
```

Reference

http://en.wikipedia.org/wiki/Chebyshev_polynomial

`chebychevpoly`

Linear combination of the first Chebyshev polynomials.

Usage

```
_ : chebychevpoly((c0,c1,...,cn)) : _
```

Where:

- `cn`: the different Chebychevs polynomials such that: chebychevpoly((c0,c1,...,cn)) = Sum of chebychev(i)*ci

Reference

http://www.csounds.com/manual/html/chebyshevpoly.html

`diffn`

Negated first-order difference.

Usage

```
_ : diffn : _
```

`signum`

The signum function signum(x) is defined as -1 for x<0, 0 for x==0, and 1 for x>0;

Usage

```
_ : signum : _
```

---

misceffects.lib

This library contains a collection of audio effects. Its official prefix is `ef`.

Dynamic

cubicnl

Cubic nonlinearity distortion. `cubicnl` is a standard Faust library.

Usage:

```
_ : cubicnl(drive,offset) : _
_ : cubicnl_nodc(drive,offset) : _
```

Where:

- `drive`: distortion amount, between 0 and 1
- `offset`: constant added before nonlinearity to give even harmonics. Note: offset can introduce a nonzero mean - feed cubicnl output to dcblocker to remove this.

References:

- https://ccrma.stanford.edu/~jos/pasp/Cubic_Soft_Clipper.html
- https://ccrma.stanford.edu/~jos/pasp/Nonlinear_Distortion.html

---

gate_mono

Mono signal gate. `gate_mono` is a standard Faust function.

Usage

```
_ : gate_mono(thresh,att,hold,rel) : _
```

Where:

- `thresh`: dB level threshold above which gate opens (e.g., -60 dB)
- `att`: attack time = time constant (sec) for gate to open (e.g., 0.0001 s = 0.1 ms)
- `hold`: hold time = time (sec) gate stays open after signal level < thresh (e.g., 0.1 s)
- `rel`: release time = time constant (sec) for gate to close (e.g., 0.020 s = 20 ms)

References

- http://en.wikipedia.org/wiki/Noise_gate
- http://www.soundonsound.com/sos/apr01/articles/advanced.asp
- http://en.wikipedia.org/wiki/Gating_(sound_engineering)

———————————————————

`gate_stereo`

Stereo signal gates. `gate_stereo` is a standard Faust function.

Usage

```
_,_ : gate_stereo(thresh,att,hold,rel) : _,_
```

Where:

- `thresh`: dB level threshold above which gate opens (e.g., -60 dB)
- `att`: attack time = time constant (sec) for gate to open (e.g., 0.0001 s = 0.1 ms)
- `hold`: hold time = time (sec) gate stays open after signal level < thresh (e.g., 0.1 s)
- `rel`: release time = time constant (sec) for gate to close (e.g., 0.020 s = 20 ms)

References

- http://en.wikipedia.org/wiki/Noise_gate
- http://www.soundonsound.com/sos/apr01/articles/advanced.asp
- http://en.wikipedia.org/wiki/Gating_(sound_engineering)

———————————————————

Filtering

`speakerbp`

Dirt-simple speaker simulator (overall bandpass eq with observed roll-offs above and below the passband).

Low-frequency speaker model = +12 dB/octave slope breaking to flat near f1. Implemented using two dc blockers in series.

High-frequency model = -24 dB/octave slope implemented using a fourth-order Butterworth lowpass.

Example based on measured Celestion G12 (12″ speaker):

`speakerbp` is a standard Faust function

Usage

```
speakerbp(f1,f2)
_ : speakerbp(130,5000) : _
```

---

piano_dispersion_filter

Piano dispersion allpass filter in closed form.

Usage

```
piano_dispersion_filter(M,B,f0)
_ : piano_dispersion_filter(1,B,f0) : +(totalDelay),_ : fdelay(maxDelay) : _
```

Where:

- `M`: number of first-order allpass sections (compile-time only) Keep below 20. 8 is typical for medium-sized piano strings.
- `B`: string inharmonicity coefficient (0.0001 is typical)
- `f0`: fundamental frequency in Hz

Outputs

- MINUS the estimated delay at `f0` of allpass chain in samples, provided in negative form to facilitate subtraction from delay-line length.
- Output signal from allpass chain

stereo_width

Stereo Width effect using the Blumlein Shuffler technique. `stereo_width` is a standard Faust function.

Usage

```
_,_ : stereo_width(w) : _,_
```

Where:

- `w`: stereo width between 0 and 1

At `w=0`, the output signal is mono ((left+right)/2 in both channels). At `w=1`, there is no effect (original stereo image). Thus, w between 0 and 1 varies stereo width from 0 to "original".

Reference

- "Applications of Blumlein Shuffling to Stereo Microphone Techniques" Michael A. Gerzon, JAES vol. 42, no. 6, June 1994

Time Based

`echo`

A simple echo effect.

`echo` is a standard Faust function

Usage

```
_ : echo(maxDuration,duration,feedback) : _
```

Where:

- `maxDuration`: the max echo duration in seconds
- `duration`: the echo duration in seconds
- `feedback`: the feedback coefficient

Pitch Shifting

`transpose`

A simple pitch shifter based on 2 delay lines. `transpose` is a standard Faust function.

Usage

```
_ : transpose(w, x, s) : _
```

Where:

- `w`: the window length (samples)
- `x`: crossfade duration duration (samples)
- `s`: shift (semitones)

Meshes

mesh_square

Square Rectangular Digital Waveguide Mesh.

Usage

`bus(4*N) : mesh_square(N) : bus(4*N);`

Where:

- `N`: number of nodes along each edge - a power of two (1,2,4,8,...)

Reference

https://ccrma.stanford.edu/~jos/pasp/Digital_Waveguide_Mesh.html

Signal Order In and Out

The mesh is constructed recursively using 2x2 embeddings. Thus, the top level of `mesh_square(M)` is a block 2x2 mesh, where each block is a `mesh(M/2)`. Let these blocks be numbered 1,2,3,4 in the geometry NW,NE,SW,SE, i.e., as 1 2 3 4 Each block has four vector inputs and four vector outputs, where the length of each vector is `M/2`. Label the input vectors as Ni,Ei,Wi,Si, i.e., as the inputs from the North, East South, and West, and similarly for the outputs. Then, for example, the upper left input block of M/2 signals is labeled 1Ni. Most of the connections are internal, such as 1Eo -> 2Wi. The `8*(M/2)` input signals are grouped in the order 1Ni 2Ni 3Si 4Si 1Wi 3Wi 2Ei 4Ei and the output signals are 1No 1Wo 2No 2Eo 3So 3Wo 4So 4Eo or

In: 1No 1Wo 2No 2Eo 3So 3Wo 4So 4Eo

Out: 1Ni 2Ni 3Si 4Si 1Wi 3Wi 2Ei 4Ei

Thus, the inputs are grouped by direction N,S,W,E, while the outputs are grouped by block number 1,2,3,4, which can also be interpreted as directions NW, NE, SW, SE. A simple program illustrating these orderings is `process = mesh_square(2);`.

Example

Reflectively terminated mesh impulsed at one corner:

```
mesh_square_test(N,x) = mesh_square(N)~(busi(4*N,x)) // input to corner
with { busi(N,x) = bus(N) : par(i,N,*(-1)) : par(i,N-1,_), +(x); };
process = 1-1' : mesh_square_test(4); // all modes excited forever
```

In this simple example, the mesh edges are connected as follows:

1No -> 1Ni, 1Wo -> 2Ni, 2No -> 3Si, 2Eo -> 4Si,

3So -> 1Wi, 3Wo -> 3Wi, 4So -> 2Ei, 4Eo -> 4Ei

A routing matrix can be used to obtain other connection geometries.

----

noises.lib

Faust Noise Generator Library. Its official prefix is `no`.

Functions Reference

`noise`

White noise generator (outputs random number between -1 and 1). `Noise` is a standard Faust function.

Usage

```
noise : _
```

`multirandom`

Generates multiple decorrelated random numbers in parallel.

Usage

```
multirandom(n) : si.bus(n)
```

Where:

- `n`: the number of decorrelated random numbers in parallel

`multinoise`

Generates multiple decorrelated noises in parallel.

Usage

```
multinoise(n) : si.bus(n)
```

Where:

- `n`: the number of decorrelated random numbers in parallel

---

noises

TODO.

---

pink_noise

Pink noise (1/f noise) generator (third-order approximation) `pink_noise` is a standard Faust function.

Usage

```
pink_noise : _;
```

Reference:

https://ccrma.stanford.edu/~jos/sasp/Example_Synthesis_1_F_Noise.html

---

pink_noise_vm

Multi pink noise generator.

Usage

```
pink_noise_vm(N) : _;
```

Where:

- `N`: number of latched white-noise processes to sum, not to exceed sizeof(int) in C++ (typically 32).

References

- http://www.dsprelated.com/showarticle/908.php
- http://www.firstpr.com.au/dsp/pink-noise/#Voss-McCartney

---

lfnoise, lfnoise0 and lfnoiseN

Low-frequency noise generators (Butterworth-filtered downsampled white noise)

Usage

```
lfnoise0(rate) : _;   // new random number every int(SR/rate) samples or so
lfnoiseN(N,rate) : _; // same as "lfnoise0(rate) : lowpass(N,rate)" [see filters.lib]
lfnoise(rate) : _;    // same as "lfnoise0(rate) : seq(i,5,lowpass(N,rate))" (no overshoot)
```

Example

(view waveforms in faust2octave):

```
rate = SR/100.0; // new random value every 100 samples (SR from music.lib)
process = lfnoise0(rate),   // sampled/held noise (piecewise constant)
          lfnoiseN(3,rate), // lfnoise0 smoothed by 3rd order Butterworth LPF
          lfnoise(rate);    // lfnoise0 smoothed with no overshoot
```

---

sparse_noise_vm

sparse noise generator.

Usage

```
sparse_noise(f0) : _;
```

Where:

- `f0`: average frequency of noise impulses per second

Random impulses in the amplitude range -1 to 1 are generated at an average
rate of f0 impulses per second.

Reference

- See velvet_noise

`velvet_noise_vm`

velvet noise generator.

Usage

`velvet_noise(amp,f0) : _;`

Where:

- `amp`: amplitude of noise impulses (positive and negative)
- `f0`: average frequency of noise impulses per second

Reference

- Matti Karjalainen and Hanna Jarvelainen, "Reverberation Modeling Using Velvet Noise", in Proc. 30th Int. Conf. Intelligent Audio Environments (AES07), March 2007.

`gnoise`

approximate zero-mean, unit-variance Gaussian white noise generator

Usage

`gnoise(N) : _;`

Where:

- `N`: number of uniform random numbers added to approximate Gaussian white noise

Reference

- See Central Limit Theorem

---

oscillators.lib

This library contains a collection of sound generators. Its official prefix is `os`.

Wave-Table-Based Oscillators

sinwaveform

Sine waveform ready to use with a `rdtable`.

Usage

```
sinwaveform(tablesize) : _
```
Where:

- `tablesize`: the table size

---

coswaveform

Cosine waveform ready to use with a `rdtable`.

Usage

```
coswaveform(tablesize) : _
```
Where:

- `tablesize`: the table size

---

phasor

A simple phasor to be used with a `rdtable`. `phasor` is a standard Faust function.

Usage

```
phasor(tablesize,freq) : _
```
Where:

- `tablesize`: the table size
- `freq`: the frequency of the wave (Hz)

---

hs_phasor

Hardsyncing phasor to be used with an `rdtable`.

Usage

```
hs_phasor(ts,freq,c) :   _
```

Where:

- `ts`: the tablesize for the related sine wavetable
- `freq`: the fundamental frequency of the phasor
- `c`: a clock signal, `c>0` resets phase to 0

---

oscsin

Sine wave oscillator. `oscsin` is a standard Faust function.

Usage

```
oscsin(freq) : _
```

Where:

- `freq`: the frequency of the wave (Hz)

---

hs_oscsin

Sin lookup table with hardsyncing phase.

Usage

```
hs_oscsin(freq,c) : _
```

Where:

- `freq`: the fundamental frequency of the phasor
- `c`: a clock signal, `c>0` resets phase to 0

---

osccos

Cosine wave oscillator.

Usage

```
osccos(freq) : _
```

Where:

- `freq`: the frequency of the wave (Hz)

---

oscp

A sine wave generator with controllable phase.

Usage

```
oscp(freq,p) : _
```

Where:

- `freq`: the frequency of the wave (Hz)
- `p`: the phase in radian

---

osci

Interpolated phase sine wave oscillator.

Usage

```
osci(freq) : _
```

Where:

- `freq`: the frequency of the wave (Hz)

LFOs

Low-Frequency Oscillators (LFOs) have prefix `lf_` (no aliasing suppression, which is not audible at LF).

lf_imptrain

Unit-amplitude low-frequency impulse train. `lf_imptrain` is a standard Faust function.

Usage

`lf_imptrain(freq) : _`

Where:

- `freq`: frequency in Hz

---

lf_pulsetrainpos

Unit-amplitude nonnegative LF pulse train, duty cycle between 0 and 1

Usage

`lf_pulsetrainpos(freq,duty) : _`

Where:

- `freq`: frequency in Hz
- `duty`: duty cycle between 0 and 1

---

lf_pulsetrain

Unit-amplitude zero-mean LF pulse train, duty cycle between 0 and 1

Usage

`lf_pulsetrain(freq,duty) : _`

Where:

- `freq`: frequency in Hz
- `duty`: duty cycle between 0 and 1

---

lf_squarewavepos

Positive LF square wave in [0,1]

Usage

```
lf_squarewavepos(freq) : _
```

Where:

- `freq`: frequency in Hz

---

lf_squarewave

Zero-mean unit-amplitude LF square wave. `lf_squarewave` is a standard Faust function.

Usage

```
lf_squarewave(freq) : _
```

Where:

- `freq`: frequency in Hz

---

lf_trianglepos

Positive unit-amplitude LF positive triangle wave

Usage

```
lf_trianglepos(freq) : _
```

Where:

- `freq`: frequency in Hz

Low Frequency Sawtooths

Sawtooth waveform oscillators for virtual analog synthesis et al. The 'simple' versions (`lf_rawsaw`, `lf_sawpos` and `saw1`), are mere samplings of the ideal continuous-time ("analog") waveforms. While simple, the aliasing due to sampling is quite audible. The differentiated polynomial waveform family (`saw2`, `sawN`, and derived functions) do some extra processing to suppress aliasing (not audible for very low fundamental frequencies). According to Lehtonen et al. (JASA 2012), the aliasing of `saw2` should be inaudible at fundamental frequencies

below 2 kHz or so, for a 44.1 kHz sampling rate and 60 dB SPL presentation level; fundamentals 415 and below required no aliasing suppression (i.e., `saw1` is ok).

`lf_rawsaw`

Simple sawtooth waveform oscillator between 0 and period in samples.

Usage

`lf_rawsaw(periodsamps)`

Where:

- `periodsamps`: number of periods per samples

`lf_sawpos_phase`

Simple sawtooth waveform oscillator between 0 and 1 with phase control.

Usage

`lf_sawpos_phase(freq,phase)`

Where:

- `freq`: frequency
- `phase`: phase

Bandlimited Sawtooth

`//─────────sawN──────────` Bandlimited Sawtooth

`sawN(N,freq)`, `sawNp`, `saw2dpw(freq)`, `saw2(freq)`, `saw3(freq)`, `saw4(freq)`, `saw5(freq)`, `saw6(freq)`, `sawtooth(freq)`, `saw2f2(freq)` `saw2f4(freq)`

Method 1 (`saw2`)

Polynomial Transition Regions (PTR) (for aliasing suppression)

Reference

- Kleimola, J.; Valimaki, V., "Reducing Aliasing from Synthetic Audio Signals Using Polynomial Transition Regions," in Signal Processing Letters, IEEE , vol.19, no.2, pp.67-70, Feb. 2012
- https://aaltodoc.aalto.fi/bitstream/handle/123456789/7747/publication6. pdf?sequence=9
- http://research.spa.aalto.fi/publications/papers/spl-ptr/

Method 2 (`sawN`)

Differentiated Polynomial Waves (DPW) (for aliasing suppression)

Reference

"Alias-Suppressed Oscillators based on Differentiated Polynomial Waveforms", Vesa Valimaki, Juhan Nam, Julius Smith, and Jonathan Abel, IEEE Tr. Acoustics, Speech, and Language Processing (IEEE-ASLP), Vol. 18, no. 5, May 2010.

Other Cases

Correction-filtered versions of `saw2`: `saw2f2`, `saw2f4` The correction filter compensates "droop" near half the sampling rate. See reference for sawN.

Usage

```
sawN(N,freq) : _
sawNp(N,freq,phase) : _
saw2dpw(freq) : _
saw2(freq) : _
saw3(freq) : _ // based on sawN
saw4(freq) : _ // based on sawN
saw5(freq) : _ // based on sawN
saw6(freq) : _ // based on sawN
sawtooth(freq) : _ // = saw2
saw2f2(freq) : _
saw2f4(freq) : _
```

Where:

- `N`: polynomial order
- `freq`: frequency in Hz
- `phase`: phase

sawNp

TODO: MarkDown doc in comments

---

saw2dpw

TODO: MarkDown doc in comments

---

saw3

TODO: MarkDown doc in comments

---

sawtooth

Alias-free sawtooth wave. 2nd order interpolation (based on `saw2`). `sawtooth` is a standard Faust function.

Usage

`sawtooth(freq) : _`

Where:

* `freq`: frequency

---

saw2f2

TODO: MarkDown doc in comments

---

saw2f4

TODO: MarkDown doc in comments

Bandlimited Pulse, Square, and Impulse Trains

Bandlimited Pulse, Square, and Impulse Trains

`pulsetrainN`, `pulsetrain`, `squareN`, `square`, `imptrain`, `imptrainN`, `triangle`, `triangleN`

All are zero-mean and meant to oscillate in the audio frequency range. Use simpler sample-rounded lf_* versions above for LFOs.

Usage

```
pulsetrainN(N,freq,duty) : _
pulsetrain(freq, duty) : _ // = pulsetrainN(2)
squareN(N, freq) : _
square : _ // = squareN(2)
imptrainN(N,freq) : _
imptrain : _ // = imptrainN(2)
triangleN(N,freq) : _
triangle : _ // = triangleN(2)
```

Where:

- `N`: polynomial order
- `freq`: frequency in Hz

pulsetrainN

TODO: MarkDown doc in comments

---

pulsetrain

Bandlimited pulse train oscillator. Based on `pulsetrainN(2)`. `pulsetrain` is a standard Faust function.

Usage

`pulsetrain(freq, duty) : _`

Where:

- `freq`: frequency
- `duty`: duty cycle between 0 and 1

---

squareN

TODO: MarkDown doc in comments

---

square

Bandlimited square wave oscillator. Based on `squareN(2)`. `square` is a standard Faust function.

Usage

```
square(freq) : _
```

Where:

- `freq`: frequency

---

impulse

One-time impulse generated when the Faust process is started. `impulse` is a standard Faust function.

Usage

```
impulse : _
```

---

imptrainN

TODO: MarkDown doc in comments

---

imptrain

Bandlimited impulse train generator. Based on `imptrainN(2)`. `imptrain` is a standard Faust function.

Usage

`imptrain(freq) : _`

Where:

- `freq`: frequency

---

triangleN

TODO: MarkDown doc in comments

---

triangle

Bandlimited triangle wave oscillator. Based on `triangleN(2)`. `triangle` is a standard Faust function.

Usage

`triangle(freq) : _`

Where:

- `freq`: frequency

Filter-Based Oscillators

Filter-Based Oscillators

Usage

`osc[b|r|rs|rc|s|w](f), where f = frequency in Hz.`

References

- http://lac.linuxaudio.org/2012/download/lac12-slides-jos.pdf
- https://ccrma.stanford.edu/~jos/pdf/lac12-paper-jos.pdf

oscb

Sinusoidal oscillator based on the biquad.

Usage

```
oscb(freq) : _
```

Where:

- `freq`: frequency

---

oscrq

Sinusoidal (sine and cosine) oscillator based on 2D vector rotation, = undamped "coupled-form" resonator = lossless 2nd-order normalized ladder filter.

Usage

```
oscrq(freq) : _,_
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Normalized_Scattering_Junctions.html

---

oscrs

Sinusoidal (sine) oscillator based on 2D vector rotation, = undamped "coupled-form" resonator = lossless 2nd-order normalized ladder filter.

Usage

```
oscrs(freq) : _
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Normalized_Scattering_
  Junctions.html

---

oscrc

Sinusoidal (cosine) oscillator based on 2D vector rotation, = undamped "coupled-form" resonator = lossless 2nd-order normalized ladder filter.

Usage

```
oscrc(freq) : _
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Normalized_Scattering_
  Junctions.html

---

osc

Default sine wave oscillator (same as oscrs). `osc` is a standard Faust function.

Usage

```
osc(freq) : _
```

Where:

- `freq`: the frequency of the wave (Hz)

---

oscs

Sinusoidal oscillator based on the state variable filter = undamped "modified-coupled-form" resonator = "magic circle" algorithm used in graphics

---

Waveguide-Resonator-Based Oscillators

Sinusoidal oscillator based on the waveguide resonator `wgr`.

`oscw`

Sinusoidal oscillator based on the waveguide resonator `wgr`. Unit-amplitude cosine oscillator.

Usage

```
oscwc(freq) : _
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Digital_Waveguide_Oscillator.html

---

`oscws`

Sinusoidal oscillator based on the waveguide resonator `wgr`. Unit-amplitude sine oscillator

Usage

```
oscws(freq) : _
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Digital_Waveguide_Oscillator.html

---

oscwq

Sinusoidal oscillator based on the waveguide resonator `wgr`. Unit-amplitude cosine and sine (quadrature) oscillator.

Usage

```
oscwq(freq) : _
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Digital_Waveguide_Oscillator. html

---

oscw

Sinusoidal oscillator based on the waveguide resonator `wgr`. Unit-amplitude cosine oscillator (default)

Usage

```
oscw(freq) : _
```

Where:

- `freq`: frequency

Reference

- https://ccrma.stanford.edu/~jos/pasp/Digital_Waveguide_Oscillator. html

---

lf_sawpos

Simple sawtooth waveform oscillator between 0 and 1.

Usage

```
lf_sawpos(freq)
```

Where:

- `freq`: frequency

---

lf_saw

Simple sawtooth waveform. `lf_saw` is a standard Faust function.

Usage

```
lf_saw(freq)
```

Where:

- `freq`: frequency

---

lf_triangle

Positive unit-amplitude LF triangle wave `lf_triangle` is a standard Faust function.

Usage

```
lf_triangle(freq) : _
```

Where:

- `freq`: frequency in Hz

---

phaflangers.lib

A library of phasor and flanger effects. Its official prefix is `pf`.

Functions Reference

`flanger_mono`

Mono flanging effect.

Usage:

`_ : flanger_mono(dmax,curdel,depth,fb,invert) : _;`

Where:

- `dmax`: maximum delay-line length (power of 2) - 10 ms typical
- `curdel`: current dynamic delay (not to exceed dmax)
- `depth`: effect strength between 0 and 1 (1 typical)
- `fb`: feedback gain between 0 and 1 (0 typical)
- `invert`: 0 for normal, 1 to invert sign of flanging sum

Reference

https://ccrma.stanford.edu/~jos/pasp/Flanging.html

`flanger_stereo`

Stereo flanging effect. `flanger_stereo` is a standard Faust function.

Usage:

`_,_ : flanger_stereo(dmax,curdel1,curdel2,depth,fb,invert) : _,_;`

Where:

- `dmax`: maximum delay-line length (power of 2) - 10 ms typical
- `curdel`: current dynamic delay (not to exceed dmax)
- `depth`: effect strength between 0 and 1 (1 typical)
- `fb`: feedback gain between 0 and 1 (0 typical)
- `invert`: 0 for normal, 1 to invert sign of flanging sum

Reference

https://ccrma.stanford.edu/~jos/pasp/Flanging.html

`phaser2_mono`

Mono phasing effect.

Phaser

```
_ : phaser2_mono(Notches,phase,width,frqmin,fratio,frqmax,speed,depth,fb,invert) : _;
```

Where:

- `Notches`: number of spectral notches (MACRO ARGUMENT - not a signal)
- `phase`: phase of the oscillator (0-1)
- `width`: approximate width of spectral notches in Hz
- `frqmin`: approximate minimum frequency of first spectral notch in Hz
- `fratio`: ratio of adjacent notch frequencies
- `frqmax`: approximate maximum frequency of first spectral notch in Hz
- `speed`: LFO frequency in Hz (rate of periodic notch sweep cycles)
- `depth`: effect strength between 0 and 1 (1 typical) (aka "intensity") when depth=2, "vibrato mode" is obtained (pure allpass chain)
- `fb`: feedback gain between -1 and 1 (0 typical)
- `invert`: 0 for normal, 1 to invert sign of flanging sum

Reference:

- https://ccrma.stanford.edu/~jos/pasp/Phasing.html
- http://www.geofex.com/Article_Folders/phasers/phase.html
- 'An Allpass Approach to Digital Phasing and Flanging', Julius O. Smith III, Proc. Int. Computer Music Conf. (ICMC-84), pp. 103-109, Paris, 1984.
- CCRMA Tech. Report STAN-M-21: https://ccrma.stanford.edu/STANM/stanms/stanm21/

`phaser2_stereo`

Stereo phasing effect. `phaser2_stereo` is a standard Faust function.

Phaser

```
_ : phaser2_stereo(Notches,phase,width,frqmin,fratio,frqmax,speed,depth,fb,invert) : _;
```

Where:

- `Notches`: number of spectral notches (MACRO ARGUMENT - not a signal)
- `phase`: phase of the oscillator (0-1)

- `width`: approximate width of spectral notches in Hz
- `frqmin`: approximate minimum frequency of first spectral notch in Hz
- `fratio`: ratio of adjacent notch frequencies
- `frqmax`: approximate maximum frequency of first spectral notch in Hz
- `speed`: LFO frequency in Hz (rate of periodic notch sweep cycles)
- `depth`: effect strength between 0 and 1 (1 typical) (aka "intensity") when depth=2, "vibrato mode" is obtained (pure allpass chain)
- `fb`: feedback gain between -1 and 1 (0 typical)
- `invert`: 0 for normal, 1 to invert sign of flanging sum

Reference:

- https://ccrma.stanford.edu/~jos/pasp/Phasing.html
- http://www.geofex.com/Article_Folders/phasers/phase.html
- 'An Allpass Approach to Digital Phasing and Flanging', Julius O. Smith III, Proc. Int. Computer Music Conf. (ICMC-84), pp. 103-109, Paris, 1984.
- CCRMA Tech. Report STAN-M-21: https://ccrma.stanford.edu/STANM/stanms/stanm21/

---

physmodels.lib

Faust physical modeling library; Its official prefix is `pm`.

This library provides an environment to facilitate physical modeling of musical instruments. It contains dozens of functions implementing low and high level elements going from a simple waveguide to fully operational models with built-in UI, etc.

It is organized as follows:

- Global Variables: Useful pre-defined variables for physical modeling (e.g., speed of sound, etc.).
- Conversion Tools: Conversion functions specific to physical modeling (e.g., length to frequency, etc.).
- Bidirectional Utilities: Functions to create bidirectional block diagrams for physical modeling.
- Basic Elements: waveguides, specific types of filters, etc.
- String Instruments: various types of strings (e.g., steel, nylon, etc.), bridges, guitars, etc.
- Bowed String Instruments: parts and models specific to bowed string instruments (e.g., bows, bridges, violins, etc.).
- Wind Instrument: parts and models specific to wind string instruments (e.g., reeds, mouthpieces, flutes, clarinets, etc.).
- Exciters: pluck generators, "blowers", etc.

- Modal Percussions: percussion instruments based on modal models.
- Vocal Synthesis: functions for various vocal synthesis techniques (e.g., fof, source/filter, etc.) and vocal synthesizers.
- Misc Functions: any other functions that don't fit in the previous category (e.g., nonlinear filters, etc.)

This library is part of the Faust Physical Modeling ToolKit. More information on how to use this library can be found on this page: https://ccrma.stanford. edu/~rmichon/pmFaust. Tutorials on how to make physical models of musical instruments using Faust can be found here as well.

Global Variables

Useful pre-defined variables for physical modeling.

speedOfSound

Speed of sound in meters per second (340m/s).

---

maxLength

The default maximum length (3) in meters of strings and tubes used in this library. This variable should be overriden allow longer strings or tubes.

Conversion Tools

Useful conversion tools for physical modeling.

f2l

Frequency to lentgh in meters.

Usage

f2l(freq) : distanceInMeters

Where:

- `freq`: the frequency

`l2f`

Lentgh in meters to frequency.

Usage

```
l2f(length) : freq
```

Where:

- `length`: length/distance in meters

`l2s`

Length in meters to number of samples.

Usage

```
l2s(l) : numberOfSamples
```

Where:

- `l`: length in meters

Bidirectional Utilities

Set of fundamental functions to create bi-directional block diagrams in Faust. These elements are used as the basis of this library to connect high level elements (e.g., mouthpieces, strings, bridge, instrument body, etc.). Each block has 3 inputs and 3 outputs. The first input/output carry left going waves, the second input/output carry right going waves, and the third input/output is used to carry any potential output signal to the end of the algorithm.

`basicBlock`

Empty bidirectional block to be used with `chain`: 3 signals ins and 3 signals out.

Usage

```
chain(basicBlock : basicBlock : etc.)
```

`chain`

Creates a chain of bidirectional blocks. Blocks must have 3 inputs and outputs. The first input/output carry left going waves, the second input/output carry right going waves, and the third input/output is used to carry any potential output signal to the end of the algorithm. The implied one sample delay created by the `~` operator is generalized to the left and right going waves. Thus, `n` blocks in `chain()` will add an `n` samples delay to both left and right going waves.

Usage

```
leftGoingWaves,rightGoingWaves,mixedOutput : chain( A : B ) : leftGoingWaves,rightGoingWaves
with{
    A = _,_,_;
    B = _,_,_;
};
```

`inLeftWave`

Adds a signal to left going waves anywhere in a `chain` of blocks.

Usage

```
model(x) = chain(A : inLeftWave(x) : B)
```

Where `A` and `B` are bidirectional blocks and `x` is the signal added to left going waves in that chain.

`inRightWave`

Adds a signal to right going waves anywhere in a `chain` of blocks.

Usage

```
model(x) = chain(A : inRightWave(x) : B)
```

Where `A` and `B` are bidirectional blocks and `x` is the signal added to right going waves in that chain.

`in`

Adds a signal to left and right going waves anywhere in a `chain` of blocks.

Usage

`model(x) = chain(A : in(x) : B)`

Where `A` and `B` are bidirectional blocks and `x` is the signal added to left and right going waves in that chain.

`outLeftWave`

Sends the signal of left going waves to the output channel of the `chain`.

Usage

`chain(A : outLeftWave : B)`

Where `A` and `B` are bidirectional blocks.

`outRightWave`

Sends the signal of right going waves to the output channel of the `chain`.

Usage

`chain(A : outRightWave : B)`

Where `A` and `B` are bidirectional blocks.

`out`

Sends the signal of right and left going waves to the output channel of the `chain`.

Usage

```
chain(A : out : B)
```

Where `A` and `B` are bidirectional blocks.

`terminations`

Creates terminations on both sides of a `chain` without closing the inputs and outputs of the bidirectional signals chain. As for `chain`, this function adds a 1 sample delay to the bidirectional signal, both ways. Of courses, this function can be nested within a `chain`.

Usage

```
terminations(a,b,c)
with{
    a = *(-1); // left termination
    b = chain(D : E : F); // bidirectional chain of blocks (D, E, F, etc.)
    c = *(-1); // right termination
};
```

`lTermination`

Creates a termination on the left side of a `chain` without closing the inputs and outputs of the bidirectional signals chain. This function adds a 1 sample delay near the termination and can be nested within another `chain`.

Usage

```
lTerminations(a,b)
with{
    a = *(-1); // left termination
    b = chain(D : E : F); // bidirectional chain of blocks (D, E, F, etc.)
};
```

`rTermination`

Creates a termination on the right side of a `chain` without closing the inputs
and outputs of the bidirectional signals chain. This function adds a 1 sample
delay near the termination and can be nested within another `chain`.

Usage

```
rTerminations(b,c)
with{
    b = chain(D : E : F); // bidirectional chain of blocks (D, E, F, etc.)
    c = *(-1); // right termination
};
```

`closeIns`

Closes the inputs of a bidirectional chain in all directions.

Usage

```
closeIns : chain(...) :  _,_,_
```

`closeOuts`

Closes the outputs of a bidirectional chain in all directions except for the main
signal output (3d output).

Usage

```
_,_,_ : chain(...) : _
```

`endChain`

Closes the inputs and outputs of a bidirectional chain in all directions except for
the main signal output (3d output).

Usage

```
endChain(chain(...)) : _
```

Basic Elements

Basic elements for physical modeling (e.g., waveguides, specific filters, etc.).

waveguideN

A series of waveguide functions based on various types of delays (see `fdelay[n]`).

List of functions

- `waveguideUd`: unit delay waveguide
- `waveguideFd`: fractional delay waveguide
- `waveguideFd2`: second order fractional delay waveguide
- `waveguideFd4`: fourth order fractional delay waveguide

Usage

```
chain(A : waveguideUd(nMax,n) : B)
```

Where:

- `nMax`: the maximum length of the delays in the waveguide
- `n`: the length of the delay lines in samples.

---

waveguide

Standard `pm.lib` waveguide (based on `waveguideFd4`).

Usage

```
chain(A : waveguide(nMax,n) : B)
```

Where:

- `nMax`: the maximum length of the delays in the waveguide
- `n`: the length of the delay lines in samples.

`bridgeFilter`

Generic two zeros bridge FIR filter (as implemented in the STK) that can be used to implement the reflectance violin, guitar, etc. bridges.

Usage

```
_ : bridge(brightness,absorption) : _
```

Where:

- `brightness`: controls the damping of high frequencies (0-1)
- `absorption`: controls the absorption of the brige and thus the t60 of the string plugged to it (0-1) (1 = 20 seconds)

`modeFilter`

Resonant bandpass filter that can be used to implement a single resonance (mode).

Usage

```
_ : modeFilter(freq,t60,gain) : _
```

Where:

- `freq`: mode frequency
- `t60`: mode resonance duration (in seconds)
- `gain`: mode gain (0-1)

String Instruments

Low and high level string instruments parts. Most of the elements in this section can be used in a bidirectional chain.

`stringSegment`

A string segment without terminations (just a simple waveguide).

Usage

```
chain(A : stringSegment(maxLength,length) : B)
```

Where:

- `maxLength`: the maximum length of the string in meters (should be static)
- `length`: the length of the string in meters

---

openString

A bidirectional block implementing a basic "generic" string with a selectable excitation position. Lowpass filters are built-in and allow to simulate the effect of dispersion on the sound and thus to change the "stiffness" of the string.

Usage

```
chain(... : openString(length,stiffness,pluckPosition,excitation) : ...)
```

Where:

- `length`: the length of the string in meters
- `stiffness`: the stiffness of the string (0-1) (1 for max stiffness)
- `pluckPosition`: excitation position (0-1) (1 is bottom)
- `excitation`: the excitation signal

---

nylonString

A bidirectional block implementing a basic nylon string with selectable excitation position. This element is based on `openString` and has a fix stiffness corresponding to that of a nylon string.

Usage

```
chain(... : nylonString(length,pluckPosition,excitation) : ...)
```

Where:

- `length`: the length of the string in meters
- `pluckPosition`: excitation position (0-1) (1 is bottom)
- `excitation`: the excitation signal

---

steelString

A bidirectional block implementing a basic steel string with selectable excitation position. This element is based on `openString` and has a fix stiffness corresponding to that of a steel string.

Usage

`chain(... : steelString(length,pluckPosition,excitation) : ...)`

Where:

- `length`: the length of the string in meters
- `pluckPosition`: excitation position (0-1) (1 is bottom)
- `excitation`: the excitation signal

---

openStringPick

A bidirectional block implementing a "generic" string with selectable excitation position. It also has a built-in pickup whose position is the same as the excitation position. Thus, moving the excitation position will also move the pickup.

Usage

`chain(... : openStringPick(length,stiffness,pluckPosition,excitation) : ...)`

Where:

- `length`: the length of the string in meters
- `stiffness`: the stiffness of the string (0-1) (1 for max stiffness)
- `pluckPosition`: excitation position (0-1) (1 is bottom)
- `excitation`: the excitation signal

---

openStringPickUp

A bidirectional block implementing a "generic" string with selectable excitation position and stiffness. It also has a built-in pickup whose position can be independenly selected. The only constraint is that the pickup has to be placed after the excitation position.

Usage

```
chain(... : openStringPickUp(length,stiffness,pluckPosition,excitation) : ...)
```

Where:

- `length`: the length of the string in meters
- `stiffness`: the stiffness of the string (0-1) (1 for max stiffness)
- `pluckPosition`: pluck position between the top of the string and the pickup (0-1) (1 for same as pickup position)
- `pickupPosition`: position of the pickup on the string (0-1) (1 is bottom)
- `excitation`: the excitation signal

---

openStringPickDown

A bidirectional block implementing a "generic" string with selectable excitation position and stiffness. It also has a built-in pickup whose position can be independenly selected. The only constraint is that the pickup has to be placed before the excitation position.

Usage

```
chain(... : openStringPickDown(length,stiffness,pluckPosition,excitation) : ...)
```

Where:

- `length`: the length of the string in meters
- `stiffness`: the stiffness of the string (0-1) (1 for max stiffness)
- `pluckPosition`: pluck position on the string (0-1) (1 is bottom)
- `pickupPosition`: position of the pickup between the top of the string and the excitation position (0-1) (1 is excitation position)
- `excitation`: the excitation signal

---

ksReflexionFilter

The "typical" one-zero Karplus-strong feedforward reflexion filter. This filter will be typically used in a termination (see below).

Usage

```
terminations(_,chain(...),ksReflexionFilter)
```

---

rStringRigidTermination

Bidirectional block implementing a right rigid string termination (no damping, just phase inversion).

Usage

```
chain(rStringRigidTermination : stringSegment : ...)
```

───────────────────────────────

lStringRigidTermination

Bidirectional block implementing a left rigid string termination (no damping, just phase inversion).

Usage

```
chain(... : stringSegment : lStringRigidTermination)
```

───────────────────────────────

elecGuitarBridge

Bidirectional block implementing a simple electric guitar bridge. This block is based on `bridgeFilter`. The bridge doesn't implement transmittance since it is not meant to be connected to a body (unlike acoustic guitar). It also partially sets the resonance duration of the string with the nuts used on the other side.

Usage

```
chain(... : stringSegment : elecGuitarBridge)
```

───────────────────────────────

elecGuitarNuts

Bidirectional block implementing a simple electric guitar nuts. This block is based on `bridgeFilter` and does essentially the same thing as `elecGuitarBridge`, but on the other side of the chain. It also partially sets the resonance duration of the string with the bridge used on the other side.

Usage

```
chain(elecGuitarNuts : stringSegment : ...)
```

---

guitarBridge

Bidirectional block implementing a simple acoustic guitar bridge. This bridge damps more hight frequencies than `elecGuitarBridge` and implements a transmittance filter. It also partially sets the resonance duration of the string with the nuts used on the other side.

Usage

```
chain(... : stringSegment : guitarBridge)
```

---

guitarNuts

Bidirectional block implementing a simple acoustic guitar nuts. This nuts damps more hight frequencies than `elecGuitarNuts` and implements a transmittance filter. It also partially sets the resonance duration of the string with the bridge used on the other side.

Usage

```
chain(guitarNuts : stringSegment : ...)
```

---

idealString

An "ideal" string with rigid terminations and where the plucking position and the pick-up position are the same. Since terminations are rigid, this string will ring forever.

Usage

```
1-1' : idealString(length,reflexion,xPosition,excitation)
```

With: * `length`: the length of the string in meters * `pluckPosition`: the plucking position (0.001-0.999) * `excitation`: the input signal for the excitation

---

`ks`

A Karplus-Strong string (in that case, the string is implemented as a one dimension waveguide).

Usage

`ks(length,damping,excitation) : _`

Where:

- `length`: the length of the string in meters
- `damping`: string damping (0-1)
- `excitation`: excitation signal

———————————————————

`ks_ui_MIDI`

Ready-to-use, MIDI-enabled Karplus-Strong string with buil-in UI.

Usage

`ks_ui_MIDI : _`

———————————————————

`elecGuitarModel`

A simple electric guitar model (without audio effects, of course) with selectable pluck position. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function. Pitch is changed by changing the length of the string and not through a finger model.

Usage

`elecGuitarModel(length,pluckPosition,excitation) : _`

Where:

- `length`: the length of the string in meters
- `pluckPosition`: pluck position (0-1) (1 is on the bridge)
- `excitation`: excitation signal

———————————————————

elecGuitar

A simple electric guitar model with steel strings (based on `elecGuitarModel`) implementing an excitation model. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function.

Usage

`elecGuitar(length,pluckPosition,trigger) : _`

Where:

- `length`: the length of the string in meters
- `pluckPosition`: pluck position (0-1) (1 is on the bridge)
- `gain`: gain of the pluck (0-1)
- `trigger`: trigger signal (1 for on, 0 for off)

---

elecGuitar_ui_MIDI

Ready-to-use MIDI-enabled electric guitar physical model with built-in UI.

Usage

`elecGuitar_ui_MIDI : _`

---

guitarBody

WARNING: not implemented yet! Bidirectional block implementing a simple acoustic guitar body.

Usage

`chain(... : guitarBody)`

---

guitarModel

A simple acoustic guitar model with steel strings and selectable excitation position. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function. Pitch is changed by changing the length of the string and not through a finger model. WARNING: this function doesn't currently implement a body (just strings and bridge)

Usage

```
guitarModel(length,pluckPosition,excitation) : _
```

Where:

- `length`: the length of the string in meters
- `pluckPosition`: pluck position (0-1) (1 is on the bridge)
- `excitation`: excitation signal

---

guitar

A simple acoustic guitar model with steel strings (based on `guitarModel`) implementing an excitation model. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function.

Usage

```
guitar(length,pluckPosition,trigger) : _
```

Where:

- `length`: the length of the string in meters
- `pluckPosition`: pluck position (0-1) (1 is on the bridge)
- `gain`: gain of the excitation
- `trigger`: trigger signal (1 for on, 0 for off)

---

guitar_ui_MIDI

Ready-to-use MIDI-enabled steel strings acoustic guitar physical model with built-in UI.

Usage

```
guitar_ui_MIDI : _
```

---

nylonGuitarModel

A simple acoustic guitar model with nylon strings and selectable excitation position. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function. Pitch is changed by changing the length of the string and not through a finger model. WARNING: this function doesn't currently implement a body (just strings and bridge)

Usage

```
nylonGuitarModel(length,pluckPosition,excitation) : _
```

Where:

- `length`: the length of the string in meters
- `pluckPosition`: pluck position (0-1) (1 is on the bridge)
- `excitation`: excitation signal

---

nylonGuitar

A simple acoustic guitar model with steel strings (based on `nylonGuitarModel`) implementing an excitation model. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function.

Usage

```
nylonGuitar(length,pluckPosition,trigger) : _
```

Where:

- `length`: the length of the string in meters
- `pluckPosition`: pluck position (0-1) (1 is on the bridge)
- `gain`: gain of the excitation (0-1)
- `trigger`: trigger signal (1 for on, 0 for off)

`nylonGuitar_ui_MIDI`

Ready-to-use MIDI-enabled nylon strings acoustic guitar physical model with built-in UI.

Usage

```
nylonGuitar_ui_MIDI : _
```

Bowed String Instruments

Low and high level basic string instruments parts. Most of the elements in this section can be used in a bidirectional chain.

`bowTable`

Extremely basic bow table that can be used to implement a wide range of bow types for many different bowed string instruments (violin, cello, etc.)

Usage

```
excitation : bowTable(offeset,slope) : _
```

Where:

- `excitation`: an excitation signal
- `offset`: table offset
- `slope`: table slope

`violinBowTable`

Violin bow table based on `bowTable`.

Usage

```
bowVelocity : violinBowTable(bowPressure) : _
```

Where:

- `bowVelocity`: velocity of the bow/excitation signal (0-1)
- `bowPressure`: bow pressure on the string (0-1)

---

bowInteraction

Bidirectional block implementing the interaction of a bow in a `chain`.

Usage

```
chain(... : stringSegment : bowInteraction(bowTable) : stringSegment : ...)
```

Where:

- `bowTable`: the bow table

---

violinBow

Bidirectional block implementing a violin bow and its interaction with a string.

Usage

```
chain(... : stringSegment : violinBow(bowPressure,bowVelocity) : stringSegment : ...)
```

Where:

- `bowVelocity`: velocity of the bow / excitation signal (0-1)
- `bowPressure`: bow pressure on the string (0-1)

---

violinBowedString

Violin bowed string bidirectional block with controllable bow position. Terminations are not implemented in this model.

Usage

```
chain(nuts : violinBowedString(stringLength,bowPressure,bowVelocity,bowPosition) : bridge)
```

Where:

- `stringLength`: the length of the string in meters
- `bowVelocity`: velocity of the bow / excitation signal (0-1)
- `bowPressure`: bow pressure on the string (0-1)
- `bowPosition`: the position of the bow on the string (0-1)

159

violinNuts

Bidirectional block implementing simple violin nuts. This function is based on `bridgeFilter`.

Usage

```
chain(violinNuts : stringSegment : ...)
```

---

violinBridge

Bidirectional block implementing a simple violin bridge. This function is based on `bridgeFilter`.

Usage

```
chain(... : stringSegment : violinBridge
```

---

violinBody

Bidirectional block implementing a simple violin body (just a simple resonant lowpass filter).

Usage

```
chain(... : stringSegment : violinBridge : violinBody)
```

---

violinModel

Ready-to-use simple violin physical model. This model implements a single string. Additional strings should be created by making a polyphonic applications out of this function. Pitch is changed by changing the length of the string (and not through a finger model).

Usage

```
violinModel(stringLength,bowPressure,bowVelocity,bridgeReflexion,
bridgeAbsorption,bowPosition) : _
```

Where:

- `stringLength`: the length of the string in meters
- `bowVelocity`: velocity of the bow / excitation signal (0-1)
- `bowPressure`: bow pressure on the string (0-1))
- `bowPosition`: the position of the bow on the string (0-1)

`violinModel_ui`

Ready-to-use violin physical model with built-in UI.

Usage

```
violinModel_ui : _
```

`violin_ui_MIDI`

Ready-to-use MIDI-enabled violin physical model with built-in UI.

Usage

```
violin_ui_MIDI : _
```

Wind Instruments

Low and high level basic wind instruments parts. Most of the elements in this section can be used in a bidirectional chain.

`openTube`

A tube segment without terminations (same as `stringSegment`).

Usage

```
chain(A : openTube(maxLength,length) : B)
```

Where:

- `maxLength`: the maximum length of the tube in meters (should be static)
- `length`: the length of the tube in meters

---

reedTable

Extremely basic reed table that can be used to implement a wide range of single reed types for many different instruments (saxophone, clarinet, etc.).

Usage

```
excitation : reedTable(offeset,slope) : _
```

Where:

- `excitation`: an excitation signal
- `offset`: table offset
- `slope`: table slope

---

fluteJetTable

Extremely basic flute jet table.

Usage

```
excitation : fluteJetTable : _
```

Where:

- `excitation`: an excitation signal

---

brassLipsTable

Simple brass lips/mouthpiece table. Since this implementation is very basic and that the lips and tube of the instrument are coupled to each other, the length of that tube must be provided here.

Usage

```
excitation : brassLipsTable(tubeLength,lipsTension) : _
```

Where:

- `excitation`: an excitation signal (can be DC)
- `tubeLength`: length in meters of the tube connected to the mouthpiece
- `lipsTension`: tension of the lips (0-1) (default: 0.5)

———————————————————————

clarinetReed

Clarinet reed based on `reedTable` with controllable stiffness.

Usage

```
excitation : clarinetReed(stiffness) : _
```

Where:

- `excitation`: an excitation signal
- `stiffness`: reed stiffness (0-1)

———————————————————————

clarinetMouthPiece

Bidirectional block implementing a clarinet mouthpiece as well as the various interactions happening with traveling waves. This element is ready to be plugged to a tube. . .

Usage

```
chain(clarinetMouthPiece(reedStiffness,pressure) : tube : etc.)
```

Where:

- `pressure`: the pressure of the air flow (DC) created by the virtual performer (0-1). This can also be any kind of signal that will directly injected in the mouthpiece (e.g., breath noise, etc.)
- `reedStiffness`: reed stiffness (0-1)

———————————————————————

`brassLips`

Bidirectional block implementing a brass mouthpiece as well as the various interactions happening with traveling waves. This element is ready to be plugged to a tube...

Usage

```
chain(brassLips(tubeLength,lipsTension,pressure) : tube : etc.)
```

Where:

- `tubeLength`: length in meters of the tube connected to the mouthpiece
- `lipsTension`: tension of the lips (0-1) (default: 0.5)
- `pressure`: the pressure of the air flow (DC) created by the virtual performer (0-1). This can also be any kind of signal that will directly injected in the mouthpiece (e.g., breath noise, etc.)

`fluteEmbouchure`

Bidirectional block implementing a flute embouchure as well as the various interactions happening with traveling waves. This element is ready to be plugged between tubes segments...

Usage

```
chain(... : tube : fluteEmbouchure(pressure) : tube : etc.)
```

Where:

- `pressure`: the pressure of the air flow (DC) created by the virtual performer (0-1). This can also be any kind of signal that will directly injected in the mouthpiece (e.g., breath noise, etc.)

`wBell`

Generic wind instrument bell bidirectional block that should be placed at the end of a `chain`.

Usage

```
chain(... : wBell(opening))
```

Where:

- `opening`: the "opening" of bell (0-1)

---

fluteHead

Simple flute head implementing waves reflexion.

Usage

```
chain(fluteHead : tube : ...)
```

---

fluteFoot

Simple flute foot implementing waves reflexion and dispersion.

Usage

```
chain(... : tube : fluteFoot)
```

---

clarinetModel

A simple clarinet physical model without tone holes (pitch is changed by changing the length of the tube of the instrument).

Usage

```
clarinetModel(length,pressure,reedStiffness,bellOpening) : _
```

Where:

- `tubeLength`: the length of the tube in meters
- `pressure`: the pressure of the air flow created by the virtual performer (0-1). This can also be any kind of signal that will directly injected in the mouthpiece (e.g., breath noise, etc.)
- `reedStiffness`: reed stiffness (0-1)
- `bellOpening`: the opening of bell (0-1)

`clarinetModel_ui`

Same as `clarinetModel` but with a built-in UI. This function doesn't implement a virtual "blower", thus `pressure` remains an argument here.

Usage

`clarinetModel_ui(pressure) : _`

Where:

- `pressure`: the pressure of the air flow created by the virtual performer (0-1). This can also be any kind of signal that will be directly injected in the mouthpiece (e.g., breath noise, etc.)

`clarinet_ui`

Ready-to-use clarinet physical model with built-in UI based on `clarinetModel`.

Usage

`clarinet_ui : _`

`clarinet_ui_MIDI`

Ready-to-use MIDI compliant clarinet physical model with built-in UI.

Usage

`clarinet_ui_MIDI : _`

`brassModel`

A simple generic brass instrument physical model without pistons (pitch is changed by changing the length of the tube of the instrument). This model is kind of hard to control and might not sound very good if bad parameters are given to it. . .

Usage

```
brassModel(tubeLength,lipsTension,mute,pressure) : _
```

Where:

- `tubeLength`: the length of the tube in meters
- `lipsTension`: tension of the lips (0-1) (default: 0.5)
- `mute`: mute opening at the end of the instrument (0-1) (default: 0.5)
- `pressure`: the pressure of the air flow created by the virtual performer (0-1). This can also be any kind of signal that will directly injected in the mouthpiece (e.g., breath noise, etc.)

`brassModel_ui`

Same as `brassModel` but with a built-in UI. This function doesn't implement a virtual "blower", thus `pressure` remains an argument here.

Usage

```
brassModel_ui(pressure) : _
```

Where:

- `pressure`: the pressure of the air flow created by the virtual performer (0-1). This can also be any kind of signal that will be directly injected in the mouthpiece (e.g., breath noise, etc.)

`brass_ui`

Ready-to-use brass instrument physical model with built-in UI based on `brassModel`.

Usage

```
brass_ui : _
```

`brass_ui_MIDI`

Ready-to-use MIDI-controllable brass instrument physical model with built-in UI.

Usage

```
brass_ui_MIDI : _
```

---

fluteModel

A simple generic brass instrument physical model without tone holes (pitch is changed by changing the length of the tube of the instrument).

Usage

```
fluteModel(tubeLength,lipsTension,mute,pressure) : _
```

Where:

- `tubeLength`: the length of the tube in meters
- `mouthPosition`: position of the mouth on the embouchure (0-1) (default: 0.5)
- `pressure`: the pressure of the air flow created by the virtual performer (0-1). This can also be any kind of signal that will directly injected in the mouthpiece (e.g., breath noise, etc.)

---

fluteModel_ui

Same as `fluteModel` but with a built-in UI. This function doesn't implement a virtual "blower", thus `pressure` remains an argument here.

Usage

```
fluteModel_ui(pressure) : _
```

Where:

- `pressure`: the pressure of the air flow created by the virtual performer (0-1). This can also be any kind of signal that will be directly injected in the mouthpiece (e.g., breath noise, etc.)

---

flute_ui

Ready-to-use flute physical model with built-in UI based on `fluteModel`.

Usage

```
flute_ui : _
```

---

flute_ui_MIDI

Ready-to-use MIDI-controllable flute physical model with built-in UI.

Usage

```
brass_ui_MIDI : _
```

Exciters

Various kind of excitation signal generators.

impulseExcitation

Creates an impulse excitation of one sample.

Usage

```
gate = button('gate');
impulseExcitation(gate) : chain;
```

Where:

- gate: a gate button

---

strikeModel

Creates a filtered noise excitation.

Usage

```
gate = button('gate');
strikeModel(LPcutoff,HPcutoff,sharpness,gain,gate) : chain;
```

Where:

- `HPcutoff`: highpass cutoff frequency
- `LPcutoff`: lowpass cutoff frequency
- `sharpness`: sharpness of the attack and release (0-1)
- `gain`: gain of the excitation
- `gate`: a gate button/trigger signal (0/1)

---

strike

Strikes generator with controllable excitation position.

Usage

```
gate = button('gate');
strike(exPos,sharpness,gain,gate) : chain;
```

Where:

- `exPos`: excitation position wiht 0: for max low freqs and 1: for max high freqs. So, on membrane for example, 0 would be the middle and 1 the edge
- `sharpness`: sharpness of the attack and release (0-1)
- `gain`: gain of the excitation
- `gate`: a gate button/trigger signal (0/1)

---

pluckString

Creates a plucking excitation signal.

Usage

```
trigger = button('gate');
pluckString(stringLength,cutoff,maxFreq,sharpness,trigger)
```

Where:

- `stringLength`: length of the string to pluck
- `cutoff`: cutoff ratio (1 for default)
- `maxFreq`: max frequency ratio (1 for default)
- `sharpness`: sharpness of the attack and release (1 for default)
- `gain`: gain of the excitation (0-1)
- `trigger`: trigger signal (1 for on, 0 for off)

`blower`

A virtual blower creating a DC signal with some breath noise in it.

Usage

`blower(pressure,breathGain,breathCutoff) : _`

Where:

- `pressure`: pressure (0-1)
- `breathGain`: breath noise gain (0-1) (recommended: 0.005)
- `breathCutoff`: breath cuttoff frequency (Hz) (recommended: 2000)

`blower_ui`

Same as `blower` but with a built-in UI.

Usage

`blower : somethingToBeBlown`

Modal Percussions

High and low level functions for modal synthesis of percussion instruments.

`djembeModel`

Dirt-simple djembe modal physical model. Mode parameters are empirically calculated and don't correspond to any measurements or 3D model. They kind of sound good though :).

Usage

`excitation : djembeModel(freq)`

Where:

- `excitation`: excitation signal
- `freq`: fundamental frequency of the bar

`djembe`

Dirt-simple djembe modal physical model. Mode parameters are empirically calculated and don't correspond to any measurements or 3D model. They kind of sound good though :).

This model also implements a virtual "exciter".

Usage

`djembe(freq,strikePosition,strikeSharpness,gain,trigger`

Where:

- `freq`: fundamental frequency of the model
- `strikePosition`: strike position (0 for the middle of the membrane and 1 for the edge)
- `strikeSharpness`: sharpness of the strike (0-5, default: 0.5)
- `gain`: gain of the strike
- `trigger`: trigger signal (0: off, 1: on)

`djembe_ui_MIDI`

Simple MIDI controllable djembe physical model with built-in UI.

Usage

`djembe_ui_MIDI : _`

`marimbaBarModel`

Generic marimba tone bar modal model.

This model was generated using `mesh2faust` from a 3D CAD model of a marimba tone bar (`libraries/modalmodels/marimbaBar`). The corresponding CAD model is that of a C2 tone bar (original fundamental frequency: ~65Hz). While `marimbaBarModel` allows to translate the harmonic content of the generated sound by providing a frequency (`freq`), mode transposition has limits and the model will sound less and less like a marimba tone bar as it diverges from C2. To make an accurate model of a marimba, we'd want to have an independent model for each bar...

This model contains 5 excitation positions going linearly from the center bottom to the center top of the bar. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

```
excitation : marimbaBarModel(freq,exPos,t60,t60DecayRatio,t60DecaySlope)
```

Where:

- `excitation`: excitation signal
- `freq`: fundamental frequency of the bar
- `exPos`: excitation position (0-4)
- `t60`: T60 in seconds (recommended value: 0.1)
- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

---

marimbaResTube

Simple marimba resonance tube.

Usage

```
marimbaResTube(tubeLength,excitation)
```

Where:

- `tubeLength`: the length of the tube in meters
- `excitation`: the excitation signal (audio in)

---

marimbaModel

Simple marimba physical model implementing a single tone bar connected to tube. This model is scalable and can be adapted to any size of bar/tube (see `marimbaBarModel` to know more about the limitations of this type of system).

Usage

```
excitation : marimbaModel(freq,exPos) : _
```

Where:

- `freq`: the frequency of the bar/tube couple
- `exPos`: excitation position (0-4)

`marimba`

Simple marimba physical model implementing a single tone bar connected to tube. This model is scalable and can be adapted to any size of bar/tube (see `marimbaBarModel` to know more about the limitations of this type of system).

This function also implement a virtual exciter to drive the model.

Usage

```
excitation : marimba(freq,strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _
```

Where:

- `excitation`: the excitation signal
- `freq`: the frequency of the bar/tube couple
- `strikePosition`: strike position (0-4)
- `strikeCutoff`: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- `strikeSharpness`: shaarpness of the strike (recommened: ~0.25)
- `gain`: gain of the strike (0-1)
- `trigger` signal (0: off, 1: on)

`marimba_ui_MIDI`

Simple MIDI controllable marimba physical model with built-in UI implementing a single tone bar connected to tube. This model is scalable and can be adapted to any size of bar/tube (see `marimbaBarModel` to know more about the limitations of this type of system).

Usage

```
marimba_ui_MIDI : _
```

`churchBellModel`

Generic church bell modal model generated by `mesh2faust` from `libraries/modalmodels/churchBell`.

Modeled after T. Rossing and R. Perrin, Vibrations of Bells, Applied Acoustics 2, 1987.

Model height is 301 mm.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

```
excitation : churchBellModel(exPos,t60,t60DecayRatio,t60DecaySlope)
```

Where:

- `excitation`: the excitation signal
- `exPos`: excitation position (0-6)
- `t60`: T60 in seconds (recommended value: 0.1)
- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

————————————————

churchBell

Generic church bell modal model.

Modeled after T. Rossing and R. Perrin, Vibrations of Bells, Applied Acoustics 2, 1987.

Model height is 301 mm.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

This function also implement a virtual exciter to drive the model.

Usage

```
excitation : churchBell(strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _
```

Where:

- `excitation`: the excitation signal
- `strikePosition`: strike position (0-6)
- `strikeCutoff`: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- `strikeSharpness`: shaarpness of the strike (recommened: ~0.25)
- `gain`: gain of the strike (0-1)
- `trigger` signal (0: off, 1: on)

————————————————

churchBell_ui

Church bell physical model based on `churchBell` with built-in UI.

Usage

```
churchBell_ui : _
```

---

englishBellModel

English church bell modal model generated by `mesh2faust` from `libraries/modalmodels/englishBell`.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 1 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

```
excitation : englishBellModel(exPos,t60,t60DecayRatio,t60DecaySlope)
```

Where:

- `excitation`: the excitation signal
- `exPos`: excitation position (0-6)
- `t60`: T60 in seconds (recommended value: 0.1)
- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

---

englishBell

English church bell modal model.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 1 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

This function also implement a virtual exciter to drive the model.

Usage

```
excitation : englishBell(strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _
```

Where:

- `excitation`: the excitation signal
- `strikePosition`: strike position (0-6)
- `strikeCutoff`: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- `strikeSharpness`: shaarpness of the strike (recommened: ~0.25)
- `gain`: gain of the strike (0-1)
- `trigger` signal (0: off, 1: on)

––––––––––––––––––––––––––––––

englishBell_ui

English church bell physical model based on `englishBell` with built-in UI.

Usage

```
englishBell_ui : _
```

––––––––––––––––––––––––––––––

frenchBellModel

French church bell modal model generated by `mesh2faust` from `libraries/modalmodels/frenchBell`.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 1 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

```
excitation : frenchBellModel(exPos,t60,t60DecayRatio,t60DecaySlope)
```

Where:

- `excitation`: the excitation signal
- `exPos`: excitation position (0-6)
- `t60`: T60 in seconds (recommended value: 0.1)
- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

———————————————————

frenchBell

French church bell modal model.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 1 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

This function also implement a virtual exciter to drive the model.

Usage

```
excitation : frenchBell(strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _
```

Where:

- `excitation`: the excitation signal
- `strikePosition`: strike position (0-6)
- `strikeCutoff`: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- `strikeSharpness`: shaarpness of the strike (recommened: ~0.25)
- `gain`: gain of the strike (0-1)
- `trigger` signal (0: off, 1: on)

———————————————————

frenchBell_ui

French church bell physical model based on `frenchBell` with built-in UI.

Usage

```
frenchBell_ui : _
```

---

germanBellModel

German church bell modal model generated by `mesh2faust` from `libraries/modalmodels/germanBell`.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 1 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

```
excitation : germanBellModel(exPos,t60,t60DecayRatio,t60DecaySlope)
```

Where:

- `excitation`: the excitation signal
- `exPos`: excitation position (0-6)
- `t60`: T60 in seconds (recommended value: 0.1)
- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

---

germanBell

German church bell modal model.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 1 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

This function also implement a virtual exciter to drive the model.

179

Usage

```
excitation : germanBell(strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _
```

Where:

- `excitation`: the excitation signal
- `strikePosition`: strike position (0-6)
- `strikeCutoff`: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- `strikeSharpness`: shaarpness of the strike (recommened: ~0.25)
- `gain`: gain of the strike (0-1)
- `trigger` signal (0: off, 1: on)

---

germanBell_ui

German church bell physical model based on `germanBell` with built-in UI.

Usage

```
germanBell_ui : _
```

---

russianBellModel

Russian church bell modal model generated by `mesh2faust` from `libraries/modalmodels/russianBell`.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 2 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

```
excitation : russianBellModel(exPos,t60,t60DecayRatio,t60DecaySlope)
```

Where:

- `excitation`: the excitation signal
- `exPos`: excitation position (0-6)
- `t60`: T60 in seconds (recommended value: 0.1)

- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

————————————————

russianBell

Russian church bell modal model.

Modeled after D. Bartocha and . Baron, Influence of Tin Bronze Melting and Pouring Parameters on Its Properties and Bell' Tone, Archives of Foundry Engineering, 2016.

Model height is 2 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

This function also implement a virtual exciter to drive the model.

Usage

`excitation : russianBell(strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _`

Where:

- `excitation`: the excitation signal
- `strikePosition`: strike position (0-6)
- `strikeCutoff`: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- `strikeSharpness`: shaarpness of the strike (recommened: ~0.25)
- `gain`: gain of the strike (0-1)
- `trigger` signal (0: off, 1: on)

————————————————

russianBell_ui

Russian church bell physical model based on `russianBell` with built-in UI.

Usage

`russianBell_ui : _`

————————————————

`standardBellModel`

Standard church bell modal model generated by `mesh2faust` from `libraries/modalmodels/standardBell`.

Modeled after T. Rossing and R. Perrin, Vibrations of Bells, Applied Acoustics 2, 1987.

Model height is 1.8 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

Usage

`excitation : standardBellModel(exPos,t60,t60DecayRatio,t60DecaySlope)`

Where:

- `excitation`: the excitation signal
- `exPos`: excitation position (0-6)
- `t60`: T60 in seconds (recommended value: 0.1)
- `t60DecayRatio`: T60 decay ratio (recommended value: 1)
- `t60DecaySlope`: T60 decay slope (recommended value: 5)

`standardBell`

Standard church bell modal model.

Modeled after T. Rossing and R. Perrin, Vibrations of Bells, Applied Acoustics 2, 1987.

Model height is 1.8 m.

This model contains 7 excitation positions going linearly from the bottom to the top of the bell. Obviously, a model with more excitation position could be regenerated using `mesh2faust`.

This function also implement a virtual exciter to drive the model.

Usage

`excitation : standardBell(strikePosition,strikeCutoff,strikeSharpness,gain,trigger) : _`

Where:

- `excitation`: the excitation signal

- **strikePosition**: strike position (0-6)
- **strikeCutoff**: cuttoff frequency of the strike genarator (recommended: ~7000Hz)
- **strikeSharpness**: shaarpness of the strike (recommened: ~0.25)
- **gain**: gain of the strike (0-1)
- **trigger** signal (0: off, 1: on)

———————————————

standardBell_ui

Standard church bell physical model based on `standardBell` with built-in UI.

Usage

```
standardBell_ui : _
```

———————————————

Vocal Synthesis

Vocal synthesizer functions (source/filter, fof, etc.).

formantValues

Formant data values.

The formant data used here come from the CSOUND manual http://www.csounds.com/manual/html/.

Usage

```
ba.take(j+1,formantValues.f(i)) : _
ba.take(j+1,formantValues.g(i)) : _
ba.take(j+1,formantValues.bw(i)) : _
```

Where:

- **i**: formant number
- **j**: (voiceType*nFormants)+vowel
- **voiceType**: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- **vowel**: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)

———————————————

voiceGender

Calculate the gender for the provided `voiceType` value. (0: male, 1: female)

Usage

```
voiceGender(voiceType) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)

––––––––––––––––––––––––––––––––

skirtWidthMultiplier

Calculates value to multiply bandwidth to obtain `skirtwidth` for a Fof filter.

Usage

```
skirtWidthMultiplier(vowel,freq,gender) : _
```

Where:

- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `freq`: the fundamental frequency of the excitation signal
- `gender`: gender of the voice used in the fof filter (0: male, 1: female)

––––––––––––––––––––––––––––––––

autobendFreq

Autobends the center frequencies of formants 1 and 2 based on the fundamental frequency of the excitation signal and leaves all other formant frequencies unchanged. Ported from `chant-lib`. Reference: https://ccrma.stanford.edu/~rmichon/chantLib/

Usage

```
_ : autobendFreq(n,freq,voiceType) : _
```

Where:

- `n`: formant index
- `freq`: the fundamental frequency of the excitation signal
- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)

- input is the center frequency of the corresponding formant

---

vocalEffort

Changes the gains of the formants based on the fundamental frequency of the excitation signal. Higher formants are reinforced for higher fundamental frequencies. Ported from `chant-lib`. Reference: https://ccrma.stanford.edu/~rmichon/chantLib/

Usage

`_ : vocalEffort(freq,gender) : _`

Where:

- `freq`: the fundamental frequency of the excitation signal
- `gender`: the gender of the voice type (0: male, 1: female)
- input is the linear amplitude of the formant

---

fof

Function to generate a single Formant-Wave-Function. Reference: https://ccrma.stanford.edu/~mjolsen/pdfs/smc2016_MOlsenFOF.pdf

Usage

`_ : fof(fc,bw,a,g) : _`

Where:

- `fc`: formant center frequency,
- `bw`: formant bandwidth (Hz),
- `sw`: formant skirtwidth (Hz)
- `g`: linear scale factor (g=1 gives 0dB amplitude response at fc)
- input is an impulse signal to excite filter

---

fofSH

FOF with sample and hold used on `bw` and a parameter used in the filter-cycling FOF function `fofCycle`. Reference: https://ccrma.stanford.edu/~mjolsen/pdfs/smc2016_MOlsenFOF.pdf

Usage

```
_ : fofSH(fc,bw,a,g) : _
```

Where: all parameters same as for `fof`

`fofCycle`

FOF implementation where time-varying filter parameter noise is mitigated by using a cycle of `n` sample and hold FOF filters. Reference: https://ccrma.stanford.edu/~mjolsen/pdfs/smc2016_MOlsenFOF.pdf

Usage

```
_ : fofCycle(fc,bw,a,g,n) : _
```

Where:

- `n`: the number of FOF filters to cycle through
- all other parameters are same as for `fof`

`fofSmooth`

FOF implementation where time-varying filter parameter noise is mitigated by lowpass filtering the filter parameters `bw` and `a` with smooth.

Usage

```
_ : fofSmooth(fc,bw,sw,g,tau) : _
```

Where:

- `tau`: the desired smoothing time constant in seconds
- all other parameters are same as for `fof`

`formantFilterFofCycle`

Formant filter based on a single FOF filter. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. A cycle of n fof filters with sample-and-hold is used so that the fof filter parameters can be varied in realtime. This technique is more robust but more computationally

expensive than `formantFilterFofSmooth`. Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

Usage

`_ : formantFilterFofCycle(voiceType,vowel,nFormants,i,freq) : _`

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `nFormants`: number of formant regions in frequency domain, typically 5
- `i`: formant number (i.e. 0 - 4) used to index formant data value arrays
- `freq`: fundamental frequency of excitation signal. Used to calculate rise time of envelope

---

formantFilterFofSmooth

Formant filter based on a single FOF filter. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Fof filter parameters are lowpass filtered to mitigate possible noise from varying them in realtime. Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

Usage

`_ : formantFilterFofSmooth(voiceType,vowel,nFormants,i,freq) : _`

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `nFormants`: number of formant regions in frequency domain, typically 5
- `i`: formant number (i.e. 1 - 5) used to index formant data value arrays
- `freq`: fundamental frequency of excitation signal. Used to calculate rise time of envelope

---

formantFilterBP

Formant filter based on a single resonant bandpass filter. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another.

Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

Usage

`_ : formantFilterBP(voiceType,vowel,nFormants,i,freq) : _`

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `nFormants`: number of formant regions in frequency domain, typically 5
- `i`: formant index used to index formant data value arrays
- `freq`: fundamental frequency of excitation signal.

---

formantFilterbank

Formant filterbank which can use different types of filterbank functions and different excitation signals. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

Usage

`_ : formantFilterbank(voiceType,vowel,formantGen,freq) : _`

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `formantGen`: the specific formant filterbank function (i.e. FormantFilterbankBP, FormantFilterbankFof,. . .)
- `freq`: fundamental frequency of excitation signal. Needed for FOF version to calculate rise time of envelope

---

formantFilterbankFofCycle

Formant filterbank based on a bank of fof filters. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

188

Usage

```
_ : formantFilterbankFofCycle(voiceType,vowel,freq) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `freq`: the fundamental frequency of the excitation signal. Needed to calculate the skirtwidth of the FOF envelopes and for the `autobendFreq` and `vocalEffort` functions

---

formantFilterbankFofSmooth

Formant filterbank based on a bank of fof filters. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

Usage

```
_ : formantFilterbankFofSmooth(voiceType,vowel,freq) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `freq`: the fundamental frequency of the excitation signal. Needed to calculate the skirtwidth of the FOF envelopes and for the `autobendFreq` and `vocalEffort` functions

---

formantFilterbankBP

Formant filterbank based on a bank of resonant bandpass filters. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the provided source to be realistic.

Usage

```
_ : formantFilterbankBP(voiceType,vowel) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `freq`: the fundamental frequency of the excitation signal. Needed for the `autobendFreq` and `vocalEffort` functions

---

SFFormantModel

Simple formant/vocal synthesizer based on a source/filter model. The source and `filterbank` must be specified by the user. `filterbank` must take the same input parameters as `formantFilterbank` (BP/FofCycle /FofSmooth). Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the synthesized voice to be realistic.

Usage

`SFFormantModel(voiceType,vowel,exType,freq,gain,source,filterbank) : _`

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u
- `exType`: voice vs. fricative sound ratio (0-1 where 1 is 100% fricative)
- `freq`: the fundamental frequency of the source signal
- `gain`: linear gain multiplier to multiply the source by

SFFormantModelFofCycle

Simple formant/vocal synthesizer based on a source/filter model. The source is just a periodic impulse and the "filter" is a bank of FOF filters. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the synthesized voice to be realistic. This model does not work with noise in the source signal so exType has been removed and model does not depend on SFFormantModel function.

Usage

```
SFFormantModelFofCycle(voiceType,vowel,exType,freq,gain) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u
- `freq`: the fundamental frequency of the source signal
- `gain`: linear gain multiplier to multiply the source by

SFFormantModelFofSmooth

Simple formant/vocal synthesizer based on a source/filter model. The source is just a periodic impulse and the filter is a bank of FOF filters. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the synthesized voice to be realistic.

Usage

```
SFFormantModelFofSmooth(voiceType,vowel,exType,freq,gain) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u
- `exType`: voice vs. fricative sound ratio (0-1 where 1 is 100% fricative)
- `freq`: the fundamental frequency of the source signal
- `gain`: linear gain multiplier to multiply the source by

SFFormantModelBP

Simple formant/vocal synthesizer based on a source/filter model. The source is just a sawtooth wave and the "filter" is a bank of resonant bandpass filters. Formant parameters are linearly interpolated allowing to go smoothly from one vowel to another. Voice type can be selected but must correspond to the frequency range of the synthesized voice to be realistic.

Usage

```
SFFormantModelBP(voiceType,vowel,exType,freq,gain) : _
```

Where:

- `voiceType`: the voice type (0: alto, 1: bass, 2: countertenor, 3: soprano, 4: tenor)
- `vowel`: the vowel (0: a, 1: e, 2: i, 3: o, 4: u)
- `exType`: voice vs. fricative sound ratio (0-1 where 1 is 100% fricative)
- `freq`: the fundamental frequency of the source signal
- `gain`: linear gain multiplier to multiply the source by

SFFormantModelFofCycle_ui

Ready-to-use source-filter vocal synthesizer with built-in user interface.

Usage

```
SFFormantModelFofCycle_ui : _
```

SFFormantModelFofSmooth_ui

Ready-to-use source-filter vocal synthesizer with built-in user interface.

Usage

```
SFFormantModelFofSmooth_ui : _
```

SFFormantModelBP_ui

Ready-to-use source-filter vocal synthesizer with built-in user interface.

Usage

```
SFFormantModelBP_ui : _
```

SFFormantModelFofCycle_ui_MIDI

Ready-to-use MIDI-controllable source-filter vocal synthesizer.

Usage

```
SFFormantModelFofCycle_ui_MIDI : _
```

SFFormantModelFofSmooth_ui_MIDI

Ready-to-use MIDI-controllable source-filter vocal synthesizer.

Usage

```
SFFormantModelFofSmooth_ui_MIDI : _
```

SFFormantModelBP_ui_MIDI

Ready-to-use MIDI-controllable source-filter vocal synthesizer.

Usage

```
SFFormantModelBP_ui_MIDI : _
```

Misc Functions

Various miscellaneous functions.

allpassNL

Bidirectional block adding nonlinearities in both directions in a chain. Nonlinearities are created by modulating the coefficients of a passive allpass filter by the signal it is processing.

Usage

```
chain(... : allpassNL(nonlinearity) : ...)
```

Where:

- `nonlinearity`: amount of nonlinearity to be added (0-1)

---

reverbs.lib

A library of reverb effects. Its official prefix is `re`.

Schroeder Reverberators

jcrev

This artificial reverberator take a mono signal and output stereo (`satrev`) and quad (`jcrev`). They were implemented by John Chowning in the MUS10 computer-music language (descended from Music V by Max Mathews). They are Schroeder Reverberators, well tuned for their size. Nowadays, the more expensive freeverb is more commonly used (see the Faust examples directory).

`jcrev` reverb below was made from a listing of "RV", dated April 14, 1972, which was recovered from an old SAIL DART backup tape. John Chowning thinks this might be the one that became the well known and often copied JCREV.

`jcrev` is a standard Faust function

Usage

```
_ : jcrev : _,_,_,_
```

---

satrev

This artificial reverberator take a mono signal and output stereo (`satrev`) and quad (`jcrev`). They were implemented by John Chowning in the MUS10 computer-music language (descended from Music V by Max Mathews). They are Schroeder Reverberators, well tuned for their size. Nowadays, the more expensive freeverb is more commonly used (see the Faust examples directory).

`satrev` was made from a listing of "SATREV", dated May 15, 1971, which was recovered from an old SAIL DART backup tape. John Chowning thinks this might

be the one used on his often-heard brass canon sound examples, one of which can be found at https://ccrma.stanford.edu/~jos/wav/FM_BrassCanon2.wav

Usage

```
_ : satrev : _,_
```

Feedback Delay Network (FDN) Reverberators

fdnrev0

Pure Feedback Delay Network Reverberator (generalized for easy scaling). `fdnrev0` is a standard Faust function.

Usage

```
<1,2,4,...,N signals> <:
fdnrev0(MAXDELAY,delays,BBSO,freqs,durs,loopgainmax,nonl) :>
<1,2,4,...,N signals>
```

Where:

- `N`: 2, 4, 8, ... (power of 2)
- `MAXDELAY`: power of 2 at least as large as longest delay-line length
- `delays`: N delay lines, N a power of 2, lengths perferably coprime
- `BBSO`: odd positive integer = order of bandsplit desired at freqs
- `freqs`: NB-1 crossover frequencies separating desired frequency bands
- `durs`: NB decay times (t60) desired for the various bands
- `loopgainmax`: scalar gain between 0 and 1 used to "squelch" the reverb
- `nonl`: nonlinearity (0 to 0.999..., 0 being linear)

Reference

https://ccrma.stanford.edu/~jos/pasp/FDN_Reverberation.html

---

zita_rev_fdn

Internal 8x8 late-reverberation FDN used in the FOSS Linux reverb zita-rev1 by Fons Adriaensen fons@linuxaudio.org. This is an FDN reverb with allpass comb filters in each feedback delay in addition to the damping filters.

Usage

```
bus(8) : zita_rev_fdn(f1,f2,t60dc,t60m,fsmax) : bus(8)
```

Where:

- `f1`: crossover frequency (Hz) separating dc and midrange frequencies
- `f2`: frequency (Hz) above f1 where T60 = t60m/2 (see below)
- `t60dc`: desired decay time (t60) at frequency 0 (sec)
- `t60m`: desired decay time (t60) at midrange frequencies (sec)
- `fsmax`: maximum sampling rate to be used (Hz)

Reference

- http://www.kokkinizita.net/linuxaudio/zita-rev1-doc/quickguide.html
- https://ccrma.stanford.edu/~jos/pasp/Zita_Rev1.html

`zita_rev1_stereo`

Extend `zita_rev_fdn` to include `zita_rev1` input/output mapping in stereo mode. `zita_rev1_stereo` is a standard Faust function.

Usage

```
_,_ : zita_rev1_stereo(rdel,f1,f2,t60dc,t60m,fsmax) : _,_
```

Where:

`rdel` = delay (in ms) before reverberation begins (e.g., 0 to ~100 ms) (remaining args and refs as for `zita_rev_fdn` above)

`zita_rev1_ambi`

Extend zita_rev_fdn to include zita_rev1 input/output mapping in "ambisonics mode", as provided in the Linux C++ version.

Usage

```
_,_ : zita_rev1_ambi(rgxyz,rdel,f1,f2,t60dc,t60m,fsmax) : _,_,_,_
```

Where:

`rgxyz` = relative gain of lanes 1,4,2 to lane 0 in output (e.g., -9 to 9) (remaining args and references as for zita_rev1_stereo above)

Freeverb

`mono_freeverb`

A simple Schroeder reverberator primarily developed by "Jezar at Dreampoint" that is extensively used in the free-software world. It uses four Schroeder allpasses in series and eight parallel Schroeder-Moorer filtered-feedback comb-filters for each audio channel, and is said to be especially well tuned.

`mono_freeverb` is a standard Faust function.

Usage

```
_ : mono_freeverb(fb1, fb2, damp, spread) : _;
```

Where:

- `fb1`: coefficient of the lowpass comb filters (0-1)
- `fb2`: coefficient of the allpass comb filters (0-1)
- `damp`: damping of the lowpass comb filter (0-1)
- `spread`: spatial spread in number of samples (for stereo)

License

While this version is licensed LGPL (with exception) along with other GRAME library functions, the file freeverb.dsp in the examples directory of older Faust distributions, such as faust-0.9.85, was released under the BSD license, which is less restrictive.

`stereo_freeverb`

A simple Schroeder reverberator primarily developed by "Jezar at Dreampoint" that is extensively used in the free-software world. It uses four Schroeder allpasses in series and eight parallel Schroeder-Moorer filtered-feedback comb-filters for each audio channel, and is said to be especially well tuned.

Usage

```
_,_ : stereo_freeverb(fb1, fb2, damp, spread) : _,_;
```

Where:

- `fb1`: coefficient of the lowpass comb filters (0-1)

- **fb2**: coefficient of the allpass comb filters (0-1)
- **damp**: damping of the lowpass comb filter (0-1)
- **spread**: spatial spread in number of samples (for stereo)

---

routes.lib

A library of basic elements to handle signal routing in Faust. Its official prefix is `ro`.

Functions Reference

cross

Cross n signals: `(x1,x2,..,xn) -> (xn,..,x2,x1)`. `cross` is a standard Faust function.

Usage

```
cross(n)
_,_,_ : cross(3) : _,_,_
```

Where:

- **n**: number of signals (int, must be known at compile time)

Note

Special case: `cross2`:

```
cross2 = _,cross(2),_;
```

---

crossnn

Cross two `bus(n)`s.

Usage

```
_,_,... : crossmm(n) : _,_,...
```

Where:

- **n**: the number of signals in the `bus`

---

crossn1

Cross bus(n) and bus(1).

Usage

`_,_,... : crossn1(n) : _,_,...`

Where:

- **n**: the number of signals in the first `bus`

---

interleave

Interleave row*col cables from column order to row order. input : x(0), x(1), x(2) ..., x(row*col-1) output: x(0+0*row), x(0+1*row), x(0+2*row), ..., x(1+0*row), x(1+1*row), x(1+2*row), ...*

Usage

`_,_,_,_,_,_ : interleave(row,column) : _,_,_,_,_,_`

Where:

- **row**: the number of row (int, known at compile time)
- **column**: the number of column (int, known at compile time)

---

butterfly

Addition (first half) then substraction (second half) of interleaved signals.

Usage

`_,_,_,_ : butterfly(n) : _,_,_,_`

Where:

- **n**: size of the butterfly (n is int, even and known at compile time)

---

hadamard

Hadamard matrix function of size `n = 2^k`.

Usage

```
_,_,_,_ : hadamard(n) : _,_,_,_
```

Where:

- `n`: `2^k`, size of the matrix (int, must be known at compile time)

Note:

Implementation contributed by Remy Muller.

---

recursivize

Create a recursion from two arbitrary processors p and q.

Usage

```
_,_ : recursivize(p,q) : _,_
```

Where:

- `p`: the forward arbitrary processor
- `q`: the feedback arbitrary processor

---

signals.lib

A library of basic elements to handle signals in Faust. Its official prefix is `si`.

Functions Reference

bus

n parallel cables. `bus` is a standard Faust function.

Usage

```
bus(n)
bus(4) : _,_,_,_
```

Where:

- **n**: is an integer known at compile time that indicates the number of parallel cables.

---

block

Block - terminate n signals. `block` is a standard Faust function.

Usage

```
_,_,... : block(n) : _,...
```

Where:

- **n**: the number of signals to be blocked

---

interpolate

Linear interpolation between two signals.

Usage

```
_,_ : interpolate(i) : _
```

Where:

- **i**: interpolation control between 0 and 1 (0: first input; 1: second input)

---

smoo

Smoothing function based on `smooth` ideal to smooth UI signals (sliders, etc.) down. `smoo` is a standard Faust function.

```
hslider(...) : smoo;
```

---

polySmooth

A smoothing function based on `smooth` that doesn't smooth when a trigger signal is given. This is very useful when making polyphonic synthesizer to make sure that the value of the parameter is the right one when the note is started.

Usage

```
hslider(...) : polysmooth(g,s,d) : _
```

Where:

- **g**: the gate/trigger signal used when making polyphonic synths
- **s**: the smoothness (see `smooth`)
- **d**: the number of samples to wait before the signal start being smoothed after **g** switched to 1

---

smoothAndH

A smoothing function based on `smooth` that holds its output signal when a trigger is sent to it. This feature is convenient when implementing polyphonic instruments to prevent some smoothed parameter to change when a note-off event is sent.

Usage

```
hslider(...) : smoothAndH(g,s) : _
```

Where:

- **g**: the hold signal (0 for hold, 1 for bypass)
- **s**: the smoothness (see `smooth`)

---

bsmooth

Block smooth linear interpolation during a block of samples.

Usage

```
hslider(...) : bsmooth : _
```

---

dot

Dot product for two vectors of size n.

Usage

```
_,_,_,_,_,_ : dot(n) : _
```

Where:

- **n**: size of the vectors (int, must be known at compile time)

---

smooth

Exponential smoothing by a unity-dc-gain one-pole lowpass. `smooth` is a standard Faust function.

Usage:

```
_ : smooth(tau2pole(tau)) : _
```

Where:

- **tau**: desired smoothing time constant in seconds, or

```
hslider(...) : smooth(s) : _
```

Where:

- **s**: smoothness between 0 and 1. s=0 for no smoothing, s=0.999 is "very smooth", s>1 is unstable, and s=1 yields the zero signal for all inputs. The exponential time-constant is approximately 1/(1-s) samples, when s is close to (but less than) 1.

Reference:

https://ccrma.stanford.edu/~jos/mdft/Convolution_Example_2_ADSR.html

---

cbus

n parallel cables for complex signals. `cbus` is a standard Faust function.

Usage

```
cbus(n)
cbus(4) : (r0,i0), (r1,i1), (r2,i2), (r3,i3)
```

Where:

- **n**: is an integer known at compile time that indicates the number of parallel cables.
- each complex number is represented by two real signals as (real,imag)

----

cmul

multiply two complex signals pointwise. `cmul` is a standard Faust function.

Usage

```
(r1,i1) : cmul(r2,i2) : (_,_);
```

Where:

- Each complex number is represented by two real signals as (real,imag), so
- `(r1,i1)` = real and imaginary parts of signal 1
- `(r2,i2)` = real and imaginary parts of signal 2

----

lag_ud

Lag filter with separate times for up and down.

Usage

```
_ : lag_ud(up, dn, signal) : _;
```

----

spats.lib

This library contains a collection of tools for sound spatialization. Its official prefix is `sp`.

panner

A simple linear stereo panner. `panner` is a standard Faust function.

Usage

```
_ : panner(g) : _,_
```

Where:

- g: the panning (0-1)

---

spat

GMEM SPAT: n-outputs spatializer. `spat` is a standard Faust function.

Usage

```
_ : spat(n,r,d) : _,_,...
```

Where:

- n: number of outputs
- r: rotation (between 0 et 1)
- d: distance of the source (between 0 et 1)

---

stereoize

Transform an arbitrary processor `p` into a stereo processor with 2 inputs and 2 outputs.

Usage

```
_,_ : stereoize(p) : _,_
```

Where:

- p: the arbitrary processor

---

synths.lib

This library contains a collection of envelope generators. Its official prefix is `sy`.

popFilterPerc

A simple percussion instrument based on a "popped" resonant bandpass filter. `popFilterPerc` is a standard Faust function.

Usage

`popFilterDrum(freq,q,gate) : _;`

Where:

- `freq`: the resonance frequency of the instrument
- `q`: the q of the res filter (typically, 5 is a good value)
- `gate`: the trigger signal (0 or 1)

---

dubDub

A simple synth based on a sawtooth wave filtered by a resonant lowpass. `dubDub` is a standard Faust function.

Usage

`dubDub(freq,ctFreq,q,gate) : _;`

Where:

- `freq`: frequency of the sawtooth
- `ctFreq`: cutoff frequency of the filter
- `q`: Q of the filter
- `gate`: the trigger signal (0 or 1)

---

sawTrombone

A simple trombone based on a lowpassed sawtooth wave. `sawTrombone` is a standard Faust function.

Usage

```
sawTrombone(att,freq,gain,gate) : _
```

Where:

- `att`: exponential attack duration in s (typically 0.01)
- `freq`: the frequency
- `gain`: the gain (0-1)
- `gate`: the gate (0 or 1)

---

combString

Simplest string physical model ever based on a comb filter. `combString` is a standard Faust function.

Usage

```
combString(freq,res,gate) : _;
```

Where:

- `freq`: the frequency of the string
- `res`: string T60 (resonance time) in second
- `gate`: trigger signal (0 or 1)

---

additiveDrum

A simple drum using additive synthesis. `additiveDrum` is a standard Faust function.

Usage

```
additiveDrum(freq,freqRatio,gain,harmDec,att,rel,gate) : _
```

Where:

- `freq`: the resonance frequency of the drum
- `freqRatio`: a list of ratio to choose the frequency of the mode in function of `freq` e.g.(1 1.2 1.5 . . .). The first element should always be one (fundamental).
- `gain`: the gain of each mode as a list (1 0.9 0.8 . . .). The first element is the gain of the fundamental.

- `harmDec`: harmonic decay ratio (0-1): configure the speed at which higher modes decay compare to lower modes.
- `att`: attack duration in second
- `rel`: release duration in second
- `gate`: trigger signal (0 or 1)

---

fm

An FM synthesizer with an arbitrary number of modulators connected as a sequence. `fm` is a standard Faust function.

Usage

```
freqs = (300,400,...);
indices = (20,...);
fm(freqs,indices) : _
```

Where:

- `freqs`: a list of frequencies where the first one is the frequency of the carrier and the others, the frequency of the modulator(s)
- `indices`: the indices of modulation (Nfreqs-1)

---

vaeffects.lib

A library of virtual analog filter effects. Its official prefix is `ve`.

Functions Reference

moog_vcf

Moog "Voltage Controlled Filter" (VCF) in "analog" form. Moog VCF implemented using the same logical block diagram as the classic analog circuit. As such, it neglects the one-sample delay associated with the feedback path around the four one-poles. This extra delay alters the response, especially at high frequencies (see reference [1] for details). See `moog_vcf_2b` below for a more accurate implementation.

Usage

```
moog_vcf(res,fr)
```

Where:

- `fr`: corner-resonance frequency in Hz (less than SR/6.3 or so)
- `res`: Normalized amount of corner-resonance between 0 and 1 (0 is no resonance, 1 is maximum)

References

- https://ccrma.stanford.edu/~stilti/papers/moogvcf.pdf
- https://ccrma.stanford.edu/~jos/pasp/vegf.html

`moog_vcf_2b[n]`

Moog "Voltage Controlled Filter" (VCF) as two biquads. Implementation of the ideal Moog VCF transfer function factored into second-order sections. As a result, it is more accurate than `moog_vcf` above, but its coefficient formulas are more complex when one or both parameters are varied. Here, res is the fourth root of that in `moog_vcf`, so, as the sampling rate approaches infinity, `moog_vcf(res,fr)` becomes equivalent to `moog_vcf_2b[n](res^4,fr)` (when res and fr are constant). `moog_vcf_2b` uses two direct-form biquads (`tf2`). `moog_vcf_2bn` uses two protected normalized-ladder biquads (`tf2np`).

Usage

```
moog_vcf_2b(res,fr)
moog_vcf_2bn(res,fr)
```

Where:

- `fr`: corner-resonance frequency in Hz
- `res`: Normalized amount of corner-resonance between 0 and 1 (0 is min resonance, 1 is maximum)

`wah4`

Wah effect, 4th order. `wah4` is a standard Faust function.

209

Usage

```
_ : wah4(fr) : _
```

Where:

- `fr`: resonance frequency in Hz

Reference

https://ccrma.stanford.edu/~jos/pasp/vegf.html

---

autowah

Auto-wah effect. `autowah` is a standard Faust function.

Usage

```
_ : autowah(level) : _;
```

Where:

- `level`: amount of effect desired (0 to 1).

---

crybaby

Digitized CryBaby wah pedal. `crybaby` is a standard Faust function.

Usage

```
_ : crybaby(wah) : _
```

Where:

- `wah`: "pedal angle" from 0 to 1

Reference

https://ccrma.stanford.edu/~jos/pasp/vegf.html

`vocoder`

A very simple vocoder where the spectrum of the modulation signal is analyzed using a filter bank. `vocoder` is a standard Faust function.

Usage

```
_ : vocoder(nBands,att,rel,BWRatio,source,excitation) : _;
```

Where:

- `nBands`: Number of vocoder bands
- `att`: Attack time in seconds
- `rel`: Release time in seconds
- `BWRatio`: Coefficient to adjust the bandwidth of each band (0.1 - 2)
- `source`: Modulation signal
- `excitation`: Excitation/Carrier signal

Licenses

STK 4.3 License

WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

LGPL License

This program is free software; you can redistribute it and/or modify it under the terms of the GNU Lesser General Public License as published by the Free Software Foundation; either version 2.1 of the License, or (at your option) any later version.

This program is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABIL-ITY or FITNESS FOR A PARTICULAR PURPOSE. See the GNU Lesser General Public License for more details.

You should have received a copy of the GNU Lesser General Public License along with the GNU C Library; if not, write to the Free Software Foundation, Inc., 59 Temple Place, Suite 330, Boston, MA 02111-1307 USA.