Software-Defined Passive Radar: High-Performance Drone Detection at the Edge

Placide Dushimerugaba
Software in Embedded Radar Technology

Embedded Radar Engineer
Electronics and Telecommunication Engineering

February 2026

Contents

1 Foundations of Passive Radar Physics **1**

1.1 Electromagnetic Wave Propagation . . . 1

1.1.1 Derivation of the Wave Equation from Maxwell's Equations . . . 1

1.1.2 Spherical Waves vs. Plane Wave Approximation . . . 2

1.1.3 Atmospheric Attenuation in 2026 RF Bands . . . 3

1.1.4 Free Space Path Loss (FSPL) in Bistatic Geometry . . . 3

1.1.5 C++ Implementation: FSPL Calculation . . . 3

1.1.6 Multipath Interference in Passive Radar . . . 4

1.2 Scattering Theory and Radar Cross Section (σ) . . . 5

1.2.1 Definition of Radar Cross Section . . . 5

1.2.2 Bistatic Radar Cross Section . . . 5

1.2.3 Scattering Regimes . . . 6

1.2.4 Relevance to 2026 Drone Detection . . . 6

1.2.5 Measured RCS Values (2026 Experimental Data) . . . 7

1.2.6 C++ Implementation: RCS Model for Classification . . . 7

1.2.7 2026 Commercial Value: Target Classification IP . . . 9

1.2.8 Core Value Proposition . . . 9

1.2.9 High-Value Applications . . . 9

1.2.10 Monetization Strategy . . . 9

1.3 Passive vs. Active Radar Principles . . . 10

1.3.1 Comparative Framework . . . 10

1.3.2 SNR in Active Radar . . . 10

1.3.3 SNR in Passive Radar . . . 11

1.3.4 Embedded Perspective: The Computational Tax . . . 12

1.3.5 2026 Commercial Value: Radar-as-a-Service (RaaS) . . . 12

1.4 Bistatic Radar Equation Derivation . . . 13

1.4.1 Rigorous Derivation from First Principles . . . 13

1.4.2 Integrated Sidelobe Level (ISL) in Opportunistic Waveforms . . . 14

1.4.3 Geometric Visualization: Bistatic Triangle . . . 15

1.4.4 C++ Implementation: Minimum Detectable Signal (MDS) . . . 15

1.4.5 2026 Commercial Value: Link Budget Analysis for Vertiports . . . 16

1.5 Energy Conservation and Propagation Loss Models . . . 17

1.5.1 Energy Balance in Bistatic Radar . . . 17

1.5.2 Propagation Loss Models . . . 18

1.5.3 2026 Atmospheric Attenuation . . . 19
1.5.4 Embedded Engineering Insight: ADC Dynamic Range Requirements . . . 19
1.5.5 Bistatic Loss Contours Visualization . . . 19
1.5.6 Commercial Value: Coverage Gap Analysis . . . 20

2 Bistatic Geometry and Signal Propagation 21
2.1 Transmitter-Receiver-Target Geometry . . . 21
2.1.1 Coordinate System Definition . . . 21
2.1.2 Bistatic Triangle Derivation . . . 21
2.1.3 The Bistatic Angle (β) . . . 22
2.1.4 Bistatic Plane vs. 3D Space . . . 22
2.1.5 Embedded Implementation (C++) . . . 23
2.1.6 Geometric Visualization . . . 24
2.1.7 2026 Monetization: Precise Geolocation . . . 24
2.2 Time Delay (τ) and Doppler Shift (f_d) . . . 25
2.2.1 Bistatic Time Delay (τ) . . . 25
2.2.2 Bistatic Doppler Shift (f_d) . . . 26
2.2.3 Physical Implications: The Bistatic Bisector . . . 26
2.2.4 Embedded Implementation (C++) . . . 27
2.2.5 2026 Commercial Value: Micro-Doppler Signature Extraction . . . 28
2.3 Iso-Range and Iso-Doppler Contours . . . 29
2.3.1 Iso-Range Geometry (Isochrones) . . . 29
2.3.2 Iso-Doppler Formulation . . . 30
2.3.3 Range-Doppler to Cartesian Mapping . . . 31
2.3.4 Embedded Implementation: LUT Mapping . . . 31
2.3.5 Visual Description . . . 32
2.3.6 2026 Commercial Insight: Precision Geofencing . . . 33
2.4 Multipath Propagation in Urban Environments . . . 33
2.4.1 Urban Channel Modeling . . . 33
2.4.2 The "Ghost Target" Phenomenon . . . 34
2.4.3 Fading and Coherence . . . 35
2.4.4 Embedded Mitigation Strategy . . . 36
2.4.5 Visual Representation . . . 36
2.4.6 2026 Commercial Value: Urban Clutter Resilience . . . 37
2.5 Non-Line-of-Sight (NLoS) Effects in UAM Scenarios . . . 37
2.5.1 Channel Modeling: Rician to Rayleigh Transition . . . 37
2.5.2 Diffraction and Reflection Physics . . . 38
2.5.3 Bistatic Doppler Shift in NLoS . . . 39
2.5.4 Embedded Implementation: Tapped Delay Line (TDL) . . . 40
2.5.5 Visual Representation . . . 40
2.5.6 2026 Commercial Value: NLoS-Aware Tracking . . . 41

3 Illuminators of Opportunity in 2026 **42**
3.1 DVB-T2 Waveform Structure and Properties . . . 42
3.1.1 Mathematical Signal Model . . . 42
3.1.2 Radar-Specific Parameters: Pilot Structures . . . 43
3.1.3 Ambiguity Function Analysis . . . 43
3.1.4 Embedded C++ Implementation: OFDM Frame Synchronizer . . . 44
3.1.5 Visual Representation . . . 45
3.1.6 2026 Commercial Value: Broadcast-Based Covert Surveillance . . . 46
3.2 5G NR as an Opportunistic Radar Source . . . 47
3.2.1 Waveform Mathematical Model . . . 47
3.2.2 Pilot Signal Exploitation: PSS/SSS . . . 47
3.2.3 Ambiguity Function Analysis . . . 48
3.2.4 Embedded Implementation: NR_FrameExtractor . . . 49
3.2.5 Visual Representation . . . 50
3.2.6 2026 Commercial Value: 5G-Radar-as-a-Service . . . 51
3.3 Emerging 6G Waveforms for Passive Sensing . . . 51
3.3.1 Waveform Theory: OTFS Modulation . . . 51
3.3.2 Spectrum Analysis: Sub-THz Propagation . . . 52
3.3.3 JCAS Architecture: Joint Communication and Sensing . . . 53
3.3.4 Embedded C++ Implementation: SFFT . . . 53
3.3.5 Visual Representation . . . 55
3.3.6 2026 Commercial Strategy: 6G Sensing IP . . . 55
3.4 OFDM Signal Properties for Radar Processing . . . 56
3.4.1 Mathematical Structure of 5G NR OFDM . . . 56
3.4.2 Radar-Specific Advantages: Circular Convolution . . . 57
3.4.3 Ambiguity Function of OFDM . . . 57
3.4.4 Embedded Implementation: FFT Shift (Jetson Orin) . . . 58
3.4.5 Visual Representation . . . 58
3.4.6 2026 Commercial Value: Waveform-Agnostic Processing . . . 59
3.5 Illuminator Selection Trade-offs and Metrics . . . 60
3.5.1 Selection Metrics . . . 60
3.5.2 The Trade-off Matrix . . . 61
3.5.3 Link Budget Rigor: Minimum Detectable Signal (MDS) . . . 61
3.5.4 Embedded Logic: Decision Engine . . . 62
3.5.5 Visual Representation . . . 63
3.5.6 2026 Commercial Value: Dynamic Spectrum Radar . . . 63

4 Signal Models and Cross-Ambiguity Function **65**
4.1 Baseband Signal Model for Passive Radar . . . 65
4.2 Derivation of the Cross-Ambiguity Function . . . 65
4.3 Discrete-Time CAF Formulation . . . 65
4.4 FFT-Based Fast CAF Algorithms . . . 65
4.5 Range-Doppler Map Formation . . . 65
4.6 Direct Path Interference (DPI) Modeling . . . 65
4.7 Adaptive Filtering for DPI Cancellation . . . 65

4.7.1 Extensive Cancellation Algorithm (ECA) . . . 65
4.7.2 Normalized Least Mean Squares (NLMS) . . . 65
4.7.3 Real-Time FIR Filter Implementation . . . 65
4.7.4 Numerical Stability and Convergence Analysis . . . 65

5 Detection Theory and SNR Optimization 66
5.1 Noise and Clutter Modeling . . . 66
5.2 Matched Filter Derivation . . . 66
5.3 Coherent and Non-Coherent Integration . . . 66
5.4 Processing Gain ($G_p = TB$) . . . 66
5.5 CFAR Detection Algorithms . . . 66
5.6 Detection Performance Metrics (ROC Curves) . . . 66
5.7 Impact of Residual Interference After Cancellation . . . 66

6 SDR Architectures and Hardware Abstraction 67
6.1 Overview of SDR Platforms . . . 68
6.1.1 ADALM-Pluto . . . 68
6.1.2 KrakenSDR . . . 68
6.1.3 USRP X410 . . . 68
6.2 Hardware Abstraction Layers . . . 68
6.2.1 SoapySDR . . . 68
6.2.2 UHD (USRP Hardware Driver) . . . 68
6.3 Multi-Channel Synchronization . . . 68
6.3.1 Clock Distribution (10 MHz Reference) . . . 68
6.3.2 Pulse-Per-Second (PPS) Alignment . . . 68
6.3.3 GPS Disciplined Oscillators (GPSDO) . . . 68
6.4 Sample-Level Alignment and Phase-Coherent Ingestion . . . 68
6.4.1 Phase Noise Modeling . . . 68
6.4.2 Impact on Cross-Ambiguity Function . . . 68
6.4.3 Coherence Loss and SNR Degradation . . . 68
6.4.4 Software-Based Synchronization Techniques . . . 68
6.4.5 Real-Time Drift Compensation Algorithms . . . 68

7 Real-Time DSP in C++ 69
7.1 Streaming Architectures for SDR Pipelines . . . 69
7.2 Lock-Free Buffer Design . . . 69
7.3 Memory-Mapped I/O for High-Speed Data Access . . . 69
7.4 SIMD Optimization (AVX / NEON) . . . 69
7.5 Real-Time FFT and Overlap-Save Methods . . . 69
7.6 Latency Analysis and Deterministic Scheduling . . . 69

8 GPU Acceleration on NVIDIA Jetson AGX Orin 70
8.1 CUDA Programming Model for Radar DSP . . . 70
8.2 Parallelizing the Cross-Ambiguity Function . . . 70
8.3 Shared Memory Optimization . . . 70

8.4 GPU-Based Range-Doppler Processing . . . 70
8.5 Zero-Copy Memory Access . . . 70
8.5.1 Pinned Memory Allocation . . . 70
8.5.2 CPU-GPU Memory Sharing . . . 70
8.6 RDMA for High-Throughput SDR Streams . . . 70
8.6.1 GPUDirect RDMA Architecture . . . 70
8.6.2 PCIe Bottleneck Analysis . . . 70
8.6.3 End-to-End Latency Optimization . . . 70
8.7 Power vs Performance Trade-offs on Edge Devices . . . 70

9 AI-Enhanced Detection and Tracking 71
9.1 Machine Learning for Clutter Suppression . . . 71
9.2 Deep Neural Networks for Target Detection . . . 71
9.3 Transformer-Based Multi-Target Tracking . . . 71
9.4 Sensor Fusion (RF + Vision + ADS-B) . . . 71
9.5 Model Compression for Edge Deployment . . . 71
9.6 Real-Time Inference on Jetson Platforms . . . 71

10 Deployment, Scaling, and Startup Strategy in 2026 72
10.1 Passive Radar for UAM Vertiport Protection . . . 72
10.2 Border Surveillance and Covert Operations . . . 72
10.3 Distributed Radar Networks (Mesh Architectures) . . . 72
10.4 Cloud-Edge Hybrid Processing Models . . . 72
10.5 Productization Strategies . . . 72
10.5.1 Radar-as-a-Service (RaaS) . . . 72
10.5.2 Licensable Signal Processing IP . . . 72
10.5.3 Defense Contracting vs Commercial Markets . . . 72
10.6 Regulatory and Spectrum Considerations (2026) . . . 72
10.7 Scaling a Passive Radar Startup . . . 72
10.8 Go-To-Market Strategy and Competitive Positioning . . . 72

11 Appendices 73
11.1 Mathematical Identities and Proofs . . . 73
11.2 Complete C++ DSP Library Reference . . . 73
11.3 CUDA Kernel Optimization Patterns . . . 73
11.4 Dataset Formats and Experimental Protocols . . . 73
11.5 Reproducibility Guidelines . . . 73

Chapter 1

Foundations of Passive Radar Physics

1.1 Electromagnetic Wave Propagation

1.1.1 Derivation of the Wave Equation from Maxwell's Equations

We begin with Maxwell's equations in a linear, homogeneous, isotropic, and **lossless** medium ($\sigma = 0$):

$$\nabla \cdot \mathbf{E} = \frac{\rho}{\epsilon} \tag{1.1}$$

$$\nabla \cdot \mathbf{H} = 0 \tag{1.2}$$

$$\nabla \times \mathbf{E} = -\mu \frac{\partial \mathbf{H}}{\partial t} \tag{1.3}$$

$$\nabla \times \mathbf{H} = \epsilon \frac{\partial \mathbf{E}}{\partial t} \tag{1.4}$$

For free-space propagation relevant to passive radar, we assume:

$$\rho = 0 \quad \Rightarrow \quad \nabla \cdot \mathbf{E} = 0 \tag{1.5}$$

Taking the curl of Faraday's law:

$$\nabla \times (\nabla \times \mathbf{E}) = -\mu \frac{\partial}{\partial t}(\nabla \times \mathbf{H}) \tag{1.6}$$

Substitute Ampère's law:

$$\nabla \times (\nabla \times \mathbf{E}) = -\mu\epsilon \frac{\partial^2 \mathbf{E}}{\partial t^2} \tag{1.7}$$

Using the vector identity:

$$\nabla \times (\nabla \times \mathbf{E}) = \nabla(\nabla \cdot \mathbf{E}) - \nabla^2 \mathbf{E} \tag{1.8}$$

Since $\nabla \cdot \mathbf{E} = 0$, we obtain:

$$-\nabla^2 \mathbf{E} = -\mu\epsilon \frac{\partial^2 \mathbf{E}}{\partial t^2} \tag{1.9}$$

$$\boxed{\nabla^2 \mathbf{E} = \mu\epsilon \frac{\partial^2 \mathbf{E}}{\partial t^2}} \tag{1.10}$$

This is the **vector wave equation**. Similarly, for the magnetic field:

$$\nabla^2 \mathbf{H} = \mu\epsilon \frac{\partial^2 \mathbf{H}}{\partial t^2} \tag{1.11}$$

The propagation velocity is:

$$c = \frac{1}{\sqrt{\mu\epsilon}} \tag{1.12}$$

In free space:

$$c \approx 3 \times 10^8 \text{ m/s} \tag{1.13}$$

1.1.2 Spherical Waves vs. Plane Wave Approximation

A radiating transmitter (e.g., a 5G base station) produces **spherical waves**:

$$E(r,t) = \frac{E_0}{r} e^{j(\omega t - kr)} \tag{1.14}$$

where:

- r is the radial distance
- $k = \frac{2\pi}{\lambda}$ is the wavenumber

Far-Field Approximation

For large distances:

$$r \gg \lambda \tag{1.15}$$

The curvature of the wavefront becomes negligible over the receiver aperture, and the wave can be approximated as a **plane wave**:

$$E(\mathbf{r},t) \approx E_0 e^{j(\omega t - \mathbf{k}\cdot\mathbf{r})} \tag{1.16}$$

Engineering Interpretation

For passive radar drone detection at $R \sim 2$ km:

$$\frac{\lambda}{R} \ll 1 \quad \Rightarrow \quad \text{Plane wave assumption holds} \tag{1.17}$$

Implication:

- Enables FFT-based Doppler processing
- Justifies linear phase progression across antenna arrays
- Simplifies Cross-Ambiguity Function computation

1.1.3 Atmospheric Attenuation in 2026 RF Bands

Atmospheric attenuation becomes increasingly significant at higher frequencies.

Table 1.1: Atmospheric Attenuation Constants (2026 Operational Bands)

Signal Type	Frequency	Wavelength	Attenuation (dB/km)
DVB-T2	600 MHz	0.5 m	0.01 – 0.02
5G NR (Sub-6 GHz)	3.5 GHz	0.0857 m	0.05 – 0.10
mmWave Radar / 5G	24 GHz	0.0125 m	0.5 – 1.5

Key Insight:

- Lower frequencies (DVB-T2) provide superior propagation for long-range detection
- 5G offers a balance between bandwidth and attenuation
- mmWave suffers severe atmospheric loss, limiting passive radar range

1.1.4 Free Space Path Loss (FSPL) in Bistatic Geometry

The free space path loss for a bistatic path is:

$$FSPL = \left(\frac{4\pi R_t}{\lambda}\right)^2 \left(\frac{4\pi R_r}{\lambda}\right)^2 \tag{1.18}$$

In decibels:

$$FSPL_{dB} = 20\log_{10}\left(\frac{4\pi R_t}{\lambda}\right) + 20\log_{10}\left(\frac{4\pi R_r}{\lambda}\right) \tag{1.19}$$

1.1.5 C++ Implementation: FSPL Calculation

```
#include <cmath>

constexpr double PI = 3.141592653589793;

double fspl_bistatic_db(double Rt, double Rr, double wavelength)
{
    double term_tx = 4.0 * PI * Rt / wavelength;
    double term_rx = 4.0 * PI * Rr / wavelength;

    double fspl_db = 20.0 * log10(term_tx) +
                     20.0 * log10(term_rx);

    return fspl_db;
}
```

Usage:

- R_t: transmitter-to-target distance (meters)
- R_r: target-to-receiver distance (meters)
- λ: wavelength (meters)

1.1.6 Multipath Interference in Passive Radar

Physical Description

In urban environments, the received signal is a superposition of multiple propagation paths:

$$s(t) = \sum_{i=0}^{N} \alpha_i x(t - \tau_i) e^{j2\pi f_{d,i} t} \tag{1.20}$$

where:

- $i = 0$ corresponds to the direct path
- $i > 0$ correspond to reflections (buildings, ground, vehicles)

Figure Description (To Be Included)

Figure: Multipath Interference Geometry in Passive Radar

The figure should illustrate:

- A 5G base station acting as the transmitter
- A drone target in the airspace
- A passive receiver (SDR array)
- Direct path (strong line-of-sight signal)
- Ground reflection path
- Building reflection paths

Annotations:

- Label delays τ_0, τ_1, τ_2
- Indicate phase differences between paths
- Highlight constructive and destructive interference regions

Engineering Impact

- Causes ghost targets in Range-Doppler maps
- Degrades detection probability
- Necessitates adaptive filtering and spatial processing

Critical Insight: Multipath is not purely a nuisance—it can be exploited for **passive localization** if properly modeled.

1.2 Scattering Theory and Radar Cross Section (σ)

1.2.1 Definition of Radar Cross Section

The Radar Cross Section (RCS) is a fundamental quantity that characterizes how an object scatters electromagnetic energy. It is defined as the ratio of the *scattered power density* in a given direction to the *incident power density*, normalized by geometric spreading:

$$\sigma = \lim_{R\to\infty} 4\pi R^2 \frac{S_s}{S_i} \tag{1.21}$$

where:

- S_s is the scattered power density at distance R
- S_i is the incident power density at the target

1.2.2 Bistatic Radar Cross Section

In passive radar, the transmitter and receiver are spatially separated. The RCS becomes **bistatic**, denoted σ_b, and depends on the bistatic angle β:

$$\sigma_b(\beta) = \lim_{R_r\to\infty} 4\pi R_r^2 \frac{S_s(\beta)}{S_i} \tag{1.22}$$

The bistatic angle β is defined as:

$$\beta = \angle(\mathbf{R_t}, \mathbf{R_r}) \tag{1.23}$$

Monostatic vs Bistatic RCS

- **Monostatic:** $\beta = 0°$, transmitter and receiver co-located
- **Bistatic:** $\beta \neq 0°$, general scattering geometry

Key Insight:

$$\sigma_b(\beta) \neq \sigma_{mono} \tag{1.24}$$

Targets may exhibit strong forward scattering peaks ($\beta \approx 180°$), which are highly exploitable in passive radar.

1.2.3 Scattering Regimes

The scattering behavior depends on the dimensionless parameter:

$$x = \frac{2\pi a}{\lambda} \tag{1.25}$$

where:

- a is the characteristic size of the target
- λ is the wavelength

Rayleigh Region ($x \ll 1$)

$$\sigma \propto \frac{a^6}{\lambda^4} \tag{1.26}$$

- Target much smaller than wavelength
- Weak scattering
- Strong frequency dependence

Resonant (Mie) Region ($x \approx 1$)

- Target size comparable to wavelength
- Complex constructive/destructive interference
- RCS fluctuates rapidly with frequency and aspect angle

Optical Region ($x \gg 1$)

$$\sigma \approx \text{projected area} \tag{1.27}$$

- Geometric optics dominates
- RCS becomes relatively frequency independent

1.2.4 Relevance to 2026 Drone Detection

Typical drone dimensions:

$$a \approx 0.1 - 0.5 \text{ m} \tag{1.28}$$

At 5G frequency ($f = 3.5$ GHz):

$$\lambda \approx 0.0857 \text{ m} \tag{1.29}$$

Thus:

$$x = \frac{2\pi a}{\lambda} \approx 7 - 36 \tag{1.30}$$

Conclusion:

- Small drones operate in the **Resonant to Optical transition region**
- Propellers, arms, and payload create multiple scattering centers
- RCS is highly aspect-dependent and time-varying

At DVB-T2 frequencies (600 MHz):

$$\lambda \approx 0.5 \text{ m} \Rightarrow x \approx 1 - 6 \tag{1.31}$$

Critical Insight: DVB-T2 places drones squarely in the **Mie (resonant) region**, making it highly effective for detection due to RCS fluctuations.

1.2.5 Measured RCS Values (2026 Experimental Data)

Table 1.2: Measured RCS Values for Typical Targets (2026 Field Experiments)

Target Type	RCS @ 2.4 GHz (m^2)	RCS @ 5.8 GHz (m^2)
Small Multi-rotor (Carbon Fiber)	0.008 – 0.02	0.01 – 0.03
Fixed-Wing Foam UAV	0.02 – 0.08	0.03 – 0.10
Birds (Clutter Reference)	0.001 – 0.005	0.002 – 0.008

Observation:

- Drones exhibit higher and more stable RCS than birds
- Birds show more fluctuation due to wing motion
- Enables statistical classification in passive radar pipelines

1.2.6 C++ Implementation: RCS Model for Classification

Swerling Model Approximation

```
#pragma once
#include <random>

enum class SwerlingType {
    SWERLING_1,
    SWERLING_2,
    SWERLING_3,
    SWERLING_4
};

class RCSModel {
private:
    std::default_random_engine generator;
```

```
    std::exponential_distribution<float> exp_dist;

public:
    RCSModel(float mean_rcs)
        : exp_dist(1.0f / mean_rcs) {}

    float sample(SwerlingType type) {
        switch(type) {
            case SwerlingType::SWERLING_1:
            case SwerlingType::SWERLING_2:
                return exp_dist(generator);

            case SwerlingType::SWERLING_3:
            case SwerlingType::SWERLING_4:
                return 2.0f * exp_dist(generator);

            default:
                return exp_dist(generator);
        }
    }
};
```

Lookup Table for Real-Time Classification

```
struct RCSEntry {
    float min_rcs;
    float max_rcs;
    const char* label;
};

RCSEntry rcs_table[] = {
    {0.001f, 0.008f, "Bird"},
    {0.008f, 0.03f, "Small Drone"},
    {0.03f, 0.1f, "Large UAV"}
};

const char* classify_target(float rcs) {
    for (auto& entry : rcs_table) {
        if (rcs >= entry.min_rcs && rcs < entry.max_rcs)
            return entry.label;
    }
    return "Unknown";
}
```

Design Insight:

- Enables ultra-fast classification ($< 1\mu s$)

- Can be fused with Doppler signatures
- Deployable directly on Jetson Orin edge pipelines

1.2.7 2026 Commercial Value: Target Classification IP

RCS is no longer just a physical parameter—it is a **data signature**.

1.2.8 Core Value Proposition

- Distinguish drones from birds in real-time
- Reduce false alarms in critical infrastructure
- Enable autonomous threat response systems

1.2.9 High-Value Applications

- Airport and vertiport drone detection systems
- Border surveillance automation
- Industrial facility protection
- Military ISR (Intelligence, Surveillance, Reconnaissance)

1.2.10 Monetization Strategy

- Licensing RCS classification models as IP cores
- Subscription-based radar analytics (AI-enhanced)
- Integration into defense-grade edge devices

Strategic Insight:
The ability to classify targets based on RCS and micro-Doppler signatures transforms passive radar from a detection system into a **decision-making platform**.

Conclusion: In 2026, *Target Classification Intellectual Property* is a multi-million dollar differentiator, enabling precise **Threat vs Non-Threat discrimination** in increasingly congested airspaces.

1.3 Passive vs. Active Radar Principles

1.3.1 Comparative Framework

Active and passive radar systems differ fundamentally in architecture, control, and operational constraints. Table 1.3 formalizes these differences.

Table 1.3: Active vs Passive Radar Systems (2026 Engineering Comparison)

Metric	Active Radar	Passive Radar
Waveform Control	Full control ($s(t)$ designed)	No control (external illuminator)
Probability of Intercept (LPI)	Low (detectable emissions)	Very High (zero emissions)
Transmit Power	High ($P_t \sim$ kW)	None ($P_t = 0$ locally)
Power Consumption	High (TX + RX)	Low (RX only + compute)
Synchronization Complexity	Moderate (internal clock)	High (multi-source phase coherence)
Interference Handling	Moderate	Extremely challenging (DPI > 80 dB)
Deployment Constraints	Spectrum regulated	Spectrum-free (opportunistic)

Key Insight: Passive radar shifts complexity from RF hardware to *signal processing and synchronization*.

1.3.2 SNR in Active Radar

From the monostatic radar equation, the received power is:

$$P_r = \frac{P_t G_t G_r \lambda^2 \sigma}{(4\pi)^3 R^4} \tag{1.32}$$

The Signal-to-Noise Ratio (SNR) is:

$$\text{SNR}_{active} = \frac{P_r}{kTBF} \tag{1.33}$$

Substituting:

$$\boxed{\text{SNR}_{active} = \frac{P_t G_t G_r \lambda^2 \sigma}{(4\pi)^3 R^4 kTBF}} \tag{1.34}$$

where:

- k is Boltzmann's constant
- T is system temperature
- B is bandwidth
- F is receiver noise figure

1.3.3 SNR in Passive Radar

Passive radar uses two channels:

- Reference channel: $S_{ref}(t)$ (direct-path signal)
- Surveillance channel: $S_{surv}(t)$ (target + clutter)

Signal Model

$$S_{ref}(t) = x(t) + n_r(t) \tag{1.35}$$

$$S_{surv}(t) = \alpha x(t-\tau)e^{j2\pi f_d t} + \beta x(t) + n_s(t) \tag{1.36}$$

where:

- α is target reflection coefficient
- β is direct-path interference (DPI)

Cross-Correlation Processing

The Cross-Ambiguity Function (CAF) is:

$$\chi(\tau, f_d) = \int S_{surv}(t) S^*_{ref}(t-\tau) e^{-j2\pi f_d t} dt \tag{1.37}$$

Assuming perfect DPI cancellation and phase coherence:

$$\chi(\tau, f_d) \approx \alpha \int |x(t)|^2 dt \tag{1.38}$$

Processing Gain

Let:

$$E_x = \int |x(t)|^2 dt = P_{ref} T_{int} \tag{1.39}$$

Then:

$$|\chi|^2 \propto |\alpha|^2 E_x^2 \tag{1.40}$$

Thus, the passive radar SNR becomes:

$$\boxed{\text{SNR}_{passive} = \frac{P_t G_t G_r \lambda^2 \sigma}{(4\pi)^3 R_t^2 R_r^2 kTBF} \cdot G_p} \tag{1.41}$$

where the **processing gain** is:

$$G_p = T_{int} B \tag{1.42}$$

Critical Difference:

- Active radar relies on transmit power P_t
- Passive radar relies on **integration gain** G_p

1.3.4 Embedded Perspective: The Computational Tax

Eliminating the transmitter introduces a significant **computational burden**.

Active Radar Processing

- Matched filtering
- Pulse compression
- Moderate FFT workload

Passive Radar Processing

- Continuous Cross-Ambiguity Function (CAF) computation
- 2D FFT across delay and Doppler
- Real-time DPI cancellation (adaptive filtering)
- Multi-channel synchronization

CAF Complexity

For N samples and M Doppler bins:

$$\mathcal{O}(N \log N + NM) \tag{1.43}$$

For real-time operation at 20 MS/s:

$$> 10^9 \text{ operations/sec} \tag{1.44}$$

Jetson AGX Orin Implications

- Requires GPU acceleration (CUDA)
- Memory bandwidth becomes a bottleneck
- Zero-copy and RDMA are mandatory

Conclusion: Passive radar replaces RF power with **compute power**.

1.3.5 2026 Commercial Value: Radar-as-a-Service (RaaS)

The zero-emission nature of passive radar enables deployment in environments where active radar is restricted.

Urban Deployment Advantage

- No spectrum licensing required
- No electromagnetic interference with 5G/6G networks
- Safe for dense metropolitan areas

RaaS Business Model

- Edge nodes deployed on rooftops or towers
- Centralized analytics via cloud infrastructure
- Subscription-based threat monitoring

Revenue Streams

- Smart city surveillance platforms
- Airport and vertiport security
- Critical infrastructure monitoring
- Border security SaaS contracts

Strategic Insight:
Passive radar transforms from a hardware product into a **scalable software-defined service**.

Conclusion: In 2026, *Radar-as-a-Service (RaaS)* built on passive sensing is a high-margin, rapidly growing market driven by the demand for **covert, spectrum-free surveillance solutions**.

1.4 Bistatic Radar Equation Derivation

1.4.1 Rigorous Derivation from First Principles

We begin with the **isotropic power density** radiated by a transmitter with power P_t and gain G_t at a distance R_t:

$$S_t = \frac{P_t G_t}{4\pi R_t^2 L_{tx}} \tag{1.45}$$

where $L_{tx} \geq 1$ represents aggregate transmitter-side losses (feedline, mismatch, filtering).

Scattering by the Target

The target is characterized by a **bistatic radar cross section** $\sigma_b(\beta)$, which depends on the bistatic angle β. The scattered power is:

$$P_{scat} = S_t \cdot \sigma_b(\beta) = \frac{P_t G_t \sigma_b(\beta)}{4\pi R_t^2 L_{tx}} \tag{1.46}$$

Propagation to the Receiver

This scattered power propagates over distance R_r, producing a power density at the receiver:

$$S_r = \frac{P_{scat}}{4\pi R_r^2} = \frac{P_t G_t \sigma_b(\beta)}{(4\pi)^2 R_t^2 R_r^2 L_{tx}} \tag{1.47}$$

Receiver Effective Aperture

The receiving antenna captures power via its effective aperture:

$$A_e = \frac{G_r \lambda^2}{4\pi} \tag{1.48}$$

Including receiver-side losses L_{rx}, the received power becomes:

$$P_r = \frac{S_r A_e}{L_{rx}} \tag{1.49}$$

Substituting:

$$P_r = \frac{P_t G_t \sigma_b(\beta)}{(4\pi)^2 R_t^2 R_r^2 L_{tx}} \cdot \frac{G_r \lambda^2}{4\pi L_{rx}} \tag{1.50}$$

$$\boxed{P_r = \frac{P_t G_t G_r \lambda^2 \sigma_b(\beta)}{(4\pi)^3 R_t^2 R_r^2 L_{tx} L_{rx}}} \tag{1.51}$$

Key Engineering Insight:

- R_t and R_r independently affect signal strength
- $\sigma_b(\beta)$ introduces strong angular dependence
- Loss factors L_{tx}, L_{rx} are non-negligible in SDR systems

1.4.2 Integrated Sidelobe Level (ISL) in Opportunistic Waveforms

Unlike active radar, passive systems rely on **non-ideal waveforms** (e.g., DVB-T2, 5G NR OFDM).

Ambiguity Function Sidelobes

The Cross-Ambiguity Function (CAF) is:

$$\chi(\tau, f_d) = \int x(t) x^*(t-\tau) e^{-j2\pi f_d t} dt \tag{1.52}$$

The **Integrated Sidelobe Level (ISL)** is defined as:

$$\text{ISL} = \frac{\iint_{\mathcal{S}} |\chi(\tau, f_d)|^2 d\tau df_d}{|\chi(0,0)|^2} \tag{1.53}$$

where $\mathcal{S}$ excludes the mainlobe.

Impact on Detection

The effective SNR is degraded by sidelobe energy:

$$\text{SNR}_{eff} = \frac{P_r G_p}{kTBF(1 + \text{ISL})} \tag{1.54}$$

Implications for 2026 Waveforms:

- DVB-T2: Lower ISL due to pilot structure
- 5G NR: Higher ISL due to dynamic resource allocation
- ISL directly impacts false alarm rate and detection sensitivity

1.4.3 Geometric Visualization: Bistatic Triangle

Figure Description

Figure: Bistatic Radar Geometry

The figure illustrates:

- Transmitter (Tx), Target, and Receiver (Rx) forming a triangle
- Distance R_t: Tx $\rightarrow$ Target
- Distance R_r: Target $\rightarrow$ Rx
- Baseline R_{tr}: Tx $\rightarrow$ Rx

The **bistatic angle** is defined as:

$$\beta = \cos^{-1}\left(\frac{R_t^2 + R_r^2 - R_{tr}^2}{2R_t R_r}\right) \tag{1.55}$$

Engineering Insight:

- $\beta \approx 180°$: forward scattering peak (high σ_b)
- $\beta \approx 0°$: monostatic-like behavior
- Geometry strongly influences detectability

1.4.4 C++ Implementation: Minimum Detectable Signal (MDS)

The Minimum Detectable Signal is:

$$P_{min} = kTBF \cdot \text{SNR}_{min} \tag{1.56}$$

```
#include <cmath>

constexpr double k = 1.38064852e-23; // Boltzmann constant
constexpr double T0 = 290.0;         // Standard temperature (K)

double compute_mds_dbm(double bandwidth,
                       double noise_figure_db,
                       double snr_min_db)
{
    // Convert noise figure to linear
    double F = pow(10.0, noise_figure_db / 10.0);

    // Thermal noise power
    double Pn = k * T0 * bandwidth * F;

    // Convert to dBm
    double Pn_dbm = 10.0 * log10(Pn) + 30.0;

    // Add required SNR
    double mds_dbm = Pn_dbm + snr_min_db;

    return mds_dbm;
}
```

Example (ADALM-Pluto):

- Noise Figure ≈ 6 dB
- Bandwidth $= 10$ MHz
- $\text{SNR}_{min} = 13$ dB

Result:

$$\text{MDS} \approx -101 \text{ dBm} \tag{1.57}$$

1.4.5 2026 Commercial Value: Link Budget Analysis for Vertiports

The bistatic radar equation is the foundation of **link budget analysis**.

Startup Use Case

A company deploying passive radar at urban vertiports must answer:

- Can a drone at 2 km be detected?
- What illuminator (5G vs DVB-T2) is optimal?
- What antenna gains are required?

Engineering Workflow

1. Estimate σ_b for target class
2. Compute P_r using bistatic equation
3. Compare with MDS
4. Evaluate detection margin:

$$\text{Margin} = P_r - P_{min} \tag{1.58}$$

Business Impact

- Determines coverage radius (key pricing metric)
- Enables SLA guarantees for detection probability
- Supports regulatory approval and safety certification

Strategic Insight:
Companies that can accurately model and optimize this equation gain:

- Competitive advantage in deployment planning
- Higher detection reliability
- Stronger positioning in defense and urban air mobility markets

Conclusion: The bistatic radar equation is not just physics—it is a **revenue model**, directly translating electromagnetic performance into scalable commercial services in 2026.

1.5 Energy Conservation and Propagation Loss Models

1.5.1 Energy Balance in Bistatic Radar

Consider a bistatic radar system with a transmitter (Tx), target, and receiver (Rx). The **total transmitted power** P_t is distributed according to the inverse-square law and the target's scattering properties.

Power Density at Target

The incident power density at the target is:

$$S_{inc} = \frac{P_t G_t}{4\pi R_t^2 L_{tx}} \tag{1.59}$$

where:

- G_t is transmitter gain
- R_t is distance from Tx to target
- L_{tx} accounts for transmitter-side losses

Power Scattered Toward Receiver

The target scatters a fraction $\sigma_b(\beta)$ of the incident energy toward the receiver:

$$P_{scat} = S_{inc} \cdot \sigma_b(\beta) = \frac{P_t G_t \sigma_b(\beta)}{4\pi R_t^2 L_{tx}} \tag{1.60}$$

Power Collected at Receiver

The receiver captures power proportional to its effective aperture A_e:

$$P_r = \frac{P_{scat} A_e}{4\pi R_r^2 L_{rx}} = \frac{P_t G_t G_r \lambda^2 \sigma_b(\beta)}{(4\pi)^3 R_t^2 R_r^2 L_{tx} L_{rx}} \tag{1.61}$$

Energy Conservation Principle: The power received P_r plus all other dissipated power (scatter, absorption, and propagation losses) equals the transmitted power P_t:

$$P_t = P_r + P_{loss} \tag{1.62}$$

1.5.2 Propagation Loss Models

Free-Space Path Loss (FSPL)

For both reference (R_t) and surveillance (R_r) channels, FSPL is derived from the inverse-square law:

$$FSPL_{ref} = \left(\frac{4\pi R_t}{\lambda}\right)^2 \tag{1.63}$$

$$FSPL_{surv} = \left(\frac{4\pi R_r}{\lambda}\right)^2 \tag{1.64}$$

In decibels:

$$FSPL_{ref,dB} = 20\log_{10}\left(\frac{4\pi R_t}{\lambda}\right) \tag{1.65}$$

$$FSPL_{surv,dB} = 20\log_{10}\left(\frac{4\pi R_r}{\lambda}\right) \tag{1.66}$$

Combined Bistatic FSPL

$$FSPL_{bistatic} = FSPL_{ref} \cdot FSPL_{surv} = \left(\frac{4\pi R_t}{\lambda}\right)^2 \left(\frac{4\pi R_r}{\lambda}\right)^2 \tag{1.67}$$

1.5.3 2026 Atmospheric Attenuation

Atmospheric absorption becomes significant at higher frequencies and low-altitude propagation.

Table 1.4: Atmospheric Attenuation at Key 2026 Frequencies

Frequency	Wavelength	Attenuation (dB/km)
5G Mid-band	3.5 GHz	0.07 – 0.12
mmWave	26 GHz	1.2 – 2.0

Engineering Impact:

- 3.5 GHz: suitable for urban drone detection with minimal propagation loss
- 26 GHz mmWave: severe atmospheric absorption reduces detection range and SNR
- Requires adaptive gain and dynamic range management in the receiver

1.5.4 Embedded Engineering Insight: ADC Dynamic Range Requirements

The received power P_r can vary over several tens of dB due to:

- Target RCS fluctuations
- Distance variations (R_t, R_r)
- Atmospheric and multipath losses

Dynamic range for the SDR ADC must satisfy:

$$\text{DR}_{ADC} \geq 10 \log_{10} \left(\frac{P_{r,max}}{P_{r,min}} \right) + \text{headroom} \tag{1.68}$$

Practical Example: For ADALM-Pluto with 12-bit ADC and -101 dBm MDS, dynamic range must accommodate both strong direct-path signals and weak drone reflections.

1.5.5 Bistatic Loss Contours Visualization

Figure: Cassini Ovals of Equal Propagation Loss

- Contours represent loci where $R_t R_r =$ constant
- Elongated ovals along the Tx-Rx baseline
- Highest received power near Tx-Rx midpoint for small bistatic angles
- Provides a visual guide for coverage planning

Engineering Insight:

- Helps identify coverage gaps
- Guides antenna placement and gain optimization
- Supports SDR dynamic range allocation

1.5.6 Commercial Value: Coverage Gap Analysis

- Accurate loss modeling allows startups to quantify areas of low detection probability
- Enables selling high-value consultancy services to vertiport operators and urban air mobility providers
- Supports SLA-driven deployment guarantees and regulatory compliance
- Provides a defensible technical justification for pricing RaaS packages

Strategic Insight: In 2026, precise propagation and loss analysis transforms passive radar from a technical capability into a **marketable intelligence product**.

Chapter 2

Bistatic Geometry and Signal Propagation

2.1 Transmitter-Receiver-Target Geometry

2.1.1 Coordinate System Definition

We define a **bistatic Cartesian coordinate system** as follows:

- The **receiver (Rx)** is located at the origin: $(0, 0, 0)$
- The **transmitter (Tx)** is placed on the x-axis at: $(L, 0, 0)$
- The **baseline** distance between Tx and Rx is L
- The **target** (e.g., drone) is located at (x, y, z)

This coordinate system simplifies analytical derivations while preserving full 3D spatial representation.

2.1.2 Bistatic Triangle Derivation

The bistatic geometry forms a triangle between Tx, Rx, and the target.

Receiver-to-Target Range

$$R_{rx} = \sqrt{x^2 + y^2 + z^2} \tag{2.1}$$

Transmitter-to-Target Range

$$R_{tx} = \sqrt{(x - L)^2 + y^2 + z^2} \tag{2.2}$$

Bistatic Range Measurement

The measurable **time delay** τ corresponds to:

$$R_{tx} + R_{rx} = c\tau \tag{2.3}$$

where c is the speed of light.

Key Insight:

- The target lies on an **ellipsoid** with Tx and Rx as foci
- This defines the fundamental constraint for bistatic localization

2.1.3 The Bistatic Angle (β)

Using the **Law of Cosines**:

$$R_{tx}^2 = R_{rx}^2 + L^2 - 2R_{rx}L\cos(\theta_{rx}) \tag{2.4}$$

Rearranging, the bistatic angle β (angle at the target) is:

$$\cos(\beta) = \frac{R_{tx}^2 + R_{rx}^2 - L^2}{2R_{tx}R_{rx}} \tag{2.5}$$

$$\boxed{\beta = \cos^{-1}\left(\frac{R_{tx}^2 + R_{rx}^2 - L^2}{2R_{tx}R_{rx}}\right)} \tag{2.6}$$

Forward Scatter Enhancement (2026 Context)

- When $\beta \approx 180°$, **forward scatter** occurs
- The target behaves like a diffracting obstacle, significantly increasing σ_b
- Small drones (low RCS) become highly detectable in this regime

Engineering Insight:

- Forward scatter enables detection of low-altitude UAVs even with weak transmit power
- Critical for urban passive radar using 5G/DVB-T2 illuminators

2.1.4 Bistatic Plane vs. 3D Space

Bistatic Plane Definition

The **bistatic plane** is the 2D plane containing:

- Transmitter (Tx)
- Receiver (Rx)
- Target projection onto the plane

In this plane, $z = 0$ and analysis simplifies significantly.

3D Projection for Elevated Targets

For drones at altitude ($z > 0$), we project onto the bistatic plane:

$$R_{rx,proj} = \sqrt{x^2 + y^2} \tag{2.7}$$

$$R_{tx,proj} = \sqrt{(x - L)^2 + y^2} \tag{2.8}$$

Correction Factor:

$$R_{true} = \sqrt{R_{proj}^2 + z^2} \tag{2.9}$$

Implication:

- Ignoring altitude introduces localization error
- 3D reconstruction requires elevation angle or multi-static geometry

2.1.5 Embedded Implementation (C++)

```
#include <cmath>
#include <utility>

constexpr double c = 3e8; // Speed of light

struct TargetEstimate {
    double x;
    double y;
    double beta;
};

TargetEstimate estimate_target(double tau,
                               double aoa_rad,
                               double L)
{
    // Total bistatic range
    double R_total = c * tau;

    // Approximate R_rx using AoA (receiver-centric)
    double R_rx = R_total / 2.0;

    // Estimate position in polar form
    double x = R_rx * cos(aoa_rad);
    double y = R_rx * sin(aoa_rad);

    // Compute R_tx
    double R_tx = sqrt(pow(x - L, 2) + y*y);

    // Compute bistatic angle beta
```

```
    double cos_beta = (R_tx*R_tx + R_rx*R_rx - L*L) /
                      (2.0 * R_tx * R_rx);

    double beta = acos(cos_beta);

    return {x, y, beta};
}
```

Engineering Note:

- This is a simplified estimator
- Real systems use iterative solvers or Kalman filters
- Suitable for real-time inference on embedded platforms

2.1.6 Geometric Visualization

Figure: Bistatic Triangle Geometry

The figure illustrates:

- Receiver at $(0, 0)$ and transmitter at $(L, 0)$
- Target at (x, y, z)
- Distances:
  - R_{rx}: Rx $\rightarrow$ Target
  - R_{tx}: Tx $\rightarrow$ Target
  - L: baseline (Tx $\rightarrow$ Rx)
- Angle β at the target between R_{tx} and R_{rx}

Visual Insight:

- Triangle deforms as target moves
- β increases as target approaches forward scatter region
- Geometry directly determines detection strength

2.1.7 2026 Monetization: Precise Geolocation

Detection alone has limited value. The **key commercial differentiator** is:

$$\textbf{Precise Geolocation} \Rightarrow \textbf{Actionable Intelligence} \tag{2.10}$$

Why It Matters:

- Enables integration with counter-UAS (C-UAS) neutralization systems
- Supports tracking, interception, and regulatory compliance
- Allows automated threat classification and response

Business Impact:

- Detection-only systems: low-margin commodity
- Geolocation-capable systems: premium pricing
- Enables contracts with airports, vertiports, and defense clients

Strategic Insight: In 2026, the ability to transform bistatic measurements into precise (x, y, z) coordinates is the **core intellectual property** that drives high-value deployments in drone defense ecosystems.

2.2 Time Delay (τ) and Doppler Shift (f_d)

2.2.1 Bistatic Time Delay (τ)

In a bistatic radar system, the received echo travels from the **Illuminator of Opportunity (IoO)** to the target and then to the receiver. This must be measured relative to the **direct path** signal from the transmitter to the receiver.

Total Propagation Time

$$t_{echo} = \frac{R_{tx} + R_{rx}}{c} \tag{2.11}$$

$$t_{direct} = \frac{L}{c} \tag{2.12}$$

Bistatic Time Delay Definition

$$\tau = t_{echo} - t_{direct} = \frac{(R_{tx} + R_{rx}) - L}{c} \tag{2.13}$$

Bistatic Range

$$\boxed{R_b = (R_{tx} + R_{rx}) - L} \tag{2.14}$$

Thus:

$$\tau = \frac{R_b}{c} \tag{2.15}$$

Geometric Interpretation:

- Constant τ defines an **ellipsoid** with Tx and Rx as foci
- Targets with identical τ lie on the same bistatic range contour

2.2.2 Bistatic Doppler Shift (f_d)

Unlike monostatic radar, bistatic Doppler depends on motion relative to both transmitter and receiver.

Vector Formulation

Let:

- $\vec{v}$: target velocity vector
- $\hat{\mathbf{u}}_{tx}$: unit vector from target toward transmitter
- $\hat{\mathbf{u}}_{rx}$: unit vector from target toward receiver

The Doppler shift is:

$$\boxed{f_d = \frac{1}{\lambda}\left[\vec{v} \cdot (\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx})\right]} \tag{2.16}$$

Derivation Insight

Each propagation leg contributes a Doppler component:

$$f_{tx} = \frac{1}{\lambda}(\vec{v} \cdot \hat{\mathbf{u}}_{tx}) \tag{2.17}$$

$$f_{rx} = \frac{1}{\lambda}(\vec{v} \cdot \hat{\mathbf{u}}_{rx}) \tag{2.18}$$

Thus:

$$f_d = f_{tx} + f_{rx} \tag{2.19}$$

Key Insight:

- Doppler is maximized when motion aligns with $(\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx})$
- Zero Doppler occurs when velocity is orthogonal to this vector

2.2.3 Physical Implications: The Bistatic Bisector

The **bistatic bisector** is the direction that bisects the angle between:

- Tx-to-target vector
- Rx-to-target vector

$$\hat{\mathbf{b}} = \frac{\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx}}{\|\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx}\|} \tag{2.20}$$

Critical Property:

- Maximum Doppler shift occurs when $\vec{v} \parallel \hat{\mathbf{b}}$
- This defines the most detectable motion direction

Engineering Insight (2026):

- Drone trajectories aligned with the bistatic bisector produce strong Doppler signatures
- Enables enhanced detection in forward-scatter geometries

2.2.4 Embedded Implementation (C++)

```
#include <cmath>
#include <array>

constexpr double c = 3e8; // Speed of light

struct Result {
    double tau_samples;
    double doppler_hz;
};

Result compute_tau_fd(double x, double y, double z,
                      double vx, double vy, double vz,
                      double L,
                      double lambda,
                      double Fs)
{
    // Receiver at (0,0,0), transmitter at (L,0,0)

    // Distances
    double R_rx = sqrt(x*x + y*y + z*z);
    double R_tx = sqrt((x - L)*(x - L) + y*y + z*z);

    // Bistatic range
    double Rb = (R_tx + R_rx) - L;

    // Time delay
    double tau = Rb / c;

    // Convert to samples
    double tau_samples = tau * Fs;

    // Unit vectors
    double u_rx_x = x / R_rx;
    double u_rx_y = y / R_rx;
    double u_rx_z = z / R_rx;
```

```
    double u_tx_x = (x - L) / R_tx;
    double u_tx_y = y / R_tx;
    double u_tx_z = z / R_tx;

    // Velocity vector
    double v_dot =
        vx * (u_rx_x + u_tx_x) +
        vy * (u_rx_y + u_tx_y) +
        vz * (u_rx_z + u_tx_z);

    // Doppler shift
    double f_d = v_dot / lambda;

    return {tau_samples, f_d};
}
```

Implementation Notes:

- τ is computed in **samples** for direct use in CAF indexing
- f_d is computed in Hz for Doppler bin mapping
- Suitable for real-time execution on embedded SDR platforms

2.2.5 2026 Commercial Value: Micro-Doppler Signature Extraction

High-resolution Doppler analysis enables extraction of **micro-Doppler signatures**:

- Rotor blade modulation (multi-rotor drones)
- Payload-induced vibration patterns
- Wing flapping (bird discrimination)

Key Capability:

$$\text{Doppler Spectrum} \Rightarrow \text{Target Identity} \tag{2.21}$$

Business Applications:

- Distinguish drones from birds (false alarm reduction)
- Identify drone type (e.g., quadcopter vs hexacopter)
- Detect payload anomalies (security threat classification)

Monetization Strategy:

- Sell as a **Drone Classification API**
- Integrate into C-UAS platforms as a premium feature

- Provide forensic analysis tools for security agencies

Strategic Insight: In 2026, τ and f_d are not just measurements—they form a **high-dimensional feature space** enabling intelligent, AI-driven radar systems that generate actionable and monetizable insights.

2.3 Iso-Range and Iso-Doppler Contours

2.3.1 Iso-Range Geometry (Isochrones)

Bistatic Range Constraint

From Section 2.2, the bistatic range is:

$$R_b = (R_{tx} + R_{rx}) - L \tag{2.22}$$

For a constant delay τ, we have:

$$R_{tx} + R_{rx} = \text{constant} = D \tag{2.23}$$

Derivation in Cartesian Coordinates

Using the coordinate system:

- Receiver at $(0, 0)$
- Transmitter at $(L, 0)$
- Target at (x, y)

$$R_{rx} = \sqrt{x^2 + y^2} \tag{2.24}$$

$$R_{tx} = \sqrt{(x - L)^2 + y^2} \tag{2.25}$$

Thus, the iso-range contour satisfies:

$$\sqrt{x^2 + y^2} + \sqrt{(x - L)^2 + y^2} = D \tag{2.26}$$

Cassini Oval Interpretation

While the above resembles an ellipse (sum of distances constant), in **bistatic detection** the received power depends on:

$$P_r \propto \frac{1}{R_{tx}^2 R_{rx}^2} \tag{2.27}$$

Thus, contours of **constant received power** satisfy:

$$R_{tx} \cdot R_{rx} = \text{constant} \tag{2.28}$$

This is the defining equation of a **Cassini Oval**.
Proof Sketch:

- Squaring both distances and multiplying yields a quartic curve
- The locus of points where the product of distances to two foci is constant forms a Cassini oval

Key Insight:

- Iso-delay contours $\rightarrow$ ellipses
- Iso-power contours $\rightarrow$ Cassini ovals
- Practical radar detection follows Cassini geometry

2.3.2 Iso-Doppler Formulation

Doppler Constraint

From Section 2.2:

$$f_d = \frac{1}{\lambda} \left[\vec{v} \cdot (\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx}) \right] \tag{2.29}$$

For constant f_d, we require:

$$\vec{v} \cdot (\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx}) = \text{constant} \tag{2.30}$$

Geometric Interpretation

Assuming constant velocity magnitude and direction, iso-Doppler contours are:

- **Hyperbolic-like curves** in the bistatic plane
- Defined by constant projection of velocity onto the bistatic bisector

Dependence on Bistatic Angle

$$f_d \propto |\vec{v}| \cos\left(\frac{\beta}{2} - \theta_v\right) \tag{2.31}$$

where θ_v is the angle between velocity vector and bistatic bisector.
Key Insight:

- Maximum Doppler occurs along the bistatic bisector
- Iso-Doppler contours are orthogonal to iso-range contours

2.3.3 Range-Doppler to Cartesian Mapping

Inverse Problem

Given:

- Time delay $\tau \Rightarrow R_b$
- Doppler shift f_d

We seek (x, y) such that:

$$R_{tx} + R_{rx} = D \tag{2.32}$$
$$\vec{v} \cdot (\hat{\mathbf{u}}_{rx} + \hat{\mathbf{u}}_{tx}) = \lambda f_d \tag{2.33}$$

Bistatic Ambiguity

The iso-range ellipse intersects iso-Doppler contour at **two symmetric points**.

Ambiguity:

- Two possible target locations produce identical (τ, f_d)

Resolution Strategies

- Use Angle of Arrival (AoA)
- Track continuity over time
- Use multi-static receivers

Engineering Insight: Ambiguity resolution is a **software problem**, not a hardware limitation.

2.3.4 Embedded Implementation: LUT Mapping

```
#include <vector>
#include <cmath>

struct GridCell {
    float x;
    float y;
};

constexpr int RANGE_BINS = 512;
constexpr int DOPPLER_BINS = 256;

// Precomputed LUT
std::vector<std::vector<GridCell>> LUT(RANGE_BINS,
```

```
                                        std::vector<GridCell>(
                                            DOPPLER_BINS));

void precompute_LUT(double L, double lambda)
{
    for (int r = 0; r < RANGE_BINS; ++r) {
        for (int d = 0; d < DOPPLER_BINS; ++d) {

            // Convert bins to physical values
            double Rb = r * 1.0;        // range resolution
            double fd = (d - DOPPLER_BINS/2) * 1.0;

            // Solve approximate position (simplified)
            double x = Rb / 2.0;
            double y = sqrt(std::max(0.0, Rb*Rb - x*x));

            LUT[r][d] = {float(x), float(y)};
        }
    }
}
```

Optimization for NVIDIA Jetson AGX Orin:

- Precompute LUT offline
- Store in GPU memory
- Use parallel lookup during real-time processing

2.3.5 Visual Description

Figure: Iso-Range and Iso-Doppler Intersection

The figure shows:

- Cassini ovals (iso-power contours)
- Elliptical iso-range contours
- Hyperbolic iso-Doppler curves
- Intersection point indicating target location

Visual Insight:

- Localization occurs at contour intersections
- Multiple intersections highlight ambiguity
- Geometry defines detection precision

2.3.6 2026 Commercial Insight: Precision Geofencing

Iso-range and iso-Doppler contours enable:

$$\textbf{Detection} \rightarrow \textbf{Localization} \rightarrow \textbf{Control} \tag{2.34}$$

Precision Geofencing:

- Define virtual boundaries in physical space
- Detect and track drones entering restricted zones
- Trigger automated alerts or countermeasures

Business Model:

- Sell "No-Drone Zone" enforcement as SaaS
- Offer tiered coverage guarantees
- Provide real-time spatial analytics dashboards

Strategic Insight: In 2026, the ability to map (τ, f_d) into precise spatial coordinates transforms radar from a sensing tool into a **security platform**, enabling scalable and high-margin services.

2.4 Multipath Propagation in Urban Environments

2.4.1 Urban Channel Modeling

In dense urban environments, the received signal is a superposition of multiple delayed, attenuated, and phase-shifted replicas of the transmitted waveform.

Multipath Channel Impulse Response

The received signal in a passive radar system is modeled as:

$$s_{rx}(t) = \sum_{i=0}^{N-1} a_i \, s(t - \tau_i) \, e^{j\phi_i} \tag{2.35}$$

where:

- a_i: amplitude attenuation of the ith path
- τ_i: propagation delay of the ith path
- ϕ_i: phase shift due to reflection and propagation
- N: number of multipath components

Passive Radar Specificity

In passive radar:

- The **reference channel** captures the direct signal $s_{ref}(t)$
- The **surveillance channel** contains:
  - Direct leakage
  - Target reflections
  - Multipath reflections from static structures

Key Challenge: Multipath affects the surveillance channel disproportionately, creating ambiguity in detection.

2.4.2 The "Ghost Target" Phenomenon

CAF Formation

The Cross-Ambiguity Function (CAF) is:

$$\chi(\tau, f_d) = \int s_{ref}(t)\, s_{rx}^*(t-\tau)\, e^{-j2\pi f_d t} dt \tag{2.36}$$

Substituting the multipath model:

$$\chi(\tau, f_d) = \sum_{i=0}^{N-1} a_i \int s(t) s^*(t-\tau-\tau_i) e^{-j2\pi f_d t} dt \tag{2.37}$$

Ghost Peaks

Each multipath component produces a peak at:

$$\tau = \tau_i, \quad f_d \approx 0 \tag{2.38}$$

Interpretation:

- Static reflectors (buildings) produce **zero-Doppler peaks**
- These appear as false targets ("ghosts") in the CAF

Difference from True Targets

- **Ghost Targets:**
  - $f_d \approx 0$
  - Stable over time
  - Fixed spatial location
- **Real Targets (e.g., drones):**

  - $f_d \neq 0$
  - Time-varying τ
  - Exhibit micro-Doppler signatures

2.4.3 Fading and Coherence

Rayleigh Fading

Occurs when no dominant line-of-sight (LOS) component exists:

$$p(r) = \frac{r}{\sigma^2} e^{-r^2/(2\sigma^2)} \tag{2.39}$$

Implication:

- Severe amplitude fluctuations
- Common in dense urban canyons

Rician Fading

Occurs when a strong LOS component is present:

$$p(r) = \frac{r}{\sigma^2} e^{-\frac{r^2+s^2}{2\sigma^2}} I_0\left(\frac{rs}{\sigma^2}\right) \tag{2.40}$$

where s represents the LOS component.

2026 Context (5G NR):

- 3.5 GHz: mixed Rayleigh/Rician conditions
- mmWave (26 GHz): highly sensitive to blockage, rapid fading

Coherence Time

$$T_c \approx \frac{1}{f_d} \tag{2.41}$$

Insight:

- Fast-moving drones reduce coherence time
- Requires rapid CAF updates for accurate tracking

2.4.4 Embedded Mitigation Strategy

Static Clutter Suppression

A basic strategy is to suppress zero-Doppler components.

```
#include <vector>
#include <cmath>

void clutter_filter(std::vector<std::vector<float>>& CAF,
                    int doppler_bins)
{
    int zero_bin = doppler_bins / 2;

    for (size_t r = 0; r < CAF.size(); ++r) {
        for (int d = zero_bin - 2; d <= zero_bin + 2; ++d) {
            CAF[r][d] = 0.0f; // Remove static clutter
        }
    }
}
```

Guard Interval Check

- Reject detections with:
  - Near-zero Doppler
  - Constant delay over time

Advanced Methods:

- CLEAN algorithm for multipath subtraction
- Adaptive filtering (e.g., STAP)

2.4.5 Visual Representation

Figure: Urban Multipath Geometry

The figure illustrates:

- A 5G base station (Illuminator of Opportunity)
- A high-rise building acting as a reflector
- A drone target in motion
- Multiple propagation paths:
  - Direct path (Tx $\rightarrow$ Rx)
  - Target reflection (Tx $\rightarrow$ Target $\rightarrow$ Rx)

  - Building reflection (Tx $\rightarrow$ Building $\rightarrow$ Rx)

Visual Insight:

- Multipath creates additional delay paths
- Ghost targets appear at incorrect positions
- Geometry complexity increases in dense cities

2.4.6 2026 Commercial Value: Urban Clutter Resilience

Core Differentiator:

$$\text{Clutter Resilience} \Rightarrow \text{Detection Reliability} \tag{2.42}$$

Why It Matters:

- Urban environments are the hardest operational domain
- High false alarm rates reduce system credibility
- Reliable detection enables real-world deployment

Business Impact:

- Systems with strong multipath mitigation command premium pricing
- Enables deployment in smart cities and critical infrastructure
- Supports contracts with governments and private security firms

Strategic Insight: In 2026, the ability to distinguish real drone targets from urban multipath artifacts transforms passive radar into a **trusted operational system**, unlocking scalable commercial adoption.

2.5 Non-Line-of-Sight (NLoS) Effects in UAM Scenarios

2.5.1 Channel Modeling: Rician to Rayleigh Transition

In Urban Air Mobility (UAM) environments, signal propagation transitions between Line-of-Sight (LoS) and Non-Line-of-Sight (NLoS) conditions.

Rician Fading Model

When a dominant LoS component exists, the received signal envelope follows a Rician distribution:

$$p(r) = \frac{r}{\sigma^2} \exp\left(-\frac{r^2 + s^2}{2\sigma^2}\right) I_0\left(\frac{rs}{\sigma^2}\right) \tag{2.43}$$

The **Rician K-factor** is defined as:

$$K = \frac{s^2}{2\sigma^2} \tag{2.44}$$

where:

- s^2: power in the deterministic LoS component
- $2\sigma^2$: power in scattered components

Rayleigh Fading Limit

In dense urban canyons:

$$s \to 0 \quad \Rightarrow \quad K \to 0 \tag{2.45}$$

Thus, the distribution reduces to Rayleigh:

$$p(r) = \frac{r}{\sigma^2} e^{-r^2/(2\sigma^2)} \tag{2.46}$$

Engineering Insight:

- High-rise environments suppress LoS paths
- Multipath dominates, degrading signal stability
- K-factor becomes a key environmental indicator

2.5.2 Diffraction and Reflection Physics

Huygens-Fresnel Principle

Every point on a wavefront acts as a secondary source of spherical waves:

$$U(P) = \iint_S U(Q) \frac{e^{-jkR}}{R} dS \tag{2.47}$$

Implication:

- Signals can propagate around obstacles
- Enables partial illumination of shadowed regions

Uniform Theory of Diffraction (UTD)

UTD models diffraction around edges:

$$E_d = E_i D(\theta_i, \theta_d) \frac{e^{-jkR}}{\sqrt{R}} \tag{2.48}$$

where:

- $D(\theta_i, \theta_d)$: diffraction coefficient
- θ_i, θ_d: incident and diffracted angles

Key Insight:

- Signals "creep" around skyscrapers via edge diffraction
- Enables NLoS detection of drones behind buildings
- However, introduces additional delay and phase distortion

2.5.3 Bistatic Doppler Shift in NLoS

Reflected Path Geometry

In NLoS conditions, the signal path includes reflections:

$$\vec{u}_{rx}^{(eff)} \neq \vec{u}_{rx} \tag{2.49}$$

Thus, the Doppler shift becomes:

$$f_d^{(NLoS)} = \frac{1}{\lambda} \left[\vec{v} \cdot (\hat{\mathbf{u}}_{tx} + \hat{\mathbf{u}}_{rx}^{(eff)}) \right] \tag{2.50}$$

Velocity Estimation Error

The error is:

$$\Delta f_d = \frac{1}{\lambda} \vec{v} \cdot (\hat{\mathbf{u}}_{rx}^{(eff)} - \hat{\mathbf{u}}_{rx}) \tag{2.51}$$

$$\Rightarrow \Delta v \propto \Delta f_d \tag{2.52}$$

Interpretation:

- Reflections distort the perceived direction of motion
- Leads to incorrect velocity estimation
- Critical issue for tracking algorithms

2.5.4 Embedded Implementation: Tapped Delay Line (TDL)

```
#include <vector>
#include <complex>
#include <cmath>

struct Tap {
    double delay;       // seconds
    double amplitude;
    double phase;       // radians
};

class TDLChannel {
public:
    std::vector<Tap> taps;

    std::complex<double> process(double t,
                                 double (*signal)(double))
    {
        std::complex<double> output = 0.0;

        for (const auto& tap : taps) {
            double delayed = signal(t - tap.delay);
            std::complex<double> coeff =
                tap.amplitude *
                std::exp(std::complex<double>(0, tap.phase));

            output += coeff * delayed;
        }

        return output;
    }
};
```

Usage:

- Simulates clustered multipath components
- Models urban canyon propagation
- Enables testing of NLoS tracking algorithms

2.5.5 Visual Representation

Figure: Multipath Shadowing in Urban Environment

The figure illustrates:

- A transmitter (5G tower) and receiver separated by baseline L

- A high-rise building blocking the direct bistatic path
- A drone located in the shadow region
- Signal propagation paths:
  - Diffracted path around building edge
  - Reflected path from adjacent structures

Visual Insight:

- Direct path is obstructed (NLoS)
- Detection relies on indirect propagation
- Increased delay and Doppler distortion are evident

2.5.6 2026 Commercial Value: NLoS-Aware Tracking

Core Capability:

$$\text{NLoS Awareness} \Rightarrow \text{Reliable Tracking in Urban Environments} \tag{2.53}$$

Why It Matters:

- UAM operations occur in dense, cluttered cities
- Traditional LoS-based systems fail in shadowed regions
- Accurate tracking requires modeling NLoS propagation

Monetization Strategy:

- Sell **NLoS-aware tracking algorithms** to:
  - Insurance companies (risk assessment)
  - Drone delivery operators
  - Smart city infrastructure providers
- Provide analytics on:
  - Coverage reliability
  - Tracking accuracy in high-clutter zones

Strategic Insight: In 2026, the ability to maintain accurate tracking under NLoS conditions is a **premium feature**, enabling risk-aware deployment of autonomous drone systems and unlocking high-value commercial partnerships.

Chapter 3

Illuminators of Opportunity in 2026

3.1 DVB-T2 Waveform Structure and Properties

3.1.1 Mathematical Signal Model

DVB-T2 employs **Orthogonal Frequency Division Multiplexing (OFDM)**, where data is transmitted over N orthogonal subcarriers.

OFDM Symbol Construction

Let:

- N: number of subcarriers
- X_k: complex data symbol on subcarrier k
- $\Delta f = \frac{1}{T_u}$: subcarrier spacing
- T_u: useful symbol duration

The baseband OFDM signal is:

$$s(t) = \sum_{k=0}^{N-1} X_k e^{j2\pi k \Delta f t}, \quad 0 \leq t < T_u \tag{3.1}$$

Including Guard Interval (GI)

To combat multipath, a cyclic prefix (guard interval) of duration T_g is added:

$$s_{GI}(t) = \begin{cases} s(t + T_u), & -T_g \leq t < 0 \\ s(t), & 0 \leq t < T_u \end{cases} \tag{3.2}$$

Total symbol duration:

$$T_s = T_u + T_g \tag{3.3}$$

Key Insight:

- OFDM converts a frequency-selective channel into parallel flat channels
- The GI preserves orthogonality under multipath conditions

3.1.2 Radar-Specific Parameters: Pilot Structures

DVB-T2 includes structured pilot tones critical for passive radar.

Continual Pilots (CP)

- Fixed subcarriers present in every OFDM symbol
- Used for frequency synchronization and phase tracking

Scattered Pilots (SP)

- Distributed across time-frequency grid
- Provide dense channel sampling

Channel Estimation

Let Y_k be the received symbol and X_k the known pilot:

$$H_k = \frac{Y_k}{X_k} \tag{3.4}$$

The channel impulse response is obtained via inverse FFT:

$$h(n) = \text{IFFT}\{H_k\} \tag{3.5}$$

Radar Insight:

- Pilots act as **known probing signals**
- Enable precise synchronization and channel reconstruction
- Critical for Cross-Ambiguity Function (CAF) computation

3.1.3 Ambiguity Function Analysis

Self-Ambiguity Function

The ambiguity function is:

$$\chi(\tau, f_d) = \int s(t)s^*(t-\tau)e^{-j2\pi f_d t}dt \tag{3.6}$$

Substituting OFDM structure:

$$\chi(\tau, f_d) = \sum_{k=0}^{N-1} |X_k|^2 \int e^{j2\pi k\Delta f\tau} e^{-j2\pi f_d t}dt \tag{3.7}$$

Thumbtack Shape

- Narrow peak at $(\tau, f_d) = (0, 0)$
- Low sidelobes due to multi-carrier structure

Interpretation:

- High resolution in both range and Doppler
- Ideal for passive radar detection

Impact of Guard Interval

- GI introduces periodicity in time domain
- Limits unambiguous range:

$$R_{max} = \frac{cT_g}{2} \tag{3.8}$$

- Excess delay beyond GI causes inter-symbol interference

3.1.4 Embedded C++ Implementation: OFDM Frame Synchronizer

```
#include <vector>
#include <complex>
#include <cmath>

class OFDMSynchronizer {
public:
    int N; // FFT size
    int GI;
    double threshold;

    OFDMSynchronizer(int fft_size, int gi)
        : N(fft_size), GI(gi), threshold(0.8) {}

    // Estimate symbol start using cyclic prefix correlation
    int detect_symbol_start(const std::vector<std::complex<double>>&
        signal)
    {
        int best_index = 0;
        double max_corr = 0.0;

        for (int i = 0; i < signal.size() - N - GI; ++i) {
            std::complex<double> corr = 0.0;

            for (int j = 0; j < GI; ++j) {
                corr += signal[i + j] *
```

```
                        std::conj(signal[i + j + N]);
            }

            double mag = std::abs(corr);

            if (mag > max_corr) {
                max_corr = mag;
                best_index = i;
            }
        }

        return best_index;
    }

    // FFT stub (replace with optimized library like FFTW)
    void fft(std::vector<std::complex<double>>& data)
    {
        // Placeholder for high-performance FFT
    }

    // Extract pilot carriers
    std::vector<std::complex<double>>
    extract_pilots(const std::vector<std::complex<double>>&
       freq_data,
                   const std::vector<int>& pilot_indices)
    {
        std::vector<std::complex<double>> pilots;

        for (int idx : pilot_indices) {
            pilots.push_back(freq_data[idx]);
        }

        return pilots;
    }
};
```

Optimization Notes:

- Replace FFT stub with FFTW or cuFFT (GPU)
- Parallelize pilot extraction on Jetson AGX Orin
- Use fixed-point arithmetic for power efficiency

3.1.5 Visual Representation

Figure: DVB-T2 Time-Frequency Grid

The figure illustrates:

- Time axis: OFDM symbols
- Frequency axis: subcarriers
- Continual pilots (fixed positions)
- Scattered pilots (diagonal pattern)
- Guard Interval preceding each symbol

Visual Insight:

- Pilot density enables robust channel estimation
- GI separates symbols and mitigates multipath
- Structured grid enables synchronization and detection

3.1.6 2026 Commercial Value: Broadcast-Based Covert Surveillance

Core Advantage:

$$\text{No Transmission} \Rightarrow \text{Low Probability of Intercept (LPI)} \tag{3.9}$$

Why DVB-T2 is Ideal:

- High-power broadcast signals already exist
- Wide coverage without infrastructure cost
- No additional RF emissions

Applications:

- Border surveillance
- Coastal monitoring
- Critical infrastructure protection

Monetization Strategy:

- Offer **covert passive radar systems** to governments
- Provide subscription-based monitoring services
- Integrate with national security platforms

Strategic Insight: In 2026, leveraging DVB-T2 as an illuminator transforms existing broadcast infrastructure into a **nationwide sensing network**, enabling scalable, low-cost, and covert surveillance solutions.

3.2 5G NR as an Opportunistic Radar Source

3.2.1 Waveform Mathematical Model

5G NR employs CP-OFDM with flexible numerology. Let:

- N: number of subcarriers
- $\Delta f = 2^{\mu} \cdot 15$ kHz: subcarrier spacing
- $T_u = \frac{1}{\Delta f}$: useful symbol duration
- T_{cp}: cyclic prefix duration
- $X_{k,l}$: symbol on subcarrier k and OFDM symbol l

Time-Domain Signal

The transmitted baseband signal is:

$$s(t) = \sum_{l} \sum_{k=0}^{N-1} X_{k,l} e^{j2\pi k\Delta f(t-lT_s)} \, \Pi\left(\frac{t - lT_s}{T_s}\right) \tag{3.10}$$

where:

$$T_s = T_u + T_{cp} \tag{3.11}$$

Including Cyclic Prefix

For each symbol:

$$s_l(t) = \begin{cases} s_l(t + T_u), & -T_{cp} \leq t < 0 \\ \sum_{k=0}^{N-1} X_{k,l} e^{j2\pi k\Delta f t}, & 0 \leq t < T_u \end{cases} \tag{3.12}$$

Engineering Insight:

- High bandwidth (FR2 up to 400 MHz) $\Rightarrow$ fine range resolution
- Short symbols $\Rightarrow$ improved Doppler tolerance

3.2.2 Pilot Signal Exploitation: PSS/SSS

Primary Synchronization Signal (PSS)

PSS is based on Zadoff-Chu (ZC) sequences:

$$d(n) = e^{-j\frac{\pi u n(n+1)}{N_{zc}}}, \quad 0 \leq n < N_{zc} \tag{3.13}$$

Key Property (CAZAC):

$$\left| \sum_{n} d(n) d^*(n - \tau) \right| = \begin{cases} N_{zc}, & \tau = 0 \\ 0, & \tau \neq 0 \end{cases} \tag{3.14}$$

Secondary Synchronization Signal (SSS)

- Provides cell identity
- Enables frame timing recovery

Bistatic Synchronization

Let $r(t)$ be received signal:

$$\tau_{est} = \arg\max_{\tau} \left| \int r(t) d^*(t-\tau) dt \right| \tag{3.15}$$

Radar Insight:

- ZC sequences provide near-ideal correlation peaks
- Enables precise delay estimation for bistatic range
- Robust to multipath interference

3.2.3 Ambiguity Function Analysis

Self-Ambiguity Function

$$\chi(\tau, f_d) = \int s(t) s^*(t-\tau) e^{-j2\pi f_d t} dt \tag{3.16}$$

Substituting OFDM structure:

$$\chi(\tau, f_d) \approx \sum_l \sum_k |X_{k,l}|^2 e^{j2\pi k \Delta f \tau} \cdot \mathrm{sinc}(f_d T_s) \tag{3.17}$$

Thumbtack Characteristics

- Sharp peak in delay due to wide bandwidth
- Narrow Doppler mainlobe due to symbol duration

Impact of Silent Periods

5G frames include control gaps and inactive slots:

- Introduce discontinuities in $s(t)$
- Result in elevated sidelobes in Doppler domain
- Increase noise floor in range-Doppler map

Engineering Trade-off:

- High resolution vs. spectral fragmentation

3.2.4 Embedded Implementation: NR_FrameExtractor

```
#include <vector>
#include <complex>
#include <arm_neon.h>

class NR_FrameExtractor {
public:
    int window_size;
    std::vector<std::complex<float>> pss_ref;

    NR_FrameExtractor(int w,
        const std::vector<std::complex<float>>& ref)
        : window_size(w), pss_ref(ref) {}

    // Sliding-window cross-correlation using SIMD
    int detect_frame_start(
        const std::vector<std::complex<float>>& iq)
    {
        int best_idx = 0;
        float max_corr = 0.0f;

        for (int i = 0; i < iq.size() - window_size; ++i) {

            float32x4_t acc_real = vdupq_n_f32(0.0f);
            float32x4_t acc_imag = vdupq_n_f32(0.0f);

            for (int j = 0; j < window_size; j += 4) {

                float32x4x2_t sig =
                    vld2q_f32((float*)&iq[i + j]);
                float32x4x2_t ref =
                    vld2q_f32((float*)&pss_ref[j]);

                // Complex multiply: sig * conj(ref)
                float32x4_t real =
                    vmlaq_f32(
                        vmulq_f32(sig.val[0], ref.val[0]),
                        sig.val[1], ref.val[1]);

                float32x4_t imag =
                    vsubq_f32(
                        vmulq_f32(sig.val[1], ref.val[0]),
                        vmulq_f32(sig.val[0], ref.val[1]));

                acc_real = vaddq_f32(acc_real, real);
                acc_imag = vaddq_f32(acc_imag, imag);
            }
```

```
            float corr =
                vgetq_lane_f32(acc_real,0) +
                vgetq_lane_f32(acc_real,1) +
                vgetq_lane_f32(acc_real,2) +
                vgetq_lane_f32(acc_real,3);

            if (corr > max_corr) {
                max_corr = corr;
                best_idx = i;
            }
        }

        return best_idx;
    }
};
```

Optimization Features:

- ARM NEON SIMD for parallel correlation
- Memory-aligned vector loads
- Suitable for edge devices (e.g., SDR platforms)

3.2.5 Visual Representation

Figure: 5G NR Resource Grid

The figure illustrates:

- Time axis: slots and OFDM symbols
- Frequency axis: subcarriers
- Highlighted signals:
  - PSS/SSS (synchronization block)
  - DMRS (Demodulation Reference Signals)
  - CSI-RS (Channel State Information RS)

Visual Insight:

- Dense pilot structure enables fine channel estimation
- Synchronization blocks act as radar beacons

3.2.6 2026 Commercial Value: 5G-Radar-as-a-Service

Core Concept:

$$\text{5G Infrastructure} + \text{Passive Radar} = \text{Covert Sensing Platform} \tag{3.18}$$

Use Case:

- Protect critical infrastructure (e.g., financial institutions)
- Monitor airspace for unauthorized drones

Monetization Strategy:

- Subscription-based **5G-Radar-as-a-Service**
- API access to:
  - Real-time tracking data
  - Threat alerts
  - Historical analytics

Deployment Advantage:

- No additional spectrum required
- Leverages existing telecom infrastructure
- Low-cost, scalable, and covert

Strategic Insight: In 2026, financial institutions such as **Bank of Kigali** can deploy passive radar layers on top of 5G networks, achieving **continuous, covert airspace surveillance** without investing in dedicated radar transmitters.

3.3 Emerging 6G Waveforms for Passive Sensing

3.3.1 Waveform Theory: OTFS Modulation

Orthogonal Time Frequency Space (OTFS) modulation operates in the **Delay-Doppler domain**, offering robustness in high-mobility environments.

Delay-Doppler Representation

Let $X[k, l]$ represent symbols in the delay-Doppler grid:

- k: delay index
- l: Doppler index

Inverse Symplectic Finite Fourier Transform (ISFFT)

The ISFFT maps Delay-Doppler symbols to the Time-Frequency domain:

$$X[n,m] = \frac{1}{\sqrt{NM}} \sum_{k=0}^{N-1} \sum_{l=0}^{M-1} X[k,l] e^{j2\pi\left(\frac{nk}{N} - \frac{ml}{M}\right)} \tag{3.19}$$

Heisenberg Transform to Time Domain

$$s(t) = \sum_{n,m} X[n,m] g(t - nT) e^{j2\pi m \Delta f (t - nT)} \tag{3.20}$$

Key Insight:

- Delay-Doppler domain directly represents physical channel parameters
- Converts time-varying multipath into a nearly static 2D representation
- Ideal for tracking high-speed drones in urban air mobility (UAM)

Radar Advantage:

- Each symbol experiences full channel diversity
- Robust against Doppler spread
- Enables high-resolution sensing without ambiguity smearing

3.3.2 Spectrum Analysis: Sub-THz Propagation

Table 3.1: Propagation Characteristics: 6G vs 5G

Parameter	6G (140 GHz)	5G (3.5 GHz)
Wavelength λ	≈ 2.14 mm	≈ 85.7 mm
Bandwidth	> 10 GHz	≤ 100 MHz
Path Loss	Very High	Moderate
Atmospheric Absorption	Significant (O_2, H_2O)	Minimal
Penetration	Poor	Good
Spatial Resolution	Ultra-high	Moderate

Atmospheric Window

- Sub-THz bands have selective transmission windows
- Strong attenuation limits range but enhances spatial confinement

Impact on Radar Cross Section (σ)

$$\sigma \propto \frac{A^2}{\lambda^2} \tag{3.21}$$

Implication:

- Smaller wavelength $\Rightarrow$ higher sensitivity to small structures
- Carbon-fiber drone frames become more detectable due to surface roughness at mm-scale

3.3.3 JCAS Architecture: Joint Communication and Sensing

Concept:

$$\text{JCAS} = \text{Communication} + \text{Radar Sensing} \tag{3.22}$$

Architecture Components:

- 6G Base Station (gNB):
  - Transmits OTFS waveforms
  - Acts as illuminator of opportunity
- Passive Receiver:
  - Extracts sensing information
  - Performs Delay-Doppler processing

Key Advantage:

- No separation between communication and radar signals
- Unified waveform enables simultaneous data + sensing

Radar-as-a-Service:

- Infrastructure provides continuous sensing coverage
- APIs expose tracking and detection capabilities

3.3.4 Embedded C++ Implementation: SFFT

```
#include <vector>
#include <complex>
#include <arm_neon.h>

void SFFT(const std::vector<std::complex<float>>& in,
          std::vector<std::complex<float>>& out,
          int N, int M)
```

```
{
    for (int n = 0; n < N; ++n) {
        for (int m = 0; m < M; ++m) {

            float32x4_t acc_real = vdupq_n_f32(0.0f);
            float32x4_t acc_imag = vdupq_n_f32(0.0f);

            for (int k = 0; k < N; k += 4) {
                for (int l = 0; l < M; l += 4) {

                    // Load input blocks (vectorized)
                    float32x4x2_t data =
                        vld2q_f32((float*)&in[k*M + l]);

                    // Compute phase term
                    float phase = 2.0f * M_PI *
                        ((float)(n*k)/N - (float)(m*l)/M);

                    float32x4_t cosv =
                        vdupq_n_f32(cosf(phase));
                    float32x4_t sinv =
                        vdupq_n_f32(sinf(phase));

                    // Complex multiply
                    float32x4_t real =
                        vmlsq_f32(
                            vmulq_f32(data.val[0], cosv),
                            data.val[1], sinv);

                    float32x4_t imag =
                        vmlaq_f32(
                            vmulq_f32(data.val[0], sinv),
                            data.val[1], cosv);

                    acc_real = vaddq_f32(acc_real, real);
                    acc_imag = vaddq_f32(acc_imag, imag);
                }
            }

            // Store result (simplified reduction)
            out[n*M + m] =
                std::complex<float>(
                    vgetq_lane_f32(acc_real,0),
                    vgetq_lane_f32(acc_imag,0));
        }
    }
}
```

Optimization Notes:

- SIMD vectorization using ARM NEON
- Loop tiling for cache efficiency
- Suitable for NVIDIA Jetson AGX Orin edge deployment

3.3.5 Visual Representation

Figure: OTFS vs OFDM Grid

The figure illustrates:

- Left: Standard OFDM grid (Time vs Frequency)
  - Symbols localized in time-frequency bins
  - Sensitive to Doppler spread
- Right: OTFS grid (Delay vs Doppler)
  - Symbols spread across entire grid
  - Each symbol experiences full channel diversity

Visual Insight:

- OTFS concentrates energy in Delay-Doppler peaks
- Provides superior resolution for moving targets

3.3.6 2026 Commercial Strategy: 6G Sensing IP

Core Idea:

$$\text{6G Signals} \Rightarrow \text{Embedded Radar Data} \tag{3.23}$$

Startup Opportunity:

- Develop algorithms to:
  - Extract Delay-Doppler signatures
  - Separate communication payload from sensing data
  - Perform target detection and tracking

Monetization Model:

- License **6G sensing IP** to:
  - Private security firms
  - Smart city operators

  - Defense contractors

- Provide SDKs for integration into edge devices

Key Value Proposition:

- No additional hardware required
- Leverages existing 6G infrastructure
- High-margin software-based revenue

Strategic Insight: In 2026 and beyond, the companies that control **signal interpretation (IP)**—not infrastructure—will dominate the passive sensing market, making 6G sensing algorithms a high-value, defensible asset.

3.4 OFDM Signal Properties for Radar Processing

3.4.1 Mathematical Structure of 5G NR OFDM

Transmitted Signal Model

The 5G NR OFDM signal is constructed as a superposition of N orthogonal subcarriers:

$$s(t) = \sum_{k=0}^{N-1} d_k e^{j2\pi(f_c + k\Delta f)t}, \quad 0 \leq t < T_u \tag{3.24}$$

where:

- d_k: complex data symbol on subcarrier k
- f_c: carrier frequency
- Δf: subcarrier spacing
- $T_u = \frac{1}{\Delta f}$: useful symbol duration

Inclusion of Cyclic Prefix (CP)

To mitigate multipath effects, a cyclic prefix of duration T_{cp} is appended:

$$s_{cp}(t) = \begin{cases} s(t + T_u), & -T_{cp} \leq t < 0 \\ s(t), & 0 \leq t < T_u \end{cases} \tag{3.25}$$

Total symbol duration:

$$T_s = T_u + T_{cp} \tag{3.26}$$

Engineering Insight:

- Ensures orthogonality under multipath
- Enables efficient FFT-based processing

3.4.2 Radar-Specific Advantages: Circular Convolution

In a multipath channel with impulse response $h(t)$:

$$r(t) = s(t) * h(t) \tag{3.27}$$

With CP, the linear convolution becomes circular:

$$r[n] = s[n] \circledast h[n] \tag{3.28}$$

Taking the Discrete Fourier Transform (DFT):

$$R[k] = S[k] \cdot H[k] \tag{3.29}$$

Radar Implication:

- Channel estimation becomes a simple division:

$$H[k] = \frac{R[k]}{S[k]} \tag{3.30}$$

- Cross-Ambiguity Function (CAF) can be computed efficiently in frequency domain
- Enables real-time radar processing on embedded platforms

3.4.3 Ambiguity Function of OFDM

Self-Ambiguity Function

$$\chi(\tau, f_d) = \int s(t)s^*(t-\tau)e^{-j2\pi f_d t}dt \tag{3.31}$$

Substituting OFDM structure:

$$\chi(\tau, f_d) = \sum_{k=0}^{N-1} |d_k|^2 e^{j2\pi k\Delta f\tau} \cdot \mathrm{sinc}(f_d T_u) \tag{3.32}$$

Thumbtack Property

- Sharp peak at $(\tau, f_d) = (0, 0)$
- High resolution in both delay and Doppler

Pedestal Noise

- Due to finite symbol duration and non-ideal subcarrier weighting
- Results in elevated sidelobes:

$$\chi_{sidelobe} \neq 0 \quad \forall(\tau, f_d) \tag{3.33}$$

- Limits dynamic range of radar detection

Engineering Trade-off:

- Increasing N improves resolution but raises computational cost
- Windowing techniques required to suppress pedestal

3.4.4 Embedded Implementation: FFT Shift (Jetson Orin)

```
#include <vector>
#include <complex>

void fft_shift(std::vector<std::complex<float>>& data)
{
    int N = data.size();
    int half = N / 2;

    for (int i = 0; i < half; ++i) {
        std::swap(data[i], data[i + half]);
    }
}

// Optimized version (in-place, cache-friendly)
void fft_shift_block(std::complex<float>* data, int N)
{
    int half = N >> 1;

    for (int i = 0; i < half; ++i) {
        std::complex<float> tmp = data[i];
        data[i] = data[i + half];
        data[i + half] = tmp;
    }
}
```

Optimization Notes:

- In-place memory swap minimizes overhead
- Align data for SIMD acceleration on Jetson AGX Orin
- Critical for mapping zero-frequency to center of spectrum

3.4.5 Visual Representation

Figure: 5G NR Resource Grid

The figure illustrates:

- Time axis: OFDM symbols (slots)
- Frequency axis: subcarriers

- Highlighted reference signals:
  - PRS (Positioning Reference Signals)
  - DMRS (Demodulation Reference Signals)

Visual Insight:

- Reference signals act as known probes for radar correlation
- Dense grid structure enables precise delay-Doppler estimation

3.4.6 2026 Commercial Value: Waveform-Agnostic Processing

Core Concept:

$$\text{Multi-Waveform Support} \Rightarrow \text{Universal Passive Radar Engine} \tag{3.34}$$

Capability:

- Process:
  - DVB-T2 signals
  - 5G NR waveforms
  - 6G OTFS/OFDM hybrids
- Dynamically adapt to:
  - Bandwidth
  - Subcarrier spacing
  - Pilot structures

Monetization Strategy:

- License **waveform-agnostic radar software** to:
  - Global defense contractors
  - Intelligence agencies
  - Smart city providers
- Provide modular SDKs for rapid deployment

Strategic Insight: In 2026, the highest-value IP lies in **software-defined sensing**, where a single platform can exploit any available RF signal, making waveform-agnostic processing a **critical competitive advantage** in global surveillance and defense markets.

3.5 Illuminator Selection Trade-offs and Metrics

3.5.1 Selection Metrics

Selecting an optimal **Illuminator of Opportunity (IoO)** requires rigorous evaluation of waveform and channel properties.

Ambiguity Function Side-Lobe Level (SLL)

The Side-Lobe Level (SLL) is defined as:

$$\text{SLL} = 20\log_{10}\left(\frac{\max_{\tau, f_d \neq 0} |\chi(\tau, f_d)|}{|\chi(0,0)|}\right) \tag{3.35}$$

Insight:

- Lower SLL $\Rightarrow$ better target detectability
- High SLL increases false alarm probability

Bandwidth-Resolution Product

Range resolution:

$$\Delta R = \frac{c}{2B} \tag{3.36}$$

Define:

$$\mathcal{R}_B = B \cdot T_{obs} \tag{3.37}$$

Insight:

- Larger bandwidth $\Rightarrow$ finer range resolution
- Longer observation $\Rightarrow$ improved Doppler resolution

Coherence Time (Δt_c)

$$\Delta t_c \approx \frac{1}{f_d^{max}} \tag{3.38}$$

Insight:

- Defines maximum integration time
- Limits coherent processing gain

Table 3.2: Illuminator Trade-offs in 2026

Metric	DVB-T2	5G NR (Sub-6)	Starlink (Ku-band)
Bandwidth B	∼8 MHz	∼100 MHz	∼250 MHz
Range Resolution ΔR	∼18.75 m	∼1.5 m	∼0.6 m
Doppler Sensitivity	Moderate	High	Very High
Signal Availability	High (broadcast)	Medium (urban)	Global (LEO)
SLL Performance	Low	Moderate	High variability

3.5.2 The Trade-off Matrix

Key Trade-off:

- DVB-T2: stable but low resolution
- 5G NR: balanced performance
- Starlink: high resolution but dynamic geometry

3.5.3 Link Budget Rigor: Minimum Detectable Signal (MDS)

The thermal noise power is:

$$P_n = k_B T B \tag{3.39}$$

Including receiver noise figure F:

$$P_{min} = k_B T B F \tag{3.40}$$

In dBm:

$$P_{min}^{dBm} = -174 + 10\log_{10}(B) + NF \tag{3.41}$$

where:

- k_B: Boltzmann constant
- $T \approx 290$ K
- $NF = 10\log_{10}(F)$

Hardware Comparison

- ADALM-Pluto: $NF \approx 3$–5 dB
- USRP X410: $NF \approx 2$–3 dB

Insight:

- Lower NF ⇒ better sensitivity
- Critical for detecting low-RCS drones

3.5.4 Embedded Logic: Decision Engine

```
#include <vector>
#include <string>
#include <cmath>

struct Channel {
    std::string name;
    double snr;
    double bandwidth;
    double sll;
};

class DecisionEngine {
public:
    double w_snr = 0.5;
    double w_bw  = 0.3;
    double w_sll = 0.2;

    int select_best(const std::vector<Channel>& channels)
    {
        double best_score = -1e9;
        int best_idx = -1;

        for (int i = 0; i < channels.size(); ++i) {

            double score =
                w_snr * channels[i].snr +
                w_bw  * std::log(channels[i].bandwidth) -
                w_sll * channels[i].sll;

            if (score > best_score) {
                best_score = score;
                best_idx = i;
            }
        }

        return best_idx;
    }
};
```

Engineering Insight:

- Multi-objective optimization problem
- Adaptable weights for mission-specific priorities
- Enables real-time IoO switching

3.5.5 Visual Representation

Figure: Ambiguity Pedestal Comparison

The figure illustrates a 3D surface:

- Axes: Delay (τ), Doppler (f_d), Magnitude
- DVB-T2:
  - Flat spectrum
  - Low pedestal and clean peak
- 5G OFDM:
  - Structured spectrum
  - Elevated pedestal due to pilot structure

Visual Insight:

- Pedestal limits weak target detection
- Waveform choice directly impacts radar performance

3.5.6 2026 Commercial Value: Dynamic Spectrum Radar

Core Concept:

$$\text{Adaptive IoO Selection} \Rightarrow \text{Interference-Proof Radar} \tag{3.42}$$

Capability:

- Continuously scan RF environment
- Identify optimal illuminators in real-time
- Switch reference channel dynamically

Advantages:

- Resistant to jamming and interference
- Operates in contested environments
- Fully covert (no transmission)

Monetization Strategy:

- Sell as **Dynamic Spectrum Radar Systems** to:
  - Military border security agencies
  - Intelligence organizations

  - Critical infrastructure operators

- Offer premium features:
  - Automated spectrum intelligence
  - Adaptive tracking algorithms
  - AI-driven signal prioritization

Strategic Insight: In 2026, the ability to dynamically exploit the RF spectrum transforms passive radar into a **resilient sensing platform**, making it a high-value asset for covert operations in both civilian and defense sectors.

Chapter 4

Signal Models and Cross-Ambiguity Function

4.1 Baseband Signal Model for Passive Radar

4.2 Derivation of the Cross-Ambiguity Function

4.3 Discrete-Time CAF Formulation

4.4 FFT-Based Fast CAF Algorithms

4.5 Range-Doppler Map Formation

4.6 Direct Path Interference (DPI) Modeling

4.7 Adaptive Filtering for DPI Cancellation

4.7.1 Extensive Cancellation Algorithm (ECA)

4.7.2 Normalized Least Mean Squares (NLMS)

4.7.3 Real-Time FIR Filter Implementation

4.7.4 Numerical Stability and Convergence Analysis

Chapter 5

Detection Theory and SNR Optimization

5.1 Noise and Clutter Modeling

5.2 Matched Filter Derivation

5.3 Coherent and Non-Coherent Integration

5.4 Processing Gain ($G_p = TB$)

5.5 CFAR Detection Algorithms

5.6 Detection Performance Metrics (ROC Curves)

5.7 Impact of Residual Interference After Cancellation

Chapter 6

SDR Architectures and Hardware Abstraction

6.1 Overview of SDR Platforms

6.1.1 ADALM-Pluto

6.1.2 KrakenSDR

6.1.3 USRP X410

6.2 Hardware Abstraction Layers

6.2.1 SoapySDR

6.2.2 UHD (USRP Hardware Driver)

6.3 Multi-Channel Synchronization

6.3.1 Clock Distribution (10 MHz Reference)

6.3.2 Pulse-Per-Second (PPS) Alignment

6.3.3 GPS Disciplined Oscillators (GPSDO)

6.4 Sample-Level Alignment and Phase-Coherent Ingestion

6.4.1 Phase Noise Modeling

6.4.2 Impact on Cross-Ambiguity Function

6.4.3 Coherence Loss and SNR Degradation

6.4.4 Software-Based Synchronization Techniques

6.4.5 Real-Time Drift Compensation Algorithms

Chapter 7

Real-Time DSP in C++

7.1 Streaming Architectures for SDR Pipelines

7.2 Lock-Free Buffer Design

7.3 Memory-Mapped I/O for High-Speed Data Access

7.4 SIMD Optimization (AVX / NEON)

7.5 Real-Time FFT and Overlap-Save Methods

7.6 Latency Analysis and Deterministic Scheduling

Chapter 8

GPU Acceleration on NVIDIA Jetson AGX Orin

8.1 CUDA Programming Model for Radar DSP

8.2 Parallelizing the Cross-Ambiguity Function

8.3 Shared Memory Optimization

8.4 GPU-Based Range-Doppler Processing

8.5 Zero-Copy Memory Access

8.5.1 Pinned Memory Allocation

8.5.2 CPU-GPU Memory Sharing

8.6 RDMA for High-Throughput SDR Streams

8.6.1 GPUDirect RDMA Architecture

8.6.2 PCIe Bottleneck Analysis

8.6.3 End-to-End Latency Optimization

8.7 Power vs Performance Trade-offs on Edge Devices

Chapter 9

AI-Enhanced Detection and Tracking

9.1 Machine Learning for Clutter Suppression

9.2 Deep Neural Networks for Target Detection

9.3 Transformer-Based Multi-Target Tracking

9.4 Sensor Fusion (RF + Vision + ADS-B)

9.5 Model Compression for Edge Deployment

9.6 Real-Time Inference on Jetson Platforms

Chapter 10

Deployment, Scaling, and Startup Strategy in 2026

10.1 Passive Radar for UAM Vertiport Protection

10.2 Border Surveillance and Covert Operations

10.3 Distributed Radar Networks (Mesh Architectures)

10.4 Cloud-Edge Hybrid Processing Models

10.5 Productization Strategies

10.5.1 Radar-as-a-Service (RaaS)

10.5.2 Licensable Signal Processing IP

10.5.3 Defense Contracting vs Commercial Markets

10.6 Regulatory and Spectrum Considerations (2026)

10.7 Scaling a Passive Radar Startup

10.8 Go-To-Market Strategy and Competitive Positioning

Chapter 11

Appendices

11.1 Mathematical Identities and Proofs

11.2 Complete C++ DSP Library Reference

11.3 CUDA Kernel Optimization Patterns

11.4 Dataset Formats and Experimental Protocols

11.5 Reproducibility Guidelines