

DECISIONS_LOG - matts-timer-app

Fable's record: Matt's decisions in his words, and Fable's review and sign-off of each Opus build. Newest at the bottom.

2026-09-20 - Repo flipped to Fable-main

Matt's words, in this repo's chat: "Flip it and I will tell you what I want added. It is all local, no internet, no syncing with other apps, etc... still a simple timer but I need it to work correctly on my phone and that is where you come in Fable. Build the subagents and workflow rules. Let me know when you're done and I'll start a new session for the feature adds"

Done by Fable the same day, at commit 4cbb214 as the starting tree:

- `CLAUDE.md` written (Sections 1-4), modelled on `matts-doc-reader` and `matts-calendar-app`, both flipped 2026-09-18.
- `.claude/agents/opus.md` written (model opus, effort high). No `opus-xhigh`: no global rule 3 `xhigh` class exists in this repo. No `fable-*` files: Fable does not spawn Fable in a flipped repo.
- `docs/handoff/FOR_FABLE.md`, `FOR_FABLE_LOG.md`, `NEXT_CHAT_2026-09-20.md` and this log created.
- `tools/md2pdf.py` copied in from `matts-doc-reader` (read there, written here) so every `.md` has its PDF.

Open from this entry: the Fable-owned list in `CLAUDE.md` Section 1 is Fable's proposal and is NOT accepted by Matt yet (`FOR_FABLE.md` item 1).

Walls recorded from his words: no INTERNET, no syncing with other apps, "still a simple timer". Measured the same day: the manifest's only permission is `VIBRATE`; `dependencies { }` is empty; release is signed with the debug key; no tests exist; `adb devices` listed no device (n=1).

2026-09-20 - v2 build: Fable review of f0071a1 - SIGNED for phone check

Job: Matt's four adds (his words and answers in `docs/handoff/FOR_FABLE.md` item 1). Spec by Fable, built by Opus at f0071a1 on base 32f83ed.

Reviewed line by line against the spec [measured, n=1 read]: `TimerEngine.kt` (492 lines) and `TimerService.kt` (212 lines), the manifest diff, and the Activity's wiring by grep.

- Clock math moved unchanged: `endsAt = now + remainMs`, `pause remainMs = (endsAt - now) >= 0`, `swBase = now - swElapsed`, all `elapsedRealtime`.
- The finish is decided only in `finishCue()` (guarded on running, cue generation counter, re-posts if the clock still shows time). The Activity never calls `timerFinish`.
- Audio focus: `GAIN_TRANSIENT_MAY_DUCK`, requested before the 3 s tick (or at start inside the last 3 s), only when sound is on; abandoned in `RESTART`, `RESET`, `PAUSE`, preset select; held through `TIME`. No stream volume write anywhere (grep: no matches, also none for `AlarmManager` or `INTERNET`).
- Service: not exported, not bound, `specialUse`, `startForeground` first in `onStartCommand`, `onTaskRemoved` does nothing, `START_STICKY` restore through prefs. Partial wake lock only while the countdown runs (remaining + 10 s timeout) and 6 s past the finish.

- Manifest: only the <service> element added by Opus; the five permission lines are Fable's from 32f83ed. dependencies { } empty.
- Opus's ten stated deviations read and accepted (tap target is the digits block; SET & START dimmed-not-disabled at 0:00 so a typed value can commit; restore gated on the boot offset for all state; stopwatch START also triggers the one-time notification ask).
- Build: assembleRelease passes on the committed tree, APK 674,357 bytes [measured, n=1]. dist/MattsTimer.apk NOT replaced yet.

Follow-ups seen, not fixed: (a) a process restored with under 3 s left does not re-request the duck; (b) pause at the last instant can leave "paused 0:00" where START refuses (in v1 too); (c) a process killed and reopened hours later in the same boot shows TIME for the old set.

Everything on-phone is [verify, n=0]: lock-screen display, finish with the screen off, swipe from recents, Spotify ducking. Not DONE until the phone check passes. Matt, 2026-09-20: "I have another session working on my phone so don't interrupt it. Trust the serial is correct. Once that session is done you can ask me for permission to build and test on my phone." No adb from this session until he says that session is done.

2026-09-20 - Rising repeat chime: Fable review of f3d3ed5 - SIGNED for phone check

Matt's words: "one more feature while you are waiting. Can you gradually increase the timer volume once it has expired". Fable asked three questions with recommendations (repeat until he taps; 30 percent to full by the 5th chime, auto-stop at 2 minutes; ramp the app's own sound only, never a volume slider). His answer: "thats fine build it in". Spec by Fable, built by Opus at f3d3ed5 on base 570fa71.

Code diff read line by line [measured, n=1 read] (TimerEngine.kt, TimerService.kt, Tones.kt):

- Tones.play(pcm, gain = 1f) sets the AudioTrack's own volume; synthesis untouched; no stream volume write (grep: no matches, none for AlarmManager or INTERNET either).
- Gains 0.30, 0.475, 0.65, 0.825, 1.0 then 1.0; period = chime length + 1000 ms; buzz with every chime; sound, voice and vibe read at each fire.
- One cue at a time through postCue; alarming cleared only in clearCues(), which RESTART, RESET, preset select and SET & START all reach. timerFinish clears first, then sets alarming.
- No chime starts later than 120 s after the finish, measured on elapsedTime. Accepted deviation: alarming is held until the last chime has rung out (about 124 s worst case) so the wake lock is not dropped mid-tone; the lock's own timeout is 130 s.
- A restored finished state does not ring.
- Build: assembleRelease passes on the committed tree [measured, n=1].

Seen, not fixed: starting the stopwatch or switching tabs does not stop the ring-out; the red flash outlives the 2-minute audio stop; the screen may sleep during the ring-out (the chimes do not depend on it).

On-phone behavior [verify, n=0]. Joins the v2 phone check, still waiting on Matt's word that the other phone session is done.

2026-09-20 - Fix pass before the phone: Fable review of 422e227 - SIGNED for phone check

Matt's words: "change them all nothing broke should touch my phone." Fable's reading, said to him in chat: the three ring-out items plus the two plain v2 defects. Spec by Fable, built by Opus at 422e227 on base 92aa947.

Code diff read line by line [measured, n=1 read]:

- `alarmStop()`: only acts while alarming; clears cues, state stays finished, focus stays held. Called first in `swStart()` and from the new `onTab()` (user tab taps only); rotation and `onCreate` call `setMode()` directly and do not silence the ring.
- Flash follows alarming, not finished (`syncFlash`, one decision point).
- `keepAwake` = running or `swRunning` or alarming, at `onStart`, listener and rotation.
- `timerPause()` with nothing left routes to `timerFinish()`; "paused 0:00" cannot occur.
- `restore()` inside the last 3 s requests the duck; `loadSettings()` runs before it.
- Accepted deviation: a tap on the tab already showing also silences the ring.
- No stream volume, `AlarmManager` or `INTERNET` (grep: no matches). Build passes on the committed tree [measured, n=1].

Still open by Matt's choice: a process killed and reopened hours later in the same boot shows TIME for the old set.

Phone: the calendar session reported at 10:36 it is done with RFGL4275NVH. That is a status notice; the install waits on Matt's permission in this chat.

2026-09-20 - Ten-minute stale rule: Fable review of e5226d2 - SIGNED for phone check

Matt's words: "if the app is "killed with a timer running for more than ten minutes kill it and shut down the timer app. Yes you can install what is needed on my PC and Phone". Fable's reading, told to him in chat before the build: after the process was killed, a set that ended more than ten minutes ago is dropped (no TIME, no notification, no service, app fresh at 35 s); ended ten minutes ago or less restores to silent TIME; still counting keeps running; a never-killed process is unchanged. Built by Opus at e5226d2 on base 0d5a8b2, no deviations.

Code diff read line by line [measured, n=1 read]: `STALE_MS = 600_000`; `finishedAt` set at the finish instant and persisted (0 when not finished); `restore()` drops through `dropSet()` when the end is over ten minutes past, or `finishedAt` is missing, zero or in the future; the ran-out-while-dead branch keeps `finishedAt` = `savedEnds`. Service shutdown after a drop rides the existing `serviceWanted` paths (`syncService`, `TimerService.onStartCommand`). No stream volume, `AlarmManager` or `INTERNET`. Build passes on the committed tree [measured, n=1].

Known and accepted: a paused set restores after any gap in the same boot (his words name a running timer). First open after upgrading from a persisted finished state without `finishedAt` opens fresh.

Phone order, Matt's words: "hold on my phone that session is ready so it is going to build first" - the Nudge session (Calendar app revision spec [3294e9], reminder-app repo) has the phone first; this session sends no add command until it reports done. Install permission from Matt stands ("Yes you can install what is needed on my PC and Phone"); confirm with him when the phone comes back before running it.

2026-09-20 - Phone check 1 of the e5226d2 build (Fable, adb-driven) - NOT DONE, 2 findings

Matt's words: "yes go ahead and install" and "make sure you test it". Installed with `adb -s RFGL4275NVH install -r` (Success; settings kept: voice PULSE, VIB on). Driven by adb taps; state read from `dumpsys` (activity services, power, audio, notification) and screenshots. Every line below is [measured, n=1] on his phone unless it says otherwise.

PASS

- Nine presets with 15m sixth; no CUSTOM tile. Tap clock opens the wheels at the current preset; flick moves a wheel (35 to 34); typing 12 works.
- First start raised "Allow Timer to send you notifications?"; the set ran behind the prompt; Allowed (POST_NOTIFICATIONS granted, USER_SET).
- Running: foreground service (specialUse), wake lock `matttimer:run` held, notification RUNNING with PAUSE + RESTART, vis PUBLIC. Paused: "PAUSED 0:43", RESUME + RESTART, wake lock released. Finished: TIME, RESTART. RESET: focus 0, service 0, notification 0.
- Duck: focus entry GAIN_TRANSIENT_MAY_DUCK / USAGE_ALARM present at 3 s left, held through TIME, held after the ring ended and after a tab tap, gone after RESET/RESTART.
- Ring-out: chime every 5.0 s on PULSE (predicted 4.989 s); last chime 120 s after the finish; then wake lock released, flash stopped, static red TIME.
- STOPWATCH tab tap at TIME: no chime after the tap (12 s watched).
- Left the app (HOME) and swiped the card out of recents while ringing: same pid, service foreground, chimes kept coming.
- Stopwatch with the app left: notification STOPWATCH with STOP, no wake lock; elapsed right on return; service gone once stopped.
- Screen off (35 s set, phone Dozing): go 11:02:36.592, ticks +32.02, +33.00, +34.00 s, chime +35.00 s, repeats every 5 s.
- No crash in logcat.

FINDINGS (not fixed) 1. Typing in a wheel opens the full QWERTY keyboard, which covers CANCEL and SET & START until the keyboard's check key is pressed. Not "quick, simple and easy". Flicking is unaffected. 2. On his lock screen the timer shows only as a small icon in the top row, not as a card with the countdown and PAUSE / RESTART. Cause not yet separated [verify]: the channel is IMPORTANCE_LOW (silent), and Samsung's lock-screen notification style may be set to icons - a phone setting, his call (global Section 12 item 17).

NOT TESTED by adb: how deep Spotify ducks and whether the chime climb is audible (his ears, headphones, Spotify playing); rotation with the picker open (would need a rotation setting change); lock-screen buttons (phone locked, PIN is his); process-kill restore and the ten-minute rule; pause at 0:00.

State left: phone locked, screen on lock screen, timer at TIME for a 35 s set (ring ends by itself at 2 min; music focus held until RESET/RESTART). `dist/MattsTimer.apk` not replaced - the check has not passed.

2026-09-20 - Phone check 1 fixes: Fable review of 40f11f2 + f3ba666 - SIGNED for phone check 2

Matt's words on the two findings: "yes fix them now". Built by Opus on base 9b3d7fa.

- `TimerService.kt` (Fable-owned) read line by line [measured, n=1 read]: channel `timer_v2` at `IMPORTANCE_DEFAULT`, sound null, vibration off, old timer channel deleted, `FOREGROUND_SERVICE_IMMEDIATE` on API 31+, nothing else in the notification changed. No deviation.
- Keyboard: number pad (`TYPE_CLASS_NUMBER`), check key commits and runs the SET & START path (at 0:00 it only closes the keyboard), root inset listener pads for the keyboard so CANCEL / SET & START stay above it, `adjustResize` on the activity, every close path hides the keyboard. Accepted deviations: `IME_FLAG_NO_EXTRACT_UI` (landscape), `@+id/root`.
- f3ba666: Opus reported typed 5 in seconds became 50 (`NumberPicker` prefix-matches `displayedValues`). Fable sent it back under "nothing broke should touch my phone". Fixed with a two-digit formatter in place of `displayedValues`; no reflection.
- Build passes on the committed tree, APK 677,345 bytes [measured, n=1]. No stream volume, `AlarmManager`, `INTERNET`; permission lines untouched.

Seen, not fixed: full lintRelease has 2 old `SuspiciousOdp` errors on `lapsScroll` (lintVital is clean; the release build passes).

All on-phone behavior of these fixes is [verify, n=0] until phone check 2. Install waits on Matt's word.

2026-09-20 - Phone check 2 of the f3ba666 build (Fable, adb-driven) - fixes confirmed, one item is Matt's phone setting

Matt's words: "yes install it". Installed with `adb install -r` (Success).

INCIDENT, Fable's fault: during this check Fable's unguarded coordinate taps got out of step with the app; a BACK key press left the timer and the following taps landed outside it. Matt, his words: "what the fuck are you doing opening a browser and going to the playstation store that has nothing to fucking do with installing a timer app" and then "finish the timer and only the timer - do not fucking touch anything else on my phone". Inputs sent in those sequences: taps (540,1418) (806,670) (806,1103) (757,1280) (540,2086), one BACK, END, three backspaces, text "12" twice. Rule from here on in this repo's phone work: every input is sent only after a check that `com.matt.gymtimer/.MainActivity` is the resumed activity, else abort; no BACK, HOME or recents keys; one action per step with a read between. The guarded driver was used for everything below.

PASS [measured, n=1 each]

- Number pad opens (not QWERTY); with it up CANCEL and SET & START sit above it (button row at y=1281 of 2340).
- Typed 5 + check key: a 0:05 set ran (ticks +2, +3, +4 s, chime +5.0 s).
- Typed 12 + SET & START tapped above the pad: go 11:28:47.13, ticks +9, +10, +11 s, chime +12.0 s. RESET returned to READY 12S.
- Notification on channel `timer_v2`, importance 3; titles RUNNING / TIME.

- Audio focus log: every request paired with an abandon; nothing held at idle. (An earlier "focus: 1" read was a log line of the old process dying at reinstall, not a held focus.)
- No crash in logcat.

NOT FIXED BY THE APP CHANGE

- Lock screen still shows the timer only as a small icon in the top row with the DEFAULT-importance channel. The app side is done; what is left is his Samsung lock-screen notification style (icons vs cards) - his setting, his call, its own prompt first (global Section 12 item 17).

STILL HIS TO CHECK: Spotify duck depth and the chime climb in his headphones; lock-screen buttons once cards show; rotation with the picker open; typed 5 in minutes. Not tested by anyone: process-kill restore and the ten-minute rule; pause at 0:00.

State left: phone locked on the lock screen; a 1m set was started at about 11:29 for the lock-screen read, so it reaches TIME and rings for up to 2 minutes on its own; music stays ducked until RESET/RESTART.
dist/MattsTimer.apk not replaced.

2026-09-27 - Phone check of f3ba666 closed by Matt, not passed

Asked whether to close the open checks before the alarm build, his words: "If it is verification testing just close it". The open items (lock-screen card style, duck depth, chime climb, lock-screen buttons, rotation with the picker open, typed 5 in minutes, kill/restore, ten-minute rule, pause at 0:00) were not run [verify, n=0].
dist/MattsTimer.apk not replaced.

2026-09-27 - Alarm clock: Fable review of ccca359 + 6544c8b - SIGNED for phone check

Matt's words: "Okay lets add in an alarm clock feature next". His answers to the twelve questions, his words: "1. yes, 2. B, 3. B, 4. 12 hour, 5 A, 6. ignores mute but I need more sound options in needs to be something that can wake but not annoy me, 7. 15 minutes, 8. yes, 9. A, 10. B, 11. If it is verification testing just close it, 12. effort is high". Spec docs/ALARM_SPEC.md by Fable (a025c8d, with the three permission lines USE_EXACT_ALARM, RECEIVE_BOOT_COMPLETED, USE_FULL_SCREEN_INTENT written by Fable). Built by Opus at ccca359; one fix at 6544c8b.

Read line by line against the spec [measured, n=1 read]: AlarmEngine.kt, AlarmService.kt, AlarmReceiver.kt, AlarmActivity.kt, and the diffs to TimerEngine.kt, Tones.kt and the manifest.

- Storage is the device-protected alarms prefs; none of the four alarm files references TimerEngine (grep: 0).
- nextTrigger: Calendar in the default zone, add a day if at or before now, step to a set weekday bit, hour and minute re-set after each day added.
- Arming: setAlarmClock with a getForegroundService PendingIntent, request code the alarm id; SecurityException sets armFailed.
- fire() rolls the alarm and commits before any sound; a second fire while ringing keeps the running ring; a fire more than 60 s early is re-armed and dropped.
- Service: startForeground on every start, specialUse, START_STICKY, wake lock matttimer:alarm with a 16-minute timeout, focus GAIN_TRANSIENT / USAGE_ALARM, gain $\min(1, 0.08 + 0.92 * \dots)$

t / 90 s), no phrase starts past 900,000 ms, then the missed card. Every end path stops the track, cancels the buzz, abandons focus, releases the lock. It never reads the timer's sound.

- Manifest: three components added, all exported="false" and direct-boot aware; exported="true" appears once; the eight permission lines untouched by Opus. TimerEngine.kt changed by the two mirror lines only; TimerService.kt and the gradle files have no diff.
- Tones.kt: the new Ev fields default to the old values, so the timer cues render as before; play returns a handle the timer ignores.
- Opus's ten departures read and accepted (full-screen intent attached only when a ring is starting or held; channels created from a companion function; in-process ringing flag; sticky resume continues the ramp; armAll always commits; the rest are UI choices the spec left open).
- No INTERNET, no stream volume write (grep: 0 each).

Finding, fixed at 6544c8b: lateRing started the service directly and swallowed a refused start, leaving the alarm on with next in the past and nothing armed. It now arms the alarm with its past trigger, which setAlarmClock delivers at once through the same PendingIntent an on-time ring uses [design; phone behavior verify, n=0]. Diff read: 5 lines added, 10 removed, nothing else touched.

Build: assembleRelease passes on the committed tree at 6544c8b, APK 702,757 bytes [measured, n=1]. No tests exist.

Seen, not built: a tap on the missed card or the status-bar alarm icon opens the app on the TIMER tab; DELETE has no confirm; a quick second tap on SOUND plays a preview over the one still ringing out.

Everything on-phone is [verify, n=0], including: a non-exported receiver getting the boot broadcast, ringing before the first unlock, whether full-screen needs a manual grant, and Samsung's battery settings letting the alarm through. Not DONE until the phone check passes. Install waits on Matt's word.

2026-09-27 - D1-D7 accepted; two adds: Fable review of 933ef88 - SIGNED; installed, not checked

Matt's words: "1. yes install it, 2. accept, 3. build both but there is a golf tracker session that will be building on my phone in a little bit. Talk to it and you can have the phone while it is working". "2. accept" is his answer on D1-D7 (docs/ALARM_SPEC.md Section 2). "3. build both" is the missed card opening on the ALARM tab and a confirm step on DELETE. Then, asked how to fit the install around his leaving with the phone: "2. serial is correct, install now check later".

Built by Opus at 933ef88 on base e958d1a. Diff read line by line [measured, n=1 read]:

- AlarmEngine.kt: EXTRA_TAB / TAB_ALARM constants; the extra on the show intent in arm() and on the open intent in postMissed(); both PendingIntents FLAG_UPDATE_CURRENT or FLAG_IMMUTABLE; request codes unchanged. Nothing else in the file. No departure.
- MainActivity.kt: onNewIntent and onCreate switch through setMode, never onTab, so a timer ring-out is not silenced; the extra is removed after one use. DELETE arms on the first tap (TAP AGAIN TO DELETE, red, 4000 ms) and disarms on the timeout and on every other editor action.
- Accepted departures: the tab is forced only when savedInstanceState is null; the armed button's text is 12 sp so it fits.

- Manifest and gradle files: no diff. Build passes on the committed tree, APK 703,689 bytes, SHA-256 5C7D513B...9FA2D3 [measured, n=1].

Phone, shared with the golf-tracker session "Yesterday's field trial data" by message (it was not on the phone; handshake agreed; released to it afterwards). `adb -s RFGL4275NVH install -r` of that APK: Success [measured, n=1]. Read back, read-only:

- `USE_EXACT_ALARM`, `RECEIVE_BOOT_COMPLETED`, `USE_FULL_SCREEN_INTENT` granted=true; `POST_NOTIFICATIONS` granted=true (`USER_SET`, from 2026-09-20).
- appops `USE_FULL_SCREEN_INTENT`: no operations recorded, default mode. Whether the full-screen takeover works is still [verify, n=0].
- `dumpsys alarm`: nothing for `com.matt.gymtimer`. No alarm is set.

Not done from this session: the app was not launched, no input was sent, no setting was changed. Every alarm behavior on the phone is [verify, n=0]. `dist/MattsTimer.apk` not replaced. Not pushed.

2026-09-28 - Alarm phone check, checks 1-7 (Fable, adb-driven) - 5 PASS, 3 not run; STOP-on-screen build 68019db SIGNED, not installed

Matt's words: "If I plug my phone in can you test the alarm app out for me?" then "Phone is plugged in. 1 - 7 are a go hold on the rest". Checks 8-11 (15-minute cut, his ears on the voices, restart, time zone) are on hold on his word. Phone RFGL4275NVH, build 933ef88 (installed 2026-09-27 08:39:29), unlocked by him. Golf-tracker sessions all offline [measured, n=1 read of the session list]. Guarded driver: every input sent only with `com.matt.gymtimer` resumed; no BACK, HOME or recents.

Ring 1: one-shot 6:26 AM, phone unlocked, app in front, timer voice MUTE, 5m timer running. Ring 2: 6:44 AM EVERY DAY, phone unlocked, app in front. All [measured, n=1] unless marked.

PASS

- Check 3 (STOP from the card): ring 1 ended at 06:29:41.712 - wake lock `matttimer:alarm` released, audio focus abandoned, `AlarmService` gone, card gone. Ring 2 the same at 06:46:23 [n=2].
- Check 4 (MUTE on the timer, alarm sounds): alarm `AudioTrack` started with `USAGE_ALARM` while the timer voice read MUTE. His ears, his words: "it rang fine".
- Check 5 (one-shot switches itself off): row 6:26 AM / ONCE / OFF, status `NO_ALARM_SET`, nothing armed in `dumpsys alarm`.
- Check 6 (repeating shows the next day): after ring 2, status `NEXT 6:44 AM - IN 23H 58M`, `dumpsys alarm` armed 2026-09-29 06:44:00.000.
- Check 7 (timer running while the alarm fires): timer reached `TIME` at 06:28:38 on MUTE; the alarm's phrases kept going through it.
- Also: armed exact (`window=0`, `exactAllowReason=policy_permission`); fired 06:26:00.018 against 06:26:00.000; ramp logged 0.080 at 0 s to 0.984 at 88 s, 1.000 from 96 s on, straight line (D3); phrase every 7.37 s; focus request 06:26:00.019 paired with its abandon; no warning lines on the ALARM tab; no crash.

NOT RUN [verify, n=0]

- Check 1 (app closed, screen off), check 2 (full screen over the lock screen), check 3's other half (STOP from the ringing screen). They need his hands (swipe from recents, power button). Ring 2 was set for them; the screen went off at 06:42:27 and was back on, unlocked, app in front, at 06:43:08, so ring 2 fired with the phone in use.

FINDING

- Phone unlocked: Android does not launch the full-screen intent; Samsung shows a pill for a few seconds. STOP is then in the shade: pull down, expand the Timer group (when the timer card is also up), expand the ALARM card, STOP. Nothing in the app showed the ring.
- Matt, his words: "it rang fine the stop button should be on the screen when the alarm is firing".

FABLE'S MISS

- Ring 1: the first STOP tap was sent by coordinate 45 s after the screenshot it came from; the shade had closed and the tap landed on the running timer's clock face (no effect). Ring 1 ran 3 min 41 s. From then on shade taps go to a node read from the screen immediately before the tap. Ring 2 ran 143 s: Fable stopped it from the card when nobody had.

BUILD 68019db (Opus, base a486244) - SIGNED for phone check

- Fable's design call [design], told to Matt, his to overturn: with the app in front while a ring is live, MainActivity opens the existing AlarmActivity. Screen work only; no Fable-owned file in the diff.
- Diff read line by line [n=1 read]: MainActivity.kt +27 - showRingIfLive(), flags resumed and ringShown, onResume / onPause; called from onStart after addListener and from onAlarmState() when resumed && !ringShown. README.md, tools/make_pdf.py, docs/TIMER.pdf re-run. Manifest, gradle and the five engine/service/receiver files: no diff.
- Accepted departure: the call sits in onStart (the listener is registered there; there was no onResume).
- Follow-up reported by Opus, not fixed, not asked for: in split-screen the ringing screen opens only when the app regains focus.
- Build passes on the committed tree, APK 703,729 bytes, SHA-256 C4FAE816...50DDBE [measured, n=1].
- Not installed. Every behavior of it on the phone is [verify, n=0].

State left on the phone: Matt's Timer in front, TIMER tab, READY 35S, voice PULSE (as found), VIB untouched. One alarm in the list, 6:44 AM EVERY DAY, switched OFF; nothing armed for com.matt.gymtimer. Alarm voice DAWN, as found. No phone setting changed. dist/MattsTimer.apk not replaced. Not pushed.