

MM6D Remote controlled switching device

Technical manual



Hardware version: v200612

Software version: v0.2

Technical manual version: v2.0

Issue date: 2021.02.21.

Draw number: 59/11/1

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	1/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

Content

I. Hardware.....	3
1. Technical data.....	4
2. General description.....	4
3. Schematic and PCB draws.....	4
4. Other draws and documents.....	4
5. Terms of use.....	4
6. Look of device.....	5
a) Manuals.....	5
b) Internal construction.....	6
c) Pinout of connectors.....	7
7. Downloadable documentation.....	8
II. Software.....	9
1. General description.....	10
2. Setup.....	10
3. Installation.....	10
4. Using the device.....	10
a) Data set and retrieval via HTTP.....	10
b) Connect to console via serial port.....	12
5. Check operation.....	12
6. Terms of use.....	14
7. Downloadable software package.....	14
III. Related links.....	15
1. Hardware.....	16
2. Software.....	16
3. Terms of use.....	16
4. Developer and manufacturer.....	16
IV. Annexes.....	17
Content.....	18

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	2/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

I. Hardware

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	3/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

1. Technical data

Supply voltage:	230V AC	IP protection:	IP 55
Auxiliary voltage:	12V DC	Mass of cover:	termoplast (ABS)
Supply current:	max. 15 A	Communication:	Wireless LAN,
Isolation class:	Class I		TTL 3.3V serial port
Mechanical size:	300 x 220 x 120 mm	Get/set data:	via HTTP
		Administration:	via serial connection

2. General description

The device has four 12V DC inputs separated by an optocoupler and four relay outputs. These have a predefined function. Their status can be queried or set via HTTP. The power outputs can also be switched manually. The continuous operation of the microcontroller is ensured by a 3.7V 500mAh LiPoly battery, the alarm sensor is provided by a non-rechargeable 6F22 9V battery.

Load capacity of outputs:

Function	Voltage	Maximal load	Overcurrent protection	Watched?
Status lamp outputs	12V DC	6W	fuse	no
Lamp output	230V AC	460W	overcurrent breaker	yes
Ventilator output	230V AC	460W		yes
Heater output	230V AC	2.3 kW		yes

3. Schematic and PCB draws

The wiring diagrams of the device is shown in Annex 2, schematic and PCB draws are in Annex 3-7. You can download it as part of the complete documentation or in separate PDF, SVG and KiCAD formats from the developer/manufacturer's website. The Gerber files needed for production of boards are included in the package.

4. Other draws and documents

Documentation package contents draw of frontpage in ODG and PDF and drilling draw in DXF and PDF format.

5. Terms of use

Hardware documentation can be modified and/or redistributed under the Creative Commons 4.0 Attribution Non-Commercial (CC-BY-NC-4.0) License. You can read the full text of the license online. (Refer to Chapter III for references.)

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	4/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

6. Look of device

a) Manuals

1. Mains voltage signal light (white LED)
2. Auxiliary voltage signal light (white LED)
3. Activity signal light (blue LED)
4. Manual mode signal light (yellow LED)
5. Alarm/General error signal light (red LED)
6. Protection error signal light (red LED)
7. Lamp on signal light (green LED)
8. Ventilator on signal light (green LED)
9. Heater on signal light (green LED)
10. Lamp manual mode switch (SW1)
11. Ventilator manual mode switch (SW2)
12. Heater manual mode switch (SW3)
13. Operation mode switch (SW4)




Figure 1: Manuals

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	5/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

b) Internal construction

1. Main board
2. Display board
3. Accumulator of microcontroller (BT101)
4. Battery of alarm input (BT201)
5. Transformers
6. Fuse of transformers (F4)
7. Fuse of auxiliary voltage (F6)
8. Fuse of external status lamps (F5)
9. Relay of external status lamp (K4)
10. Relay of lamp output (K1)
11. Relay of ventilator output (K2)
12. Relay of heater output (K3)
13. Breaker of lamp output (F1)
14. Breaker of ventilator output (F2)
15. Breaker of heater output (F3)
16. Mains connectors (P1-3)
17. Console connector (P18)
18. Alarm sensor connectors (P13-14)
19. Status lamp connectors (P15-17)
20. Lamp connectors (P4-6)
21. Ventilator connectors (P7-9)
22. Heater connectors (P10-12)
23. Mounting holes




Figure 2: Internal construction

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	6/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

c) Pinout of connectors

[illegible]

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	7/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

7. Downloadable documentation

The complete documentation of the hardware in the .tar.gz format compressed file can be downloaded from the manufacturer's website or Github. (Refer to Chapter III for references.) Name of package is: *mm6d-hw-200612-2.0.tar.gz*.

Content of package - only important files:

mm6d-hw	KiCAD and LibreCAD files
— cad_files	<i>display board</i>
— display	project file
display.pro	schematic draw
display.sch	PCB draw
display.kicad_pcb	drilling file
display.drl	Gerber files
display-*.gbr	<i>drilling draws</i>
— drilling	front of box
front.dxf	mounting plate
mountingplate.dxf	<i>main board</i>
— mainboard	project file
mainboard.pro	schematic draw
mainboard.sch	PCB draw
mainboard.kicad_pcb	drilling file
mainboard.drl	Gerber files
mainboard-*.gbr	<i>internal wiring</i>
— wiring	project file
wiring.pro	schematic draw
wiring.sch	documentation
— documents	Technical manual
mm6d_en.pdf	drilling draws
drl_*.pdf	pcb draws
pcb_*.pdf	schematic draws
sch_*.pdf	frontpage
— frontpage	pictures of frontpage
*	pictures
— pictures	look of the unit
mm6d.jpg	PCB draws
pcb_*.svg	schematic draws
sch_*.svg	
— LICENCE	terms of use
— README.md	short description

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	8/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

II. Software

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	9/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

1. General description

The task of the program is to operate the hardware and communicate with the central controller.

The program displays initialization steps and error messages on the serial console.

When an HTTP request is received, the client's IP address and username argument are checked. If appropriate, read inputs or or turn outputs on/off. After displays the result on the web interface. Incoming requests are indicated by the flashing of the blue activity LED.

2. Setup

You can found source file of software in *source* directory. Before installing the program, you need to set these values:

```
// settings
const char* wifi_ssid      = "";
const char* wifi_password  = "";
const String www_username  = "";
const String allowedaddress = "";
```

3. Installation

Use a micro USB cable and Arduino IDE software to install program to microcontroller.

4. Using the device

The device operates automatically does not require any human intervention.

a) Data set and retrieval via HTTP

An example for how to use argument:

<http://192.168.1.21/set/lamp/off?uid=bob>

<http://192.168.1.12/operation?uid=bob&a=0&l=1&v=0&h=0>

URL of information and data pages:

URL	type	description	args.
http://ipaddress/	text/html	Start and information page	
http://ipaddress/version	text/plain	Get software name and version	
http://ipaddress/operation		Get all data, restore alarm and set outs	uid, l, v, h
http://ipaddress/get/all		Get all status	uid
http://ipaddress/get/alarm		Get status of alarm sensors	
http://ipaddress/get/manualswitch		Get status of manual switch	

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	10/28
	Technical manual				
Name:	Pozsár Zsolt	Date:	2021.02.21.		

URL	type	description	args.
http://ipaddress/get/operationmode		Get operation mode	
http://ipaddress/get/protection		Get status of overcurrent protection	
http://ipaddress/set/all/off		Switch off all outputs	
http://ipaddress/set/alarm/off	text/plain	Restore alarm input	uid
http://ipaddress/set/heater/off		Switch off heater	
http://ipaddress/set/heater/on		Switch on heater	
http://ipaddress/set/lamp/off		Switch off lamp	
http://ipaddress/set/lamp/on		Switch on lamp	
http://ipaddress/set/ventilator/off		Switch off ventilator	
http://ipaddress/set/ventilator/on		Switch on ventilator	

uid: user ID
a: restore alarm
l, v, h: outputs (lamp, ventilator and heater)




Figure 3: Start page

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	11/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

b) Connect to console via serial port

The console connector of the device and the RS-232 serial port of the computer must be connected by means of a level shifter adapter with a null modem cable. The level shifter adapter is required due to the different voltages of the logic levels (0 V / 3.3 V and -12 V / + 12 V).

The console connector of the device and the USB port of the computer must be connected using an Adafruit 954, FTDI TTL-232R-RPI or similar 3.3V serial / USB cable.

Connection parameters

speed (baudrate):	115 200 bps
data bits:	8
parity bit:	no
stop bit:	1
flow control:	no

Connect via linux terminal

Name of ports (device files):

RS-232 serial port:	/dev/ttyS0, /dev/ttyS1, ...
serial/USB converter:	/dev/ttyUSB0, /dev/ttyUSB1, ...

Make sure you are a member of the dialout group:

```
username@localhost$ id
```

If not, set up your group membership:

```
username@localhost$ sudo usermod -a -G dialout username
```

Connect with GNU Screen program:

```
username@localhost$ screen port_name 115200
```

Connect with Minicom program:

```
username@localhost$ minicom -b 115200 -o -D port_name
```

Connect with Windows terminal (Putty)

Name of ports:

RS-232 serial port:	COM1, COM2, ...
serial port/USB converter:	variable, see the device manager

Select the serial connection mode and communication port, set the speed and start the connection.

5. Check operation

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	12/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

```

Bash
MM6D * Remote controlled switching device * v0.1
Copyright (C) 2020 Pozsar Zsolt <pozsar.zsolt@szerafingomba.hu>
* Initializing GPIO ports...done.
* Connecting to wireless network.....done.
  device MAC address: EC:FA:BC:C1:0A:72
  my IP address:      192.168.1.21
  subnet mask:       255.255.255.0
  gateway IP address: 192.168.1.1
* Starting webserver...done.

```

Figure 4: Serial console with messages

You can check operation of controller with a web browser, use index.html in *testpage* folder.




Figure 5: Test page

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	13/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

6. Terms of use

This program is free software: you can redistribute it and/or modify it under the terms of the European Union Public License 1.1 version.

This program is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE.

You can read the full text of the license online. (Refer to Chapter III for references.)

7. Downloadable software package

The software package in .tar.gz format compressed file can be downloaded from the manufacturer's website or Github. (Refer to Chapter III for references.)

Name of package is: *mm6d-sw-0.2.tar.gz*.

Content of package - only important files:

mm6d-sw	
— documents	documentation
*	documentation
— libraries	external libraries
*.tar.gz	libraries in archive file
clone	clone script
— testpage	test page
index.html	startpage
— source	source code
mm6d.ino	source code
— LICENCE	terms of use
— README.md	short description

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	14/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

III. Related links

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	15/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.

1. Hardware

Full package	http://www.szerafingomba.hu/equipments/mm6d/mm6d-hw-200612-2.0.tar.gz
Download from Github	http://github.com/pozsarzs/mm6d-hw.git
Technical manual	http://www.szerafingomba.hu/equipments/mm6d/technical-manual-200612-0.2-2.0-en.pdf

Schematic and PCB draws (PDF):

Schematics	http://www.szerafingomba.hu/equipments/mm6d/sch_mm6d-1.pdf http://www.szerafingomba.hu/equipments/mm6d/sch_mm6d-2.pdf http://www.szerafingomba.hu/equipments/mm6d/sch_mm6d-3.pdf
PCB main board	http://www.szerafingomba.hu/equipments/mm6d/pcb_mm6d-1-sold.pdf http://www.szerafingomba.hu/equipments/mm6d/pcb_mm6d-1-comp.pdf http://www.szerafingomba.hu/equipments/mm6d/pcb_mm6d-1-silk.pdf
PCB display board	http://www.szerafingomba.hu/equipments/mm6d/pcb_mm6d-2-sold.pdf http://www.szerafingomba.hu/equipments/mm6d/pcb_mm6d-2-silk.pdf

2. Software

Software package	http://www.szerafingomba.hu/software/mm6d/mm6d-sw-0.2.tar.gz
Download from Github	http://github.com/pozsarzs/mm6d-sw.git

3. Terms of use

CC-BY-NC-4.0	https://creativecommons.org/licenses/by-nc/4.0/legalcode
CC-BY-NC-4.0	https://creativecommons.org/licenses/by-nc/4.0/
EUPL v1.2	https://eupl.eu/1.2/en/

4. Developer and manufacturer

Homepage	https://www.szerafingomba.hu
E-mail	info@szerafingomba.hu

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	16/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.


IV. Annexes

Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	17/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.


Content

1. Error messages and signs
2. Internal wiring
3. Schematic of main board
4. PCB solder side of main board
5. PCB component side of main board
6. PCB silkscreen of main board
7. Schematic of display board
8. PCB solder side of display board
9. PCB silkscreen of display board


Titles:	MM6D Remote controlled switching device	Rev.:	200612	Pages:	18/28
	Technical manual				
Name:	Pozsár Zsolt			Date:	2021.02.21.




Annex 2: Internal wiring




Annex 3: Schematic of main board



Annex 4: PCB solder side of main board




Annex 5: PCB component side of main board




Draw no.: 59/11/3		
Main board		
Pozsar Zsolt – http://www.szerafingomba.hu		
Sheet:		
File: mainboard.kicad_pcb		
Title: MM6D Remote controlled switching device		
Size: A4	Date: 2020-06-12	Rev: 200612
KiCad E.D.A.	kicad 4.0.5+dfsg1-4	Id: 1/1

Annex 6: PCB silkscreen of main board




Draw no.: 59/11/4		
Display board		
Pozsar Zsolt – http://www.szerafingomba.hu		
Sheet: /		
File: display.sch		
Title: MM6D Remote controlled switching device		
Size: A4	Date: 2020-06-12	Rev: 200612
KiCad E.D.A. kicad 4.0.5+dfsg1-4		Id: 1/1

Annex 7: Schematic of display board



Annex 8: PCB solder side of display board



Annex 9: PCB silkscreen of display board