MM7D Air quality measuring device

Technical manual

Hardware version: v200620
Software version: v0.1
Technical manual version: v1.0
Issue date: 2020.08.24.
Draw number: 59/12/1

Content

I. Hardware

1. Technical data

Supply voltage:	5 V DC SELV
Supply current:	max. 1 A
Isolation class:	Class III
Mechanical size:	71 x 71 x 27 mm
IP protection:	IP 20
Mass of cover:	termoplast (ABS)
Communication:	Wireless LAN,
	TTL 3.3V serial port
Getting data:	via HTTP
Administration:	via serial connection

2. General description

This device can measure temperature and humidity of growing house air, and detect some unwanted gas (CO2, NH3, NOx, alcohol, benzene etc.) and smoke, and has got three different color status LED. The measured values can be queried and LEDs can be turn on and off via wireless network via HTTP. The device box contains only the temperature and humidity sensor, the gas sensor must be connected with a short cable.

3. Schematic and PCB draws

The wiring diagrams of the device is shown in Annex 1, PCB draws are in Annex 2-4. You can download it as part of the complete documentation or in separate PDF, SVG and KiCAD formats from the developer/manufacturer's website. The Gerber files needed for production are included in the package.

4. Other draws and documents

Documentation package contents mechanical draw of used box in PDF.

5. Terms of use

6. Look of unit

a) Manuals and connectors

1. POWER signal light (white LED)
2. ACT signal light (blue LED)
3. STATUS signal light (green LED)
4. STATUS signal light (yellow LED)
5. STATUS signal light (red LED)
6. Power supply connector (P1)
7. Console connector (P2)
8. Cable of external gas sensor



Figure 1: Manuals and connectors

b) Internal construction

1. Microcontroller (U101)
2. DHT11 sensor (U103)
3. Connector of external gas sensor (U102)
4. Cable of external gas sensor (U102)
5. Power voltage connector (P1)
6. Console connector (P2)



Figure 2: Internal construction

c) Pinout of connectors

connector	pin	function	note
P1	center	+ 5 V supply voltage input	ø 5.5/2.1 mm power connector
	shield	GND	
P2	2	serial port RXD	DB9F
	3	serial port TXD	
	5	GND	
U102	1	+5 V	
	2	GND	
	4	Analog data	

7. Downloadable documentation

The complete documentation of the hardware in the .tar.gz format compressed file can be downloaded from the manufacturer's website or Github. (Refer to Chapter III for references.) Name of package is: *mm7d-hw-200620-1.0.tar.gz.*

Content of package - only important files:

```
mm7d-hw
├──cad_files                        KiCAD files
│     ├──mm7d                       documentation of PCB
│     │     mm7d.pro                    project file
│     │     mm7d.sch                    schematic draw
│     │     mm7d.kicad_pcb              PCB draw
│     │     mm7d.drl                    drilling file
│     │     mm7d-*.gbr                  Gerber files
│     └──wiring                     internal wiring
│           wiring.pro                 project file
│           wiring.sch                 schematic draw
├──documents                        documentation
│     mm7d_en.pdf                     Technical manual
│     pcb_*.pdf                       pcb draws
│     sch_*.pdf                       schematic draws
├──pictures                         pictures
│     mm7d.jpg                        look of the unit
│     pcb_*.svg                       PCB draws
│     sch_*.svg                       schematic draws
│
├──LICENCE                          terms of use
└──README.md                        short description
```

II. Software

1. General description

The device measures three characteristics of the air, which can be queried remotely and it has got three status LED, which can be set remotely.

The program displays initialization steps and error messages on the serial console.

When an HTTP request is received, the client's IP address and username argument are checked. If appropriate, perform a measurement or turn the status LEDs on / off. After displays the result on the web interface. Incoming requests are indicated by the flashing of the blue activity LED.

2. Setup

You can found source file of software in *software* directory. Before installing the program, you need to set these values:

```
// settings
const char* wifi_ssid       = "";
const char* wifi_password   = "";
const String uid            = "";
const String allowedaddress = "";
```

3. Installation

Use a serial cable and Arduino IDE software to install program to microcontroller. Before installation procedure unpack required libraries from *libraries* directory or clone from Github.com to *~/Arduino/libraries/*.

4. Using the device

The device operates automatically does not require any human intervention.

a) Data set and retrieval via HTTP

An example for how to use argument:

http://192.168.1.12/set/greenled/off?uid=bob

URL of information and data pages:

(On next page.)

URL	type	description	args.
http://*ipaddress*/	text/html	Start and information page	
http://*ipaddress*/version	text/plain	Get software name and version	
http://*ipaddress*/get/all		Get all data	uid
http://*ipaddress*/get/humidity		Get relative humidity in %	
http://*ipaddress*/get/temperature		Get temperature in °C	
http://*ipaddress*/get/unwantedgaslevel		Get rel. level of unwanted gases in %	
http://*ipaddress*/set/all/off		Switch off all LEDs	
http://ipaddress/set/greenled/off		Switch off green LED	
http://ipaddress/set/greenled/on		Switch on green LED	
http://ipaddress/set/redled/off		Switch off red LED	
http://ipaddress/set/redled/on		Switch on red LED	
http://ipaddress/set/yellowled/off		Switch off yellow LED	
http://ipaddress/set/yellowled/on		Switch on yellow LED	



Figure 3: Start page

b) Connect to console via serial port

The console connector of the device and the RS-232 serial port of the computer must be connected by means of a level shifter adapter with a null modem cable. The level shifter adapter is required due to the different voltages of the logic levels (0 V / 3.3 V and -12 V / + 12 V).

The console connector of the device and the USB port of the computer must be connected using an Adafruit 954, FTDI TTL-232R-RPI or similar 3.3V serial / USB cable.

Connection parameters

speed (baudrate):	115 200 bps
data bits:	8
parity bit:	no
stop bit:	1
flow control:	no

Connect via linux terminal

Name of ports (device files):

RS-232 serial port:	/dev/ttyS0, /dev/ttyS1, ...
serial/USB converter:	/dev/ttyUSB0, /dev/ttyUSB1, ...

Make sure you are a member of the dialout group:

```
username@localhost$ id
```

If not, set up your group membership:

```
username@localhost$ sudo usermod -a -G dialout username
```

Connect with GNU Screen program:

```
username@localhost$ screen port_name 115200
```

Connect with Minicom program:

```
username@localhost$ minicom -b 115200 -o -D port_name
```

Connect with Windows terminal (Putty)

Name of ports:

RS-232 serial port:	COM1, COM2, ...
serial port/USB converter:	variable, see the device manager

Select the serial connection mode and communication port, set the speed and start the connection.



Figure 4: Serial console with messages



Figure 5: Test page

5. Check operation

You can check operation of controller with a web brower, use index.html in *testpage* folder.

6. Terms of use

This program is free software: you can redistribute it and/or modify it under the terms of the European Union Public License 1.1 version.

This program is distributed in the hope that it will be useful, but WITHOUT ANY WARRANTY; without even the implied warranty of MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE.

You can read the full text of the license online. (Refer to Chapter III for references.)

7. Downloadable software package

The software package in .tar.gz format compressed file can be downloaded from the manufacturer's website or Github. (Refer to Chapter III for references.)

Name of package is: *mm7d-sw-0.1.tar.gz.*

Content of package - only important files:

```
mm7d-sw
     ├──documents                    documentation
     │       *                            documentation
     ├──libraries                    external libraries
     │       *.tar.gz                     libraries in archive file
     │       clone                        clone script
     ├──testpage                     test page
     │       index.html                   startpage
     ├──source                       source code
     │       mm7d.ino                     source code
     │
     ├──LICENCE                      terms of use
     └──README.md                    short description
```

III. Related links

1. Hardware

Full package	http://www.szerafingomba.hu/equipments/mm7d/mm7d-hw-200620-1.0.tar.gz
Download from Github	http://github.com/pozsarzs/mm7d-hw.git
Technical manual	http://www.szerafingomba.hu/equipments/mm7d/technical-manual-200620-0.1-1.0-en.pdf

Schematic and PCB draws (PDF):

Schematics	http://www.szerafingomba.hu/equipments/mm7d/sch_mm7d-1.pdf
	http://www.szerafingomba.hu/equipments/mm7d/sch_mm7d-2.pdf
PCB solder side	http://www.szerafingomba.hu/equipments/mm7d/pcb_mm7d-sold.pdf
PCB component side	http://www.szerafingomba.hu/equipments/mm7d/pcb_mm7d-comp.pdf
PCB silkscreen	http://www.szerafingomba.hu/equipments/mm7d/pcb_mm7d-silk.pdf

2. Software

Software package	http://www.szerafingomba.hu/softwares/mm7d/mm7d-sw-0.1.tar.gz
Download from Github	http://github.com/pozsarzs/mm7d-sw.git

3. Terms of use

CC-BY-NC-4.0	https://creativecommons.org/licenses/by-nc/4.0/legalcode
CC-BY-NC-4.0	https://creativecommons.org/licenses/by-nc/4.0/
EUPL v1.2	https://eupl.eu/1.2/en/

4. Developer and manufacturer

Homepage	https://www.szerafingomba.hu
E-mail	info@szerafingomba.hu

IV. Annexes

Content

Sign	Message	Web	Console	RED light	Sound
E01	Failed to read CO_2 sensor!	value: 999	yes	no	beep
E02	Failed to read T/RH sensor!	value: 999	yes	no	beep
E03	Authentication error!	yes	yes	no	2x beep
E04	Not allowed client IP address!	yes	yes	no	3 x beep
E05	Page not found!	yes	yes	no	no

Annex 1: Error messages and signs



Draw no.: 59/12/6

Internal wiring

Pozsar Zsolt – http://www.szerafingomba.hu

Sheet: /
File: wiring.sch

Title: MM7D Air quality measuring device

Size: A4	Date: 2020-06-20	**Rev: 200620**
KiCad E.D.A. kicad 4.0.5+dfsg1-4		Id: 1/1

Annex 2: Internal wiring



Annex 3: Schematic of printed circuit board



Draw no.: 59/12/3

Pozsar Zsolt – http://www.szerafingomba.hu

Sheet:
File: mm7d.kicad_pcb

Title: MM7D Air quality measuring device

Size: A4	Date: 2020-06-20	**Rev: 200620**
KiCad E.D.A. kicad 4.0.5+dfsg1-4		Id: 1/1

Annex 4: PCB solder side



Draw no.: 59/12/3

Pozsar Zsolt – http://www.szerafingomba.hu

Sheet:
File: mm7d.kicad_pcb

Title: MM7D Air quality measuring device

Size: A4	Date: 2020-06-20	**Rev: 200620**
KiCad E.D.A. kicad 4.0.5+dfsg1-4		Id: 1/1

Annex 5: PCB component side



Draw no.: 59/12/3		
Pozsar Zsolt – http://www.szerafingomba.hu		
Sheet: File: mm7d.kicad_pcb		
Title: MM7D Air quality measuring device		
Size: A4	Date: 2020-06-20	**Rev: 200620**
KiCad E.D.A. kicad 4.0.5+dfsg1-4		Id: 1/1

Annex 6: PCB silkscreen