STUDENT HANDOUT ▪ Setup & Quick Reference

Renode Lab on GitHub Codespaces

Three embedded systems — Cortex-M4, RISC-V Linux SoC, custom RV64 — emulated entirely in your browser.

Welcome. Over the next few hours you will simulate three different embedded systems — a Cortex-M4 microcontroller, a multi-core RISC-V Linux SoC, and a custom 9-line RV64 SoC of your own — all inside a browser tab, with **nothing installed on your laptop**.

This document walks you through the setup once. After that, everything you need is in the per-lab `README.md` files in the repository.

1. What you need before starting

1.1 A personal GitHub account

If you don't already have one, create a **free personal account** at https://github.com/join. School-issued accounts work too, but a personal account is preferred so the Codespace and any edits you make follow you after the course ends.

GitHub's free tier includes:

Resource	Free quota / month
Codespaces compute	120 core-hours (≈ 60 hours on a 2-core machine)
Codespaces storage	15 GB-month

The whole renode-lab fits comfortably in those limits if you **stop your Codespace** when you take a break and **delete it** when you're done for the day. Leaving a Codespace running idle burns compute hours; leaving it created-but-stopped burns storage. We'll cover both at the end.

1.2 A modern web browser

Chrome, Firefox, Safari, or Edge — anything from the last two years. You will spend the entire lab in two browser tabs:

1. The **VS Code** tab that GitHub auto-opens (your terminal + editor live here).
2. The **noVNC desktop** tab on port 6080 (Renode's GUI analyzers — UART windows, GPIO/LED indicators, etc.).

1.3 Working knowledge of basic Linux

You should be comfortable doing all of these from a terminal without looking them up:

- Navigating: `pwd`, `cd`, `ls`, `ls -la`
- Reading files: `cat`, `less`, `head`, `tail`, `tail -f`
- Editing files: `nano`, `vim`, or just VS Code's editor pane
- Pipes and redirection: `|`, `>`, `>>`, `2>&1`
- Background jobs: `&`, `Ctrl-C`, `Ctrl-Z`, `jobs`, `fg`
- Inspecting processes: `ps`, `pgrep -af <name>`
- Reading exit codes and recognising errors

You do **not** need to know Docker, Kubernetes, or anything about Codespaces internals.

1.4 Familiarity with basic SoC concepts

You should already understand, at a hand-wave level:

- A CPU **fetches** instructions from memory addresses, then **executes** them. The address it's about to fetch from is the **program counter (PC)**.
- A **bus** lets the CPU talk to memory regions and **memory- mapped peripherals** (UART, GPIO, timers,

interrupt controller, etc.). Each peripheral lives at a known base address.

- A **UART** sends bytes one wire at a time; on most cores there's a "transmit holding register" and a "line status register" with a `TX-FIFO-empty` bit.
- A **GPIO port** has registers for direction (input/output), output data (`ODR`), and atomic set/reset (`BSRR` on STM32).
- An **ELF** is a packaged binary with a known **entry point**; on Cortex-M, after reset the CPU loads SP from address `0x0` and PC from address `0x4` (the vector table).
- A **bootloader** (BBL, OpenSBI, U-Boot) initialises the SoC enough to hand control to a kernel.
- A **kernel** schedules processes; a **userspace shell** like BusyBox is the program you type commands into.

Lab 01 will exercise the first four bullets, lab 02 the last three, and lab 03 lets you build the bus + RAM + UART picture from nine lines of declarative platform description.

2. First launch (only do this once)

2.1 Open the lab repository

Visit https://github.com/prag79/renode-lab. Sign in to your GitHub account if prompted.

2.2 Click the "Open in GitHub Codespaces" badge

Near the top of the page you'll see this badge:

Click it. GitHub will:

1. Show a **"Create codespace"** screen — accept the defaults (2-core machine, 8 GB RAM, 32 GB storage). Click **Create codespace**.
2. Spin up a small Linux VM somewhere in their cloud (≈30 s).
3. Pull the prebuilt image `ghcr.io/prag79/renode-lab:latest` from the GitHub Container Registry (≈30–60 s, only on first launch — afterwards it's cached).
4. Open VS Code in your browser, attached to the running container.

A second tab will auto-open at `*.app.github.dev:6080/vnc.html` — that's the noVNC desktop. If it shows "Failed to connect", give it 10 seconds and click **Connect** in the noVNC page.

2.3 Verify the environment

In the VS Code terminal (open one with **Ctrl-‘** if it isn't already), type:

```
lab list
```

You should see the three available labs:

```
Available labs:
  01       - bundled STM32F4 demo (sanity check)
  02       - Linux on SiFive HiFive Unleashed (RISC-V)
  03       - custom RV64 SoC + bare-metal hello world
  monitor  - plain Renode interactive monitor
```

Then run lab 01:

```
lab 01
```

You should land at a `(STM32F4_Discovery)` prompt within a couple of seconds. That's the **Renode monitor** — Renode's interactive command line. From here, type:

```
start
sysbus.cpu PC
sysbus.cpu PC
```

If the second `sysbus.cpu PC` prints a different value than the first, your environment is healthy. Type `quit` to exit.

If anything above fails, see **§ 5 Troubleshooting**.

3. The three exercises

Each lab has its own detailed `README.md` with a 7-section walkthrough — bring up, what just happened, first commands, headless UART recipes, useful monitor command tables, mini- experiments, and clean exit.

Lab	Time	What you'll do	Detailed README
01	~20 min	Boot a bundled Contiki firmware on a simulated STM32F4 Discovery board. Read UART, single-step the CPU, blink the on-board LED from the simulator.	`labs/01-bundled-stm32f4/README.md`
02	~30 min	Boot an unmodified RISC-V Linux kernel (5 cores, OpenSBI, BusyBox userspace) on the SiFive HiFive Unleashed model. Poke around `/proc`, trace UART traffic at the bus level.	`labs/02-linux-on-hifive/README.md`
03	~45 min	Cross-compile bare-metal C for RV64. Run it on a 9-line custom SoC you can edit. Add a second peripheral with one line.	`labs/03-custom-soc/README.md`

Do them **in order**. Each one introduces a concept that the next assumes (the three Renode primitives `mach create`, `LoadPlatformDescription`, `LoadELF` + `start`).

4. Where your edits live

The `lab NN` command does not run the lab from `/labs/...` directly. On first invocation it copies the lab into a **writable scratch tree** under your home directory and runs it from there:

Path	What it is	Survives Codespace stop?	Survives container rebuild?	Survives Codespace delete?
`/labs/<lab-name>/`	Read-only image content	yes	no	no
`~/work/<lab-name>/`	Editable copy made by `lab NN`	**yes**	no	no
`/workspaces/renode-lab/`	The cloned git repo	yes	yes	only if `git push`-ed

Practical rules:

- If you just want to tweak a `.resc` or a `hello.c` and re-run, edit `~/work/<lab-name>/...`. The next `lab NN` reuses your edits (`cp -ru` is idempotent — it never overwrites existing files).
- If you want changes to **outlive Codespace deletion**, copy them into `/workspaces/renode-lab/labs/...` and `git push`. That requires you to fork the repo first (GitHub will offer this when you try to push).

5. Troubleshooting

Symptom	Likely cause	Fix
`lab 01` prompt appears but `sysbus.cpu PC` keeps returning `0x00000000`	You haven't typed `start` yet — the bundled `.resc` loads the ELF but doesn't release the CPU from reset	Type `start` once.
The terminal is unreadable: UART log lines stream non-stop and your typing doesn't echo	UART output is being mirrored to the console at INFO level	`pause` (type blindly, then **Enter**), then `logLevel 3 sysbus.uart4`, then `start`.

Symptom	Likely cause	Fix
noVNC tab shows "Failed to connect" or HTTP 502	Port 6080's WebSocket handshake hadn't completed when the tab opened	Wait 10 s and click **Connect** in the noVNC page. If still broken: in VS Code's **Ports** panel, right-click port 6080 → **Port Visibility** → **Public** (or sign in to the popup).
Browser tab opens but shows the noVNC welcome screen, not a desktop	URL is missing the path	Append `/vnc.html` to the URL, then **Connect**.
`pgrep -af 'Xvfb|fluxbox|x11vnc|websockify'` shows fewer than four processes	The headless desktop didn't fully start	Run `/usr/local/bin/entrypoint.sh true`. Check the per-service logs in `/tmp/Xvfb_:1.log`, `/tmp/fluxbox.log`, `/tmp/x11vnc_-display_:1.log`, `/tmp/websockify.log`.
`lab` does nothing or says command not found	You're in a shell where `/usr/local/bin` isn't on `$PATH` (rare)	Run it with the full path: `/usr/local/bin/lab list`.
Codespace fails to start with "Failed to pull image"	GHCR rate-limited you or the image package is private	Visit https://github.com/prag79?tab=packages → `renode-lab` → check it's **Public**. Retry.
You changed something under `/labs/...`, ran `lab NN`, and your change had no effect	Edits to `/labs/...` are overlaid on a read-only image and discarded on container rebuild — the dispatcher uses `~/work/<lab-name>/...`	Edit the file under `~/work/<lab-name>/...` instead, then `lab NN` again.

6. Cost discipline (so you don't burn quota)

GitHub will not charge you anything as long as you stay inside the free tier. Two habits keep you there:

1. **Stop the Codespace when you walk away.** In the bottom-left of VS Code (or the **Codespaces** menu in your GitHub profile) click **Stop codespace**. Compute billing pauses immediately. Storage keeps ticking at ~$0.07 / GB / month — tiny, but cumulative.
2. **Delete the Codespace when you're done for the day** — but only after committing or copying out anything you want to keep. From your laptop terminal:

   ```
   gh codespace list                                  # find the name
   gh codespace delete --codespace <name> --force
   ```

   …or use the web UI at https://github.com/codespaces.

You can always recreate a Codespace from the badge in the README. The first launch is the only slow one (~60 s); after that it's instant.

7. Where to go after the labs

- The Renode user docs: https://renode.readthedocs.io/
- Renode's bundled platform `.repl` files for ~100 other boards: `/opt/renode/platforms/` inside your Codespace
- The Antmicro YouTube channel for SoC-modelling walkthroughs.

If you find a bug or have an improvement, open a PR against https://github.com/prag79/renode-lab. The full toolchain (lab content → Docker image → GHCR → Codespaces) is in this one repository and welcomes contributions.

Quick reference card (print this if you want a single-page cheat sheet):

```
Open lab:           click the badge in the README
Verify install:     lab list && lab 01 -> start -> sysbus.cpu PC -> quit
Edit + re-run:      edit ~/work/<lab>/..., then lab NN
Read UART:          (in monitor) sysbus.uartN CreateFileBackend @/tmp/uartN.log true
                    (in another terminal) tail -f /tmp/uartN.log
Quiet log spam:     logLevel 3 sysbus.uartN
Pause/resume CPU:   pause / start
Read PC:            sysbus.cpu PC
Step one insn:      sysbus.cpu Step
Reset firmware:     machine Reset
Exit Renode:        quit
Stop Codespace:     bottom-left of VS Code -> Stop codespace
Delete Codespace:   gh codespace delete -c <name> --force
```