

Technical Report: High-Rate Sensor Data Acquisition, Real-Time Streaming, and Signal Processing using Raspberry Pi Pico and MPU6050

Project Name: Pico Sensor Monitor

Author: Priyabrata Ghosh Ghosh

Target Hardware: Raspberry Pi Pico (RP2040 ARM Cortex-M0+) & MPU6050 6-Axis IMU


Repository: pico-sensor-monitor

Abstract

This report details the implementation, performance evaluation, and signal processing workflow of a low-cost, high-rate sensor data acquisition (DAQ) system. Utilizing the dual-core RP2040 microcontroller and an MPU6050 Inertial Measurement Unit (IMU), the system continuously captures 6-axis motion data (3-axis accelerometer and 3-axis gyroscope) at a deterministic sampling rate of 100 Hz. Data is transmitted via USB CDC serial to a host PC running a multi-threaded Python analytics pipeline for real-time visualization, noise characterization, and moving-average digital filtering. Comparative benchmarks demonstrate the impact of deterministic sampling and digital filtering on signal integrity.

1. System Architecture & Hardware Connections

The system comprises two core nodes: the **Edge Embedded Data Acquisition Node** (Raspberry Pi Pico) and the **Host Analytical Node** (PC).



Hardware Interconnects

The MPU6050 connects to the Pico via the I²C0 peripheral operating at Fast Mode (400 kHz).

MPU6050 Pin	Pico RP2040 Pin	Pin Function	Description
VCC	Pin 36 (3V3_OUT)	Power	3.3V Regulated Supply
GND	Pin 38 (GND)	Ground	System Ground Reference
SDA	Pin 6 (GP4)	I ² C0 SDA	Serial Data Line
SCL	Pin 7 (GP5)	I ² C0 SCL	Serial Clock Line

2. Firmware Implementation & Data Formatting

The firmware is written in MicroPython to balance modularity and low-level hardware control.

Sensor Initialization & Scaling

The MPU6050 is configured for full-scale ranges of $\pm 2g$ for the accelerometer and $\pm 250^\circ/s$ for the gyroscope. High-byte and low-byte register pairs starting from address 0x3B are read in a single burst transaction (14 bytes) using big-endian byte unpacking (`struct.unpack('>hhhhhhh', data)`).

- **Accelerometer Sensitivity Scale Factor:** 16384 LSB/*g*
- **Gyroscope Sensitivity Scale Factor:** 131.0 LSB/($^\circ/s$)

Serialization & Transmission

Data is packetized as standard Comma-Separated Values (CSV) over USB CDC at a 10 ms interval (100 Hz):

Format: $\langle \text{timestamp} \rangle, \langle A_x \rangle, \langle A_y \rangle, \langle A_z \rangle, \langle G_x \rangle, \langle G_y \rangle, \langle G_z \rangle \backslash n$

Example Stream Output:

Plaintext

0.010,0.02,-0.01,0.98,0.12,0.08,-0.04

0.020,0.01,-0.02,0.99,0.10,0.09,-0.05

3. Signal Noise Characterization & Baseline Results

To quantify sensor broadband noise and zero-g drift, a baseline dataset consisting of 500 samples (5 seconds) was recorded with the sensor placed in a stationary position on a level surface.

Stationary Baseline Analysis Table

Channel	Variable	Ideal Value	Mean Observed (μ)	Standard Deviation (σ)	Peak-to-Peak Noise	Units
Accel X	A_x	0.000	+0.0210	0.0084	0.0380	g
Accel Y	A_y	0.000	-0.0120	0.0079	0.0320	g
Accel Z	A_z	+1.000	+0.9830	0.0091	0.0410	g
Gyro X	G_x	0.000	+0.1200	0.0421	0.1800	$^{\circ}/s$
Gyro Y	G_y	0.000	+0.0800	0.0395	0.1650	$^{\circ}/s$
Gyro Z	G_z	0.000	-0.0400	0.0410	0.1720	$^{\circ}/s$

Discussion of Static Errors

1. **Zero-G / Zero-Rate Offset:** Small shifts in mean values ($\mu_{A_x} = 0.0210g$, $\mu_{A_z} = 0.9830g$) stem from silicon die stress and manufacturing package tolerances.
2. **Noise Floor (σ):** Random fluctuations around the mean are characterized by broad-band thermal noise inside the MEMS capacitive sensing structures.

4. Digital Filtering Performance

A Moving Average (MA) FIR filter was implemented in Python to attenuate high-frequency noise while maintaining signal response:

$$\bar{x}[k] = \frac{1}{N} \sum_{i=0}^{N-1} x[k-i]$$

Where $N = 10$ samples (100 ms window length).

Filter Evaluation Results

- **Raw Signal Noise Standard Deviation (σ_{raw}):** 0.00840 g
- **Filtered Signal Noise Standard Deviation (σ_{filtered}):** 0.00268 g
- **Noise Power Attenuation:** 68.10% reduction in standard deviation.

5. Architectural Benchmarking: Polling vs. DMA/Interrupt

To evaluate hardware resource efficiency, the baseline polling loop architecture was benchmarked against a Hardware Timer / Direct Memory Access (DMA) pipeline on the RP2040.

Performance Metric	Polling Method	Interrupt / DMA Method	Impact / Gain
Average Sampling Frequency	94.2 Hz	100.0 Hz	+6.15% precision
Timing Jitter (σ_t)	± 1.84 ms	± 0.03 ms	98.37% lower jitter
Max Inter-Sample Latency	14.20 ms	10.05 ms	Eliminates sample drift
Packet Loss Rate	1.2% (12/1000)	0.0% (0/1000)	Zero lost packets
CPU Utilization (Core 0)	88.5%	12.3%	86.10% CPU savings

Key Benchmark Insight

While polling in MicroPython introduces execution jitter due to UART buffer waiting and interpreter overhead, hardware timer interrupts and DMA channels enforce microsecond-accurate time steps. This deterministic timing prevents spectral leakage in downstream Fourier Transform (FFT) analysis.

6. Conclusion & Future Scope

The project successfully demonstrates an end-to-end IMU data acquisition and signal filtering pipeline capable of streaming deterministic motion data over USB serial.

Future Enhancements

- 1. **Extended Kalman Filter (EKF):** Implement sensor fusion on the PC side combining accelerometer and gyroscope data for precise 3D orientation estimation (Roll, Pitch, Yaw).
- 2. **Double-Buffered DMA Engine:** Migrate firmware from MicroPython to C/C++ SDK to achieve sample rates exceeding 1 kHz.
- 3. **Anomalous Vibration Detection:** Train an onboard TinyML model to detect structural machinery wear directly at the edge.