

EX NO: 1b	CHARACTERISTICS STUDY OF SIDE BAND POWER AND FREQUENCIES IN AM USING MATLAB
DATE:	

PROGRAM (MATLAB CODE)

```

clc;
clear;
close all;
Am=1;
fm=500;
Ac=5;
fc=5000;
fs=20*fc;
t=0:1/fs:4/fm;
m = Am*sin(2*pi*fm*t);
c = Ac*sin(2*pi*fc*t);
mu = Am/Ac;
am = Ac*(1+mu*sin(2*pi*fm*t)).*sin(2*pi*fc*t);
dem = abs(hilbert(am)); dem = dem-mean(dem);
N=length(am); f=linspace(-fs/2,fs/2,N);
AM_FFT=abs(fftshift(fft(am)))/N;
USB=fc+fm; LSB=fc-fm;
Pc=Ac^2/2; Psb=(mu^2*Pc)/4;
figure('Name','AM Modulation','NumberTitle','off');

```

```

subplot(3,2,1), plot(t,m), title('Message'),
grid on subplot(3,2,2), plot(t,c),
title('Carrier'), grid on subplot(3,2,3),
plot(t,am), title('AM Signal'), grid on
subplot(3,2,4), plot(t,dem),
title('Demodulated'), grid on
subplot(3,2,5), plot(f,AM_FFT), xlim([fc-3*fm fc+3*fm]),
title('Sidebands'), grid on subplot(3,2,6), bar([Pc Psb Psb]),
set(gca,'XTickLabel',{'Carrier','USB','LSB'}), title('Power'), grid on
fprintf('μ=%.2f | USB=%d Hz | LSB=%d Hz | Pc=%.2f W | Ps
b=%.3f W\n',mu,USB,LSB,Pc,Psb);

```

