CONTACTLESS HEARTBEAT AND RESPIRATION MONITORING USING 2.4 GHZ WIFI CHANNEL STATE INFORMATION (CSI) WITH NODEMCU AND ESP32

P. Venkata Kishor Kumar Reddy (Lead Project Investigator)

K. Kamalesh • T. Perumal (Co-Investigators)

Department of Electronics and Communication Engineering / Computer Science & Engineering

Koneru Lakshmaiah Education Foundation (KL University), Vaddeswaram, Andhra Pradesh, India

---

Authors & Project Team:

- **P. Venkata Kishor Kumar Reddy** (Lead Project Investigator)
- **K. Kamalesh** (Co-Investigator)
- **T. Perumal** (Co-Investigator)

Department: Electronics and Communication Engineering / Computer Science & Engineering

Institution: Koneru Lakshmaiah Education Foundation (KL University), Vaddeswaram, Andhra Pradesh, India

Academic Year: 2026

ABSTRACT

Traditional cardiopulmonary vital signs monitoring requires contact sensors—such as wet adhesive gel ECG electrodes, smartwatches, or tight photoplethysmography (PPG) finger clips. While accurate, these contact-based devices cause skin irritation, restrict movement, and easily detach during sleep or continuous healthcare monitoring.

In this project, I developed and experimentally validated a completely **contactless vital signs radar** using low-cost, off-the-shelf microcontrollers: one **NodeMCU (ESP8266)** transmitter and one **ESP32** receiver operating on **2.4 GHz WiFi (Channel 11)**. Instead of relying on crude Received Signal Strength Indicator (RSSI) numbers, my system captures **Channel State Information (CSI)** directly from the physical radio layer (PHY) of incoming 802.11n packets at 80 Hz. When radio waves travel across the room and reflect off the human chest, the microscopic mechanical vibrations caused by breathing (5–12 mm) and systolic cardiac contractions (0.2–0.5 mm) introduce subtle constructive and destructive phase shifts across individual OFDM subcarrier frequencies.

The NodeMCU broadcasts continuous high-power (+20.5 dBm) ESP-NOW beacon frames. The ESP32 receiver demodulates the raw CSI subcarrier matrix in hardware and streams real-time telemetry over a 115200 baud UART link to a Python desktop dashboard. My signal processing engine filters ambient college hostel noise, cancels ceiling fan vibrations (15 Hz) using common-mode subcarrier median subtraction, separates breathing from cardiac waves with zero-phase Butterworth bandpass filters, and computes dominant frequencies using Welch Power Spectral Density (PSD).

In live experimental testing against a commercial medical fingertip pulse oximeter:

- **Ground Truth Sensor: 64.0 BPM**
- **My WiFi CSI Radar: 65.0 BPM**

- **Absolute Error: $\pm 1.0\text{ BPM}$ (~98.5% Accuracy)**
- **Signal Quality Index (SQI): $> 90\%$** in an active room with operating ceiling fans and campus router interference.

---

1. INTRODUCTION & MOTIVATION

Monitoring Heart Rate (HR in beats per minute - BPM) and Respiration Rate (RR in breaths per minute - RPM) is essential for health assessment, ICU observation, post-surgery recovery, and detecting life-threatening conditions like sleep apnea or arrhythmias.

```
Conventional Contact-Based Monitoring:[ Human Body ] <—— Adhesive Gel Electrodes ——> [ Bulky ECG
```

Why Existing Technologies Fall Short:

1. **ECG (Electrocardiography):** Requires sticky adhesive electrodes with conductive gel on bare skin. This causes skin rashes over multi-hour tracking and restricts patient movement.

2. **PPG (Finger Oximeter / Smartwatch):** Requires tight skin contact. Finger clips frequently slip off when a patient turns in bed, and smartwatches require daily battery charging.

3. **Specialized mmWave Radars (60 GHz / 77 GHz):** Although contactless, radar evaluation boards (like Texas Instruments IWR6843) cost $200–$400, require specialized antennas, and are not ubiquitous in household environments.

The WiFi Solution

Standard 2.4 GHz WiFi is already present in virtually every home, hospital, and college hostel. By writing custom firmware for inexpensive ($4) IoT microcontrollers, we can turn everyday WiFi signals into a non-invasive biometric radar.

---

2. RELATED WORK: WHY RSSI FAILS AND CSI SUCCEEDS

Previous attempts at WiFi sensing often relied on **Received Signal Strength Indicator (RSSI)**. However, RSSI has fundamental physical limitations:

Feature	Standard WiFi RSSI	Channel State Information (CSI) (My System)		
Data Nature	1 single average integer (e.g. `-65 dBm`)	Complex matrix $H(f, t) = \	H\	e^{j\angle H}$
Number of Channels	1 coarse value for the whole 20 MHz band	**56 separate orthogonal OFDM subcarriers**		
Sensitivity	Cannot detect 0.2 mm vibrations	Detects **sub-millimeter** chest wall displacements		
Multipath Effect	Destroyed by multi-path interference	**Exploits multipath reflections** to amplify signals		
Accuracy	Fluctuate wildly from room movements	Clinical-grade agreement ($\pm 1\text{ BPM}$)		

RSSI is like looking at a dark room through sunglasses—you only perceive overall light levels. CSI provides **56 distinct laser beams** at slightly different frequencies. When your heart pulses, specific subcarriers experience sharp constructive interference, allowing us to isolate the heartbeat cleanly even in noisy environments.

---

3. WORKING PRINCIPLE & THEORETICAL PHYSICS

3.1 Carrier Frequency & Micro-Phase Modulation

WiFi Channel 11 operates at a center frequency of $f_c = 2.462\text{ GHz}$. The wavelength λ is:

$$\lambda = \frac{c}{f_c} = \frac{3 \times 10^8\text{ m/s}}{2.462 \times 10^9\text{ Hz}} \approx 0.1218\text{ m} = 12.18\text{ cm}$$

The chest undergoes two distinct mechanical motions:

1. **Respiration (Breathing):** Thoracic cavity expansion shifts the chest skin forward by **5.0 mm to 12.0 mm** at $0.15 - 0.35\text{ Hz}$ ($9 - 21\text{ breaths/min}$).

2. **Cardiac Ballistocardiogram (Heartbeat):** Every ventricular contraction ejects blood into the aorta, producing a microscopic skin displacement of only **0.2 mm to 0.5 mm** at $0.8 - 2.0\text{ Hz}$ ($50 - 120\text{ beats/min}$).

When the chest reflects the incoming radio wave, the round-trip path changes by $2\Delta d(t)$. This induces a phase shift $\Delta \phi(t)$:

$$\Delta \phi(t) = \frac{2\pi}{\lambda} [2\Delta d(t)] = \frac{4\pi \Delta d(t)}{\lambda}$$

- **For Breathing ($\Delta d \approx 6.0\text{ mm}$):**

  $$\Delta \phi_{\text{resp}} = \frac{4\pi \times 6.0\text{ mm}}{121.8\text{ mm}} \approx 0.619\text{ rad} \approx 35.5^\circ$$

- **For Heartbeat ($\Delta d \approx 0.3\text{ mm}$):**

  $$\Delta \phi_{\text{cardiac}} = \frac{4\pi \times 0.3\text{ mm}}{121.8\text{ mm}} \approx 0.031\text{ rad} \approx 1.77^\circ$$

  This 1.8° phase rotation modulates the received RF amplitude in the millivolt range, creating a high-frequency cardiac ripple riding on top of the slow breathing wave.

3.2 First Fresnel Zone (FFZ) Geometry

To achieve maximum reflection sensitivity, the subject must be positioned inside the **First Fresnel Zone (FFZ)**:

$$r_1 = \sqrt{\frac{\lambda \cdot d_1 \cdot d_2}{d_1 + d_2}}$$

For a board separation distance $D = d_1 + d_2 = 1.0\text{ m}$ with the subject positioned symmetrically ($d_1 = d_2 = 0.5\text{ m}$):

$$r_1 = \sqrt{\frac{0.1218 \times 0.5 \times 0.5}{1.0}} = \sqrt{0.03045} \approx 0.174\text{ m} = 17.4\text{ cm}$$

Sitting within $30 - 50\text{ cm}$ of the line connecting the two antennas places the human chest directly on the boundary of the First Fresnel Ellipse, producing the largest amplitude fluctuations.

```
                        FIRST FRESNEL ZONE (FFZ) GEOMETRY         [ NodeMCU TX ]
```

---

4. SYSTEM ARCHITECTURE & FLOWCHARTS

4.1 End-to-End System Flowchart

```
flowchart TD    A["NodeMCU TX (ESP8266)<br/>80 Hz Beacons @ +20.5 dBm<br/>Channel 11"] -->|2.4 GHz
```

---

5. SOFTWARE & PROGRAM WALKTHROUGH

The project codebase is organized into modular firmware and software components:

```
WIFI_HEARTBEAT/├── firmware/│   ├── nodemcu_tx/nodemcu_tx.ino    # NodeMCU 80 Hz high-power transm
```

5.1 NodeMCU Transmitter Program (`nodemcu_tx.ino`)

* **Radio Configuration:** Locks to Channel 11 (2.462 GHz).

* **Maximum RF Power:** Executes `WiFi.setOutputPower(20.5)` to output +20.5 dBm (112 mW), allowing the transmitter to overpower ambient campus router noise.

* **Continuous Beaconing:** Uses `micros()` timing to fire an ESP-NOW broadcast frame to `FF:FF:FF:FF:FF:FF` every $12,500\text{ }\mu\text{s}$ (80 Hz).

* **Watchdog Protection:** Calls `yield()` on every loop cycle to keep the ESP8266 background software watchdog happy, ensuring 24/7 continuous transmission without freezes.

5.2 ESP32 Receiver Program (`esp32_rx.ino`)

* **Promiscuous Mode:** Sets `esp_wifi_set_promiscuous(true)` and locks strictly to Channel 11 without running background network scans.

* **Hardware CSI Engine:** Registers `esp_wifi_set_csi_rx_cb()` with LLTF and HT-LTF preamble capture enabled.

* **Campus Noise Rejection Gate:** Evaluates incoming RSSI. Any packet with $\text{RSSI} < -95\text{ dBm}$ is dropped, ensuring distant corridor beacons do not corrupt the local radar channel.

* **Subcarrier Telemetry:** Demodulates real (I) and imaginary (Q) components across 16 active subcarriers and streams them over UART at 115200 baud in formatted CSV strings:

`CSI,,,,,,,...,`

5.3 Digital Signal Processing Engine (`signal_processor.py`)

1. **Dynamic fs Estimation:** Calculates the median timestamp delta (Δt) between incoming packets: $f_s = 1.0 / \Delta t$ (nominally 80.0 Hz).

2. **Ceiling Fan Rejection (Common-Mode Median Subtraction):** A 3-blade ceiling fan spinning at 300 RPM causes rhythmic reflections at ~15 Hz across all subcarriers. By computing the median across all 16 subcarriers and subtracting it:

$$\tilde{A}_k(t) = A_k(t) - \text{median}_{j=1..16}\left(A_j(t)\right)$$

room-wide ambient flicker cancels out, preserving the localized chest reflection.

3. **Respiration Filter:** 2nd-order zero-phase Butterworth bandpass filter ($0.10 - 0.45\text{ Hz}$).

4. **Cardiac Filter:** 3rd-order Butterworth bandpass filter ($0.80 - 2.00\text{ Hz}$) applied after subtracting the estimated breathing waveform.

5. **Welch Power Spectral Density (PSD):** Evaluates windowed Welch periodograms to extract the dominant cardiac frequency f_{cardiac}, converting it to BPM:

$$\text{BPM} = f_{\text{cardiac}} \times 60$$

6. **Signal Quality Index (SQI):** Computes the spectral purity ratio between the peak cardiac power and total in-band spectral energy. Rises to **$>90\%$** during steady posture.

---

6. COMMANDS RUN TO EXECUTE THE SYSTEM

Here are the exact commands I run in Windows PowerShell to set up and launch the system:

```
# Step 1: Install required Python dependenciespip install pyserial pyqtgraph PyQt5 numpy scipy esp
```

---

7. HOW I SOLVED REAL-WORLD CAMPUS CHALLENGES

Challenge 1: Campus WiFi Router Jamming & Weak Signal (-93 dBm)

* **The Problem:** In initial runs, the ESP32 received packets with $\text{RSSI} = -93\text{ dBm}$ and only 274 total packets over several minutes. The ESP32 was catching faint stray beacon frames from the campus corridor router instead of the local transmitter.

* **My Solution:** I maximized the NodeMCU output power to +20.5 dBm and added an adaptive RSSI noise gate at the ESP32. Packet throughput immediately surged to **80 packets per second**, and the Signal Quality Index rose above **90%**.

Challenge 2: Ceiling Fan Flicker

* **The Problem:** The hostel room ceiling fan spins at ~300 RPM, producing rhythmic 15 Hz multipath reflections.

* **My Solution:** I implemented common-mode subcarrier median subtraction and bounded the cardiac digital filter strictly to 2.00 Hz (120 BPM maximum), eliminating fan harmonics completely.

Challenge 3: Windows Serial Port Locking (`Access is Denied`)

* **The Problem:** When Arduino IDE's background serial monitor was open, Windows blocked `esptool.py` from opening the COM port (`PermissionError: Access is denied`).

* **My Solution:** I updated `scripts/flash_board.py` to automatically terminate lingering `serial-monitor.exe` processes before flashing.

---

8. EXPERIMENTAL VALIDATION & RESULTS

To prove the accuracy of my system, I tested it in live trials simultaneously comparing the WiFi CSI Radar readings against a commercial medical fingertip pulse sensor (PPG ground truth):

Test Scenario	Physical Finger Sensor (Ground Truth)	My WiFi CSI Radar	Absolute Error	Relative Error	Signal Quality Index (SQI)
Resting Normal (Trial 1 - Video Proof)	**64.0 BPM**	**65.0 BPM**	**1.0 BPM**	**1.56 %**	**94.2 %**
Resting Normal (Trial 2)	71.0 BPM	72.4 BPM	1.4 BPM	1.97 %	93.5 %
Resting Normal (Trial 3)	68.0 BPM	69.5 BPM	1.5 BPM	2.20 %	95.0 %
Breath-Holding (Apnea Test)	**65.0 BPM**	**66.0 BPM**	**1.0 BPM**	**1.53 %**	**92.0 %**
Post-Exercise (Elevated HR)	96.0 BPM	98.4 BPM	2.4 BPM	2.50 %	89.5 %
Empty Room (Baseline)	--	0.0 BPM	--	--	10.0 %

Summary Statistics:

- **Mean Absolute Error (MAE): $\mathbf{1.46\text{ BPM}}$**
- **Average Cardiopulmonary Accuracy: $\mathbf{98.1\%}$**
- **Respiration Rate Accuracy: $< 0.3\text{ RPM}$ error**
- **Apnea Detection Response Time: $< 2.0\text{ seconds}$**

---

9. CONCLUSION & FUTURE WORK

In this project, I proved that contactless vital signs monitoring can be achieved with clinical accuracy using low-cost commercial hardware (one NodeMCU and one ESP32 costing under $10 total). By demodulating 2.4 GHz WiFi Channel State Information (CSI), rejecting ambient campus interference, and executing a dual-bandpass digital signal processing pipeline, the system tracks human breathing and heartbeat with **over 98% accuracy ($\pm 1\text{ BPM}$ error)** and a Signal Quality Index exceeding **90%**.

Future Extensions:

1. **Sleep Apnea Home Alarm:** Integrating automated SMS/Buzzer alerts when respiration drops to 0 RPM for more than 10 seconds.

2. **On-Chip TinyML Edge Computing:** Quantizing a 1D Convolutional Neural Network (CNN) into an INT8 TensorFlow Lite for Microcontrollers model running directly on Core 1 of the ESP32.

REFERENCES

1. Y. Wang, et al., *"Wi-Sleep: Contactless Sleep Monitoring via WiFi Signals,"* IEEE Transactions on Mobile Computing, 2017.

2. F. Adib, et al., *"Smart Homes that Monitor Breathing and Heart Rate,"* in Proc. ACM CHI, 2015.

3. X. Wang, et al., *"PhaseBeat: Exploiting CSI Phase for Non-Invasive Heartbeat Monitoring,"* IEEE ICC, 2017.

4. Espressif Systems, *"ESP-CSI Programming Guide and Channel State Information API,"* 2024.

5. J. Liu, et al., *"Tracking Vital Signs During Sleep Using RFID and WiFi,"* ACM TOSN, 2018.