

The software installation is a prerequisite to Chapter 8.

About this document:

Welcome to the software installation guide for Apress book, “Introduction to Python Network Automation: The First Journey, 2nd Edition”. This guide has been created by the authors as a complementary material to the book, but it is not part of the actual book. Its purpose is to provide a clear and concise set of instructions to help you install the necessary software to follow along with the book's examples and exercises.

By following the steps outlined in this guide, you will be able to set up the required software for Python network automation and start exploring the practical concepts covered in the book. Please note that this guide is not intended to be a comprehensive resource on network automation or Python, but rather a focused guide to help you get started quickly and easily.

If you have any questions or issues during the installation process, please don't hesitate to reach out to the authors or consult the resources listed in the guide. We hope this guide proves helpful in your journey towards mastering Python network automation.

Version:	1.0
Created:	21/Mar/2023
Last updated:	N/A

What's required?

Host OS:	Windows 11
Desktop Hypervisor:	VMware Workstation 17 Pro
File name:	c8000v-universalk9.17.06.03a.ova
Internet connection:	Yes


Installation Steps:

Here are the steps to create virtual routers using VMware Workstation 17 for Cisco CSR 8000v routers. Once you create the first virtual machine (router), c8kv01, you will clone it to create the second virtual router named c8kv02.


1. Download the .ova file from Cisco Product download page. You will require a Cisco Login ID as well as a valid contract to download the latest version of Cisco CSR 8000 virtual Edge router images.

<https://software.cisco.com/download/home>


<https://software.cisco.com/download/home/286326827>



<https://software.cisco.com/download/home/286327102/type>



<https://software.cisco.com/download/home/286327102/type/282046477/release/Bengaluru-17.6.3a>



2. Go to VMware Workstation 17 and navigate to the main menu, then under the “File” menu, select “Open”. Alternatively press “Ctrl+O”


Open...

Ctrl+O


3. In your Downloads folder, locate Cisco c8000v iso file you have downloaded from Cisco Website and select your image and click “Open”.

c8000v-universalk9.17.06.03a


4. Name your virtual router as c8kv01 and select the Storage path, then click on “Next” button.




5. Leave the default Deployment option as “Small – 16GB Disk” and select “Next”.



6. Enter the minimum information for your virtual router and select “Import” button.



7. Wait until the virtual machine (router) is imported.



8. Once your router is imported, it will start the boot with the following screen. Just sit back and let it go through its POST cycles.



9. The router will go through some background system configurations and then reboot once and you will see the following screen. The system will boot into “*C8000V – package.conf”.



10. Observe the screen and you may think that the screen is stuck/frozen. Let the router to do its own thing for awhile and wait patiently. After all, we are

trying to install this on your laptop, not on a powerful ESXi servers in the DC, so some performance issue is expected during the installation.

```
fsck_or_mkfs.sh[847]: e2fsck 1.43-WIP (18-May-2015)
fsck_or_mkfs.sh[847]: /dev/mapper/config: clean, 11/32768 files, 1138/131072 blo
cks
fsck_or_mkfs.sh[847]: fsck return value for /dev/mapper/config: 0
auditctl[887]: No rules
auditctl[887]: enabled 1
auditctl[887]: failure 1
auditctl[887]: pid 0
auditctl[887]: rate_limit 0
auditctl[887]: backlog_limit 8192
auditctl[887]: lost 0
auditctl[887]: backlog 1
auditctl[887]: backlog_wait_time 60000
auditctl[887]: enabled 1
auditctl[887]: failure 1
auditctl[887]: pid 0
auditctl[887]: rate_limit 0
auditctl[887]: backlog_limit 8192
auditctl[887]: lost 0
auditctl[887]: backlog 1
auditctl[887]: backlog_wait_time 60000
rmon_vars.sh[903]: MGMT_INTF_NOT_CHANGED: 00:0c:29:7c:bf:b8 is eth0 mac
launch_net.sh[1003]: Starting launch_net
launch_cloud_net.sh[1031]: Instance booted in private cloud
```

11. Now, when you see the following screen, you know that the router has booted properly, ignore the Failed to initialize messages.

```
"SOFTWARE"), AND/OR USING SUCH SOFTWARE CONSTITUTES YOUR FULL
ACCEPTANCE OF THE FOLLOWING TERMS. YOU MUST NOT PROCEED FURTHER IF YOU
ARE NOT WILLING TO BE BOUND BY ALL THE TERMS SET FORTH HEREIN.

Your use of the Software is subject to the Cisco End User License Agreement
(EULA) and any relevant supplemental terms (SEULA) found at
http://www.cisco.com/c/en/us/about/legal/cloud-and-software/software-terms.html.

You hereby acknowledge and agree that certain Software and/or features are
licensed for a particular term, that the license to such Software and/or
features is valid only for the applicable term and that such Software and/or
features may be shut down or otherwise terminated by Cisco after expiration
of the applicable license term (e.g., 90-day trial period). Cisco reserves
the right to terminate any such Software feature electronically or by any
other means available. While Cisco may provide alerts, it is your sole
responsibility to monitor your usage of any such term Software feature to
ensure that your systems and networks are prepared for a shutdown of the
Software feature.

% Failed to initialize nvram
% Failed to initialize backup nvram

All TCP AO KDF Tests Pass
cisco C8000V (UXE) processor (revision UXE) with 2028082K/3075K bytes of memory.
```

12. Now run your Cisco favourite command, "show version".


```
c8kv01#show version
Cisco IOS-XE Software, Version 17.06.03a
Cisco IOS Software [Bengaluru], Virtual XE Software (X86_64_LINUX_IOSD-UNIVERSAL
K9-M), Version 17.6.3a, RELEASE SOFTWARE (fc1)
Technical Support: http://www.cisco.com/techsupport
Copyright (c) 1986-2022 by Cisco Systems, Inc.
Compiled Fri 08-Apr-22 04:51 by mcpre

Cisco IOS-XE software, Copyright (c) 2005-2022 by cisco Systems, Inc.
All rights reserved. Certain components of Cisco IOS-XE software are
licensed under the GNU General Public License ("GPL") Version 2.0. The
software code licensed under GPL Version 2.0 is free software that comes
with ABSOLUTELY NO WARRANTY. You can redistribute and/or modify such
GPL code under the terms of GPL Version 2.0. For more details, see the
documentation or "License Notice" file accompanying the IOS-XE software,
or the applicable URL provided on the flyer accompanying the IOS-XE
software.


ROM: IOS-XE ROMMON

c8kv01 uptime is 2 minutes
Uptime for this control processor is 6 minutes
--More--
```


13. Now let's power off the virtual machine from VMware workstation by selecting the virtual machine and power off option. At this stage, you should have your first virtual router and the four Linux servers under the VM Library.




14. Since we need to modify the Network Adapter settings to use "NAT", highlight c8kv01 and on the right screen and select "Edit virtual machine settings".



15. By default all three network adapters are configured in Bridged (Automatic) mode. Select the first Network Adapter, "Network Adapter", and then change it to "NAT: Used to share the hosts's IP Address". Now select "OK" to exist the Virtual Machine Settings.



16. Power on c8kv01 using “Power on this virtual machine”.




17. Once your virtual router goes through the POST process again and comes up. You need to configure the router’s management IP address, configure DNS, default gateway of the last resort. The original IP configuration gets disappeared, although your Administrator ID and password will still work.

Using the following screenshot as the reference, configure your GigabitEthernet1 with the same or similar settings to allow the communication to other servers and the internet.



```
c8kv01#
c8kv01#conf t
Enter configuration commands, one per line. End with CNTL/Z.
c8kv01(config)#interface GigabitEthernet1
c8kv01(config-if)#ip add 192.168.127.171 255.255.255.0
c8kv01(config-if)#no shut
c8kv01(config-if)#exit
c8kv01(config)#ip dns server
c8kv01(config)#ip domain lookup
c8kv01(config)#ip name-server 192.168.127.2
c8kv01(config)#ip route 0.0.0.0 0.0.0.0 192.168.127.2
c8kv01(config)#exit
c8kv01#
*Mar 20 13:33:03.859: %SYS-5-CONFIG_I: Configured from console by console
c8kv01#ping 192.168.0.1
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.1, timeout is 2 seconds:
!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/2/4 ms
c8kv01#ping www.google.com
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 142.250.66.196, timeout is 2 seconds:
!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 12/12/13 ms
c8kv01#
```

Perform the ping test to your internet router's interface, then google DNS (8.8.8.8) or www.google.com. If your configuration is all correct, then your router should be able to communicate to outside world via your laptop's wireless lan, home/work internet router and out to the net.


18. Use PuTTY to SSH into your new edge router.



19. Make sure you accept the rsa2 key fingerprint.



20. Confirm that your SSH login works here. If you cannot login properly, go back to the router console on the VMware Workstation and reset the username and password accordingly.



21. While you are here, let's check the router's directory setup too.

```


192.168.127.171 - PuTTY
c8kv01#dir
Directory of bootflash:/



524292 drwx      16384 Mar 20 2023 13:42:18 +00:00  tracelogs
524289 drwx      4096 Mar 20 2023 13:11:10 +00:00  .installer
31      -rw-      244 Mar 20 2023 13:08:51 +00:00  .iox_dir_list
131077 drwx      4096 Mar 20 2023 13:08:46 +00:00  .dbpersist
27      -rw-     1754 Mar 20 2023 13:08:37 +00:00  cvac.log
524432 drwx      4096 Mar 20 2023 13:08:07 +00:00  iox_host_data_share
262151 drwx      4096 Mar 20 2023 13:08:04 +00:00  guest-share
131079 drwx      4096 Mar 20 2023 13:07:51 +00:00  onep
524402 drwx      4096 Mar 20 2023 13:07:46 +00:00  license_evlog
30      -rw-      209 Mar 20 2023 13:07:44 +00:00  csrlxc-Cfg.log
28      -rw-       1 Mar 20 2023 13:07:42 +00:00  .cvac_version
29      -rw-      16 Mar 20 2023 13:07:42 +00:00  ovf-env.xml.md5
524401 drwx      4096 Mar 20 2023 13:07:36 +00:00  pnp-info
26      -rw-      30 Mar 20 2023 13:07:16 +00:00  throughput_monitor_params
23      -rw-      603 Mar 20 2023 13:05:00 +00:00  mode_event_log
393221 drwx      4096 Mar 20 2023 13:01:56 +00:00  virtual-instance
25      -rw-     1923 Mar 20 2023 13:00:48 +00:00  trustidrootx3_ca_092024.ca
24      -rw-    20109 Mar 20 2023 13:00:48 +00:00  ios_core.p7b
262145 drwx      4096 Mar 20 2023 13:00:36 +00:00  core
393218 drwx      4096 Mar 20 2023 13:00:32 +00:00  bootlog_history
262146 drwx      4096 Mar 20 2023 13:00:28 +00:00  .prst_sync
22      -rw-     5955 Mar 20 2023 12:58:02 +00:00  packages.conf
21      -rw-    51449264 Mar 20 2023 12:58:02 +00:00  c8000v-rpboot.17.06.03a.SPA.pkg
20      -rw-    755016792 Mar 20 2023 12:58:01 +00:00  c8000v-mono-universalk9.17.06.03a.SPA.pkg
17      -rw-    4387912 Mar 20 2023 12:57:48 +00:00  c8000v-firmware_nim_ge.17.06.03a.SPA.pkg
16      -rw-    17708108 Mar 20 2023 12:57:48 +00:00  c8000v-firmware_nim_cwan.17.06.03a.SPA.pkg
19      -rw-    5571660 Mar 20 2023 12:57:48 +00:00  c8000v-firmware_nim_xdsl.17.06.03a.SPA.pkg
18      -rw-    11568204 Mar 20 2023 12:57:48 +00:00  c8000v-firmware_nim_shdsl.17.06.03a.SPA.pkg
14      -rw-    11760716 Mar 20 2023 12:57:47 +00:00  c8000v-firmware_ngwic_tlel.17.06.03a.SPA.pkg
15      -rw-    12981324 Mar 20 2023 12:57:47 +00:00  c8000v-firmware_nim_async.17.06.03a.SPA.pkg
12      -rw-     66636 Mar 20 2023 12:57:47 +00:00  c8000v-firmware_dreamliner.17.06.03a.SPA.pkg
13      -rw-    2376780 Mar 20 2023 12:57:47 +00:00  c8000v-firmware_dsp_sp2700.17.06.03a.SPA.pkg
393217 drwx      4096 Mar 20 2023 12:57:14 +00:00  appqoe-service
131073 drwx      4096 Mar 20 2023 12:57:12 +00:00  .rollback_timer
11      drwx      16384 Mar 20 2023 12:55:05 +00:00  lost+found

11575476224 bytes total (10063724544 bytes free)
c8kv01#


```


22. Now you have a virtual router for your lab. To test commands on multiple devices, we always need an extra virtual router. Let's power off c8kv01 and then make a clone of this device and name the second virtual router as c8kv02.





23. Once c8kv02 is created from the cloning process, power on the second virtual router and change the hostname to c8kv02 and the IP address to 192.168.127.172 with subnet of 255.255.255.0.







24. Once the configuration is completed, perform the ping tests and save the configuration.


```
c8kv01#en
c8kv01#config terminal
Enter configuration commands, one per line. End with CNTL/Z.
c8kv01(config)#hostname c8kv02
c8kv02(config)#interface GigabitEthernet1
c8kv02(config-if)#ip address 192.168.127.172 255.255.255.0
c8kv02(config-if)#end
c8kv02#w
*Mar 20 23:48:54.469: %SYS-5-CONFIG_I: Configured from console by consoler
Building configuration...
[OK]
c8kv02#
*Mar 20 23:49:01.148: %SYS-6-PRIVCFG_ENCRYPT_SUCCESS: Successfully encrypted private config file
c8kv02#ping 192.168.0.1
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 192.168.0.1, timeout is 2 seconds:
!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 2/2/3 ms
c8kv02#ping 8.8.8.8
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 8.8.8.8, timeout is 2 seconds:
!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 12/13/14 ms
c8kv02#_
```

25. SSH into the second router and make sure that your SSH is working correctly.




That's it! Now you have completed the installation of Cisco virtual routers for the testing lab. Now continue your reading and study with the book.

Warning: Leave the default selection at “Small – 16GB Disk”, we have tried to create a virtual router using the “Small – 8GB Disk” option and was running into errors.



Error encountered 1.



Error encountered 2.

