

TellMeLight Rev A KiCad schematic baseline

USB-C J1: VBUS enters protected 5V rail; CC1/CC2 use 5.1k Rd pull-downs.

USB data: J1 D+/D- -> TPD2EUSB30 U5 -> 27R series resistors -> RP2040 U1 USB pins.

Power: VBUS -> AP2112K-3.3 U4 -> 3V3 for RP2040, flash, and LP5024 logic.

MCU: RP2040 U1 uses W25Q32JVSS U3 QSPI flash, 12 MHz Y1, SWD1, BOOT SW1, RESET SW2.


LED driver: RP2040 I2C0 SDA/SCL -> LP5024 U2 with 4.7k pull-ups to 3V3.

Light zones: LP5024 OUT0..OUT17 sink six common-anode RGB LEDs D1..D6 from VLED.

Reserved: LP5024 OUT18..OUT23 are kept for Rev B brightness or status expansion.

This file is the Rev A block-level schematic/net plan. Pin-by-pin signoff remains a review item.

KiCad BOM placeholders below represent selected Rev A components; wiring still follows the net-plan notes above.



Block-level schematic baseline generated by tools/hardware/generate-rev-a-kicad.mjs		
USB-C RP2040 + LP5024 six-zone AI session light		
TellMeLight		
Sheet: /		
File: tellmelight_rev_a.kicad_sch		
Title: TellMeLight Rev A		
Size: A4	Date: 2026-05-30	Rev: A0
KiCad E.D.A. 10.0.3		Id: 1/1