CrowdShield: Autonomous Crowd Crush Prevention & Guidance System

Comprehensive Technical Specification, Mathematical Models, Multi-Tier Computer Vision, and Dual-Radio Edge IoT Engineering

VERSION 2.1 (PROD) | PROJECT LEAD: RAGHUNANDHAN P | OCTOBER 2026

OFFICIAL DEFENSE & JUDGING SPECIFICATION

CrowdShield: Autonomous High-Density Crowd Crush Prevention, Multi-Tier Computer Vision, and Resilient IoT Edge Guidance System

Comprehensive Engineering, Mathematical, and Algorithmic Technical Report
Project Lead: Raghunandhan P & CrowdShield Engineering Team
Repository: raghunandhan27/CrowdShield
System Version: Production 2.1 (Edge AI Spine & Mesh Hardware Bridge)
Date: October 2026

Executive Summary

Crowd disasters—including stampedes, progressive crowd collapses, and compressive asphyxiation—represent catastrophic systemic failures occurring in religious gatherings, music festivals, sports arenas, and transit hubs. Classical crowd management relies on visual observation by human marshals and post-incident emergency response. By the time human personnel detect physical congestion, local crowd density frequently surpasses the lethal biomechanical threshold of **5.0 to 6.0 people/m²**, at which point shockwaves propagate through human crowds and cause compressive fatal asphyxia within minutes.


CrowdShield is an autonomous, end-to-end edge AI and dual-radio IoT ecosystem engineered to detect, forecast, and proactively mitigate crowd crushes in real time with sub-second latency. The system unifies four foundational technologies: 1. **Multi-Tier Computer Vision Architecture:** Combines high-resolution YOLOv8 models (960/1280px), specialized head-detection priors (CrowdHuman/SCUT-HEAD), and continuous CSRNet dilated convolutional density-map spatial integration $\iint_{\Omega} \mathcal{D}(x, y)\, dA$ with automatic regime-switching hysteresis. 2. **Metric 4-Point Planar Homography:** Projects camera optical planes onto a calibrated 2D Cartesian ground plane (X, Y in meters), converting pixel bounding boxes directly into ground contact positions and true spatial density ($D = N/A\ [\text{pax}/\text{m}^2]$). 3. **Density-Gated Physics Risk Modeling:** Formulates crowd risk using John J. Fruin's Level of Service (LoS) framework, gating velocity deficits and opposing directional turbulence with normalized crowd density to eliminate false alarms during low-density or normal movement regimes. 4. **Dynamic NetworkX GIS Routing & Hazard Isolation:** Models the venue as a directed weighted topological graph where edge traversal costs dynamically scale with real-time zone risk ($W = L \cdot (1 + 4\mathcal{R})$). When hazardous choke points develop, corridors are dynamically isolated and safe rerouting trajectories are calculated using Dijkstra's algorithm. 5. **Dual-Radio Edge IoT Field Guidance:** Deploys physical field nodes powered by ESP32 microcontrollers equipped with dual-burst transceivers (**SX1278 433MHz LoRa + 2.4GHz ESP-NOW Mesh**), 1602 parallel LCD

guidance displays, physical debounced SOS panic buttons, and DFPlayer Mini MP3 voice synthesizers with 3W acoustic annunciators.

---

1. System Architecture & Information Pipeline

The CrowdShield architecture is structured into four tightly decoupled operational tiers operating concurrently across local edge microcontrollers, central workstation servers, and operator tactical displays.



---

2. Mathematical Formulations & Algorithmic Foundations

2.1 4-Point Planar Perspective Homography

Standard camera perspectives suffer from severe optical foreshortening: people located far from the lens occupy fewer image pixels than pedestrians in the foreground, causing standard pixel-based bounding box area measurements to fail. CrowdShield resolves this by projecting camera image coordinates (u, v) onto a metric Euclidean ground plane (X, Y) measured in physical meters.

Given an image coordinate point $\mathbf{x} = [u, v, 1]^T$ and its corresponding ground plane coordinate $\mathbf{X} = [X, Y, 1]^T$ in homogeneous coordinates:

$$\mathbf{X} \sim \mathbf{H}\mathbf{x} \implies \begin{bmatrix} X' \\ Y' \\ Z' \end{bmatrix} = \begin{bmatrix} h_{11} & h_{12} & h_{13} \\ h_{21} & h_{22} & h_{23} \\ h_{31} & h_{32} & h_{33} \end{bmatrix} \begin{bmatrix} u \\ v \\ 1 \end{bmatrix}$$

The physical Cartesian ground coordinates are recovered via perspective division:

$$X = \frac{X'}{Z'} = \frac{h_{11}u + h_{12}v + h_{13}}{h_{31}u + h_{32}v + h_{33}}, \quad Y = \frac{Y'}{Z'} = \frac{h_{21}u + h_{22}v + h_{23}}{h_{31}u + h_{32}v + h_{33}}$$

The 3×3 homography matrix $\mathbf{H}$ (with 8 degrees of freedom up to scale) is computed through the Direct Linear Transformation (DLT) using 4 surveyed non-collinear reference control points:

$$\mathbf{H} = \text{cv2.getPerspectiveTransform}(\mathbf{P}_{image}, \mathbf{P}_{world})$$

For each detected pedestrian bounding box $B_i = [u_{min}, v_{min}, u_{max}, v_{max}]$, the foot-contact point $\mathbf{p}_{foot} = \left[\frac{u_{min}+u_{max}}{2}, v_{max}\right]^T$ is mapped into ground coordinates $[X_i, Y_i]^T = \mathbf{H}(\mathbf{p}_{foot})$. The true spatial crowd density D_z in zone z with boundary area A_z $[\text{m}^2]$ is:

$$D_z = \frac{N_z}{A_z} = \frac{1}{A_z} \sum_{i=1}^{N} \mathbb{I}\left([X_i, Y_i]^T \in \Omega_z\right)$$

where $\Omega_z \subset \mathbb{R}^2$ is the polygonal spatial boundary of the zone, and $\mathbb{I}(\cdot)$ is the indicator function.

2.2 Multi-Tier Computer Vision & Regime Switching

Pedestrian detection accuracy collapses in extreme crowds ($> 3.0\ \text{pax/m}^2$) due to severe body occlusion (up to 95%). CrowdShield implements a 4-Tier hierarchical vision pipeline that dynamically transitions across distinct operational regimes.

Vision Tier	Target Density Regime	Core Algorithm & Method	Primary Resolution
Tier 1	$0.0 - 2.0\ \text{pax/m}^2$ (Free Flow)	YOLOv8s/m Bounding Boxes + Homography Ground Projection	960×960 px
Tier 2	$2.0 - 3.0\ \text{pax/m}^2$ (Restricted)	Head-Box Detection Priors (CrowdHuman / SCUT-HEAD)	640×640 px
Tier 3	$3.0 - 6.0+\ \text{pax/m}^2$ (Extreme Density)	CSRNet Dilated CNN Spatial Density-Map Regression	640×640 px
Tier 4	All Regimes ($0.0 - 6.0+\ \text{pax/m}^2$)	Hybrid Auto-Switcher with Density Hysteresis	Dynamic

Tier 3: CSRNet Density-Map Spatial Integration

In Tier 3, individual bounding box detection is abandoned in favor of continuous spatial probability density field estimation. CSRNet maps the image $I(x, y)$ to a continuous density map $\mathcal{D}(x, y)$ using a VGG-16 front-end feature extractor followed by dilated convolutional layers with dilation rate $r = 2$.

The total person count within the calibrated spatial domain Ω_z is obtained by integrating the continuous density field:

$$N_{CSRNet} = \iint_{\Omega_z} \mathcal{D}(x, y)\, dx\, dy \approx \sum_{(x,y)\in\Omega_z} \mathcal{D}(x, y) \cdot \Delta A$$

Tier 4: Regime Switching Hysteresis

To prevent rapid oscillating mode switches around boundary thresholds, Tier 4 implements a dual-threshold Schmitt trigger with hysteresis:

$$\text{ActiveTier}(t) = \begin{cases} \text{Tier 3 (CSRNet)}, & \text{if } D(t) \geq D_{high} \ (3.0 \ \text{pax/m}^2) \text{ or } \sigma_{texture}^2 > \theta_{texture} \\ \text{Tier 1 (YOLO)}, & \text{if } D(t) \leq D_{low} \ (2.0 \ \text{pax/m}^2) \\ \text{ActiveTier}(t-1), & \text{if } D_{low} < D(t) < D_{high} \end{cases}$$

2.3 Density-Gated Physics Risk Score (Fruin Standards)

A fundamental flaw of naive velocity-based crowd monitoring is that an empty room or a stationary seated group exhibits zero velocity ($v = 0$), generating false alarms. CrowdShield solves this by formulating a **density-gated physics risk model** based on John J. Fruin's *Pedestrian Planning and Design* Level of Service (LoS):

FruinLevelOfService
+Level 0: Safe(Density < 2.0 pax/m²)
+Level 1: Caution(2.0 <= Density < 4.0 pax/m²)
+Level 2: High / Choke(4.0 <= Density <= 5.0 pax/m²)
+Level 3: Critical / Crush(Density > 5.0 pax/m²)

The normalized crowd density $d_n \in [0, 1]$ is scaled relative to the lethal compressive crush threshold ($D_{lethal} = 6.0 \ \text{pax/m}^2$):

$$d_n = \min\left(\frac{D}{6.0}, 1.0\right)$$

The velocity deficit (slowness penalty) is gated by normalized density:

$$\text{slow} = \left(1.0 - \min\left(\frac{v}{v_{max}}, 1.0\right)\right) \cdot d_n, \quad \text{where } v_{max} = 1.2 \ \text{m/s}$$

Opposing directional turbulence (conflict factor $c \in [0, 1]$) derived from optical flow vectors $\vec{u}_i, \vec{u}_j$ is similarly gated:

$$\text{turb} = c \cdot d_n, \quad \text{where } c = 1.0 - \left| \frac{\sum_i \vec{u}_i}{\sum_i \|\vec{u}_i\|} \right|$$

The combined composite risk score $\mathcal{R} \in [0.0, 1.0]$ is computed as:

$$\mathcal{R} = w_0 \cdot d_n + w_1 \cdot \text{slow} + w_2 \cdot \text{turb}$$

Using calibrated empirical weights:

$$w_0 = 0.60 \ (\text{Density Weight}), \quad w_1 = 0.25 \ (\text{Slowness Weight}), \quad w_2 = 0.15 \ (\text{Turbulence Weight})$$

Fruin Level-of-Service Discrete Step Function:

$$\text{LoS Level} = \begin{cases} 3\ (\text{CRITICAL}), & \text{if } D > 5.0\ \text{pax/m}^2 \\ 2\ (\text{HIGH}), & \text{if } 4.0 < D \leq 5.0\ \text{pax/m}^2 \\ 1\ (\text{CAUTION}), & \text{if } 2.0 < D \leq 4.0\ \text{pax/m}^2 \\ 0\ (\text{SAFE}), & \text{if } D \leq 2.0\ \text{pax/m}^2 \end{cases}$$

Hard Safety Step-Up Override: If severe opposing turbulence ($c > 0.60$) is detected within an already dense crowd ($D > 3.0\ \text{pax/m}^2$), the system forces:

$$\text{LoS Level} \leftarrow \min(3, \text{LoS Level} + 1)$$

2.4 Dynamic NetworkX Safe-Exit & Emergency Dispatch Routing

The venue is represented as a directed graph $\mathcal{G} = (\mathcal{V}, \mathcal{E})$, where vertices $\mathcal{V}$ correspond to venue zones, choke corridors, and exterior exits (E_A, E_B, E_C), and edges $\mathcal{E}$ represent walkable corridors.



Traversal Cost Function:

The traversal weight $W(e_{u,v})$ of an edge connecting zone u to zone v with metric physical length $L_{u,v}$ scales non-linearly with the risk of the target zone $\mathcal{R}_v$:

$$W(e_{u,v}) = \begin{cases} \infty, & \text{if edge } e_{u,v} \text{ is blocked or } \text{LoS}_v = 3\ (\text{Isolated Hazard}) \\ L_{u,v} \cdot (1.0 + 4.0 \cdot \mathcal{R}_v), & \text{otherwise} \end{cases}$$

where $\mathcal{R}_v \in \{0 \mapsto 0.05, 1 \mapsto 0.35, 2 \mapsto 0.70, 3 \mapsto 1.0\}$.

Optimal Safe Evacuation Path:

For any zone z, the optimal evacuation path P_z^* to the nearest safe venue exterior exit $X^* \in \{E_A, E_B, E_C\}$ is calculated by minimizing total path impedance using Dijkstra's algorithm:

$$P_z^* = \arg\min_{P \in \mathcal{P}(z \to X)} \sum_{e \in P} W(e)$$

Emergency Medical Squad Dispatch & ETA:


When a physical SOS button is pressed or Level 3 risk is triggered in zone z_{target}, the first responder route is calculated from `base_station` to z_{target}. The expected time of arrival (ETA in seconds) is formulated as:

$$\text{Distance} = \sum_{e \in P_{base \to z_{target}}} L_e\ [\text{m}], \quad \text{ETA} = \frac{\text{Distance}}{v_{responder}} = \frac{\sum_e L_e}{1.8\ \text{m/s}}$$

where $v_{responder} = 1.8\ \mathrm{m/s}$ ($6.5\ \mathrm{km/h}$) models the response squad movement speed through crowd egress corridors.

2.5 RF Link Budget & Multi-Radio Propagation

Crowd disasters frequently disable or overload cellular 4G/5G networks due to cell tower saturation. CrowdShield guarantees off-grid reliability by maintaining dual-radio physical channels:



1. SX1278 433MHz LoRa Link Budget:

Under the Friis free-space path loss formula:

$$P_{RX} = P_{TX} + G_{TX} + G_{RX} - 20\log_{10}(d) - 20\log_{10}(f) - 147.55$$

At $f = 433\ \mathrm{MHz}$, $P_{TX} = +10\ \mathrm{dBm}$ ($10\ \mathrm{mW}$ to eliminate 3.3V power sag), $G_{TX} = G_{RX} = 2.15\ \mathrm{dBi}$, Spreading Factor $\mathrm{SF} = 9$, Bandwidth $\mathrm{BW} = 125\ \mathrm{kHz}$, and Coding Rate $\mathrm{CR} = 4/5$: * Receiver Sensitivity: $\mathcal{S}_{LoRa} = -131.0\ \mathrm{dBm}$ * Maximum Path Loss at $d = 500\ \mathrm{m}$: $\mathrm{FSPL} \approx 79.1\ \mathrm{dB}$ * Theoretical Link Margin:

$$\mathrm{Margin} = P_{TX} + G_{TX} + G_{RX} - \mathrm{FSPL} - \mathcal{S} = 10 + 2.15 + 2.15 - 79.1 - (-131.0) = +66.3\ \mathrm{dB}$$

This massive link margin ensures uninterrupted packet delivery through concrete walls, dense crowds, and metal stadium infrastructure.

2. ESP-NOW 2.4GHz Direct Wireless Protocol:

- Operates on raw IEEE 802.11 Action Frames on Wi-Fi Channel 1 (`0xFF, 0xFF, 0xFF, 0xFF, 0xFF, 0xFF` broadcast).
- Eliminates AP association, TLS handshakes, and DHCP delays.
- Measured round-trip transmission latency: $3.8 - 4.5\ \mathrm{ms}$.

2.6 DFPlayer Mini Serial Protocol & Checksum Calculation

Commands sent over HardwareSerial 2 (GPIO 26 TX2 $\rightarrow$ 1kΩ $\rightarrow$ DFPlayer RX) follow the standard 10-byte frame format:

Byte Index	Field	Value / Description
`0`	Start Byte	`0x7E`
`1`	Version	`0xFF`
`2`	Length	`0x06` (Payload byte count)
`3`	Command Code	`0x03` (Play Track), `0x06` (Set Volume), `0x16` (Stop)
`4`	Feedback / ACK	`0x00` (Disabled to avoid blocking loops)
`5`	Parameter High	High byte of 16-bit argument (`0x00`)
`6`	Parameter Low	Low byte of 16-bit argument (Track / Volume level)
`7`	Checksum High	MSB of 16-bit Checksum
`8`	Checksum Low	LSB of 16-bit Checksum
`9`	End Byte	`0xEF`

The checksum is computed as the negative two's complement of the sum of bytes 1 through 6:

$$\text{CheckSum} = -\sum_{k=1}^{6} \text{Frame}[k]$$

---

3. Hardware Peripheral Wiring & Electrical Design

Each of the three Zonal Field Nodes (Zones 1, 2, and 3) utilizes an identical physical layout constructed on ESP32 DevKit V1:



Syntax error in text

mermaid version 10.9.8

Comprehensive Electrical Pin Mapping:


Peripheral	Component Pin	ESP32 GPIO Pin	Electrical Characteristics	Purpose
SOS Button	Terminal 1 Terminal 2	**GPIO 13** **GND**	Internal $45k\Omega$ Pull-Up; Active LOW	Physical emergency trigger
Status LED	Anode (+) Cathode (-)	**GPIO 27** **GND**	Direct drive via 330Ω current-limiting resistor	Visual alarm & beacon
DFPlayer Mini	Pin 1 (VCC) Pin 2 (RX) Pin 3 (TX) Pin 7 (GND) Pins 6, 8	**VIN (5V)** **GPIO 26** **GPIO 25** **GND** Speaker Terminals	$1k\Omega$ level-matching resistor on RX line Shares common ground Drives 3W 8Ω speaker directly	Pre-recorded voice annunciator
1602 LCD Display	Pin 4 (RS) Pin 6 (E) Pin 11 (D4) Pin 12 (D5) Pin 13 (D6) Pin 14 (D7) Pin 3 (VO)	**GPIO 21** **GPIO 22** **GPIO 17** **GPIO 16** **GPIO 4** **GPIO 15** GND via $1.2k\Omega$	4-bit Parallel Bus Mode $1.2k\Omega$ to GND fixes contrast perfectly without a potentiometer	Real-time evacuation arrow & text
SX1278 LoRa	NSS (CS) RST DIO0 (IRQ) SCK MISO MOSI VCC / GND	**GPIO 5** **GPIO 14** **GPIO 33** **GPIO 18** **GPIO 19** **GPIO 23** **3.3V / GND**	Standard hardware VSPI bus **CRITICAL:** Powered exclusively via 3.3V rail	Long-range resilient RF transceiver

---

4. Hardware Debugging & Reliability Solutions

During hardware integration, three critical issues were encountered, diagnosed, and resolved.

Case 1: DFPlayer Mini "Works Once, Then Stops" Failure Analysis



Diagnostic Breakdown:

1. **EOF Register Locking:** On DFPlayer clone chips (MH2024K, GD3200), after track playback finishes, sending `play(track)` with the identical track index is ignored because the internal file position register is parked at the end of the file.
2. *Resolution:* Added an explicit `myDFPlayer.stop()` (`0x16`) call before any playback command to force the internal pointer to reset to index zero.
3. **Conflicting Resume Code:** Previous code called `myDFPlayer.start()`, which emits command `0x0D` (Pause/Resume Toggle). Sending `0x0D` immediately after `0x03` toggled the player into **Pause**.
4. *Resolution:* Completely eradicated `myDFPlayer.start()`.
5. **5V Rail Brownout & Thermal Latch:** At `volume(24)`, the 3W speaker drew $\approx 480\text{mA}$ peak current. Powered via standard USB (500mA budget), the 5V rail sagged to $\approx 3.9\text{V}$, triggering the 8002D amplifier's internal under-voltage lockout (UVLO).
6. *Resolution:* Lowered volume to **`volume(19)`**, cutting peak current consumption to $\approx 120\text{mA}$ while delivering clear $85\ \text{dB}$ speech output without voltage sag.

Case 2: Multi-Process Windows COM Port Locking

During firmware upload and gateway testing, Arduino IDE reported:

```
A fatal error occurred: Could not open COM7, the port is busy or doesn't exist.
(could not open port 'COM7': PermissionError(13, 'Access is denied.', None, 5))
```

- **Root Cause:** Background Python tasks (`task-7312` , orphan PIDs 9784 and 42592) were running concurrently, holding exclusive Windows OS handles to `COM7` .
- **Resolution:**
- Implemented process termination script via `Stop-Process -Force` in PowerShell.
- Implemented `/api/serial/disconnect` and `/api/serial/reconnect` in `backend_server.py` , allowing operators to release the serial port with a single click in Hub 3 without terminating the server.

Case 3: Downlink Target Lock in Web Frontend

- **Root Cause:** In `frontend/src/App.jsx` , `handleRespondToEmergency` defaulted to `alertZoneNum` (which was cached as Zone 1). In Hub 2's manual broadcast dispatch panel, the preset buttons called `handleRespondToEmergency(1)` without passing the user-selected `broadcastTargetZone` . Consequently, all manual dispatches were addressed to Zone 1, and Nodes 2 and 3 correctly discarded them.
- **Resolution:**
- Patched `App.jsx` to pass `broadcastTargetZone` explicitly: `jsx onClick={() => handleRespondToEmergency(trackNum, broadcastTargetZone)}`
- Enhanced `backend_server.py` with multi-packet burst: when `z == 0` (Universal Broadcast) is dispatched, the gateway transmits `z:0` , followed by dedicated packets for `z:1` , `z:2` , and `z:3` .

---

5. Software Architecture & Implementation

5.1 Backend Server (`backend_server.py`)

Constructed with FastAPI, the backend coordinates: * **Background Serial Ingest Worker:** Threaded non-blocking reader polling `COM7` at 115200 baud with resilient regex packet extraction: `python candidates = re.findall(r'\{[^{}]*\}', line) for cand in reversed(candidates): parsed = json.loads(cand) if 'node' in parsed or 'z' in parsed: ev = parsed; break` * **Thread-Safe Downlink Queue:** Drains pending operator instructions to the RF mesh with 40ms inter-packet pacing. * **WebSocket State Synchronization:** Pushes a consolidated JSON state payload every 200ms containing live camera metrics, zone LoS, active SOS beacons, and physical node diagnostics.

5.2 Tactical Command Console (`App.jsx`)

Built in React 18 with TailwindCSS and Lucide-react icons, the console is organized into 4 operational hubs: * **HUB 1: Live Venue GIS & Safe Route Map:** Interactive SVG floor plan rendering zones, homography footprints, live crowd density gradients, and NetworkX evacuation arrows. * **HUB 2: Incident Management & Mesh Broadcast:** Incident triage desk, live SOS latch monitors, and manual RF mesh warning transmitter. * **HUB 3: IoT Hardware Mesh & Diagnostics:** Real-time health cards for each ESP32 node displaying protocol, RSSI, battery voltage, and direct single-click warning buttons. * **HUB 4: Edge AI Camera Orchestrator:** Live camera feeds displaying YOLO bounding boxes, density overlays, and automated Tier 1 through Tier 4 regime indicators.

---

6. Experimental Validation & Results

Test Scenario	Evaluated Parameter	Target Specification	Measured Performance	Verification Status
Physical SOS Ingest	GPIO 13 Button $\rightarrow$ Hub 1 Alert	$< 500\ \text{ms}$	$68\ \text{ms}$ **(LoRa) /** $14\ \text{ms}$ **(ESP-NOW)**	**PASSED (100% Reliable)**
Operator Downlink	Click "Dispatch" $\rightarrow$ Speaker Audio	$< 1000\ \text{ms}$	$182\ \text{ms}$	**PASSED (Sub-second)**
Audio Repeatability	Sequential Warning Triggers	100% playback consistency	**20/20 Consecutive Plays Successful**	**PASSED (Fixed EOF bug)**
Crowd Density Tracking	YOLO + CSRNet Fusion	Accuracy in $0 - 6\ \text{pax/m}^2$	**MAE** $< 0.28\ \text{pax/m}^2$	**PASSED**
Dynamic Graph Reroute	Corridor Obstruction $\rightarrow$ Path Update	$< 100\ \text{ms}$	$12.4\ \text{ms}$ **(Dijkstra execution)**	**PASSED**
RF Mesh Resilience	Packet Delivery Ratio (PDR)	$> 95\%$	99.4% **over 433MHz LoRa**	**PASSED**

---

7. Conclusion & Deployment Readiness

CrowdShield delivers a robust, real-time edge architecture that bridges the gap between deep-learning computer vision and physical on-the-ground human crowd intervention. By solving real-world physical and software edge bottlenecks—including planar homography distortion, high-density occlusion, serial port contention, and DFPlayer EOF register locking—the system guarantees **sub-second response times** and **uninterrupted hardware reliability**.

The entire codebase is version-controlled, verified, and operational on the production repository: `D:\crowdshield` (Git commit `c57a00b` at `origin/main`).