NEXASTORE

Technical Support Knowledge



DISPLAY

NexaDisplay Monitor Troubleshooting Guide

No signal, flicker, resolution, HDR and docking problems

NexaStore Support Library • 2026 Edition

1. No Signal or Blank Screen

Observation	Check
Monitor has no power	Verify outlet, power cable/adapter and power button
Power on, 'No Signal'	Select correct input; reseat cable; wake/restart source device
Works on HDMI, not USB-C	Confirm source USB-C supports display output and cable supports video
Works direct, not through dock	Test dock power, firmware, cable bandwidth and supported display topology
Intermittent black screen	Test another cable/port; lower refresh/resolution temporarily; inspect dock/GPU stability

2. Resolution and Refresh Rate

Problem	Likely cause / action
Native resolution unavailable	Cable/adapter/dock bandwidth, driver or incorrect input mode
High refresh option missing	Port/cable may not support required bandwidth; verify monitor specification
Text appears blurry	Use native resolution and recommended scaling; check chroma/output settings if relevant
Screen tears / stutters	Review variable-refresh settings, GPU output and application frame rate
Display resets after sleep	Update supported graphics/dock firmware; test direct connection

3. Flicker, Color and HDR

Symptom	Checks
Flickering	Test refresh rate, cable, adaptive-sync setting and another source
Washed-out colors	Check HDR mode, color range/profile and monitor preset
HDR too dim/bright	Verify OS HDR configuration and application HDR support
Wrong color temperature	Reset monitor profile or select appropriate creator/standard mode
Artifacts	Test direct cable and another source; persistent artifacts may indicate GPU or panel issue

4. Multi-Monitor and Docking

- Confirm the laptop/GPU supports the requested number, resolution and refresh rate of displays.
- A dock's advertised port count does not guarantee every high-resolution combination simultaneously.
- Test a problematic monitor directly from the source before blaming the panel.
- For USB-C docks, verify host-port capabilities, dock power and cable rating.
- Reduce resolution/refresh temporarily to diagnose bandwidth limits.

5. Isolation Matrix

Test	If problem disappears	Likely area
Replace video cable	Yes	Cable
Connect monitor directly, bypass dock	Yes	Dock / dock link
Use another monitor on same source	Yes	Original monitor/cable
Use original monitor with another source	Yes	Original computer/GPU/dock
Issue appears before OS loads	No software dependency	Hardware/firmware path becomes more likely

6. Support-Agent Retrieval

Question	Source
'Why is 165 Hz missing?'	This guide + exact monitor specification
'Does my laptop USB-C support display?'	Exact laptop model manual
'Is the monitor still under warranty?'	Warranty entitlement service
'Create a replacement request'	Authorized support/return workflow
'My package arrived with a cracked panel'	Damaged Product Policy, not ordinary troubleshooting

Educational notice

This fictional document is designed for the NexaStore support-agent RAG corpus.