Serial commands for Lumedica OCT software

(last updated April 2, 2020)

Serial port settings are COM32, 115200 Baud, No Parity, 8 Data Bits, 1 Stop Bit.

"**StartCapture VolumeScan**" – captures a volume scan per the parameters set on the configuration tab. Returns "**CaptureComplete**".

"**StartCapture CircleScan**" – captures a set of circle scans per the parameters set on the configuration tab. Returns "**CaptureComplete**".

"**StartCapture RadialScan**" – captures a set of radial scans per the parameters set on the configuration tab. Returns "**CaptureComplete**".

"**StartCapture LongScan**" - captures a set of long scans per the parameters set on the configuration tab. Returns "**CaptureComplete**".

"**SaveQueueImages**" – saves all processed B-Scan data in the queue as .tif files. Returns "**SaveQueueImagesComplete**".

"**SaveRawQueueImages**" – saves all raw B-Scan data in the queue as .tif files. Returns "**SaveRawQueueImagesComplete**".

"**SaveFundusCameraImage**" – saves the last image from the fundus camera. Returns "**SaveFundusImageComplete**".

"**SetSampleName *SAMPLE_NAME***" – changes the sample name to SAMPLE_NAME. Does not return anything.

"**SetScanOffsets *X Y***" – sets the scanning offsets. The values for X and Y range from -1.0 to 1.0. Does not return anything.

The commands and parameters are currently case-sensitive.

All commands and responses are terminated with a newline character.