

# Chedam: work log

Cumulative record of every working day, newest first. This copy covers up to Wednesday, October 7, 2026. Owner: Sreya.  
Baseline: Master Specification v1.0.

## Days in this log

- **2026-10-07:** Fixes from Sreya's testing; P1 step 3 deployed; P1 step 4 offline selling built, tested and deployed; till opens offline; P1 step 5 receipts and printers built and deployed; P1 step 6 returns, exchanges and store credit built and deployed; P1 step 7 shelf labels built; manual test sheet; Pi health, backup and power-cut checks
- **2026-10-06:** P0 gate: power pull x10 passed after two real fixes (Wi-Fi lost at boot, confirmed writes lost); untrusted-certificate warning
- **2026-10-05:** P0 steps 1-9 built and deployed; gate: 3-device login, update + rollback, backup + restore, memory under load passed: hub base, schema + event log, access, devices, forgot PIN, client app; work log started
- **2026-10-03:** New network: own router, Pi re-flashed, SSH keys documented, HDMI fixed
- **2026-10-02:** P0 kickoff: spec review, dev PC tools, first Pi flash and first hub setup (TELUS network)

## Fixes from Sreya's testing; P1 step 3 deployed; P1 step 4 offline selling built, tested and deployed; till opens offline; P1 step 5 receipts and printers built and deployed; P1 step 6 returns, exchanges and store credit built and deployed; P1 step 7 shelf labels built; manual test sheet; Pi health, backup and power-cut checks

### Summary

- **Sreya's report:** (1) the setup wizard showed "3 steps left" (Language, Clock, Owner account) but those steps could not be opened; (2) the laptop showed "Not a paired device" after pairing; (3) the sample PIN for Demo Owner did not work; (4) the camera scanner works on the iPhone (R5 ✓).
- **Cause (1):** those three steps are completed by the hub's first start; the dev store was made by sample data, so they were never marked, and the wizard had no screens for them. Fixed: screens for Language, Clock and Owner account.
- **Cause (2):** the Surface **was** paired at 11:54:54 (hub records), but no sign-in succeeded after it (one wrong PIN at 11:55:03, no later sign-in). The page in the screenshot was an owner session started earlier with the password on an unpaired browser. Fixed: home now says so and offers "Pair this browser".
- **Cause (3):** Demo Owner's PIN is no longer 1357 (checked offline against the stored hash on the Pi; the four other sample PINs still match). It was changed at some point (an admin-UI edit of Demo Owner happened at 11:45). The audit log could not show it because secret fields were left out entirely. Fixed: the log now names a changed secret field (`pin`, never its value). **Not reset:** Sreya signs in with the owner email and password on the paired laptop, then Owner account → Change my PIN.
- Step 3 (selling) and the fixes deployed (`dev-50b7ad0`), then step 4 (`dev-9a17683`).
- **P1 step 4, offline selling:** the till prices sales with the hub's own code, sells through an outage (also after a reload), prints offline receipts and uploads them when the hub is back. 584 tests pass.

### 1. Fixes (commit `50b7ad0`)

| File                                                                                              | Change                                                                                                                                                                                                                                |
|---------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>client/src/screens/wizard/Language.svelte, Clock.svelte, Owner.svelte, Wizard.svelte</code> | The three first-start steps can be opened, completed and re-run (FR-1.15). Clock compares hub and device time and sets the store time zone; Owner account edits name, email, password, links to Change my PIN and a new recovery code |
| <code>client/src/screens/Home.svelte</code>                                                       | "This browser is not paired" card with <b>Pair this browser</b> ; Sell and Stock no longer listed as "coming in a later phase"                                                                                                        |
| <code>hub/pb_hooks/lib/event_log.js</code>                                                        | Hidden fields that change (PIN, password, device key) are named in <code>changed</code> , never their values                                                                                                                          |
| Tests                                                                                             | step2: PIN changed in the admin UI is logged by name only; step4: no hash values in the log (names allowed), a revoked device shows <code>key_hash</code> changed                                                                     |

Checked in the browser on a fresh dev hub (same 3 steps open): Language → Clock ("This device and the hub agree") → Owner account → Business profile; 3 of 10 done.

Deploy: `bash hub/scripts/deploy.sh --sample-data` → `dev-50b7ad0`, integrity ok, 35 permissions, sales/till settings present, 53 MB.

### 2. P1 step 4: offline selling

| File                                                    | What                                                                             |
|---------------------------------------------------------|----------------------------------------------------------------------------------|
| <code>hub/pb_migrations/1791300008_p1_offline.js</code> | <code>sales.offline_ref</code> , <code>synced_at</code> , <code>sync_note</code> |

|                                                         |                                                                                                                                                         |
|---------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_hooks/lib/offline.js                             | Offline pack; upload of an offline sale: arithmetic checked with pricing_core.js, recorded as charged, S- number, stock may go negative                 |
| hub/pb_hooks/lib/stock.js                               | Urgent "oversold while offline" task per product, closes itself when stock is back at 0 or more                                                         |
| hub/pb_hooks/sales.pb.js                                | GET /api/chedam/sales/offline-pack, POST /api/chedam/sales/offline                                                                                      |
| client/vite.config.js                                   | virtual:pricing-core: the app imports the hub's pricing file at build time                                                                              |
| client/src/lib/offline_price.js                         | Offline lookup and quote, same rules as the hub                                                                                                         |
| client/src/lib/offline.svelte.js                        | Dexie (IndexedDB): pack and queue; upload in order every 10 s                                                                                           |
| Sell, Till, Receipt, ConnectivityBar, App, session, api | Offline prices, offline receipts, waiting count, till close waits for uploads, signed-in person kept over an offline reload                             |
| hub/tests/step14-offline.test.mjs                       | 27 tests, including <b>parity</b> : the till's offline prices equal the hub's quote on 6 carts (basket, discounts, override, exemption, packs, weights) |
| tools/devhub/dev-login.mjs                              | Pairs and signs in a sample person on the local dev hub (for browser checks)                                                                            |

Decisions DL-86..89 in docs/P1-mini-spec.md.

### Checked in the browser (local dev hub, Cal Cashier)

1. Opened the till; Sell downloaded the pack (11 products, in IndexedDB).
2. **Stopped the hub.** Cola x2, chips, bananas 1.235 kg → "offline prices", **\$9.88 / cash \$9.90** (same as online).
3. First payment try: "This device could not save the sale ... do not hand over the goods" (safety message worked) → bug found and fixed (below).
4. Started the hub, reloaded, **stopped it again and reloaded during the outage**: the till came back to Sell as Cal Cashier with the cart (bug found and fixed below).
5. Paid \$20 → **OFF-X3G8-0002**, change \$10.10, full receipt, "1 offline sale waiting".
6. **Started the hub**: the queue emptied by itself; on the hub: **S-000001**, offline ref OFF-X3G8-0002, total 9.88, rounding 2 ¢, change 10.10, linked to the till, 3 sale movements "S-000001 (offline OFF-X3G8-0002)".

Deploy: dev-9a17683, migration 1791300008 applied, no errors, integrity ok, 49 MB.

### 3. Sreya's offline test and the change it led to (DL-90)

Sreya's test on the Pi (dev-9a17683):

- **Case 1:** Pi on, products in the cart, Pi switched off before payment → the sale completed and the receipt printed. ✓
- **Case 2:** Pi switched off **before** the till was opened → the till could not be opened, so nothing could be sold. The Till screen only said "The hub is not answering".
- Sale and till close (Z report) checked online. ✓

Cause: opening a till needed the hub (by design in step 4). In a store this means no selling at all if the Pi or Wi-Fi is down at opening time. Sreya chose to allow opening offline.

| File                                                 | Change                                                                                                                                                                                                                            |
|------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/<br>pb_migrations/1791300009_p1_offline_tills.js | tills.offline, device_time, synced_at, sync_note                                                                                                                                                                                  |
| hub/pb_hooks/lib/tills.js, sales.pb.js               | POST /api/chedam/tills/offline-open: the till's own id (repeat = first result), float, opener, the device's opening time if within the last 24 h; numbered on arrival; another till still open on the device is noted with a task |

|                                     |                                                                                                                                  |
|-------------------------------------|----------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_hooks/lib/offline.js         | Offline pack also carries the default float and the denominations                                                                |
| client/src/lib/offline.svelte.js    | Till opening queued ahead of the sales; the device's till kept in one place ( <code>tillInfo</code> )                            |
| Till.svelte                         | Offline: explains what works, opens the till on the device; cash drops, pay-outs and closing wait for the hub                    |
| Sell.svelte, ConnectivityBar.svelte | "Till open (opened offline)"; waiting count includes the till opening; online, the till opening uploads before the till is shown |
| hub/tests/step14-offline.test.mjs   | 8 tests: number, float, repeat, other device refused, sale lands in it, Z figures, second open till noted, opening time          |
| tools/devhub/dev-login.mjs          | Missing <code>readFileSync</code> import (the helper did not run)                                                                |

Checked in the browser (local dev hub, Cal Cashier): signed in, **stopped the hub**, Till → counted \$100 (5 × \$20) → "Till (opened offline)", sold a cola for \$1.75 cash → OFF-P9X3-0001. **Started the hub**: the opening and the sale uploaded by themselves; Till screen showed **Till 1**, 1 sale, expected cash **\$101.75**.

Tests: **592 passed, 0 failed**. Not deployed yet (waiting for Sreya's go-ahead).

#### 4. Deploy of the offline till opening

Sreya's go-ahead → `bash hub/scripts/deploy.sh --sample-data` → **dev-7a51b25**, migration 1791300009 applied, API healthy, no errors.

#### 5. P1 step 5: receipts, printers and the cash drawer (no hardware yet)

Sreya has no receipt printer or drawer yet, so everything was built against the standard ESC/POS commands and checked with a pretend printer that shows exactly what a real one would receive.

| File                                                                | What                                                                                                                                                                                                                            |
|---------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_hooks/lib/receipt_layout.js                                  | Receipt, Z/X report and test page as one layout → ESC/POS bytes, or the same lines as text; 48/42/32 characters; accents simplified for the printer                                                                             |
| hub/pb_hooks/lib/printing.js, bin/printer.sh, printing.pb.js        | Printers setting and per-device printer, network scan (port 9100), test print, print/reprint a sale, receipt as text, Z/X report, drawer for a no-sale                                                                          |
| hub/pb_migrations/1791300010_p1_printing.js                         | <code>sales.reprints</code> , <code>sales.drawer_opened</code> , <code>cash_movements.drawer_opened</code> ; <code>settings</code> <code>printing.printers</code> , <code>printing.receipt</code>                               |
| client/src/screens/Printers.svelte (Home → <b>Receipt printer</b> ) | Find printers, add by address, test print (with drawer), paper width, which device prints where, print when paid, full-receipt threshold, preview of the last sale as printed                                                   |
| PrintButtons.svelte, printer.svelte.js; Sell, Sales, Till, Receipt  | Receipt prints when paid (drawer opens for cash), Reprint (COPY), print on this device, customer's name for \$150+; no-sale opens the drawer; Print X / Z report; on-screen receipt shows Total → Cash rounding → Total in cash |
| hub/tests/step15-printing.test.mjs                                  | 31 tests with a fake network printer                                                                                                                                                                                            |
| tools/devhub/fake-printer.mjs                                       | Pretend printer for the laptop: shows each job as text, marks [DRAWER OPENS], [BARCODE], [CUT]                                                                                                                                  |

Decisions DL-91..93 in `docs/P1-mini-spec.md`.

#### Checked in the browser (local dev hub, Mira Manager, fake printer on 127.0.0.1:9100)

1. Receipt printer → Add by address → **Test print first**: test page arrived (48-character ruler, bold total, barcode, cut). Saved.
2. Opened the till, sold a cola and chips, paid \$10 cash → "Printed on Receipt printer · drawer opened"; the printer got [DRAWER OPENS], the receipt with till number, GST/PST lines, change \$4.05, [BARCODE S-000001], [CUT].
3. **Reprint** → "copy 1", printed " **COPY (reprint 1)** ", no drawer.

4. Till → No sale with a reason → "No-sale recorded. Drawer opened." (kick only). **Print X report** → printed with expected cash \$205.95.
5. Preview at 58 mm: every line within 32 characters.

Tests: **623 passed, 0 failed** (16 suites). Not deployed yet (waiting for Sreya's go-ahead).

## 6. Deploy of step 5

Sreya's go-ahead → **dev-8820126**, migration **1791300010** applied, API healthy, no errors. On the Pi, the hub's own user ran the printer network scan: 9 s, no printer found (none connected), memory fine.

## 7. P1 step 6: returns, exchanges and store credit

| File                                                                                  | What                                                                                                                                                                                             |
|---------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791300011_p1_returns.js                                            | returns, return_lines, store_credits, refunds; payment method "exchange"; permission sales.return; return policy settings (Q2 defaults)                                                          |
| hub/pb_hooks/lib/returns.js, returns.pb.js                                            | Find the sale; what can still come back; refund per line (BR-23); approvals (BR-17); no receipt at the lowest 30-day price as store credit; stock per item; refunds; exchange in one transaction |
| hub/pb_hooks/lib/sales.js                                                             | Store credit as payment (balance checked and reduced; given back on void); exchange payment only from a return; sales with returns cannot be voided                                              |
| hub/pb_hooks/lib/tills.js, receipt_layout.js, printing.js                             | Z/X report: returns, tax refunded by type, refunds by method, cash refunds out of expected cash; return slip with store credit barcode and signature line                                        |
| hub/pb_migrations_dev/1791300102_dev_sample_numbers.js                                | <b>Temporary</b> GST/HST 999999999 RT0001, PST PST-9999-9999, BN 999999999 in the sample store (fills empty fields only)                                                                         |
| client/src/screens>Returns.svelte (Sell → <b>Return</b> )                             | Find by scan/number, date, amount, card last 4, or no receipt; quantities and where each item goes; refund and PIN; refund chooser; slip printed                                                 |
| Sell.svelte, RefundChooser, ReturnSlip, exchange.svelte.js, PrintButtons, Till.svelte | Exchange finished on Sell (difference paid or refunded); Store credit payment; return slips printed (drawer for cash refunds); returns on the Till screen                                        |
| hub/tests/step16-returns.test.mjs                                                     | 43 tests                                                                                                                                                                                         |

Decisions DL-94..97 in docs/P1-mini-spec.md.

## Checked in the browser (local dev hub, Mira Manager, fake printer)

1. Return → scan/type **S-000001** → 1 of 2 chips → refund \$3.99 + GST \$0.20 = **\$4.19** → Cash **\$4.20** (rounded) → **R-000001**; slip printed with [DRAWER OPENS], the temporary GST/PST numbers, signature line, [BARCODE R-000001].
2. Exchange: 1 cola back (\$1.76) → Sell → chips \$4.19 → pay screen showed exchange credit \$1.76, to pay **\$2.43**, cash \$2.45 → paid \$5, change \$2.55 → **S-000002 + R-000002** recorded together, both printed.
3. Till screen: Returns 2 · \$5.95 (cash \$4.20); expected cash \$200 + \$16.15 – \$4.20 = **\$211.95**.
4. No receipt: scanned a chocolate bar → only "Store credit \$3.13" offered → **SC-...** code printed.

Tests: **666 passed, 0 failed** (17 suites).

## 8. Deploy of step 6

Sreya's go-ahead → **dev-63986da**, migrations **1791300011** and **1791300102** applied, API healthy, no errors. On the Pi: 36 permissions; business numbers now the temporary **999999999 RT0001 / PST-9999-9999 / 999999999**.

## 9. P1 step 7: shelf labels

Sreya will test steps 5, 6 and 7 together.

| File                                                       | What                                                                                                                                                                                                                         |
|------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791300012_p1_labels.js                  | label_layouts (6 presets), label_templates (Shelf label, Bilingual shelf label), label_batches, label_batch_items; product size (size_qty, size_unit); permission labels.manage (manager, staff)                             |
| hub/pb_hooks/lib/labels.js, labels.pb.js; lib/catalogue.js | Batch with merging; automatic adds on a new price or a product going on sale (BR-25, Labels module on); add by code, category, list; batches as snapshots; "printed" with the changed-since check; last 10; layout fit check |
| client/src/lib/labels/                                     | barcode.js (EAN-13/UPC-A/EAN-8/CODE128), unitprice.js, geometry.js, pdf.js (jsPDF, exact size, alignment page)                                                                                                               |
| client/src/screens/Labels.svelte (Home → <b>Labels</b> )   | To print · Printed · Layouts · Templates; start position picked on a drawing of the sheet                                                                                                                                    |
| ProductEdit.svelte                                         | "Size of one" (for the unit price)                                                                                                                                                                                           |
| client/package.json                                        | jspdf 4.2.1 (exact; 0 vulnerabilities; loaded only on the Labels screen)                                                                                                                                                     |
| hub/<br>pb_migrations_dev/1791300103_dev_sample_sizes.js   | Sizes for the sample products (only where empty)                                                                                                                                                                             |
| hub/tests/step17-labels.test.mjs                           | 38 tests                                                                                                                                                                                                                     |

Decisions DL-98..100 in docs/P1-mini-spec.md.

### Checks

1. Barcodes: every code decoded back by ZXing (the scanner library), all 95 CODE128 characters; then a sample sheet rendered at 300 dpi and read row by row: all barcodes decoded, including a UPC-A 6-pack.
2. Labels looked at as images (A4 3×8 and Letter 3×10 with cut lines): name, French name, size, origin, price /kg or pack name, unit price, barcode or PLU; nothing overlapping.
3. Browser (local dev hub, Mira Manager): Labels showed the 14 sample products waiting ("new product"); start position 4 picked on the sheet drawing → **Make the PDF** → real PDF, 14 labels from position 4 → **Printed fine** → batch empty, "Batch 1 · 14 labels" under Printed. Layout editor: 4 columns on A4 → "Too wide: the labels need 268.7 mm of 210 mm", Save disabled; alignment page opened.

Tests: **704 passed, 0 failed** (18 suites).

## 10. Manual test sheet, Pi health, backup and power-cut test

**Manual test sheet** for Sreya: docs/testing/Chedam-Manual-Tests-P1-1-7.xlsx (85 checks in 9 areas: setup and access, products, stock, selling, offline, receipts and printer, returns, labels, reliability; Pass / Fail / Blocked / Not tested; Summary tab). Built by tools/testing/build\_test\_sheet.py.

**Pi health (read-only), 11:39:** hub active, 0 restarts, version dev-63986da; 57 MB hub memory (target < 150 MB), 235 MB free; 44 °C, no throttling or under-voltage; disk 3% used; clock synced (America/Vancouver); database integrity ok (WAL); no hub errors in 24 h; no SD card errors; Wi-Fi guard online; HTTPS chedam.local 200 in 0.2 s from the laptop; site certificates renew every 12 h, root valid to 2036; data 8.5 MB.

**Backups:** drive = the 7.4 GB USB stick (not the Seagate). Nightly backups verified 2026-10-06 and 2026-10-07 (02:30). Manual backup now: 174 KB encrypted, verified on the drive in 1.7 s; restore test 0.4 s, counts equal. - **Gap found and fixed:** the restore test compared only the P0 setup tables. chedam-backup now also compares products, stock, tills, sales, payments, returns, store credit and labels. Run on the Pi from a temporary copy: all 27 tables equal to live (sales 3 = 3, sale lines 8 = 8, payments 3 = 3, stock movements 20 = 20, ...). Installed on the Pi with the next deploy.

**Power-cut (data loss) test:** the P0 power test hub (throwaway database on the same SD card, tools/powerest/) with writes every ~70 ms from the laptop; instead of pulling the plug, the Pi was hard-reset with sysrq b (immediate reboot,

no sync, no unmount) 40 s into each cycle.

| Cycle | Confirmed writes | Lost | Duplicates | Audit log | Integrity (store / test) | Store hub | Back in |
|-------|------------------|------|------------|-----------|--------------------------|-----------|---------|
| 1     | 972              | 0    | 0          | matches   | ok / ok                  | active    | 40 s    |
| 2     | 1976             | 0    | 0          | matches   | ok / ok                  | active    | 43 s    |
| 3     | 3017             | 0    | 0          | matches   | ok / ok                  | active    | 42 s    |

The store's own data before/after: 3 sales, 5,633 cents, 3 payments, 20 stock movements: unchanged; integrity ok. A product Sreya saved 10 s before the third reset ("Usb2.0 otg") was kept. Report: `docs/gate/powertest-2026-10-07-p1-sysrq.json`. Test hub removed. A real plug pull stays in the manual sheet (I01, I02): sysrq leaves the SD card powered.

## Failed cases and fixes

| Symptom                                                               | Cause                                                                                                                | Fix                                                                             |
|-----------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------|
| Wizard steps Language/Clock/Owner greyed out                          | Marked done only by the hub's first start; no screens                                                                | Screens for the three steps                                                     |
| "Not a paired device" after pairing                                   | The page shown was an owner password session from before pairing; pairing needs a new sign-in                        | Home explains it, "Pair this browser"                                           |
| Sample owner PIN rejected                                             | PIN changed since (checked against the hash on the Pi, no sign-in attempt used); the log did not show secret changes | Log names changed secret fields; Sreya changes her PIN after a password sign-in |
| Pack: barcodes came as <code>[91,93]</code>                           | JSON fields are raw bytes in the hub's JS engine, also through <code>publicExport()</code>                           | Parse <code>getString()</code> for JSON fields                                  |
| Parity test "failed" with equal values                                | Key order differs between hub and till objects                                                                       | Compare with sorted keys                                                        |
| Offline Z count expected 4, got 3                                     | My test: 2 of the 5 uploads were refused on purpose                                                                  | Expect 3                                                                        |
| A stray <code>cat &gt;</code> waited for input and the test ran 400 s | My command                                                                                                           | Stopped; commands now read from <code>/dev/null</code>                          |
| Offline sale not saved ("storage is full or blocked")                 | IndexedDB cannot store Svelte's reactive proxies                                                                     | Store plain copies                                                              |
| Reload during an outage went to the name list                         | Who is signed in was only in memory                                                                                  | Kept on the device, used only with the same person's unexpired token (DL-89)    |
| Header said "Not a paired device" offline                             | Device details come from the hub                                                                                     | Uses the saved device key                                                       |
| A NUL byte and line breaks landed in <code>vite.config.js</code>      | Escapes inside a here-document                                                                                       | Rewrote the plugin; checked no NUL remains                                      |
| "1 sales waiting"                                                     | Plural                                                                                                               | Fixed                                                                           |
| Till could not be opened with the hub off (Sreya, case 2)             | Opening needed the hub                                                                                               | Opens on the device, uploads first (DL-90)                                      |
| Till opened offline showed the upload time                            | Hub used the arrival time                                                                                            | Uses the device's time when plausible                                           |
| "0 sales and the till opening waiting"                                | Wording                                                                                                              | Only what is waiting is named                                                   |
| Printing tests counted 2 jobs too many                                | The network scan's knock (an empty connection) looked like a print job                                               | Fake printer ignores empty connections                                          |
| Card sale in the test refused                                         | My test paid a made-up amount                                                                                        | Pays the quoted total                                                           |
| "Deposit/fee" lost its indent under the item                          | Line wrapping dropped leading spaces                                                                                 | Indent kept on every wrapped line (test added)                                  |
| X report showed "-\$0.00"                                             | Minus sign on zero                                                                                                   | "\$0.00" when nothing was taken off                                             |

|                                                |                                                                                              |                                                                                                       |
|------------------------------------------------|----------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------|
| Network scan finds nothing on the laptop       | It reads the Pi's network ( <code>ip</code> ), which Windows lacks                           | Expected; on the laptop add the printer by address                                                    |
| No-receipt credit came out as \$0              | A product's first price is stored as a change from \$0, and the lowest-price rule took the 0 | Zero is never a selling price: ignored (test added)                                                   |
| Test used a price the lookup does not return   | My test                                                                                      | Reads the unit's price                                                                                |
| Schema test expected 35 permissions            | Step 6 adds <code>sales.return</code>                                                        | 36                                                                                                    |
| EAN guard bars ran through the digits          | Long guard bars under centred digits                                                         | Plain bars, digits under them                                                                         |
| Price overlapped the barcode on a 6-pack label | Fixed half-width for the barcode                                                             | Barcode gets the space the price leaves; the price shrinks before the barcode gets too narrow to scan |
| "Produit de Ecuador"                           | French country names need their article                                                      | "Origine : Équateur" (and "Produit du Canada")                                                        |
| Route helper not found in a handler            | Each handler runs in its own JS engine                                                       | Helper inlined (known rule, conventions.md)                                                           |
| Page size test: 612.0000000000001 pt           | Rounding of 215.9 mm                                                                         | Compared as numbers                                                                                   |
| Undoing the sample catalogue failed            | Its products now have label lines                                                            | The sample's undo removes them first                                                                  |
| Schema test expected 36 permissions            | Step 7 adds <code>labels.manage</code>                                                       | 37                                                                                                    |

Tests: **584 passed, 0 failed** (15 suites).

## For Sreya

1. **Sign in again on the laptop:** on the name list choose **Owner: sign in with email and password** (your own password), then Store setup → **Owner account** → **Change my PIN**. Use the same address every time on a device (e.g. always `https://chedam.local`): pairing is remembered per address.
2. Finish the 3 setup steps (Language, Clock, Owner account) and enter the **GST/PST numbers** in Business profile (they print on receipts).
3. Try **Sell**: open the till (Till → Open till), sell, close with the Z report. To test offline: switch the Pi off (or its Wi-Fi) during a sale, keep selling, switch it back on and watch "waiting to upload" go to zero.

## Next

1. Deploy step 7 (needs Sreya's go-ahead). Sreya tests steps 5, 6 and 7 together with real cases; replace the temporary GST/PST/BN numbers before selling for real.
2. When a printer arrives: Find printers, test print, test with drawer, one cash sale. Labels: print the alignment page on plain paper first.
3. P1 step 8: product import and export.
4. Open (to plan in the coming days): Q1 accountant review (tax classes, deposits, exemption reasons), Q2 return defaults.

## P0 gate: power pull ×10 passed after two real fixes (Wi-Fi lost at boot, confirmed writes lost); untrusted-certificate warning

### Summary

- **New Android phone** ("1plus", Android 10, Chrome 151) worked without the certificate installed. Not a bug: Chrome lets a person tap through "Your connection is not private". The app now warns with an amber bar (DL-62).
- **Power-pull gate test (NFR-09, ×10): PASS on run 3.** 47,573 confirmed writes, **0 lost**, 0 duplicates, audit log complete, both databases intact, the real hub restarted by itself every time (48-78 s).
- It found two real problems first, both fixed and proven: 1. **Wi-Fi lost after power cuts during boot:** the Wi-Fi settings files were left empty. Fix: `chedam-netguard` (DL-60), tested by deleting the profile: recovered unattended in 127 s. 2. **Confirmed writes lost in a power cut** (23 of 1,646): SQLite confirmed before writing to the card. Fix: `synchronous=FULL` (DL-61).
- My test script crashed once (too short a timeout after a cold boot); fixed, and confirmed writes are now kept in a file as they happen.
- Gate status: 3-device login ✓, update + rollback ✓, backup + restore ✓, memory under load ✓, power pull ×10 ✓. Left: camera over HTTPS.

### 1. New phone works without the certificate

|               |                                                                                                                                                                                                                                                                                             |
|---------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Hub record    | "1plus", approved, Android 10, Chrome 151, app 0.9.0                                                                                                                                                                                                                                        |
| Why it worked | Chrome's warning page "Your connection is not private" has Advanced → <b>Proceed (unsafe)</b> . After that the page works, but the hub is not verified (an impostor on the Wi-Fi would not be noticed) and Chrome refuses the app's offline mode (service worker) and may refuse the camera |
| Fix           | The app detects the service worker's certificate error and shows an amber bar: "This device does not trust the hub's certificate yet, so offline mode and the camera will not work. <b>Install the certificate</b> " (link to the HTTP guide). Commit <code>61d86f0</code> , deployed       |

### 2. Power-pull test tools

| File                                          | Role                                                                                                                                                                                                                                                                                                                                                                                                      |
|-----------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>tools/powertest/pi-powertest.sh</code>  | <code>install</code> : a throwaway test hub that survives reboots (systemd service <code>chedam-powertest</code> , same binary, hooks, migrations and memory limits as the real hub, data in <code>/var/lib/chedam-powertest</code> on the same SD card, 127.0.0.1:8199); <code>check</code> : integrity of both databases, services, records vs. audit entries, power flag, boot id; <code>remove</code> |
| <code>tools/powertest/power-writer.mjs</code> | On the laptop through an SSH tunnel it restarts by itself: 3 writers (about 26 writes per second, each with its audit entry), notices the cut and the <b>reboot</b> (boot id), then checks: every confirmed write present, no duplicates, audit = records, integrity, real hub active                                                                                                                     |

Dry run with a software reboot: 520 confirmed writes, 0 lost, PASS.

### 3. Run 1: the writer crashed, then the Pi came back without Wi-Fi

| Time (UTC) | What happened                                                                                                                |
|------------|------------------------------------------------------------------------------------------------------------------------------|
| 16:04      | "Hub gone" for 6 s, no reboot: the laptop's SSH tunnel dropped (Wi-Fi blip); correctly not counted. Sreya had not pulled yet |
| 16:06      | Pull 1 → back after a reboot at 16:07                                                                                        |

|       |                                                                                                                                                                                                                 |
|-------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 16:07 | <b>My script crashed</b> while checking: listing ~17,000 records on a freshly booted Pi Zero took more than its 4 s timeout. The list of confirmed writes was only in memory, so this cycle could not be judged |
| after | Sreya pulled two more times; the Pi stopped answering (ping, SSH)                                                                                                                                               |

On the hub's monitor: a normal login prompt, but "My IP address is **127.0.1.1**" (no network address). The router listed 3 Wi-Fi devices, none the Pi. Sreya connected a keyboard:

| Check                         | Result                                         |
|-------------------------------|------------------------------------------------|
| <code>nmcli dev status</code> | wlan0 wifi disconnected                        |
| <code>rfkill list</code>      | not blocked                                    |
| <code>dmesg</code>            | Wi-Fi firmware loaded normally (BCM43430/1)    |
| <code>nmcli con show</code>   | <b>only 1o</b> : no Wi-Fi network known at all |

Sreya reconnected with `sudo nmcli dev wifi connect "TP-LINK_2CBE" password "..." ifname wlan0` (her password, typed by her), and the hub was back at 192.168.50.101.

### Root cause

- Raspberry Pi OS 13 keeps the Imager Wi-Fi settings in `/etc/netplan/90-NM-*.yaml`, from which NetworkManager's profile is generated **at every boot**.
- Both files were **0 bytes**: they are rewritten during boot, and a power cut before the data reached the card left them empty (the new length was saved, the contents were not).
- Sreya's new profile carried yesterday's time (04:49), because the Pi's clock was wrong at boot: no network to set it and no RTC (the DL-23 risk, seen live).
- Data after these three cuts: both databases intact; 17,863 test records = 17,863 audit entries.
- My setup script only adds a power-save setting; it does not touch the Wi-Fi profiles.

### Fix: chedam-netguard (DL-60)

- `hub/system/chedam-netguard + .service + .timer` (every minute), installed by `deploy.sh` and `setup-hub.sh`:
- **online**: an fsync'd spare copy of each valid Wi-Fi profile (must have an SSID and not be empty);
- **2 min without an address**: restore the spare copies if no Wi-Fi network is known, then reconnect;
- **10 min**: reboot, at most once an hour.
- **Controlled test on the Pi**: the profile was removed and Wi-Fi disconnected (with a 9-minute safety timer that would have put it back). Log:
- 09:43:55 profile removed;
- 09:46:33 "no Wi-Fi network known after 127 s ... restored spare copies";
- 09:46:37 "reconnected wlan0".

The hub was back at 192.168.50.101 with nobody touching it. The safety net was not needed (removed).

### Fix: test script

- Checks after a reboot get 60 s with 3 attempts, and a failed check is reported, not a crash.
- Every confirmed write is appended to a file at once.

## 4. Run 2: confirmed writes lost (stopped after cycle 1)

| Check                                     | Result             |
|-------------------------------------------|--------------------|
| Integrity, duplicates, audit, hub restart | all fine           |
| <b>Confirmed writes lost</b>              | <b>23 of 1,646</b> |

- **Cause**: PocketBase opens SQLite in WAL mode with `synchronous=NORMAL`, which confirms a commit before forcing it onto the card. In a power cut the last confirmed transactions can vanish. That breaks NFR-02 ("no lost or

uplicated sales").

- **Fix (DL-61):** `hub/pb_hooks/durability.pb.js` sets `PRAGMA synchronous = FULL` on PocketBase's single non-concurrent (write) connection before every request, at start-up and every minute.
- Health page item "Saved before confirming" (bad if not FULL); test added; **329** tests pass.
- On the Pi: "Saved before confirming: Yes"; 30 writes in 2,147 ms (about 70 ms each, including the audit entry).
- Report kept: `docs/gate/powertest-2026-10-06-run2-synchronous-normal.json`.

## 5. Run 3: PASS 10/10

| Cycle | Confirmed so far | Lost | Duplicates | Audit = records | Integrity real / test | Hub back after |
|-------|------------------|------|------------|-----------------|-----------------------|----------------|
| 1     | 873              | 0    | 0          | yes             | ok / ok               | 49 s           |
| 2     | 7,746            | 0    | 0          | yes             | ok / ok               | 48 s           |
| 3     | 10,239           | 0    | 0          | yes             | ok / ok               | 53 s           |
| 4     | 10,530           | 0    | 0          | yes             | ok / ok               | 51 s           |
| 5     | 10,775           | 0    | 0          | yes             | ok / ok               | 54 s           |
| 6     | 11,399           | 0    | 0          | yes             | ok / ok               | 64 s           |
| 7     | 11,770           | 0    | 0          | yes             | ok / ok               | 54 s           |
| 8     | 13,123           | 0    | 0          | yes             | ok / ok               | 65 s           |
| 9     | 13,845           | 0    | 0          | yes             | ok / ok               | 61 s           |
| 10    | 47,573           | 0    | 0          | yes             | ok / ok               | 78 s           |

- Each boot logged "EXT4 orphan cleanup", the normal filesystem repair after a power cut.
- Wi-Fi came back on its own every time (netguard did not need to act).
- Power was clean (`throttled=0x0`).
- 1-2 writes per cut were saved without being confirmed: they reached the card, but the answer was lost with the power. That is expected; the till retries them (idempotent ids in later phases).
- Report kept: `docs/gate/powertest-2026-10-06-run3.json`.
- The test hub was removed; the real hub is active.

## 6. Session 2: status check and a race fix

- Git: clean, `main` in sync with GitHub before starting. The Pi runs `dev-484c657`; the later commit `aebd3d5` was documents only.
- Full test run (`PB_BIN=C:/Tools/pocketbase.exe node hub/tests/run-all.mjs`): **1 failure**, `step9-updates` "one urgent task". It passed 3 times when run alone, so it was intermittent.
- **Cause (a real bug, not only the test):** when the hub applies an install result, it saved the update record and then its urgent task as two separate writes. The every-minute job and the status screen can both apply the same result at the same moment, so a reader could see "rolled back" before the task existed, and two appliers could each raise a task. `lib/backup.js` had the same pattern.
- **Fix (commit 85da79a):** in `hub/pb_hooks/lib/updates.js` and `hub/pb_hooks/lib/backup.js`, finding the record, saving it and raising/closing the task now run in one transaction. The hub has a single writer, so the second applier waits, then finds nothing left to apply.
- **Verified:** full run 329/329 passed; `step9-updates` and `step7-backups` then passed 5 times in a row each.
- Not deployed yet: needs Sreya's go-ahead.

## 7. Session 2 (continued): P0 closed, P1 started

### P0 closed (DL-63)

- Sreya: skip the camera test; the certificate trust step can be solved later.
- Recorded as DL-63 in `docs/P0-mini-spec.md`: camera over HTTPS (R5) and the phone trust step move to P1

step 2 (phone scanning) and are tested before the P1 gate. The pilot week waits for a pilot store (Q9); P0 and P1 are piloted together.

## P1 plan

- docs/P1-mini-spec.md: goal, 10 build steps with requirement IDs, decisions DL-64..71, open questions (Q1 accountant blocks the P1 release, not the build; Q2; Q7; who sees costs).

## P1 step 1, hub side: catalogue and tax tables (commit d078aad)

| File                                                     | What                                                                                                                                                                                 |
|----------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791300001_p1_catalogue_schema.js      | tax_types, tax_rates (effective dates), tax_classes, deposits_fees, categories, products, selling_units (single, pack, case, by weight; nested), price_history                       |
| hub/pb_migrations/1791300002_p1_catalogue_reference.js   | Permissions catalogue.edit (staff, manager), prices.edit and tax.manage (manager); GST 5%, BC PST 7%; classes Standard, GST only, Zero-rated, Exempt; all marked pending review (Q1) |
| hub/pb_migrations_dev/1791300100_dev_sample_catalogue.js | 8 categories, 12 sample products (bananas by kg, cola single/12-pack/case, water single and 6-pack sharing a barcode, an age-restricted item, one Draft)                             |
| hub/pb_hooks/lib/catalogue.js                            | BR-07 checks (what keeps a product a Draft), base quantity of nested packs, barcode and PLU uniqueness, price history, the Drafts task, lookup and product view                      |
| hub/pb_hooks/lib/tax.js                                  | Tax rates for a class at a date; checks on rates and classes                                                                                                                         |
| hub/pb_hooks/catalogue.pb.js                             | POST /api/chedam/catalogue/products (product + units in one transaction), GET /api/chedam/catalogue/lookup?code=, GET /api/chedam/catalogue/products/{id}                            |
| hub/pb_hooks/lib/event_log.js                            | Table rules run inside the save's transaction (SIDE_EFFECTS); "before" read from the database                                                                                        |
| hub/pb_hooks/lib/access.js                               | New tables; price changes and activation need prices.edit                                                                                                                            |
| hub/tests/step11-catalogue.test.mjs                      | 67 tests                                                                                                                                                                             |

Command: PB\_BIN=C:/Tools/pocketbase.exe node hub/tests/run-all.mjs → **396 passed, 0 failed** (11 suites).

Not deployed to the Pi yet (needs Sreya's go-ahead). Product screens are next.

## Sreya's answers and the deploy

- Deploy: approved. Accountant review (Q1): in progress. Cashiers: no costs or margins.
- DL-72 (commit f75d9a1)**: new permission costs.view (owner, manager, accountant, staff). Without it the hub hides cost\_cents on products and the amounts of cost-history rows in every API answer (lists, single records, realtime, through onRecordEnrich in access.pb.js), and the product view endpoint leaves them out. Migration 1791300003\_p1\_costs\_view.js; 7 tests. Full run: **403 passed, 0 failed**.
- Deployed** with bash hub/scripts/deploy.sh --sample-data: pre-deploy backup integrity ok, version dev-f75d9a1, migrations 1791300001..3 and 1791300100 applied, no errors.
- Checked on the Pi** (sqlite3 as chedam-hub): 11 active products and 1 Draft; "Case of 2 x 12" base quantity 24; GST 5% and BC PST 7%, both pending review; Drafts task open ("1 product is a Draft and cannot be sold"); 26 price-history rows, each with its event; integrity ok; PocketBase memory 54 MB; health 200 over HTTPS from the PC; the lookup refuses a request without sign-in (401).

## Failed cases and fixes (session 2)

| Symptom                                                 | Cause                                                                                                                                  | Fix                                                                                                                                            |
|---------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| Sample data migration failed: "base unit cannot change" | PocketBase's <code>record.original()</code> still shows the pre-create values when the same record object is saved a second time       | Read the stored values from the database inside the transaction. The event log's "before" had the same weakness and now reads the database too |
| "Barcode 91 already belongs to Bananas"                 | In the JS hooks <code>get()</code> on a JSON field returns raw bytes (91 = "[")                                                        | Parse <code>getString()</code> (already a known gotcha)                                                                                        |
| A Draft showed outdated reasons                         | Reasons were computed when the product was created, before its units existed                                                           | Recomputed whenever a unit changes                                                                                                             |
| 400 answer lost the list of problems                    | PocketBase rewrites the data of thrown errors                                                                                          | The endpoint rolls back, then answers the list itself                                                                                          |
| 13 tasks after loading sample data                      | Each product passed through Draft, so the Drafts task was created and closed 11 times                                                  | Reopen the last Drafts task (DL-71)                                                                                                            |
| Migrations could not be reverted                        | Hard-deleting units re-validated their Active product                                                                                  | Hard deletes (superuser only) skip that refresh                                                                                                |
| Reversibility test missed the P1 migrations             | It counted only names starting 17912                                                                                                   | Counts every 1791... migration                                                                                                                 |
| Backups test failed sometimes ("already running")       | The real every-minute backup job started a nightly backup during the test (any time after 02:30)                                       | Test hubs switch that job off ( <code>CHEDAM_TEST_NO_BACKUP_CRON</code> ) and call the tick themselves; 5/5 passes                             |
| Review: nested packs, inner pack resized                | A case did not follow when its inner pack changed size; nested packs of "each" items allowed fractions; an inner pack could be removed | Fixed, 3 tests added                                                                                                                           |

## 8. Session 3: P1 step 1 screens (commit 266962e)

| Screen / file                                                  | What                                                                                                                                                                                                                                                                                                    |
|----------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>client/src/screens/Products.svelte</code>                | List with search by name, barcode or PLU, category and status filters, main unit's price, margin % (costs.view only), Draft reason                                                                                                                                                                      |
| <code>client/src/screens/ProductEdit.svelte</code>             | Product form: fields shown by type (weighed, perishable, regulated, imported), selling units with nested packs, barcodes, live cost / margin / markup / per-item price (costs.view only), "Save and make active" (prices.edit), archive, price history, Draft reasons. Read-only without catalogue.edit |
| <code>client/src/screens/Categories.svelte</code>              | Add, edit, remove (only when empty), colour, order, till visibility, return window                                                                                                                                                                                                                      |
| <code>client/src/screens/Tax.svelte</code>                     | Classes and what they charge in the store's province, rates with dates (in use / upcoming / ended), add rate, set end, add custom class; "pending accountant review" notice                                                                                                                             |
| <code>client/src/lib/catalogue.js</code>                       | Money in cents, margins, device-made ids, nested pack quantities                                                                                                                                                                                                                                        |
| Home, <code>session.svelte.js</code> , <code>App.svelte</code> | Products tile; the Drafts task opens the Drafts list; addresses <code>#products</code> , <code>#categories</code> , <code>#tax</code>                                                                                                                                                                   |
| <code>tools/devhub/dev-hub.sh</code>                           | Local dev hub with the sample store on 127.0.0.1:8095 for checking screens in the browser                                                                                                                                                                                                               |

### Checked in the browser (local dev hub)

- Paired the preview browser with a dev pairing code; signed in as Mira Manager (sample PIN).
- Drafts task → "Show" → Drafts list → mango form shows "'Single' needs a price of at least \$0.01".
- Price \$1.99 and a 4-pack at \$6.99 added: the form showed "= 4 items", cost \$3.80, margin 45.6%, markup 83.9%, \$1.75 per item. "Save and make active" → Active.
- Tax screen: Standard = GST 5% + PST 7%, GST only, Zero-rated 0%, Exempt; both rates "in use".
- Categories: added "Spices".

- Signed in as Cal Cashier: no Add/Categories buttons, no margins in the list; product form read-only with no cost or margin; barcode 2000000000053 found Sparkling water.
- Phone width (375 px): no sideways scrolling. No console errors.

### Failed cases and fixes (session 3)

| Symptom                                                       | Cause                                                     | Fix                                                                                        |
|---------------------------------------------------------------|-----------------------------------------------------------|--------------------------------------------------------------------------------------------|
| Price field showed "0.001.99" after typing                    | A unit with no price was filled with "0.00" as text       | Empty prices and costs start blank                                                         |
| Typing <code>#tax</code> while a product was open did nothing | The open screen won over the address (also in P0 screens) | An address that differs from the open screen now wins                                      |
| "1 products"                                                  | Plural not handled                                        | Fixed                                                                                      |
| Zero-rated product said "No tax"                              | The class treatment was not used                          | Shows "0% (zero-rated)" or "No tax (exempt)"                                               |
| Preview could not start <code>bash</code>                     | The preview runner needs the full path                    | Git's <code>bash</code> by its full path (Program Files, Git, bin, <code>bash.exe</code> ) |

## 9. Session 4: step 1 screens deployed; P1 step 2 (stock)

### Deploy (Sreya: "proceed")

- `bash hub/scripts/deploy.sh --sample-data: version dev-42ea867`, no errors; the Pi serves the new app (checked the built file over HTTPS from the PC).

### Hub side (commit `aa956dd`)

| File                                                                                               | What                                                                                                                                                                                                                                           |
|----------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>hub/pb_migrations/1791300004_p1_stock_schema.js</code>                                       | <code>stock_levels</code> (loose + sealed packs, on hand), <code>stock_lots</code> (expiry, cost per base unit), <code>stock_movements</code> , <code>stock_counts</code> , <code>stock_count_lines</code> ; read-only through the generic API |
| <code>hub/pb_migrations/1791300005_p1_stock_reference.js</code>                                    | Permissions <code>stock.receive</code> , <code>stock.adjust</code> , <code>stock.count</code> (staff, manager), <code>stock.approve</code> (manager); settings <code>stock.reasons</code> , <code>stock.approval_value_cents = 2500</code>     |
| <code>hub/pb_hooks/lib/stock.js</code> , <code>lib/stock_http.js</code> , <code>stock.pb.js</code> | Receive, adjust/damage/loss, approve/reject, pack break/make, counts, product stock view, shrink report; one transaction each; <code>op_id</code> makes retries safe                                                                           |
| <code>hub/pb_hooks/lib/tasks.js</code>                                                             | Shared rule-task helper (Drafts task, stock approvals)                                                                                                                                                                                         |
| <code>hub/pb_migrations_dev/1791300101_dev_sample_stock.js</code>                                  | Sample deliveries, cola in cases, an expired milk lot                                                                                                                                                                                          |
| <code>hub/tests/step12-stock.test.mjs</code>                                                       | 56 tests (the test hub can now leave out a sample file: <code>skipDev</code> )                                                                                                                                                                 |

### Screens (commit `0eac2df`)

- **Stock** list (in stock / low / out), **product stock** (sealed and loose, lots by expiry, history, damage / loss / adjust with reason and photo, open or make packs), **Add stock** (camera, USB scanner or typing; "packs or singles?"; unknown barcode → new product form with the barcode; last cost with ▲/▼ %; lot and expiry; the list stays on the phone until saved), **Counts**, **Approvals**, **Shrink report** with CSV export.
- Camera: `client/src/lib/scan.js` + `components/Scanner.svelte`: BarcodeDetector, else ZXing (@zxing/library 0.23.0) loaded only when needed (DL-78).

### Checked in the browser (local dev hub, signed in as Sam Staff, then Mira Manager)

- Stock list showed the sample levels (cola 82).
- Add stock: cola typed twice → quantity 2; water barcode → "Packs or singles?" → 6-pack at last cost \$3.60; unknown barcode → new product form with the barcode filled in → saved as Draft → "Add it to the delivery" → back in the list; saved 3 lines; the list cleared.
- Camera button: the preview browser blocks cameras; the app showed "Camera permission was refused ... or type the code". **Real phones still to test (R5).**
- Staff loss of 3 vape pods (\$27) → "a manager approves it"; manager approved → stock 2; shrink report \$27.00, Theft.
- Count: cola counted 3 sealed cases + 10 loose = 82, expected 84 (82 + 2 received), variance -2; submitted, approved; stock 82, lots add up to 82.
- Phone width: no sideways scrolling after a fix; the list survived a page reload.

## ZXing check without a camera

A script drew EAN-13 barcodes into grayscale pictures and decoded them the way the app does: clean and moderately noisy pictures were read correctly; very heavy noise was not (expected).

## Failed cases and fixes (session 4)

| Symptom                                               | Cause                                                                                                           | Fix                                                                          |
|-------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------|
| Every stock request failed: "stockCtx is not defined" | Each PocketBase JS handler runs in its own VM; helpers at the top of a <code>.pb.js</code> file are not visible | Helpers moved to <code>lib/stock_http.js</code>                              |
| Breaking a 12-pack gave 12 <i>sealed singles</i>      | The 12-pack "contains Singles"; the code put inner units back as sealed                                         | A pack whose inner unit is a single or by-weight unit opens into loose stock |
| My reject test: "already decided"                     | That write-off (\$18) was under the \$25 limit and posted at once                                               | The test receives more stock first and writes off \$30                       |
| ZXing tried QR, Data Matrix, Aztec... on every frame  | <code>decode()</code> resets the format list                                                                    | 1D reader used directly with the retail formats                              |
| 0628915120011 read as 628915120011                    | A 0-led EAN-13 is also a valid UPC-A; readers may report either                                                 | Lookup and uniqueness treat both forms as one code (DL-77), 3 tests          |
| Code box squeezed on a phone; "1 entries"             | Layout and plural                                                                                               | Fixed                                                                        |

Tests: **464 passed, 0 failed** (12 suites).

## 10. Session 5: step 2 deployed; P1 step 3 (till and checkout)

### Deploy (Sreya: "ok. proceed")

- `bash hub/scripts/deploy.sh --sample-data: version dev-aba2da4`, no errors. On the Pi: 11 stock levels (258.75 base units), 14 lots, integrity ok, PocketBase 52 MB.

### Hub side (commit 0c278bfe)

| File                                               | What                                                                                                                                                                                                                                                                                                                                                                                                                         |
|----------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791300006_p1_sales_schema.js    | <code>tills</code> , <code>cash_movements</code> , <code>sales</code> , <code>sale_lines</code> , <code>payments</code> , <code>tax_exemptions</code> , <code>holds</code> , <code>soft_holds</code> (read-only through the generic API)                                                                                                                                                                                     |
| hub/pb_migrations/1791300007_p1_sales_reference.js | Permissions <code>sales.sell</code> , <code>sales.discount</code> , <code>sales.tax_exempt</code> (cashier, manager), <code>sales.approve</code> , <code>sales.void</code> , <code>till.manage</code> (manager), <code>sales.view</code> (manager, accountant); settings: payment methods, cash rounding, US rate, discount and override limits, soft holds, exemption reasons, numbers, float, denominations, variance task |

|                                                                         |                                                                                                               |
|-------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------|
| hub/pb_hooks/lib/pricing_core.js                                        | Pure sale arithmetic: cart discount spread before tax, tax per type rounded once, tax included, cash rounding |
| hub/pb_hooks/lib/sales.js, lib/tills.js, lib/sales_http.js, sales.pb.js | Quote, complete, approvals, void, holds, soft holds, exempt report; tills: open, cash, close, Z report        |
| hub/tests/step13a-pricing.test.mjs, step13-sales.test.mjs               | 16 + 75 tests                                                                                                 |

Decisions DL-79..85 in docs/P1-mini-spec.md.

## Screens (commit 456a609)

**Sell** (grid, search, scanning, weight, packs or singles, ID check, line edit, cart discount, tax exempt, hold/recall, training, live quote, manager PIN, payments), **Till** (float, drops, pay-outs, no-sale, close, Z report, till settings), **Sales** (find, receipt, reprint, void, exempt report), **Receipt**.

## Checked in the browser (local dev hub, Cal Cashier)

- Opened till 1 with \$20×5, \$5×4, \$1×10 = \$130.00.
- Basket: cola scanned twice, chips, PLU 4011 bananas 1.235 kg → **\$9.88, cash \$9.90** (GST 35 ¢, PST 21 ¢, deposits 20 ¢), as worked by hand. Paid \$20 → change **\$10.10**, receipt S-000001.
- Vape pods: "Check ID ... 19+" → ID checked; 20% cart discount → \$17.91 → "Manager approval needed: Cart discount above 10%" → Mira Manager's PIN → card \*\*\*\*4242 approved → S-000002, "You saved \$4.00".
- Close: expected \$139.90, counted \$139.00 → Z report "Short \$0.90"; GST \$1.15 on \$22.96, PST \$1.33 on \$18.97, cash \$9.90, card \$17.91.
- Phone width: no sideways scrolling.

## Failed cases and fixes (session 5)

| Symptom                                      | Cause                                                                                                    | Fix                                                           |
|----------------------------------------------|----------------------------------------------------------------------------------------------------------|---------------------------------------------------------------|
| Approved sales still refused (403)           | PocketBase's shared store keeps a copy of a JS object; adding an approval to the map afterwards was lost | Write the map back after every change                         |
| Soft-hold test: nothing held                 | My setup sale was on the manager's device, which had no open till                                        | Test sells on the cashier's till                              |
| Training sales missing from the Z report     | They were not linked to the till                                                                         | Linked when a till is open, still kept out of money and stock |
| My rounding test failed                      | My arithmetic: 18.549 rounds to 19                                                                       | Test uses 18.49 → 18                                          |
| A shell edit failed with "unexpected EOF"    | Quotes inside a here-document                                                                            | Wrote those files with the file tool; nothing half-written    |
| Cart column pushed off screen                | The scrolling category row widened its grid column                                                       | <code>min-w-0</code> on the column                            |
| A typed banana weight went into the scan box | <code>autofocus</code> does not work on prompts that appear later                                        | Prompts take the focus themselves                             |
| Approval dialog build warning                | <code>bind:this</code> on a plain variable                                                               | <code>\$state (null)</code>                                   |

Tests: **555 passed, 0 failed** (14 suites).

## Failed cases and fixes

| Symptom                                 | Cause                                                                      | Fix                                               |
|-----------------------------------------|----------------------------------------------------------------------------|---------------------------------------------------|
| A device worked without the certificate | The person tapped through Chrome's warning                                 | Amber warning bar in the app (DL-62)              |
| "Hub gone" with no reboot               | Laptop SSH tunnel dropped for a few seconds                                | Correctly ignored (boot id unchanged)             |
| Writer crashed after pull 1             | 4 s timeout too short for a freshly booted Pi Zero listing ~17,000 records | 60 s, 3 attempts; confirmed writes kept in a file |
| My journal query found nothing          | The script logs in UTC, the Pi in Pacific time                             | Queried the right local time                      |

|                                                   |                                                                    |                                       |
|---------------------------------------------------|--------------------------------------------------------------------|---------------------------------------|
| <b>Hub came back without Wi-Fi</b>                | Netplan Wi-Fi files emptied by a power cut during boot             | chedam-netguard (DL-60)               |
| \n turned into a real line break in a Python edit | Quoting layers                                                     | Fixed the line directly               |
| <b>23 confirmed writes lost</b>                   | SQLite <code>synchronous=NORMAL</code>                             | <code>synchronous=FULL</code> (DL-61) |
| Intermittent test failure "one urgent task"       | Update/backup result applied in two writes, by two callers at once | One transaction per result (85da79a)  |

## Next

1. Sreya: go-ahead to deploy step 3 (selling) to the Pi; then try a sale on the iPhone/Android and the PC.
2. Camera test on real phones (R5, DL-63): Add stock → Scan with camera, and Sell → 📷.
3. P1 step 4: offline selling (tills keep selling when the hub is unreachable).
4. Open: Q1 accountant review (tax classes, deposits, exemption reasons; blocks the P1 release), Q2 return defaults; GST/PST numbers to enter in the business profile (they print on receipts).

## P0 steps 1-9 built and deployed; gate: 3-device login, update + rollback, backup + restore, memory under load passed: hub base, schema + event log, access, devices, forgot PIN, client app; work log started

### Summary

- Full health check of the re-flashed Pi: healthy, OS up to date, no hub software yet.
- Restored admin access (the sudoers rule is lost on every re-flash).
- Changed `setup-hub.sh` so the display setting can be switched **both ways** (monitor on or headless) and re-runs leave the boot config unchanged.
- Ran hub setup with `--keep-display`, rebooted and verified everything. HTTPS works by name and by IP.
- iPhone 13 Pro and Android 9 installed the new "Chedam Store CA" and opened the hub page without warnings ("Chedam hub is running").
- Started this cumulative work log ([Work Log/](#)).
- P0 step 1 (hub base) is complete.
- P0 step 3 (access) is complete: permission engine with role templates, overrides and BR-33, PIN sign-in with lockout, owner recovery code, "Who can do this?". 92 more tests (124 in total) passing; deployed and checked on the Pi.
- P0 step 4 (devices) is built and tested on the PC (67 new tests, 192 in total): pairing by code/QR or by approval request, device key checked on every request, name-then-PIN sign-in on paired devices only, one person per device, device manager (approve, lock, sign out, rename, assign, remove), certificate guide. Deployed to the Pi and checked; pairing the real phones is next.
- Forgot PIN decided and built: a manager sets a temporary PIN, and the person chooses their own at the next sign-in.
- P0 step 5 (client shell) is built and tested on the PC: an installable Svelte app that opens offline, with the connectivity bar, name-then-PIN sign-in, choosing a new PIN, owner sign-in, idle auto-lock, large text and high contrast, and the device manager with QR codes. It replaces the temporary pages. 213 hub tests pass.
- P0 step 6 (setup wizard) is built, tested and deployed: one-time setup code on a new hub, owner and first device in one step, recovery code, business profile, logo and receipt, team, storage, features, references, backups; skipped steps become tasks. 251 hub tests pass.
- P0 step 7 (backups) is built and tested **on the Pi** with a disk image: encrypted, verified backups, restore test, and a real restore in 2-3 s that keeps the HTTPS certificate authority. Sreya's hard drive showed read errors, so nothing was written to it. 281 hub tests pass.
- **3 devices signed in as the owner** (iPhone, Android 9 phone, Surface laptop) after fixing a sign-in mix-up and the laptop certificate. Issue logged: the Android 9 phone runs Chrome 98, too old for the app's styles (Tailwind 4 needs Chrome 111+), so its screens are misaligned.
- P0 step 8 (hub health page) is built and deployed; 302 hub tests pass.
- P0 step 9 (updates) is built and tested on the Pi: a signed install in 1.7 s, and a broken update rolled back automatically in 4 s; tampered packages are refused. 323 hub tests pass.
- First backup to the new SD card made by Sreya and verified independently; **0.9.0 published** to `chedam-releases` and downloaded and verified by the Pi from GitHub.
- P0 gate, memory under load: 10 devices for 5 minutes peak at **108 MB** (budget 150 MB). A stress burst first reached 194 MB; per-device rate limits now hold it at 120 MB.
- Re-tested the step 3 bugs and issues: all fixed. A third copy of one bug (recovery code) was found and fixed.
- P0 step 2 (schema v1 + event log) is complete: 14 tables, reference data, dev sample store, a transactional append-only event log, 32 automated tests passing, deployed to the Pi with a backup first.

Naming note: the local folder `chedam-updates/` in the project is Sreya's YouTube and notes repo (gitignored). It is **not** the update channel. Nothing is renamed; the public update-package repo name will be decided when step 9 (Updates) starts.

### 1. Health check (before any change)

One SSH session ran these checks:

```
whoami; hostname; hostname -I; cat /proc/device-tree/model; grep PRETTY /etc/os-release; uname -r
uptime; sudo -n true; free -m; df -h / /boot/firmware; lsblk
vcgencmd measure_temp; vcgencmd get_throttled; vcgencmd measure_volts core
timedatectl; ip route; ping -c2 1.1.1.1
apt list --upgradable; dpkg-query -W <packages>; systemctl is-active ...; systemctl --failed
cat /boot/firmware/config.txt /boot/firmware/cmdline.txt
```

| Area          | Result                                                                    |
|---------------|---------------------------------------------------------------------------|
| Hardware      | Pi Zero 2 W Rev 1.0, 33.2 °C, throttled 0x0, core 1.2875 V                |
| OS            | Debian 13 trixie, kernel 6.18.50+rpt-rpi-v8, 0 pending updates            |
| Uptime        | 1 day 12 h, load 0.00, no failed units                                    |
| Memory / disk | 415 MB total, 273 MB available / 119 GB card, 2.3 GB used                 |
| Network       | 192.168.50.101 via 192.168.50.1, internet ping 7 ms                       |
| Time          | NTP synced, America/Vancouver, no RTC                                     |
| sudo          | <b>Needed a password</b> (re-flash reset it)                              |
| Hub software  | Not installed: no caddy, chrony, ufw, sqlite3 or <code>/opt/chedam</code> |
| Display       | <code>video=HDMI-A-1:1280x720@60D</code> present (monitor in use)         |

### 2. Admin access

**Failed case: Permission denied (publickey) when restoring sudo**

- The `ssh -t chedam "...sudo tee..."` command was typed **inside an SSH session on the Pi** (prompt `chedam@chedam:~ $`).
- So the Pi tried to SSH into itself and had no key for that. Re-flashing was not needed.
- Fix: run only the inner command on the Pi:

```
echo 'chedam ALL=(ALL) NOPASSWD:ALL' | sudo tee /etc/sudoers.d/010-chedam && sudo chmod 440 /etc/sudo
sudo -n true && echo OK
```

### 3. Display becomes a switch (DL-24 updated)

Sreya's requirement: the monitor is optional on the Zero 2 W pilot, but the option must stay. Pi 4 production hubs will use a display to operate the hub directly.

Change in `hub/scripts/setup-hub.sh` (boot config section):

- Removes any earlier chedam block, then writes a block between `# chedam-begin` and `# chedam-end`.
- `--keep-display`: display driver `vc4-kms-v3d` and display detection **on**, Bluetooth off.
- No flag: headless. The display driver and detection are off, `gpu_mem=16`, Bluetooth off; this saves ~50 MB of RAM.
- Audio and camera detection are always off.

```
sudo bash ~/hub/scripts/setup-hub.sh --keep-display      # monitor on (current)
sudo bash ~/hub/scripts/setup-hub.sh                    # headless
sudo reboot                                              # after switching
```

**Failed case: an extra `[a11]` line on every run**

- The test (switching off, on, off, on on a copy of `config.txt`) worked, but each run appended another `[all]` line. It was harmless but untidy.
- Fix: moved `[all]` inside the marked block. The original config (`config.txt.chedam-orig`, saved by the first run) was restored and setup run twice. Both runs gave the same checksum (`d91ff929`), and the only differences from the original were audio off, camera detection off and the chedam block.

#### 4. Hub setup on 192.168.50.101

```
scp -r scripts system chedam:hub/
# on the Pi: download + verify PocketBase
wget pocketbase_0.40.4_linux_arm64.zip checksums.txt
grep linux_arm64 checksums.txt | sha256sum -c -      # OK
sudo apt-get update
sudo bash ~/hub/scripts/setup-hub.sh --keep-display
sudo systemctl reboot
```

Verification after reboot:

| Check                   | Result                                                                                                |
|-------------------------|-------------------------------------------------------------------------------------------------------|
| Services                | chedam-hub, caddy, chrony, avahi-daemon, ufw active; no failed units                                  |
| Memory                  | PocketBase 28 MB + Caddy 37 MB = 65 MB (budget 150 MB, NFR-08); 264 MB available with display on      |
| Watchdog                | RuntimeWatchdogUsec=14s                                                                               |
| Time                    | chrony, 0.0000007 s from NTP, leap normal                                                             |
| Temperature             | 38.6 °C, throttled 0x0                                                                                |
| Display                 | /dev/dri/card0 present                                                                                |
| Firewall                | 22, 80, 443/tcp and 5353/udp allowed (IPv4 + IPv6)                                                    |
| CA download             | <code>http://chedam.local/ca.crt</code> → 200, "Chedam Store CA - 2026 ECC Root", valid to 2036-08-13 |
| HTTPS                   | <code>https://chedam.local/api/health</code> and <code>https://192.168.50.101/api/health</code> → 200 |
| Certificate check       | <code>openssl s_client ... -CAfile ca.crt</code> → Verify return code 0, with and without SNI         |
| HTTP                    | Redirects to HTTPS (302)                                                                              |
| Caddy errors since boot | 0                                                                                                     |

PC test commands (Git Bash; `--resolve` avoids Windows mDNS problems, and `--ssl-no-revoke` avoids the Schannel revocation error):

```
curl --resolve chedam.local:80:192.168.50.101 -o ca.crt http://chedam.local/ca.crt
curl --ssl-no-revoke --resolve chedam.local:443:192.168.50.101 --cacert ca.crt https://chedam.local/a
curl --ssl-no-revoke --cacert ca.crt https://192.168.50.101/api/health
```

#### 5. Phones (risk R5, first part)

| Device                    | How                                                                                                                             | Result                                                                |
|---------------------------|---------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------|
| iPhone 13 Pro, iOS 26.6.1 | Safari <code>http://chedam.local/ca.crt</code> → install profile → Settings > General > About > Certificate Trust Settings → on | <code>https://chedam.local</code> shows the placeholder, no warning   |
| Android 9                 | Chrome <code>http://192.168.50.101/ca.crt</code> → install for VPN and apps                                                     | <code>https://192.168.50.101</code> shows the placeholder, no warning |

The camera test over HTTPS comes later, when the client app exists.

#### 6. Work log started

- Folder `Work Log/`: one Markdown source per day in `Work Log/entries/YYYY-MM-DD.md`.
- `tools/worklog/build_worklog.py` builds `Work Log/Chedam-Work-Log-YYYY-MM-DD.pdf` with **all** days, newest first.
- Earlier PDFs are kept, so each day has its own complete snapshot.

```
python tools/worklog/build_worklog.py          # newest day
python tools/worklog/build_worklog.py 2026-10-05 # a specific day
```

The days 2026-10-02 and 2026-10-03 were written up from the session records and `docs/P0-pi-setup-log-2026-10-03.pdf`.

## 7. P0 step 2: schema v1 and event log

Spec basis: Section 10 (data model, event log), Section 13 (build process: migrations and sample data first), NFR-20 (reversible migrations), BR-30 (UTC), BR-33 (managers cannot grant more than they hold).

### Files added

| File                                                     | Purpose                                                                                                                                                                                                                                                                                            |
|----------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791200001_p0_schema_v1.js             | 13 new tables + the PocketBase <code>users</code> collection extended: business, locations, settings, modules, permissions, roles, permission_overrides, devices, storage_areas, tasks, events, backups, updates. Common fields on every table. API rules all closed (superuser only) until step 3 |
| hub/<br>pb_migrations/1791200002_p0_reference_data.js    | 22 modules (3 core always on, 15 switchable, 4 later), shop-type presets, 20 P0 permissions (5 owner-only), 5 role templates, 12 default settings                                                                                                                                                  |
| hub/<br>pb_migrations_dev/1791200100_dev_sample_store.js | Dev-only sample store: "Demo Grocery", main location, grocery preset modules, 4 storage areas, 5 people (one per role, random unknown passwords), 1 setup task                                                                                                                                     |
| hub/pb_hooks/event_log.pb.js + lib/event_log.js          | Event log: one <code>events</code> row per create/update/delete, in the same transaction; actor and device stamped from the request; append-only                                                                                                                                                   |
| hub/tests/step2-schema-eventlog.test.mjs                 | 32 automated tests against a throwaway local PocketBase                                                                                                                                                                                                                                            |
| hub/scripts/deploy.sh                                    | PC → hub deploy: copy, SQLite online backup + integrity check, rsync, restart, health, migrations, errors                                                                                                                                                                                          |
| docs/conventions.md                                      | Data, event-log, migration and workflow rules for all phases                                                                                                                                                                                                                                       |

### Design choices

- **Common fields:** `id` (a device may create it offline), `created_at`, `updated_at`, `created_by`, `updated_by`, `device_id`, `deleted_at`. `updated_by` was added beyond the spec's list, so each change records who made it.
- **The event log runs inside the same transaction** as the change (`onRecord*Execute + runInTransaction`). If the event can't be written, the change is rolled back, so the log never misses a write.
- **Actor and device are stamped by the hub** in request hooks. A client cannot forge `created_by`, and the device comes from the `X-Chedam-Device` header (verified in step 4).
- **Hidden fields** (`pin_hash`, `recovery_code_hash`, `key_hash`, `pairing_code_hash`) never reach the API or the log.
- **Role levels:** owner 100, manager 80, accountant 50, cashier 40, staff 30. Owner-only permissions: `modules.manage`, `setup.run`, `owner.manage`, `backups.restore`, `updates.install`.
- **Sample data is separate** from real migrations, so a store hub never receives demo records.

### Commands

```
# local tests (PC, Git Bash)
PB_BIN='C:\Tools\pocketbase.exe' node hub/tests/step2-schema-eventlog.test.mjs
# deploy to the Pi with sample data
bash hub/scripts/deploy.sh --sample-data
# verify on the Pi
ssh chedam 'sudo -u chedam-hub sqlite3 /opt/chedam/pb_data/data.db "select table_name, action, count('
```

### Failed cases and fixes

| Symptom                                                                 | Cause                                                                                                        | Fix                                                                                                          |
|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|
| pocketbase.exe: command not found in Git Bash                           | That shell started before C:\Tools was added to PATH                                                         | Full path C:\Tools\pocketbase.exe / PB_BIN                                                                   |
| migrate down hung                                                       | It waits for a y/N confirmation                                                                              | Pipe y (input: "y\n" in the tests)                                                                           |
| Python check query error (ESCAPE expression must be a single character) | Backslash escaping in an inline script                                                                       | Filter with <code>substr(name,1,1) != '_'</code>                                                             |
| Sample migration: Cannot read property 'forEach' of undefined           | A JSON field read with <code>get()</code> returns raw bytes                                                  | <code>JSON.parse(record.getString("value"))</code>                                                           |
| Test stop step hung                                                     | Waited for the exit of a process that had already exited                                                     | Check <code>exitCode/signalCode</code> first                                                                 |
| Create returned 400 "Something went wrong"                              | <code>e.request</code> doesn't exist in PocketBase 0.40 JS hooks (found with <code>serve --dev logs</code> ) | <code>e.requestInfo().headers["x_chedam_device"]</code> (names lowercased, <code>_</code> → <code>_</code> ) |
| A Python edit put real newlines inside JS strings                       | Escaping in a heredoc                                                                                        | Fixed with a direct edit                                                                                     |

### Test results (PC, 32/32 passed)

- Schema/reference: 22 modules, 3 core on, 15 switchable, 20 permissions, 5 roles, owner holds all, manager holds no owner-only permission, 12 settings.
- Sample: business + location, 4 storage areas, 5 people, 1 task, 7 grocery modules on.
- Event log: device-made id accepted; forged `created_by` overwritten; device stamped; create/update/soft-delete/delete each logged with correct before/after/changed; delete keeps the last state; no PIN hash, password or tokenKey in the log; events can't be edited or deleted, even by a superuser.
- Atomicity: with the event write forced to fail, the create fails and the record is not in the table.
- Migrations: down 3 and up again both clean.

### On the Pi (after deploy)

| Check                 | Result                                                                                                       |
|-----------------------|--------------------------------------------------------------------------------------------------------------|
| Pre-deploy backup     | <code>pre-deploy-&lt;UTC&gt;.db</code> , integrity ok                                                        |
| Migrations applied    | schema v1, reference data, dev sample store                                                                  |
| Rows                  | modules 22, permissions 20, roles 5, settings 12, business 1, locations 1, storage_areas 4, users 5, tasks 1 |
| Events                | 78 = every write above (incl. 7 module updates for the grocery preset)                                       |
| Secrets in events     | 0                                                                                                            |
| SQLite journal        | WAL                                                                                                          |
| PocketBase memory     | 42 MB (budget 150 MB)                                                                                        |
| Errors in the journal | none                                                                                                         |

## 8. P0 step 3: Access

Spec basis: FR-1.03 (owner password, PIN, printed recovery code), FR-1.04 (people with role and PIN), FR-1.09 (owner signs in on any device), FR-1.10 (role templates, per-person overrides with end date, "Who can do this?"), NFR-11 (hub-side permission checks, PIN lockout after 5 tries, auto-lock), BR-33 (managers can't grant more than they hold).

### Files added or changed

| File | Purpose |
|------|---------|
|------|---------|

|                                                           |                                                                                                                                                                                                                                                 |
|-----------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791200003_p0_access.js                 | PIN and recovery code become bcrypt password fields (hidden); pin_set and recovery_code_created_at added; API rules set on all 14 tables; token lifetime 12 h. Reversible                                                                       |
| hub/pb_hooks/lib/access.js                                | Permission engine: effective permissions (role + allow overrides – deny overrides; owner = all), the per-table access map, protected fields, self/assignee field limits, BR-33 checks for people, roles, overrides, modules, settings, business |
| hub/pb_hooks/lib/auth.js                                  | PIN rules, lockout counter, recovery code generator, secret check                                                                                                                                                                               |
| hub/pb_hooks/access.pb.js                                 | Guard on every list/view/create/update/delete; password sign-in lockout; token refresh check; endpoints (below)                                                                                                                                 |
| hub/pb_migrations_dev/1791200101_dev_sample_pins.js       | Dev-only PINs for the 5 sample people (test values; dev hubs only)                                                                                                                                                                              |
| hub/pb_hooks/lib/event_log.js                             | Fix: put the original app back after the transaction (see failed cases)                                                                                                                                                                         |
| hub/tests/lib/hub.mjs, step3-access.test.mjs, run-all.mjs | Shared test harness, 92 access tests, one-command runner                                                                                                                                                                                        |
| docs/conventions.md, docs/P0-mini-spec.md                 | Access rules for later phases; decisions DL-28 to DL-32                                                                                                                                                                                         |

## Endpoints

| Method and path                       | Who                                             | What                                                                      |
|---------------------------------------|-------------------------------------------------|---------------------------------------------------------------------------|
| GET /api/chedam/auth/pin-users        | anyone on the LAN (step 4: paired devices only) | Names for the till sign-in screen                                         |
| POST /api/chedam/auth/pin             | anyone                                          | {user, pin} → sign-in token; wrong tries count toward lockout             |
| POST /api/chedam/users/{id}/pin       | yourself, or users.manage above them            | Set or change a PIN (4-6 digits, no repeats or straight runs)             |
| POST /api/chedam/users/{id}/unlock    | users.manage above them                         | Clear a lockout                                                           |
| POST /api/chedam/owner/recovery-code  | owner                                           | New printable code, shown once (format xxxxx-xxxxx-xxxxx-xxxxx)           |
| POST /api/chedam/auth/recover         | anyone with the code                            | {email, code, new_password} → new password + sign-in; the code is used up |
| GET /api/chedam/access/me             | signed in                                       | My role and effective permissions                                         |
| GET /api/chedam/access/users/{id}     | self or users.view                              | Someone's effective permissions and where each comes from                 |
| GET /api/chedam/access/who-can/{code} | users.view                                      | "Who can do this?" (via role or override, with end date)                  |

## Who may do what (summary of the access map)

- **Anyone signed in:** reads the business profile, locations, settings, modules, permissions, roles and storage areas.
- **People:** list with users.view; a person can view and edit their own record (name, email, phone, language, accessibility, password only); add/edit others needs users.manage; giving or changing roles needs access.manage; no hard delete.
- **Overrides:** access.manage only; never on yourself; only on people below you; never grant what you don't hold; owner-only permissions only by the owner.
- **Roles:** templates can't be deleted; only the owner edits templates; the owner role always holds everything; managers create and edit only roles below their own level.
- **Modules:** owner only; only enabled can change; core can't be switched off; "later" modules can't be switched on; who/when stamped.

- **Settings:** `security.*` owner only; keys can't be renamed.
- **Audit log:** `events.view`. Tasks: `tasks.view` / `tasks.manage` (the assignee may update status/note). Devices: `devices.view` / `devices.manage`. Backups and updates: read-only through the API.

## Failed cases and fixes

| Symptom                                                                                                      | Cause                                                                                                                                                                                                                            | Fix                                                                                                                          |
|--------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------|
| No way to check a bcrypt PIN in JS hooks                                                                     | <code>\$security</code> has no bcrypt                                                                                                                                                                                            | Use a PocketBase <code>password</code> field:<br><code>record.getRaw("pin").validate(plain)</code>                           |
| Owner recovery sign-in failed: failed to delete all previous MFAs ... transaction has already been committed | The event-log wrapper replaced <code>e.app</code> with the transaction and never restored it, so PocketBase's clean-up after a password change used a finished transaction. <b>This would have broken every password change.</b> | Restore <code>e.app</code> in a <code>finally</code> block after <code>runInTransaction</code>                               |
| 5th wrong password returned 400, not 423                                                                     | The failure was counted, but that same response didn't report the new lock                                                                                                                                                       | After counting, re-read the person and answer "locked" (same as PIN sign-in)                                                 |
| Assumed PocketBase leaves <code>e.record</code> empty on a wrong password                                    | Traced with debug lines: the hook gets the person and <code>e.next()</code> checks the password                                                                                                                                  | Removed the extra lookup and the debug lines                                                                                 |
| Step 2 test still sent <code>pin_hash</code> and reversed only 3 migrations                                  | The schema changed in step 3                                                                                                                                                                                                     | Test uses the <code>pin</code> field, checks for no <code>\$2a\$</code> hashes, and reverses every Chedam migration it finds |
| <code>sed</code> edits to the test harness didn't apply                                                      | Escaping in shell quoting                                                                                                                                                                                                        | Direct edits                                                                                                                 |

## Test results (PC)

`node hub/tests/run-all.mjs` → step2 32/32, step3 92/92.

Step 3 covers: - PIN sign-in, the PIN list showing no secrets, and wrong PINs refused. - Lockout after 5 wrong PINs and after 5 wrong passwords (423), and unlock by a manager but not a cashier. - The PIN rules. - Who can read and change each table. - Managers adding cashiers but not owners or other managers, and editing people below them but not the owner. - Role changes, and the rule that you can't change your own role. - Suspending someone signs them out at once. - Overrides: allow, deny, past and future end dates, owner-only, and "can't grant what you don't hold". - Role templates, the owner role, and deleting custom roles. - The module, setting and business rules. - The recovery code: shown once, case-insensitive, used once. - Who-can and my-permissions. - The audit trail: lockouts, overrides and module switches are logged, and no hashes appear anywhere.

## On the Pi (after deploy, checked on the Pi itself)

| Check                                  | Result                                                                                                                                   |
|----------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------|
| Deploy                                 | Backup + integrity ok; migrations <code>1791200003_p0_access.js</code> and <code>1791200101_dev_sample_pins.js</code> applied; no errors |
| PIN list                               | 5 people                                                                                                                                 |
| Signed-out request                     | 401                                                                                                                                      |
| PIN sign-in time                       | 0.50 s (bcrypt cost 10 on the Pi Zero 2 W)                                                                                               |
| <code>access/me</code> for the cashier | role cashier, permissions <code>tasks.view</code>                                                                                        |
| Cashier lists people                   | 403                                                                                                                                      |
| bcrypt hashes in the event log         | 0                                                                                                                                        |
| PocketBase memory                      | 44 MB                                                                                                                                    |

The dev PINs are in the dev seed file only and are not repeated in this log.

## 9. Re-test of the step 3 bugs and issues

Sreya asked which 2 bugs and 2 issues came up in step 3, whether they were fixed, and to test them again.

| # | Kind          | What                                                                                                                                             | Status after re-test                                                                                                                          |
|---|---------------|--------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| 1 | Bug           | Event-log wrapper left <code>e.app</code> pointing at a finished transaction, so the owner's recovery sign-in (and every password change) failed | Fixed. Tests "recovery code + new password signs the owner in" and "new password works" pass                                                  |
| 2 | Bug           | The 5th wrong password answered 400 instead of 423 (locked)                                                                                      | Fixed. Test "5 wrong passwords lock the owner too" passes                                                                                     |
| 3 | Issue         | PocketBase JS hooks have no <code>bcrypt</code> function                                                                                         | Solved with PocketBase <code>password</code> fields; PIN tests pass                                                                           |
| 4 | Issue         | The step 2 test was out of date after the step 3 schema change                                                                                   | Updated; step 2 suite passes (now 33 tests)                                                                                                   |
| 5 | Bug found now | Same as bug 2 on the <b>recovery code</b> path: the 5th wrong code answered 400, not 423                                                         | Fixed: one shared <code>auth.failAndThrow()</code> now serves PIN, password and recovery code. New test "5th wrong recovery code answers 423" |

Baseline before any change: `node hub/tests/run-all.mjs` → 32/32 and 92/92.

## 10. P0 step 4: Devices (FR-1.07, 1.08)

### Files added or changed

| File                                                                                                                     | Purpose                                                                                                                                                                                                                                                                                                                                |
|--------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>hub/pb_migrations/1791200004_p0_devices.js</code>                                                                  | <code>paired_via</code> , <code>paired_at</code> on devices; generic create closed; settings <code>devices.pairing_code_minutes</code> (10), <code>devices.online_seconds</code> (120), <code>devices.max_pending_requests</code> (10). Reversible                                                                                     |
| <code>hub/pb_hooks/lib/devices.js</code>                                                                                 | Device check for every <code>/api/</code> request, pairing codes, keys, last seen, device view                                                                                                                                                                                                                                         |
| <code>hub/pb_hooks/devices.pb.js</code>                                                                                  | Middleware + endpoints (below)                                                                                                                                                                                                                                                                                                         |
| <code>hub/pb_hooks/access.pb.js</code>                                                                                   | Password and PIN sign-in need a paired device (owner excepted); sign-in records who is on the device; assigned devices; recovery-code fix                                                                                                                                                                                              |
| <code>hub/pb_hooks/lib/access.js</code>                                                                                  | Devices: generic create closed, protected fields, BR-33 on assigning                                                                                                                                                                                                                                                                   |
| <code>hub/pb_hooks/lib/auth.js</code> , <code>lib/event_log.js</code>                                                    | <code>failAndThrow()</code> ; device stamped only when verified                                                                                                                                                                                                                                                                        |
| <code>hub/pb_public/</code>                                                                                              | Temporary pages until the Svelte client (step 5): <code>device-setup.html</code> (certificate guide, works over HTTP), <code>pair.html</code> (pair, then pick your name and enter PIN), <code>devices.html</code> (device manager with QR code), <code>assets/</code> (shared CSS/JS, vendored QR library, <code>VENDORED.md</code> ) |
| <code>hub/system/Caddyfile</code>                                                                                        | HTTP serves the guide and its CSS; <code>/hub.json</code> gives the hub IP for QR codes                                                                                                                                                                                                                                                |
| <code>hub/scripts/deploy.sh</code>                                                                                       | Also updates the Caddy config when it changed (keeps the IP, validates, keeps a copy, reloads)                                                                                                                                                                                                                                         |
| <code>hub/tests/lib/hub.mjs</code> , <code>step2...</code> , <code>step3...</code> , <code>step4-devices.test.mjs</code> | <code>pair()</code> helper and automatic device headers; existing suites now sign in on paired devices; 67 new tests                                                                                                                                                                                                                   |
| <code>docs/P0-mini-spec.md</code> , <code>docs/conventions.md</code>                                                     | DL-33 to DL-38, device rules, the open "forgot PIN" item                                                                                                                                                                                                                                                                               |

### Endpoints

| Method and path                                    | Who            | What                                                                      |
|----------------------------------------------------|----------------|---------------------------------------------------------------------------|
| POST <code>/api/chedam/devices/pairing-code</code> | devices.manage | <code>{name, type}</code> → one-time code <code>xxxx-xxxx</code> (10 min) |
| POST <code>/api/chedam/devices/pair</code>         | new device     | <code>{code}</code> → device id + key, approved                           |
| POST <code>/api/chedam/devices/request</code>      | new device     | <code>{name, type}</code> → id + key, waits for approval                  |
| GET <code>/api/chedam/devices/me</code>            | the device     | Its status and who is signed in (works while pending or locked)           |

|                                                                       |                |                                                                               |
|-----------------------------------------------------------------------|----------------|-------------------------------------------------------------------------------|
| POST /api/chedam/devices/me/sign-out                                  | the device     | Sign out whoever is on it                                                     |
| GET /api/chedam/devices                                               | devices.view   | Device manager list: online, signed in, assigned, version, last seen, browser |
| POST /api/chedam/devices/{id}/approve, lock, unlock, sign-out, revoke | devices.manage | Device manager actions                                                        |
| PATCH /api/collections/devices/records/{id}                           | devices.manage | Rename, type, assign person or printer                                        |

### Sign-in flow (Sreya: "select name and then PIN")

The device is paired once. After that the sign-in page shows the people's names as large buttons. Tap your name, enter your PIN on the keypad and press OK. A wrong PIN shakes the keypad and shows "Wrong name or PIN". After 5 wrong tries the person is locked (423). "Not you? Back to names" returns to the list. The owner also has "sign in with email and password", which works on any device. "Forgot your PIN?" shows the current options (see the open item in the mini-spec).

### Commands

```
PB_BIN='C:\Tools\pocketbase.exe' node hub/tests/run-all.mjs
npm pack qrcode-generator@2.0.4 # vendored QR library; integrity checked against the npm register
```

### Failed cases and fixes

| Symptom                                                                          | Cause                                                                                                            | Fix                                                                                                |
|----------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------|
| Shell edit script stopped with "unexpected EOF while looking for matching quote" | Quotes and backticks of JS code inside a bash heredoc                                                            | Wrote the Python edit script to a file and ran it                                                  |
| Helpers at the top of <code>devices.pb.js</code> would be undefined in handlers  | Each PocketBase JS handler runs in its own VM and cannot see top-level variables of the <code>.pb.js</code> file | Moved them into <code>lib/devices.js</code> (loaded with <code>require</code> inside each handler) |
| Test "key and code hashes never in API output" failed                            | The test read the record as <b>superuser</b> , and PocketBase shows hidden fields to superusers on purpose       | The test now reads as the manager (who never sees them); superuser = development admin only        |
| "Paired as ..." message vanished at once                                         | The status refresh after pairing cleared the message                                                             | Show the message after the refresh                                                                 |
| PIN typed by the browser test tool did nothing                                   | The tool inserts text without key events (a real keyboard sends them)                                            | Tested by tapping the on-screen keypad, as on a phone                                              |
| Deploy to the Pi blocked                                                         | Deploying to the hub needs Sreya's approval in this session                                                      | Sreya approved; deployed                                                                           |

### Test results (PC)

node hub/tests/run-all.mjs → step2 33/33, step3 92/92, step4 67/67 (192 in total).

Step 4 covers: - **Pairing codes**: who may make them, the format, lower case with a space accepted, single use, expiry, approved by the code's maker. - **Device keys**: unknown, wrong or missing keys refused (401); keys never in API output or the log. - **Ask to join**: pending until approved; the cap on open requests (429). - **Device needed**: no PIN list or PIN sign-in without a device; a cashier's password sign-in or token without a device refused; the owner works on an unpaired browser. - **One person per device**: the earlier token is refused, tokens can't move devices, sign-out. - **Device manager**: list (online, signed in, version, own device marked); sign-out, lock (423)/unlock, rename; protected fields; no generic create. - **Assigned devices**: list and sign-in limited; BR-33 on assign and remove. - **Revoke**: device and token refused, no double remove. - **Recovery**: the 423 fix, and owner recovery on a till. - **Log**: last-seen writes throttled (≤1 event for 10 requests), lock/unlock/revoke logged with actor and the manager's device, no hashes. - **Guessing**: 20 wrong codes pause pairing (429).

### Browser check (local dev hub, PC)

Paired with a code from the URL. The name list showed 5 sample people. A wrong PIN gave "Wrong name or PIN" and the right PIN signed in (manager), with the Device manager link shown. The device manager showed the till online with

its version and browser. Pair a new device showed the QR code, the code and a countdown. At phone width (375 px) the certificate guide opened the Android steps automatically, with no sideways scrolling.

### On the Pi (after deploy, checked from the PC over the LAN)

| bash hub/scripts/deploy.sh --sample-data |                                                                                                                                               |
|------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| Check                                    | Result                                                                                                                                        |
| Deploy                                   | Backup integrity ok; 1791200004_p0_devices.js applied; Caddy config updated for 192.168.50.101 and reloaded (old copy in backups/); no errors |
| Certificate guide over plain HTTP        | http://192.168.50.101/device-setup.html 200, its CSS 200; other HTTP pages still redirect to HTTPS (302)                                      |
| https://192.168.50.101/hub.json          | {"ip":"192.168.50.101","name":"chedam.local"}                                                                                                 |
| Pages over HTTPS                         | pair.html, devices.html, assets/qrcode.js 200                                                                                                 |
| PIN list without a device                | 403                                                                                                                                           |
| Made-up device header                    | 401                                                                                                                                           |
| Wrong pairing code                       | 400                                                                                                                                           |
| Device settings                          | 3 devices.* settings present                                                                                                                  |
| PocketBase memory                        | 40 MB (budget 150 MB)                                                                                                                         |
| Temperature                              | 37.0 °C                                                                                                                                       |

## 11. Forgot PIN: temporary PIN (Sreya’s decision)

Sreya: "manager reset temporary and user need to reset again".

- A PIN set by someone else (manager with users.manage above the person, or superuser) is **temporary**. It works for 24 h (security.temp\_pin\_hours).
- With a temporary PIN, the hub allows only these until a new PIN is chosen: setting your own PIN, access/me, devices/me and sign-out. Everything else answers 403 "Choose your own new PIN first." (auth.pinChangeGate, run in the request middleware).
- The new PIN must differ from the temporary one, and the PIN rules apply. An expired temporary PIN is refused with a clear message.
- pin\_must\_change and pin\_temp\_expires\_at are protected fields, and both changes are in the audit log.
- Migration 1791200005\_p0\_temp\_pin.js (reversible). Tests: step3b-temp-pin.test.mjs, 14/14.
- In the app: the manager uses "Someone forgot their PIN" on the home screen; the person then sees "Choose your own PIN" (enter twice).

## 12. P0 step 5: client shell (FR-1.09, FR-12.01, NFR-16/17)

### Hub side

| File                                            | Purpose                                                                                                                               |
|-------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------|
| hub/pb_migrations/1791200006_p0_connectivity.js | Settings network.check_url (Cloudflare's 204 check) and network.hotspot_ssids                                                         |
| hub/pb_hooks/lib/net.js, status.pb.js           | Check once a minute (cron); GET /api/chedam/status → {internet: offline/router/hotspot, hub_time}; open to waiting/locked devices too |
| hub/pb_hooks/access.pb.js                       | access/me also returns pin_must_change, large text, high contrast, language                                                           |
| hub/tests/step5-status.test.mjs                 | 7 tests: open, values, hub clock, offline/online via the check address, guests can't force a check, waiting device                    |

### Client (client/)

| Part             | What                                                                                                                                                                                                                                                                |
|------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Stack            | Svelte 5.57.1, Tailwind 4.3.3, Vite 8.3.2, qrcode-generator 2.0.4 (same integrity hash as checked in step 4). Exact versions; <code>npm audit</code> 0 vulnerabilities                                                                                              |
| Build            | <code>npm run build</code> → <code>hub/pb_public/</code> (about 35 KB gzipped JS + 4 KB CSS). <code>deploy.sh</code> builds it before copying                                                                                                                       |
| PWA              | Manifest, icons (drawn by <code>client/scripts/make-icons.mjs</code> , no image library needed), service worker generated with the exact file list                                                                                                                  |
| Screens          | Pair (code / ask to join), Waiting (approval or locked), Names, PIN pad, Choose your own PIN, Owner sign-in, Home (modules switched on, "Someone forgot their PIN", My settings, Install), Devices (manager)                                                        |
| Connectivity bar | Online (router) / Online (hotspot) / Offline, "Hub not reachable", device clock warning (2+ min)                                                                                                                                                                    |
| Auto-lock        | After <code>security.auto_lock_minutes</code> idle: signed out on that device, name list returns                                                                                                                                                                    |
| Removed          | The temporary step 4 pages ( <code>pair.html</code> , <code>devices.html</code> , <code>assets/chedam.js</code> , vendored <code>qrcode.js</code> ). The certificate guide moved to <code>client/public/</code> and now opens the app with <code>/?pair=CODE</code> |
| Caddy            | HTTP serves <code>/device-setup.html</code> and <code>/setup.css</code>                                                                                                                                                                                             |

## Browser check (local dev hub on the PC)

| Check                  | Result                                                                                                                                                                                                                                 |
|------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Session kept           | The earlier paired till and Mira's session came back after the app update                                                                                                                                                              |
| Connectivity bar       | "Online (router)"                                                                                                                                                                                                                      |
| Forgot PIN, end to end | Mira set a temporary PIN for Sam → Sam signed in with it → forced to "Choose your own PIN". A mismatch was caught, reusing the temporary PIN was refused, the new PIN was set and Sam reached his home screen (no Devices tile: staff) |
| Offline shell          | Service worker active, 8 files cached. With the hub <b>stopped</b> , a reload still opened the app with the red "Hub not reachable" bar and a clear message                                                                            |
| Recovery               | Hub started again → bar back to "Online (router)"; Sam's session came back                                                                                                                                                             |
| Device manager         | Mira → Devices → Pair a new device → QR code + code + countdown                                                                                                                                                                        |
| Phone size, dark mode  | Readable, no sideways scrolling                                                                                                                                                                                                        |
| Certificate guide      | Page and <code>setup.css</code> 200; continues to <code>/?pair=CODE</code>                                                                                                                                                             |

## Failed cases and fixes

| Symptom                                                                        | Cause                                                                                                                                                                                    | Fix                                                                             |
|--------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------|
| Step 2 test "12 default settings" failed (13)                                  | It counted settings; step 4/5 add their own                                                                                                                                              | Checks the 12 step-2 keys by name                                               |
| Svelte warning: <code>pad</code> not declared with <code>\$state</code>        | Component reference in a plain variable                                                                                                                                                  | <code>let pad = \$state()</code>                                                |
| Offline reload showed a blank page                                             | The module script is requested with an <code>Origin</code> header and the hub answers <code>Vary: Origin</code> , so the cached copy (stored without <code>Origin</code> ) did not match | Cache look-ups use <code>ignoreVary: true</code> (our files are content-hashed) |
| Crash "Cannot read properties of null (reading 'user')" when signing out       | Home still drew <code>s.me.user</code> for a moment after sign-out cleared it                                                                                                            | Home renders only while someone is signed in                                    |
| After the hub came back, the name list kept its error until the next 30 s poll | Nothing reacted to the hub returning                                                                                                                                                     | The app refreshes as soon as the hub answers again; the name list retries       |
| First page load after restarting the dev hub was refused by the browser pane   | The page was opened before the server was listening                                                                                                                                      | Waited 2 s and opened it again                                                  |

## Test results (PC)

node hub/tests/run-all.mjs → step2 33/33, step3 92/92, step3b 14/14, step4 67/67, step5 7/7 (213).

### On the Pi (after deploy, Sreya's go-ahead)

| Check                                  | Result                                                                                                                                                |
|----------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| Deploy                                 | App built (35 KB gzipped JS); backup integrity ok; migrations ...05_p0_temp_pin, ...06_p0_connectivity applied; Caddy updated and reloaded; no errors |
| App over HTTPS (IP and chedam.local)   | /, sw.js, manifest.webmanifest, icons: 200                                                                                                            |
| Certificate guide over HTTP            | device-setup.html, setup.css: 200                                                                                                                     |
| /api/chedam/status                     | internet: router; hub clock matches                                                                                                                   |
| Wi-Fi name readable by the hub (nmcli) | yes, so hotspot detection works                                                                                                                       |
| PocketBase memory                      | 40 MB                                                                                                                                                 |

### 13. Phones paired; bug: the app froze on the iPhone with the Pi off

Sreya paired the Android 9 phone ("9lite") and the iPhone; both appear in the device list. With the Pi powered off, the app on the iPhone froze: no button did anything.

|          |                                                                                                                                                                                                                                                                                                                                                                                                          |
|----------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Cause    | When the hub is switched off, a phone's requests are not refused; they wait (nothing answers at that address). (1) The service worker waited for page loads with <b>no time limit</b> . (2) Each button waited up to 8 s for the hub, some twice in a row, with no feedback. (3) The status bar checked only every 30 s. The PC test had missed it: a stopped server on the same machine refuses at once |
| Fix      | Page loads get 3 s, then the cached app opens. Requests get 6 s; once the hub is known to be down, requests fail at once until it answers again. The bar checks every 5 s while the hub is down. Signing out with the hub off returns to the name list. "Check" shows "Checking..."                                                                                                                      |
| Test     | A test server that accepts connections and never answers (like a switched-off hub seen from a phone): bar red after 4.0 s; sign-out 51 ms; reload shows the app at once with the red bar; real hub started again (page not touched): back to "Online (router)" with the name list after 4.3 s                                                                                                            |
| Deployed | Commit 6ede814; deploy ok (backup integrity ok, no errors)                                                                                                                                                                                                                                                                                                                                               |

Note: a phone gets the fixed version the next time it opens the app **while the Pi is on**. Open it, wait a few seconds, then close and reopen once.

### 14. P0 step 6: setup wizard (FR-1.01-1.06, 1.13, 1.15)

Sreya chose: **a setup code on the hub** for the first device (DL-44).

#### Hub

| File                                         | Purpose                                                                                                                                                                                                                        |
|----------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/<br>pb_migrations/1791200007_p0_setup.js | devices.paired_via gains "setup" (reversible)                                                                                                                                                                                  |
| hub/pb_hooks/lib/setup.js,<br>setup.pb.js    | Setup code (made at startup, by a once-a-minute job and on demand; kept in pb_data/setup-code); monitor message pb_data/console.issue: GET /api/chedam/setup/status, POST /api/chedam/setup/start, POST /api/chedam/setup/step |
| hub/pb_hooks/lib/access.js                   | business.setup_state changes only through the step endpoint                                                                                                                                                                    |
| hub/system/chedam-console.path +<br>.service | When the hub's message changes, the monitor's login screen re-reads it (agetty --reload); /etc/issue.d/chedam.issue links to the message                                                                                       |
| hub/scripts/setup-hub.sh, deploy.sh          | Install the monitor units and link; print the setup code on a new hub                                                                                                                                                          |
| hub/tests/step6-setup.test.mjs               | 38 tests on a hub <b>without</b> sample data                                                                                                                                                                                   |

The 38 tests cover: - **The code**: made on a new hub, kept across restarts, shown in the monitor message. - **Refused at start**: a wrong code, a short password, a guessable PIN and a bad email. - **Start**: returns the device key and recovery

code once. Afterwards the code file is gone, the monitor message changes and the code can't be reused. - **The new owner:** PIN, password and recovery code all work. The first device is approved and the owner is signed in on it. - **Store records:** one business with Canadian defaults, plus the main location. - **Steps:** - Language, clock and owner are already done after start. - The profile can be edited, but `setup_state` can't be changed directly. Unknown steps are refused. - A skipped step becomes one task (skipping twice doesn't make two), and doing it later closes the task. When all steps are done, setup is complete. - **Who may run it:** a manager can't mark steps, and start is refused once the store is set up. A PIN the owner sets for someone is temporary. - **Audit log:** setup writes are logged as `system:setup`, with no secrets.

## App

| Screen                      | What                                                                                                                                                                        |
|-----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Set up your store (3 parts) | Welcome + language + setup code; clock check against the hub (warns at 2+ minutes); owner name, email, password twice, PIN twice, device name                               |
| Recovery code               | Shown once, Print button, "I have printed it or written it down" required                                                                                                   |
| Wizard                      | Progress chips (✓ done, ↻ skipped), resumes at the first unfinished step, every step has Save or Skip                                                                       |
| Business profile            | Store and legal name, type, address, phone, email, GST/HST, PST, BN, CAD, time zone, fiscal year start, prices with or without tax; the main location gets the same address |
| Logo and receipt            | Logo upload (up to 2 MB), colours from the logo (editable, readability warning), receipt header and footer, live receipt preview                                            |
| Your team                   | Add people with role, first PIN (temporary), phone, email                                                                                                                   |
| Storage areas               | "Add the usual four", add with temperature range, mark not used                                                                                                             |
| Features                    | Ticked from the shop-type preset, change any; core always on, later ones not available                                                                                      |
| References                  | Bank name, processor and merchant ID, CRA payroll, CBSA importer, accountant; warning: no account numbers or passwords                                                      |
| Backups                     | Explained; skip only (adds the task) until step 7                                                                                                                           |
| Home                        | "Finish setting up your store (N steps left)", task list with "Do it", Store setup tile, "Print a new recovery code" (owner)                                                |

## Browser check (brand-new local hub, no sample data)

| Check                                           | Result                                                                                                                                                                                                                            |
|-------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Hub start                                       | <code>setup-code</code> and the monitor message made at startup                                                                                                                                                                   |
| First screen                                    | "Set up your store · 1 of 3"; no sideways scrolling at phone width                                                                                                                                                                |
| Wrong code                                      | Refused at the end with a clear message, back to part 1                                                                                                                                                                           |
| Clock check                                     | "OK (under 2 minutes)"                                                                                                                                                                                                            |
| Right code typed in lower case without the dash | Owner created; this browser paired as "Owner's computer"; recovery code shown once; Continue locked until confirmed                                                                                                               |
| Business profile                                | Saved; wizard moved to Logo and receipt (4 of 10)                                                                                                                                                                                 |
| Logo                                            | Test logo in orange <code>#e8701a</code> and navy <code>#1b2f5e</code> : both found exactly; button colour darkened to <code>#b45714</code> for readable white text; receipt preview with logo, name, address, GST number, footer |
| Team                                            | Cashier added with a temporary first PIN                                                                                                                                                                                          |
| Features                                        | Convenience preset ticked Promotions, Labels, Vendors and Purchasing, Regulated Items, Operations                                                                                                                                 |
| Skips                                           | References and Backups skipped → 8 of 10 done, two tasks on Home with "Do it"                                                                                                                                                     |
| Saved data                                      | Logo file, colours, receipt text, GST number in the database; logo loads without sign-in (200 image/png)                                                                                                                          |

## Failed cases and fixes

| Symptom | Cause | Fix |
|---------|-------|-----|
|---------|-------|-----|

|                                                                        |                                                                                              |                                                                                                           |
|------------------------------------------------------------------------|----------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------|
| Setup routes answered 404                                              | <code>onServe</code> does not exist in PocketBase JS hooks, so the whole file failed to load | <code>onBootstrap</code> (after start-up) plus a once-a-minute job and on-demand from the status endpoint |
| A <code>sed</code> edit broke a line in <code>setup.js</code>          | The inserted comment swallowed the rest of the line                                          | Fixed by hand                                                                                             |
| Heredoc test script failed in bash                                     | Quotes inside the heredoc                                                                    | Wrote the test file directly                                                                              |
| Svelte warnings "captures the initial value of business"               | The forms are meant to start from the saved values once                                      | <code>untrack()</code> makes it explicit                                                                  |
| Storage: Shelf showed "0 to 0 °C" and the four areas were in A-Z order | PocketBase number fields have no "empty" (they save 0); all four got the same sort number    | 0 to 0 shows as "room temperature"; each area gets its own sort number                                    |

## On the Pi (after deploy)

| Check                                 | Result                                                                                                                                                                                     |
|---------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Deploy                                | Backup integrity ok; <code>1791200007_p0_setup.js</code> applied; monitor units installed; no errors                                                                                       |
| Monitor message                       | <code>console.issue = "Chedam hub: https://4"</code> (this dev hub has an owner, so no setup code); <code>/etc/issue.d/chedam.issue</code> linked; <code>chedam-console.path</code> active |
| <code>/api/chedam/setup/status</code> | <code>needs_setup: false</code>                                                                                                                                                            |
| PocketBase memory                     | 41 MB                                                                                                                                                                                      |

The setup code on the **monitor** will be seen for real on a brand-new hub, for example the spare-card restore test in step 7/10. The dev hub keeps its sample store.

## 15. P0 step 7: backups (FR-1.14, NFR-03, NFR-04, NFR-12)

Sreya's plan: use her hard drive as the second drive in the testing phase. Production: OTG adapter plus a spare SD card.

## Design (DL-48 to DL-52)

| Part                                                                                                       | What                                                                                                                                                                                                                                                                                                                              |
|------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Root helper <code>hub/system/chedam-backup</code> (Python, installed to <code>/opt/chedam/bin</code> )     | Actions: <code>drives</code> , <code>key-init</code> , <code>key-show</code> , <code>run</code> , <code>test-restore</code> ; technician-only <code>restore</code><br><code>FILE --key KEYFILE</code>                                                                                                                             |
| Hub ↔ helper                                                                                               | Hub writes <code>pb_data/backup/request.json</code> ; <code>chedam-backup.path</code> runs the helper (low priority: <code>Nice=10</code> , idle I/O); answer in <code>result.json</code>                                                                                                                                         |
| One backup                                                                                                 | SQLite online snapshot → <code>PRAGMA integrity_check</code> → <code>gzip</code> → <b>age</b> encryption → <code>Chedam-Backups/&lt;store&gt;/chedam-YYYYMMDD-HHMMSS-&lt;kind&gt;.db.gz.age + .sha256 + .ca</code> (HTTPS CA, encrypted) → read back from the drive, decrypt, check again, compare table counts = <b>verified</b> |
| Retention                                                                                                  | Newest per day 14, per week 8, per month 12, plus the newest 3; only Chedam's own files                                                                                                                                                                                                                                           |
| Key                                                                                                        | <code>age X25519</code> key in <code>/opt/chedam/keys</code> (root only); owner prints it; owner can show it again                                                                                                                                                                                                                |
| Hub ( <code>lib/backup.js</code> , <code>backups.pb.js</code> , <code>migration ... 08_p0_backups</code> ) | Status, <code>drives</code> , choose drive, key (owner), <code>run</code> , restore test (owner), nightly schedule ( <code>backup.schedule</code> , retry after 1 h, 3 per day), lost-job detection (30 min), one urgent task on failure closed by the next good backup, first backup completes the setup step                    |
| App                                                                                                        | Wizard Backups step: drive → key (print, confirm) → first backup. Backups screen: last good backup, back up now, restore test, drive and nightly time, backup key, recent backups. Home tile                                                                                                                                      |
| Scripts                                                                                                    | <code>deploy.sh</code> and <code>setup-hub.sh</code> install <code>age</code> , the helper and its units                                                                                                                                                                                                                          |

## Sreya's hard drive

|          |                                                                                                                                                                                                                                                                                              |
|----------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Drive    | Seagate ST31500341AS (Barracuda 7200.11, about 2009), 1.5 TB, NTFS, label "SCRAPP", in a USB enclosure (XT-U33502) with its own power; 1.07 TB free                                                                                                                                          |
| Pi power | Clean the whole time ( <code>throttled=0x0</code> ); a 3.5" drive has its own adapter                                                                                                                                                                                                        |
| Problem  | 4 read errors, each after a 30 s timeout and a USB reset, at sectors 6,229,920 to 6,230,944 (about 3.2 GB into the disk). On NTFS that is near where the Master File Table usually sits, and writing any file updates that table                                                             |
| Decision | <b>Nothing was written to the drive</b> , to protect Sreya's files. It was only mounted read-only once (to read free space) and unmounted. Advice: copy anything important off it on Windows and check it there ( <code>chkdsk</code> ); use a healthy USB stick or drive for Chedam backups |

## Failed cases and fixes

| Symptom                                                                            | Cause                                                                                      | Fix                                                                                                                     |
|------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|
| Restore test got 409 "A backup job is still running"                               | A job marked failed as "lost" (no answer for 30 min) left the in-memory busy flag set      | The flag is cleared with the lost job, and a run counts as busy only while its record is still running (test caught it) |
| Test "request went to the helper" failed                                           | It checked before the fake helper's 100 ms poll                                            | Wait 400 ms                                                                                                             |
| Listing drives took <b>2 minutes</b> with the hard drive                           | The listing mounted each drive to read free space; the sick drive took minutes to mount    | The listing never mounts (now 0.55 s); free space comes from each backup                                                |
| A stuck mount could hold up the helper indefinitely                                | No time limit                                                                              | 90 s limit; reports "The drive is not responding"                                                                       |
| The test image was not listed                                                      | Loop devices have type "loop"                                                              | Allowed for test images only<br>( <code>CHEDAM_BACKUP_ALLOW_LOOP=1</code> )                                             |
| Test script lost the image ID                                                      | <code>set -e</code> stopped before saving it; <code>losetup</code> needs <code>sudo</code> | Looked up by file                                                                                                       |
| The pre-restore copy was readable by every account on the Pi                       | <code>copy2</code> kept root 644                                                           | <code>chedam-hub</code> , 0640                                                                                          |
| A rebuilt hub would get a new HTTPS certificate authority (every phone reinstalls) | Not part of the backup                                                                     | Each backup saves the CA (encrypted); restore puts it back                                                              |
| step2 test failed once: "unknown shorthand flag: 'O'"                              | The random test password started with "-" (about 1 in 64) and was read as a command option | Test passwords start with "Pw" (both harnesses)                                                                         |

## Tests

PC: `node hub/tests/run-all.mjs` → **281** (step7-backups 30/30, with a fake helper that answers like the real one).

On the Pi, the real helper with a 256 MB disk image (ext4) as the drive:

| Check                                                         | Result                                                                                                                                                            |
|---------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Drive list                                                    | 0.55 s; lists the image and Sreya's drive without mounting                                                                                                        |
| Key                                                           | Made; secret never printed in the terminal                                                                                                                        |
| Backup                                                        | <b>1.1 s</b> , 44 KB encrypted; verified (read back, decrypted, integrity ok, same counts: 5 users, 100 events, ...)                                              |
| On the drive                                                  | Only <code>Chedam-Backups/demostore/...age</code> , <code>.sha256</code> , <code>.ca</code> ; file starts with <code>age-encryption.org/v1:sha256sum -c</code> OK |
| Restore test                                                  | Consistent, 0.2 s                                                                                                                                                 |
| Real restore ( <code>chedam-backup restore ... --yes</code> ) | <b>2-3 s</b> including the hub restart; health ok; integrity ok; same data; pre-restore copy kept                                                                 |

|                     |                                                                                                                  |
|---------------------|------------------------------------------------------------------------------------------------------------------|
| HTTPS after restore | Same CA fingerprint (12:4B:3C:BF...); the laptop with this morning's <code>ca.crt</code> connects without change |
| Hub-to-helper path  | A request written as <code>chedam-hub</code> was picked up by the path unit and answered                         |
| Power               | <code>throttled=0x0</code> throughout; PocketBase 39 MB                                                          |

Restore procedure for a dead hub: `docs/P0-backup-restore.md`.

## 16. Backup card, sign-in mix-up, certificates, 3 devices signed in

### New backup card

Sreya connected a 7.4 GB SD card in a USB reader ("Storage Device", FAT32, UUID A8D7-32C4). Read-only check: the first 64 MB read in 5 s with no errors. Power stayed clean (`throttled=0x0`). The card is supported; nothing has been written to it yet. The first backup is made from the app (Backups → drive → key → Back up now → Test a restore).

### Sign-in mix-up (not a logic bug)

| What Sreya saw                                                           | Cause (from the hub's records)                                                                                                                                                                                                                                                      | Fix                                                                    |
|--------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------|
| iPhone at <code>https://chedam.local</code> showed a "registration" page | The iPhone was <b>not paired</b> : its pairing code ("13pro") was made but never used, so the app showed "Pair this device"                                                                                                                                                         | New pairing code from the owner on the laptop, scanned with the iPhone |
| Owner email + password refused on the iPhone and the laptop              | <b>Demo Owner never had a password</b> : the dev sample store gives every person a random, unknown password (0 password changes in the audit log). The file <code>pb_migrations_dev/1791200101_dev_sample_pins.js</code> holds <b>PINs</b> for the name + PIN screen, not passwords | Sreya set a password in the admin UI (users → Demo Owner)              |
| "Locked"                                                                 | 5 wrong tries locked the owner for 15 minutes ( <code>pin_locked_until</code> 00:53 UTC), the lockout working as designed (NFR-11)                                                                                                                                                  | Cleared <code>pin_locked_until</code> in the admin UI (or wait 15 min) |
| Sample people had wrong tries (Demo Owner 2, Cal Cashier 4)              | Guessed PINs                                                                                                                                                                                                                                                                        | Use the PINs from the dev seed file                                    |

Lessons for the docs and for later: - The dev sample owner needs a known way in. A dev hub's owner password is set in the admin UI (`/_/_`). The setup wizard does this properly for real stores. - Telling apart "not paired", "no password set" and "locked" is hard for the user. The screens could be clearer (for example "This device is not paired yet" in place of a page that looks like registration). Noted for the step 5/6 polish.

### Certificates on the three devices

| Device                                 | Before                                                                                                                          | After                                                                                                               |
|----------------------------------------|---------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------|
| Android 9 (9lite)                      | Trusted (paired, HTTPS since the morning)                                                                                       | Same                                                                                                                |
| Surface laptop (Windows, Chrome)       | <b>Not trusted</b> : Chrome showed "Not secure" with <code>https</code> crossed out on <code>https://192.168.50.101/_/_/</code> | Sreya installed <code>ca.crt</code> into Current User → Trusted Root Certification Authorities and restarted Chrome |
| iPhone 13 Pro (iOS 26.6.1, Chrome 154) | Profile installed; trust toggle needed checking                                                                                 | Certificate Trust Settings → Chedam Store CA on; paired                                                             |

Test for any device: `https://192.168.50.101/hub.json` opens with no warning.

### Result: 3 devices signed in (P0 gate item "3 devices log in")

| Device        | Hub record                   | Browser (from the hub)         | Signed in  |
|---------------|------------------------------|--------------------------------|------------|
| iPhone 13 Pro | "13pro", approved, app 0.5.0 | iOS 26.6.1, Chrome 154 (CriOS) | Demo Owner |

|                                          |                                           |                             |            |
|------------------------------------------|-------------------------------------------|-----------------------------|------------|
| Android 9 phone (Honor 9 Lite, LLD-AL10) | "9lite", approved, app 0.5.0              | Android 9, <b>Chrome 98</b> | Demo Owner |
| Surface laptop                           | Owner on any device (not paired, FR-1.09) | Chrome on Windows           | Demo Owner |

Two earlier iPhone pairing attempts ("13pro", "13pronew") were removed in the device manager (status revoked), as intended.

### Issue: Android 9 phone shows misaligned screens

|         |                                                                                                                                                                                                                                                                                                                                                 |
|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Symptom | Screens work but are not properly aligned on the Android 9 phone                                                                                                                                                                                                                                                                                |
| Cause   | The phone's Chrome is version <b>98</b> (February 2022). The app uses Tailwind CSS 4, which needs Chrome 111+ (cascade layers, <code>color-mix()</code> , <code>oklch</code> colours). Chrome 98 ignores those rules, so part of the styling is lost. My assumption that Android 9 would have Chrome 138 was wrong (risk note in the mini-spec) |
| Options | (a) Update Chrome on that phone from the Play Store (Android 9 still gets Chrome up to about 138), which fixes it at once if updates work. (b) Make the app's CSS work on older Chrome too (Tailwind 3.4 or a compatibility build), the safer choice for pilot stores with old phones                                                           |
| Status  | Decided (DL-53): no extra work; Sreya will test on another, up-to-date phone                                                                                                                                                                                                                                                                    |

## 17. P0 step 8: hub health page (FR-12.09)

### What it shows

| Item                      | Source (read as the hub's sandboxed user)                                                          | Status rule                                                                   |
|---------------------------|----------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------|
| Hub running for           | <code>/proc/uptime</code> , model from <code>/proc/device-tree/model</code>                        | info                                                                          |
| Temperature               | <code>/sys/class/thermal/thermal_zone0/temp</code>                                                 | warn $\geq 70$ °C, bad $\geq 80$ °C (the Pi slows down)                       |
| Power supply              | <code>rpi_volt</code> sensor <code>in0_lcrit_alarm</code> (under-voltage now)                      | bad if too low                                                                |
| Hub app memory            | <code>/proc/self/status</code> <code>VmRSS</code>                                                  | warn > 150 MB (NFR-08)                                                        |
| Free memory               | <code>/proc/meminfo</code> <code>MemAvailable</code>                                               | warn < 100 MB, bad < 50 MB                                                    |
| Free storage / store data | <code>df</code> on <code>pb_data</code> ; size of <code>data.db</code> + WAL                       | warn < 15 %, bad < 5 %                                                        |
| Clock                     | <code>chronyc -c tracking</code> (stratum, offset, leap); <code>/dev/rtc0</code>                   | warn if not synchronised or > 2 s off; notes "no battery clock (RTC)" (DL-23) |
| Internet                  | connectivity status (FR-12.01)                                                                     | info                                                                          |
| Last backup               | backups status                                                                                     | bad if no drive or > 50 h; warn > 26 h (NFR-04)                               |
| Last restore test         | <code>backup.last_restore_test</code>                                                              | bad if failed; warn > 35 days (NFR-03)                                        |
| Devices online            | device manager view                                                                                | warn if devices wait for approval                                             |
| Waiting to sync           | offline queue arrives with selling (P1)                                                            | info                                                                          |
| Versions                  | app build ( <code>sw.js</code> ), schema (newest non-dev migration), PocketBase, Caddy, OS, kernel | info                                                                          |
| Pending updates           | <code>updates</code> table (channel in step 9)                                                     | warn if one failed                                                            |

- The top line shows the worst status ("All good" / "Needs a look" / "Needs attention now"). Answers are cached for 20 s, and "Check now" forces a fresh check.
- Endpoint: `GET /api/chedam/health` (health.view: owner, manager). App: Hub health screen (refreshes every 30 s, links to Backups and Devices), a home tile with ✓ / ! / ✗, and a red "The hub needs attention" card on the home screen.

### Checks

| Check | Result |
|-------|--------|
|-------|--------|

|                                                                                                                   |                                                                                                                                                                                     |
|-------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Which readings the hub user can access on the Pi                                                                  | All, except <code>vcgencmd/throttling</code> flags (needs root); the <code>rpi_volt</code> sensor gives under-voltage instead                                                       |
| Same commands <b>inside the hub's systemd sandbox</b> ( <code>systemd-run</code> with the service's restrictions) | chrony: synced, stratum 2; df: 117.7 GB free of 125.4 GB; 40.8 °C; power alarm 0; Caddy 2.6.2; PocketBase 0.40.4                                                                    |
| Tests <code>step8-health.test.mjs</code>                                                                          | 21/21: 401 signed out, 403 cashier, every item present with a status, no backup drive → bad, 30 h old backup → warn, fresh → ok, restore test "never", schema shown, cached answers |
| All tests                                                                                                         | <b>302</b> passing                                                                                                                                                                  |
| Deploy                                                                                                            | Backup integrity ok; no errors; endpoint answers 401 without sign-in                                                                                                                |

## Failed cases and fixes

| Symptom                                                    | Cause                                                                                                        | Fix                                                        |
|------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|------------------------------------------------------------|
| "Schema" showed<br><code>1791200101_dev_sample_pins</code> | The newest migration was the dev sample-data one                                                             | Ignore files containing <code>_dev_</code>                 |
| The fix then showed "Schema ?"                             | Backslash escaping through Python → JS → SQL <code>ESCAPE</code> broke the query (the same trap as on day 2) | <code>instr(file, '_dev_') = 0</code> , no escaping needed |

## 18. P0 step 9: updates (FR-12.02, FR-12.04, NFR-20)

Sreya created the public repo `repatikosamid-prog/chedam-releases` (DL-54). The full guide is in `docs/P0-updates.md`; the decisions are DL-55 to DL-58.

## What was built

| Part                                                                                                           | What                                                                                                                                                                                                                                                                                                                    |
|----------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Signing key                                                                                                    | Ed25519 made with OpenSSL in <code>~/.chedam/update-signing.key</code> (outside the repo; Windows permissions: Sreya's account only); public key <code>hub/system/update-signing.pub</code>                                                                                                                             |
| <code>tools/release/make-release.sh</code>                                                                     | Build the app → stage hub code (refuses dev migrations) → <code>manifest.json</code> (version, notes, commit, migrations) → <code>tar.gz</code> → sign → check the signature against the repo's public key → signed <code>stable/channel.json</code> in <code>../chedam-releases</code> ; <code>--publish</code> pushes |
| <code>hub/system/chedam-update (root) + .path/.service</code>                                                  | <code>check</code> (https channel, signatures, checksum), <code>scan</code> (USB <code>chedam-update/</code> and <code>/opt/chedam/updates/inbox</code> ), <code>install</code> (signature → DB snapshot + code copy → swap → restart → health or automatic rollback)                                                   |
| Hub: migration ...<br><code>09_p0_updates</code> , <code>lib/updates.js</code> ,<br><code>updates.pb.js</code> | Status, check online/USB, install now (owner) or in the 02:00–05:00 window, results read after the restart, an urgent task on failure, a daily background check when online (not blocking)                                                                                                                              |
| App                                                                                                            | Updates screen (installed version, check online / USB stick, release notes, "signed ✓", install now / tonight, history), home tile; product version 0.9.0                                                                                                                                                               |
| Scripts                                                                                                        | <code>deploy.sh/setup-hub.sh</code> install the helper, units and public key; <code>/opt/chedam/keys</code> stays root-only (it also holds the backup key); a deploy writes <code>VERSION = dev-&lt;commit&gt;</code>                                                                                                   |
| Local clone                                                                                                    | <code>C:\Users\Venkata\Desktop\Projects\chedam-releases</code> with a README                                                                                                                                                                                                                                            |

## Tests

PC: `step9-updates.test.mjs` 21/21 with a fake helper: - **Check**: cashier refused; online check finds 2 updates; the channel address is passed; no duplicate records; the offline check is recorded. - **USB scan**: finds the package. - **Install**: manager refused, owner installs now; a second install is refused while one runs (409); the result is read after the restart. - **Rollback**: reported, with an urgent task. - **Install window**: scheduled → installed when the window opens; the task closes. - **Daily check**: sent without waiting, its answer recorded at the next tick. - **Audit log**: installs and rollbacks are logged.

All suites: **323**.

On the Pi with the real helper and real signed packages (local, not yet published):

| Test                                                                                 | Result                                                                                                                                                                                                    |
|--------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Package 0.9.0                                                                        | 118,545 bytes, 44 files, no dev data, keys or databases; signature ok                                                                                                                                     |
| Scan of the inbox                                                                    | Found 0.9.0 (signed)                                                                                                                                                                                      |
| Install 0.9.0 over <code>dev-cd633e3</code>                                          | <b>1.7 s</b> (3 s end to end); VERSION 0.9.0; app build <code>0.9.0-15ad57cd6968</code> ; 5 users and 129 events unchanged; integrity ok; dev migrations kept                                             |
| Broken 0.9.1 (signed; migration throws on purpose; built in the scratch folder only) | First run: rolled back after <b>93 s</b> (waited out the 90 s limit). After the fail-fast fix: rolled back after <b>4 s</b> ; version 0.9.0; data and integrity unchanged; broken migration never applied |
| Good 0.9.0 again ( <code>--force</code> ) after the fixes                            | 1.6 s, healthy                                                                                                                                                                                            |
| Tampered package (1 byte added)                                                      | <b>Refused:</b> "The signature does not match"; nothing changed                                                                                                                                           |

## Failed cases and fixes

| Symptom                                                                                    | Cause                                                                                                      | Fix                                                                           |
|--------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------|
| Permission command for the key failed ( <code>Invalid parameter ":USERNAME:(R,W)"</code> ) | PowerShell variables written inside a Bash command                                                         | Ran it in PowerShell; the key is now readable by Sreya's account only         |
| <code>deploy.sh/setup-hub.sh</code> would have opened <code>/opt/chedam/keys</code> to 755 | Copy-paste of the updates folder line                                                                      | Kept at 700 (the backup key lives there)                                      |
| Hub test: second install was not refused; test crashed                                     | The fake helper finished in 0.2 s, so the first install was already done                                   | The fake install takes 1.5 s; the 409 is checked at once                      |
| Daily check would block a hub job for up to 2 min                                          | It waited for the helper's answer                                                                          | It now only sends the request; the answer is read at the next tick            |
| <code>make-release.sh</code> : "Cannot find module 'c/Users/.../package.json'"             | Node on Windows cannot read Git Bash paths written inside a script                                         | Read the version with a relative path                                         |
| Building the broken test package: "Cannot connect to C: resolve failed"                    | GNU tar takes <code>C:</code> as a remote host                                                             | Used <code>/c/...</code> paths                                                |
| Broken update took 93 s to roll back                                                       | The installer waited the full 90 s although the hub logged "failed to apply migration" after 3 s           | It watches the log while waiting and rolls back at the first crash            |
| After that fix the rollback was reported as "did not come up" although it had worked       | The rollback check read the log "since this second", which still held the crash lines from the same second | Journal <b>cursors</b> : each check reads only lines written after it started |

## 19. First real backup verified; 0.9.0 published

### Backup to the new SD card (made by Sreya in the app)

| Check                                      | Result                                                                                                                                                                                                                                 |
|--------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Records                                    | 2 backups, both <b>verified</b> : a nightly one, which started by itself the moment the drive and key were ready (tonight's slot had not run yet, the catch-up rule), and the first backup from the wizard (48,118 bytes); 7.9 GB free |
| Setup task "choose a backup USB drive"     | done                                                                                                                                                                                                                                   |
| Sreya's restore test in the app            | passed, consistent, 0.3 s                                                                                                                                                                                                              |
| Independent check (card mounted read-only) | Only Chedam's folder added (plus Windows' "System Volume Information"); <code>sha256sum -c</code> OK for both; both files start with <code>age-encryption.org/v1;</code> <code>.ca</code> files present                                |
| Independent restore test (helper)          | Newest backup rebuilt in 0.3 s, consistent (5 users, 4 devices, 120 events, ...)                                                                                                                                                       |
| Power                                      | <code>throttled=0x0</code> (the 4 I/O errors on record are the old hard drive's)                                                                                                                                                       |

## Publishing 0.9.0 (with Sreya's OK)

```
bash tools/release/make-release.sh --notes "Chedam 0.9.0 (P0): ..." --publish
```

| Check                                          | Result                                                                                              |
|------------------------------------------------|-----------------------------------------------------------------------------------------------------|
| Package                                        | chedam-app-0.9.0.tar.gz, 118,582 bytes, sha256 d6f0b698..., built from committed code, signature ok |
| Public repo chedam-releases                    | Commit 3c87ec6: README, stable/channel.json(.sig), packages/chedam-app-0.9.0.tar.gz(.sig)           |
| Pi downloads from GitHub (chedam-update check) | Channel and package signatures valid, checksum matches; 0.9.0 found as newer than dev-f632959       |

## Issue found and fixed

| Symptom                                                                 | Cause                                                                                                                                                                                                                                                                 | Fix                                                                                                        |
|-------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------|
| Git warned "LF will be replaced by CRLF" for files in the releases repo | Git on Windows may convert line endings in files it takes for text. A 64-byte signature has no zero byte about 78% of the time, so Git can treat it as text, and changing a single byte breaks the signature. This time the files arrived intact (verified by the Pi) | .gitattributes with * -text in chedam-releases (commit ba25f3c); make-release.sh refuses to run without it |

## 20. P0 gate: memory under load (NFR-07, NFR-08, risk R6)

### Method

| Part     | What                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|----------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Test hub | tools/loadtest/pi-loadtest.sh: a <b>throwaway</b> hub on the Pi (same PocketBase binary, hooks and migrations including the sample store; its own data folder; 127.0.0.1:8099 only), started with the <b>same limits as the service</b> (GOMEMLIMIT 100 MiB, MemoryHigh 150 MB, MemoryMax 220 MB), plus a sampler (RSS/peak every 2 s, load, free memory). The store's real hub was not touched. Deleted afterwards                                                    |
| Load     | tools/loadtest/hub-load.mjs on the laptop through an SSH tunnel: <b>10 devices</b> (twice the pilot's 5, NFR-07), each paired and signed in by PIN, every 1-2 s: connectivity, device status, my permissions, settings, modules, storage areas; writes (create + update, each also writes an event) by the roles allowed to; a PIN sign-in every 10 rounds (bcrypt); health page; plus every 30 s a <b>burst</b> of simultaneous audit-log reads (100 events per page) |
| Duration | 5 minutes per run                                                                                                                                                                                                                                                                                                                                                                                                                                                      |

### Results

| Run                                                    | Requests | Errors                  | Latency p50 / p95 / p99 | Hub memory peak (VmHWM) | Pi free memory (lowest) | NFR-08      |
|--------------------------------------------------------|----------|-------------------------|-------------------------|-------------------------|-------------------------|-------------|
| 1 (script mistakes, see below)                         | 12,729   | 1,106                   | 34 / 136 / 530 ms       | 86 MB                   | 174 MB                  | (not valid) |
| 2: burst of <b>50</b>                                  | 10,805   | 0                       | 37 / 766 / 5,034 ms     | <b>197 MB</b>           | 92 MB                   | <b>FAIL</b> |
| 3: burst of <b>10</b> (all devices at once: realistic) | 11,723   | 0                       | 35 / 94 / 552 ms        | <b>108 MB</b>           | 174 MB                  | <b>PASS</b> |
| 4: burst of 50, <b>with rate limits</b>                | 11,961   | 360 × 429 (bursts only) | 36 / 470 / 920 ms       | <b>120 MB</b>           | 162 MB                  | <b>PASS</b> |

The real hub afterwards: 43 MB, healthy through Caddy.

### Fix: per-device rate limits (DL-59)

- Migration 1791200010\_p0\_rate\_limits.js:
- limits: audit-log lists 10 per 3 s, all lists 40 per 3 s, PIN sign-in 15 per 10 s, all API calls 150 per 3 s;
- the device's address comes from X-Forwarded-For (Caddy sets it), and 127.0.0.1 is exempt.
- Without the trusted header, every device would look like 127.0.0.1 behind Caddy and share one allowance.

- Test `step10-ratelimit.test.mjs` (5/5):
- a flooding device gets about 10 answers, the rest 429;
- another device is not affected, and the flooder is served again after 3 s;
- a busy till (36 requests in 3 s) is never limited;
- 127.0.0.1 is exempt.
- All suites: **328**.

## Failed cases and fixes

| Symptom                                               | Cause                                                                                                                                                                                              | Fix                                                                                                                                  |
|-------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------|
| Run 1: 1,106 errors                                   | Test script: cashier and accountant tills tried to add storage areas (correctly refused, 403); the bursts sorted the audit log by <code>created_at</code> , but its field is <code>at</code> (400) | Writes only by roles allowed to; sort by <code>at</code> .<br>The run-1 memory figure was not valid: the bursts had failed instantly |
| Run 2: 197 MB, p99 5 s                                | 50 simultaneous audit-log reads: each SQLite connection keeps its own page cache, and PocketBase has no option to cap connections                                                                  | Per-device rate limits (DL-59)                                                                                                       |
| "Through Caddy" check on the Pi failed (curl exit 77) | My Pi account cannot read Caddy's certificate file                                                                                                                                                 | Checked from the laptop: 200                                                                                                         |

## Next

1. Sreya: install 0.9.0 from the Updates screen (steps in the chat).
2. Gate tests left: **power pull ×10** mid-write (Sreya pulls the plug, I run the writes and the checks) and **camera over HTTPS** on the iPhone and an up-to-date Android phone.

2026-10-03 (Saturday, October 3, 2026)

## New network: own router, Pi re-flashed, SSH keys documented, HDMI fixed

Source: docs/P0-pi-setup-log-2026-10-03.pdf (detailed log of this day) and docs/P0-restart-new-network.md (the plan). This entry carries its content forward.

### Summary

- The TELUS modem gives no admin access, so DHCP reservations are impossible. The dev hub moved behind our **own TP-Link router**, which is LAN-cabled to the bedroom wall port.
- Network: subnet 192.168.50.0/24, gateway 192.168.50.1, 2.4 GHz SSID TP-LINK\_2CBE.
- Pi chedam at **192.168.50.101** (MAC 88:A2:9E:5C:17:65, reservation enabled); dev PC DESKTOP-AHG4TD7 at 192.168.50.100.
- The SD card was wiped and re-flashed. Key-only SSH works, and the OS is updated.
- HDMI console made visible. setup-hub.sh gained the --keep-display option.
- Commits: ea0a7e6, 678eee4, bacf585.

### Why SSH keys instead of a password

With a key pair, the private key never leaves the PC and the Pi holds only the public key. No secret crosses the network, keys cannot be guessed, and scripts can log in, so password login is switched off.

| File            | Where                     | Rule                                                          |
|-----------------|---------------------------|---------------------------------------------------------------|
| id_ed25519      | PC C:\Users\Venkata\.ssh\ | Private. Never share, paste or commit; back it up privately   |
| id_ed25519.pub  | PC, same folder           | Public, one line ending chedam-dev. Safe to copy              |
| authorized_keys | Pi /home/chedam/.ssh/     | Allowed public keys; folder 700, file 600                     |
| known_hosts     | PC .ssh\                  | Remembered Pi identities; ssh-keygen -R <ip> after a re-flash |
| config          | PC .ssh\                  | Alias ssh chedam                                              |

Key procedures recorded:

- create the key pair
- put the public key on the Pi with Imager (REMOVE old keys, then BROWSE to the .pub file)
- add or replace keys with type new.pub | ssh chedam "cat >> ~/.ssh/authorized\_keys"
- what to do when locked out (monitor + keyboard, or re-flash)

### Steps

1. Backed up .ssh with Copy-Item \$env:USERPROFILE\.ssh \$env:USERPROFILE\.ssh\_backup -Recurse.
2. Cleared old host fingerprints by deleting known\_hosts and known\_hosts.old. There was a backup.
3. Router: changed the admin password, set the LAN to 192.168.50.1/24 (different from TELUS 192.168.1.x), kept it in router mode, and turned on 2.4 GHz.
4. Re-flashed the card. Imager: Pi Zero 2 W, Lite 64-bit, chedam/chedam, new Wi-Fi, CA, SSH public-key only.
5. Found the Pi in the router's DHCP client list and created the reservation.
6. Updated the SSH config to HostName 192.168.50.101 and removed HostKeyAlias.
7. Ran sudo apt update && sudo apt full-upgrade -y and checked that sshd -T shows passwordauthentication no.
8. Readiness check: model, OS, IP, active Wi-Fi, multi-user.target; reboot test passed.
9. Forced HDMI output (see below).

### Failed cases and fixes

| Attempt / symptom                        | Cause                                                                                          | Fix                                                                                              |
|------------------------------------------|------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------|
| ssh-keygen -R <old-ip> errored           | PowerShell treats < as an operator                                                             | Use real addresses; deleting known_hosts avoided needing the old IP                              |
| Key pair deleted during "start fresh"    | Not needed: a key is not tied to a network                                                     | Restored from .ssh_backup                                                                        |
| ssh 192.168.50.101 denied as venkata     | No user given, so the Windows name was used                                                    | ssh chedam@192.168.50.101                                                                        |
| ssh chedam@chedam timed out              | Windows cannot resolve a bare name                                                             | IP, chedam.local, or the alias                                                                   |
| -i \$env:venkata\.ssh\... not found      | \$env:USERPROFILE is a real variable, not a placeholder                                        | Keep \$env:USERPROFILE                                                                           |
| Permission denied (publickey)            | Imager wrote an old remembered key (... COL3o srey...), not the PC's (... LuhpI0dY chedam-dev) | Re-flash; REMOVE old keys, BROWSE to id_ed25519.pub                                              |
| A command pasted into Imager's key box   | Get-Content ... \  Set-Clipboard text pasted as the key                                        | REMOVE, then BROWSE to the file                                                                  |
| "REMOTE HOST IDENTIFICATION HAS CHANGED" | Expected after a re-flash (new host key)                                                       | ssh-keygen -R 192.168.50.101                                                                     |
| Reservation saved as Disabled (TP-Link)  | Router default                                                                                 | Tick it, then Enable Selected; leave ARP binding off                                             |
| HDMI blank                               | dmesg: vc4-drm: Cannot find any crtc or sizes                                                  | Append video=HDMI-A-1:1280x720@60D to the single line in /boot/firmware/cmdline.txt, then reboot |
| Lines after sudo cp lost                 | The sudo password prompt ate the pasted lines                                                  | Paste one command at a time when sudo may prompt                                                 |

HDMI fix commands:

```
sudo cp /boot/firmware/cmdline.txt /boot/firmware/cmdline.txt.bak
sudo sed -i '1 s/$/ video=HDMI-A-1:1280x720@60D/' /boot/firmware/cmdline.txt
sudo reboot
```

## Lessons

- Before flashing, check that the key shown in Imager ends the same as type C: \Users\Venkata\.ssh\id\_ed25519.pub. Imager remembers old keys.
- Always back up .ssh before changes.
- With password login off, losing id\_ed25519 means re-flashing or using a keyboard and screen.
- No passwords or key contents are stored in the repo.

2026-10-02 (Friday, October 2, 2026)

## P0 kickoff: spec review, dev PC tools, first Pi flash and first hub setup (TELUS network)

### Summary

- Read Master Specification v1.0 and pulled out the P0 (Foundation) scope, done-criteria and phase gate.
- Wrote docs/P0-readiness-checklist.md: hardware, software with versions and links, Pi flashing steps, accounts.
- Installed and verified the developer tools on the Windows PC (all checksums matched the official ones).
- Flashed the Pi. The first attempts failed on SSH keys (including the private key being pasted into Imager); the key was replaced and SSH worked.
- Wrote the hub setup (hub/scripts/setup-hub.sh + hub/system/\*) and ran it on the Pi at 192.168.1.241 (TELUS network). HTTPS worked by name and IP.
- Wrote docs/P0-mini-spec.md (P0 build order, decisions DL-21 to DL-25).
- Decisions from Sreya: RTC skipped for now; cloud backup tested later when client IDs exist; test phones are Android 9 and iPhone 13 Pro (iOS 26.6.1); update channel option A (source stays private, signed packages in a separate public repo).

### 1. Spec review

Source: SDLC Docs Tools software installers and ReadMe/MASTER Specifications/Chedam - Master Specification v1.0.pdf (41 pages).

The PDF text was extracted with pdftotext -layout. The release-plan and architecture pages are images, so they were rendered with PyMuPDF and read as pictures.

P0 requirements: FR-1.01 to 1.10, 1.13, 1.14, 1.15; FR-12.01 to 12.04, 12.08, 12.09.

**Done when:** 3 devices log in, the hub survives a power pull, an update installs and rolls back. The phase gate adds: memory under 150 MB (NFR-08), a load test (R6), an iOS/Android HTTPS camera test (R5), and a verified backup and restore.

### 2. Developer PC tools

Already present: Git 2.52.0, VS Code 1.135, Python 3.13, Windows OpenSSH.

| Tool                  | Version               | Verified against                           | Result                                     |
|-----------------------|-----------------------|--------------------------------------------|--------------------------------------------|
| Node.js               | 24.21.0 (LTS Krypton) | nodejs.org SHASUMS256 + OpenJS signature   | Match, installed                           |
| PocketBase (Windows)  | 0.40.4                | PocketBase checksums.txt                   | Match                                      |
| DuckDB CLI            | 1.5.6                 | GitHub release digest                      | Match                                      |
| Raspberry Pi Imager   | 2.0.11.1              | GitHub digest + Raspberry Pi Ltd signature | Match, installed                           |
| DB Browser for SQLite | 3.13.1                | winget manifest + SignPath signature       | Match, installed                           |
| mkcert                | 1.4.4                 | Scoop manifest (file is unsigned)          | Match                                      |
| GitHub CLI            | 2.102.0               | n/a                                        | Installed, logged in as repatikosamid-prog |

Commands used for verification (Git Bash):

```
sha256sum *.msi *.exe *.zip
curl -s https://nodejs.org/dist/v24.21.0/SHASUMS256.txt | grep x64.msi
```

```
powershell Get-AuthenticodeSignature <file>
```

### Failed case: mkcert not recognized

- Symptom: `mkcert -install` → "The term 'mkcert' is not recognized".
- Cause: the file was still named `mkcert-v1.4.4-windows-amd64.exe`, and `C:\Tools` was not on PATH. PowerShell also never runs a program from the current folder without `.\`.
- Fix: copied `mkcert.exe`, `pocketbase.exe` and `duckdb.exe` to the top of `C:\Tools` and added `C:\Tools` to the user PATH. A new PowerShell window was needed for the change to show.

Then Sreya ran `mkcert -install` (local dev CA added to the Windows trust store) and `gh auth login` (fine-grained token).

The installers folder was added to `.gitignore`. PocketBase had created test data there.

### 3. Flashing the Pi (first time)

Imager settings: Pi Zero 2 W, Raspberry Pi OS Lite 64-bit, hostname `chedam`, user `chedam`, Wi-Fi 2.4 GHz, country CA, time zone America/Vancouver, SSH public-key only.

#### Failed case 1: hostname and username

- The hostname was typed as `Chedam` and the username as the GitHub name.
- Fix: lowercase `chedam` for both, so every script and guide matches.

#### Failed case 2: no SSH key existed

- SSH was set to password authentication, and the PC had no key yet.
- Fix: `ssh-keygen -t ed25519 -C "chedam-dev"`.

#### Failed case 3: Permission denied (publickey)

- Debug output showed the PC offering its key and the Pi refusing it for both usernames:

```
ssh -v -o BatchMode=yes chedam@chedam.local true
```

- Cause: the key written to the card was not the PC's key.
- The "host key differs" warning came from an old `192.168.1.241` entry in `known_hosts`. It was removed with `ssh-keygen -R`.

#### Failed case 4 (security): private key pasted into Imager

- Imager listed 7 "keys". They were the 7 lines of the **private key** (`BEGIN OPENSSH PRIVATE KEY`).
- Risk: the private key was copied onto the SD card and partly shown in a screenshot.
- Fix: removed all 7 entries, deleted the key pair, generated a new one, and pasted **only** `id_ed25519.pub` (one line, `ssh-ed25519 ... chedam-dev`). Re-flashing overwrote the card.

#### Failed case 5: `.local` name not resolving from Windows tools

- Git Bash `ssh` and Windows `ssh` both failed on `chedam.local`, while `Resolve-DnsName` worked.
- Fix: an SSH alias `chedam` pointing at the IP, in `~/.ssh/config`. The Pi first booted slowly (~5 min), so early checks also failed.

Login worked: `chedam@chedam`, Debian 13 trixie, aarch64, 415 MB RAM, 117 GB card.

### Admin access

`sudo` asked for a password, so Sreya ran this once:

```
ssh -t chedam "echo 'chedam ALL=(ALL) NOPASSWD:ALL' | sudo tee /etc/sudoers.d/010-chedam && sudo chmo
```

## 4. Hub setup (first time, Pi at 192.168.1.241)

OS update (ran in the background, ~15 min):

```
sudo apt-get update && sudo apt-get -y full-upgrade && sudo apt-get -y install chrony sqlite3 ufw
```

PocketBase 0.40.4 linux\_arm64 was downloaded on the Pi and checked with `sha256sum -c` against `checksums.txt`.

Files written in the repo:

| File                               | Purpose                                                                                                                                                                                  |
|------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| hub/scripts/setup-hub.sh           | Idempotent setup: packages, service user <code>chedam-hub</code> , <code>/opt/chedam</code> , PocketBase service, Caddy, watchdog, journald, Wi-Fi power save off, boot config, firewall |
| hub/system/chedam-hub.service      | PocketBase on 127.0.0.1:8090, auto-restart, <code>GOMEMLIMIT=100MiB</code> , <code>MemoryMax=220M</code> , hardening                                                                     |
| hub/system/Caddyfile               | HTTPS for <code>chedam.local</code> and the hub IP, using a per-store CA; plain HTTP only for <code>/ca.crt</code>                                                                       |
| hub/system/watchdog.conf           | Hardware watchdog 14 s                                                                                                                                                                   |
| hub/system/journald.conf           | Logs capped at 64 MB (SD card wear)                                                                                                                                                      |
| hub/system/wifi-powersave-off.conf | Lower Wi-Fi latency                                                                                                                                                                      |
| hub/system/index.html              | Placeholder page "Chedam hub is running"                                                                                                                                                 |

Run on the Pi:

```
scp -r scripts system chedam:hub/
ssh chedam 'sudo bash ~/hub/scripts/setup-hub.sh'
ssh chedam 'sudo systemctl reboot'
```

## Failed case 6: GitHub repo creation

- `gh repo create ... --public` → "Resource not accessible by personal access token".
- Cause: the fine-grained token cannot create repositories. Sreya has to create the public repo on github.com.

## Failed case 7: HTTPS tests from the PC returned nothing

- Windows `curl` (Schannel) → "the revocation status is unknown". A private CA has no revocation server.
- Fix for command-line tests: `--ssl-no-revoke`. Browsers are not affected.

## Failed case 8: Caddy error at start

- Caddy tried to install its root certificate into the Pi's own trust store and failed ("failed to execute sudo").
- Fix: the `skip_install_trust` global option in the Caddyfile.

## Results after reboot

| Check       | Result                                                                                               |
|-------------|------------------------------------------------------------------------------------------------------|
| Services    | chedam-hub, caddy, chrony, avahi-daemon active                                                       |
| HTTPS       | <code>https://chedam.local/api/health</code> and <code>https://192.168.1.241/api/health</code> → 200 |
| Certificate | Valid against "Chedam Store CA - 2026 ECC Root" (valid to 2036); IP cert has IP SAN                  |
| Memory      | PocketBase 27 MB + Caddy 41 MB; total RAM rose from 415 to 462 MB after headless config              |
| Watchdog    | 14 s                                                                                                 |
| Temperature | 52.6 °C, no throttling                                                                               |

## 5. Decisions recorded (docs/P0-mini-spec.md)

