

RUTINA DE CONTROL DE COLAS

00010			
00020	MUP	PUSH	HL
00030		PUSH	DE
00040		PUSH	BC
00050		LD	A, (T0)
00060		CP	0
00070		JR	Z, MUPI
00080		ADD	A, A
00090		LD	C, A
00100		LD	B, 0
00110		LD	HL, T0
00120		LD	D, 0
00130		LD	E, C
00140		ADD	HL, DE
00150		PUSH	HL
00160		POP	DE
00170		INC	DE
00180		INC	DE
00190		LDDR	
00200	MUPI	LD	A, (T0)
00210		INC	A
00220		LD	(T0), A
00230		POP	BC
00240		POP	DE
00250		POP	HL
00260		RET	
00270			
00280	MDOWN	PUSH	HL
00290		PUSH	DE
00300		PUSH	BC
00310		LD	HL, T0+3
00320		LD	DE, T0+1
00330		LD	A, (T0)
00340		DEC	A
00350		LD	(T0), A
00360		ADD	A, A
00370		LD	C, A
00380		LD	B, 0
00390		LDIR	
00400		POP	BC
00410		POP	DE
00420		POP	HL
00430		RET	
00440			
00450			
00460			
00470	SPRI1	LD	A, (VAR0)
00480		AND	%00111111
00490		LD	B, A
00500		INC	B
00510		LD	IX, TAS1-2
00520	BUS	INC	IX
00530		INC	IX
00540		DJNZ	BUS
00550		LD	L, (IX)
00560		LD	H, (IX+1)
00570		PUSH	HL
00580		POP	IX
00590		LD	B, (IX)
00600		INC	IX
00610		LD	A, B

0630		RET	Z
00640	BUS1	CALL	MUP
00650		LD	H,(IX+1)
0660		LD	L,(IX)
00670		LD	(TO+1),HL
00680		INC	IX
0690		INC	IX
0700		DJNZ	BUS1
00710		RET	
0720			
0730	SPRIPE	CALL	MUP
00740		LD	HL,TABLA1
00750		LD	(TO+1),HL
0760		CALL	MUP
00770		LD	HL,TABLA2
00780		LD	(TO+1),HL
0790		RET	
0800			
00810	RESET	LD	A,0
00820		LD	(TO),A
0830		RET	